

5000种场效应管参数查询 (请同时按电脑键盘ctrl和F键输入型号可查询)

更多彩电维修资料请到《彩电维修资料网》<http://www.tv160.net> 查询吧!

ID	型号	厂家	用途	构造	沟道方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing	
1	2SJ11	东芝	DC, LF A, Chop	J	P	D	20	GDS	-10m	100m	4-2
2	2SJ12	东芝	DC, LF A, Chop	J	P	D	20	GDS	-10m	100m	4-2
3	2SJ13	东芝	DC, LF A, Chop	J	P	D	20	GDS	-100m	600m	4-35
4	2SJ15	富士通	DC, LF A	J	P		18	GDO	-10m	200m	4-1
5	2SJ16	富士通	DC, LF A	J	P		18	GDO	-10m	200m	4-1
6	2SJ17		C-MIC	J	P		20	GDO	0.5m	10m	4-47
7	2SJ18		LF PA	J(V)	P		170	GDO	-5	63	4-45
8	2SJ19	NEC	LF D	J(V)	P		140	GDO	-100m	800m	4-41
9	2SJ20	NEC	LF PA	J(V)	P		100	GDO	-10	100	4-42
10	2SJ22		C-MIC	J	P	D	80	GDO	0.5m	50m	4-48
11	2SJ39	三菱	LF A	J	P	D	50	GDO	-10m	.15/CH	4-81
12	2SJ40	三菱	LF A, A-SW	J	P	D	50	GDO	-10m	300m	4-151
13	2SJ43	松下	LF A	J	P	D	50	GDS	20m	250m	4-80A
14	2SJ44	NEC	LF LN A	J	P	D	40	GDO	-10m	400m	4-53A
15	2SJ45	NEC	LF A	J	P	D	40	GDO	-10m	400m	4-53A
16	2SJ47	日立	LF PA	MOS	P	E	-100	DSX	-7	100	4-28A
17	2SJ48	日立	LF PA, HS PSW	MOS	P	E	-120	DSX	-7	100	4-28A
18	2SJ49	日立	LF PA, HS PSW	MOS	P	E	-140	DSX	-7	100	4-28A
19	2SJ49(H)	日立	HS PSW	MOS	P	E	-140	DSX	-7	100	4-28A
20	2SJ50	日立	LF/HF PA, HS PSW	MOS	P	E	-160	DSX	-7	100	4-28A
21	2SJ50(H)	日立	HS PSW	MOS	P	E	-160	DSX	-7	100	4-28A
22	2SJ51	日立	LF LN A	J	P	D	40	GDO	-10m	800m	4-97A
23	2SJ55	日立	LF/HF PA, HS PSW	MOS	P	E	-180	DSX	-8	125	4-28A
24	2SJ56	日立	LF/HF PA, HS PSW	MOS	P	E	-200	DSX	-8	125	4-28A
25	2SJ56(H)	日立	HF PA, HS PSW	MOS	P	E	-200	DSX	-8	125	4-28A
26	2SJ68	日立	LF LN A	J	P	D	-40	DSX	-10m	300m	4-79A
27	2SJ69	日立	LF LN A	J	P	D	-40	DSX	-10m	300m	4-79A
28	2SJ70	日立	LF LN A	J	P	D	-40	DSX	-10m	800m	4-97A
29	2SJ72	东芝	LF LN A	J	P	D	25	GDS	-10m	600m	4-74A
30	2SJ73	东芝	LF LN A	J	P	D	25	GDS	-10m	0.6/CH	4-98
31	2SJ74	东芝	LF LN A	J	P	D	25	GDS	-10m	400m	4-90
32	2SJ75	东芝	LF LN A	J	P	D	25	GDS	-10m	0.4/CH	4-99
33	2SJ76	日立	LF D, HS PSW	MOS	P	E	-140	DSX	-500m	30	4-116A
34	2SJ77	日立	LF D, HS PSW	MOS	P	E	-160	DSX	-500m	30	4-116A
35	2SJ77(K)	日立	HF PA, HS PSW	MOS	P	E	-160	DSX	-500m	30	4-116A
36	2SJ78	日立	LF D, HS PSW	MOS	P	E	-180	DSX	-500m	30	4-116A
37	2SJ79	日立	LF D, HS PSW	MOS	P	E	-200	DSX	-500m	30	4-116A
38	2SJ79(K)	日立	HF PA, HS PSW	MOS	P	E	-200	DSX	-500m	30	4-116A
39	2SJ81	日立	LF PA	MOS	P		-120	DSX	-7	100	4-117A
40	2SJ82	日立	LF PA	MOS	P		-140	DSX	-7	100	4-117A
41	2SJ83	日立	LF PA	MOS	P		-160	DSX	-7	100	4-117A
42	2SJ84	松下	LF A	J	P	D	15	GDS	-10m	200m	4-105A
43	2SJ85	日立	LF PA	MOS	P						
44	2SJ86	日立	LF PA	MOS	P						
45	2SJ87	日立	LF PA	MOS	P						
46	2SJ90	东芝	LF LN A	J	P	D	30	GDS	-10m	0.2/CH	4-75
47	2SJ91	东芝	LF PA	MOS	P		-140	DSX	-8	120	4-118
48	2SJ92	东芝	LF PA	MOS	P		-140	DSX	-7	100	4-119
49	2SJ96	日立	LF/HF PA, HS PSW	MOS	P		-60	DSX	-8	100	4-117A
50	2SJ99	日立	LF/HF PA, HS PSW	MOS	P	E	-140	DSS	-8	100	4-117B
51	2SJ100	日立	LF/HF PA, HS PSW	MOS	P	E	-160	DSS	-8	100	4-117B
52	2SJ101	日立	LF/HF PA, HS PSW	MOS	P	E	-40	DSS	-5	30	4-116B
53	2SJ102	日立	LF/HF PA, HS PSW	MOS	P	E	-60	DSS	-5	30	4-116B
54	2SJ103	东芝	LF A, A-SW	J	P	D	50	GDS	-10m	300m	4-82B
55	2SJ104	东芝	LF A, A-SW	J	P	D	25	GDS	-10m	400m	4-82C
56	2SJ105	东芝	LF A, A-SW	J	P	D	50	GDS	-10m	200m	4-70A

5000种场效应管参数

更多彩电维修资料请到《彩电维修资料网》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道	方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
57	2SJ106	东芝	LF A,A-SW	J	P	D	50	GDS	-10m	150m	4-105A
58	2SJ107	东芝	LF A,A-SW	J	P	D	25	GDS	-10m	200m	4-70B
59	2SJ108	东芝	LF LN A	J	P	D	25	GDS	-10m	200m	4-70B
60	2SJ109	东芝	LF LN A	J	P	D	30	GDS	-10m	200m	4-148
61	2SJ110	东芝	LF A,A-SW	J	P	D	25	GDS	-10m	400m	4-82C
62	2SJ111	东芝	LF LN A	J	P	D	25	GDS	-10m	400m	4-82C
63	2SJ112	日立	HS PSW, RF PA	MOS	P	E	-100	DSS	-10	100	4-28B
64	2SJ113	日立	HS PSW, RF PA	MOS	P	E	-100	DSS	-10	100	4-149
65	2SJ114	日立	HS PSW, RF PA	MOS	P	E	-200	DSS	-8	100	4-149
66	2SJ115	东芝	LF PA	MSO	P	E	-160	DSS	-8	100	4-119
67	2SJ116	日立	HS PSW, RF PA	MOS	P	E	-400	DSS	-8	125	4-28B
68	2SJ117	日立	HS PSW, RF PA	MOS	P	E	-400	DSS	-2	40	4-116B
69	2SJ118	日立	HS PSW, RF PA	MOS	P	E	-140	DSS	-8	100	4-149
70	2SJ119	日立	HS PSW, RF PA	MOS	P	E	-160	DSS	-8	100	4-149
71	2SJ120(L)	日立	HS PSW, RF PA	MOS	P	E	-40	DSS	-2	10	4-150
72	2SJ122	日立	HS PSW, RF PA	MOS	P	E	-60	DSS	-10	50	4-116B
73	2SJ123	东芝	LF PA, HS SW	MOS	P	E	-70	DSS	-10	30	4-138
74	2SJ125	三菱	LF PA,A-SW	J	P	D	50	DGO	-10m	150m	4-128
75	2SJ126	东芝	HS SW	MOS	P	E	-60	DSX	-10	40	4-182
76	2SJ127	日立	HS PSW	MOS	P	E	-120	DSS	-10	50	4-116B
77	2SJ128,128	NEC	SW	MOS	P	E	-100	DSS	±2	20	4-276/Z:281
78	2SJ129	松下	LF A	J	P	D	50	GDS	-10m	300m	4-213B
79	2SJ130(L)	日立	HS SW	MOS	P	E	-300	DSS	-1	20	4-150
80	2SJ131		SW	MOS	P	E	-170	DSS	-10	100	4-207
81	2SJ132,132	NEC	SW	MOS	P	E	-30	DSS	±2	20	4-276/Z:281
82	2SJ133,133	NEC	SW	MOS	P	E	-60	DSS	±2	20	4-276/Z:281
83	2SJ134	NEC	SW	MOS	P	E	-100	DSS	±6	20	4-164
84	2SJ135	NEC	SW	MOS	P	E	-100	DSS	±5	30	4-274
85	2SJ136	NEC	SW	MOS	P	E	-60	DSS	±12	40	4-164
86	2SJ137	NEC	SW	MOS	P	E	-60	DSS	±10	30	4-274
87	2SJ138	NEC	SW	MOS	P	E	-100	DSS	±12	60	4-164
88	2SJ139	NEC	SW	MOS	P	E	-100	DSS	±10	35	4-274
89	2SJ140	NEC	SW	MOS	P	E	-60	DSS	±19	60	4-164
90	2SJ141	NEC	SW	MOS	P	E	-60	DSS	±13	35	4-274
91	2SJ142	NEC	SW	MOS	P	E	-100	DSS	±13	35	4-274
92	2SJ143	NEC	SW	MOS	P	E	-60	DSS	±16	35	4-274
93	2SJ144	东芝	LF A-SW	J	P	D	50	GDS	-10m	100m	4-246B
94	2SJ145	三菱	LF A-SW	J	P	D	50	GDO	-10m	150m	
95	2SJ146	松下	SW	MOS	P	E	-50	DSS	-100m	150m	4-193B
96	2SJ147	东芝	DDC, Motor D	MOS	P	E	-60	DSS	-12	40	4-182
97	2SJ148	东芝	HS SW, A-SW	MOS	P	E	-60	DSX	-200m	400m	4-82D
98	2SJ151	NEC	SW	MOS	P	E	-100	DSS	±3	35	4-164
99	2SJ152	NEC	SW	MOS	P	E	-100	DSS	±3	30	4-274
100	2SJ153	NEC	SW	MOS	P	E	-60	DSS	±6	40	4-164
101	2SJ154	NEC	SW	MOS	P	E	-60	DSS	±5	30	4-274
102	2SJ155	松下	SW	MOS	P	E	-50	DSS	-3	30	4-190
103	2SJ156	松下	SW	MOS	P	E	-50	DSS	-5	30	4-190
104	2SJ157	松下	SW	MOS	P	E	-100	DSS	-3	30	4-190
105	2SJ158	松下	SW	MOS	P	E	-100	DSS	-5	30	4-190
106	2SJ159	松下	SW	MOS	P	E	-160	DSS	-3	30	4-190
107	2SJ160	日立	LF PA	MOS	P	E	-120	DSX	-7	100	4-149
108	2SJ161	日立	LF PA	MOS	P	E	-140	DSX	-7	100	4-149
109	2SJ162	日立	LF PA	MOS	P	E	-160	DSX	-7	100	4-149
110	2SJ163	松下	SW	J	P	D	65	GDS	-10m	150m	4-193D
111	2SJ164	松下	SW	J	P	D	65	GDS	-10m	300m	4-213C
112	2SJ165	NEC	HS SW	MOS	P	E	-50	DSS	-0.1	250m	4-104C
113	2SJ166	NEC	HS SW	MOS	P	E	-50	DSS	-0.1	200m	4-275A
114	2SJ167	东芝	HS SW, A-SW	MOS	P	E	-60	DSS	-200m	300m	4-70
115	2SJ168	东芝	HS SW, A-SW	MOS	P	E	-60	DSS	-200m	200m	4-105D
116	2SJ169	日立	SW-Reg, DDC	MOS	P	E	-60	DSS	-12	50	4-116B
117	2SJ170	日立	SW-Reg, DDC	MOS	P	E	-80	DSS	-12	50	4-116B

5000种场效应管参数

更多彩电维修资料请到《彩电维修资料网》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道	方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
118	2SJ171	日立	SW-Reg, DDC	MOS	P	E	-50	DSS	-9.7	40	4-116B
119	2SJ172	日立	Motor/Relay-D	MOS	P	E	-60	DSS	-10	40	4-116B
120	2SJ173	日立	Motor/Relay-D	MOS	P	E	-60	DSS	-15	50	4-116B
121	2SJ174	日立	Motor/Relay-D	MOS	P	E	-60	DSS	-20	75	4-116B
122	2SJ175	日立	Motor/Relay-D	MOS	P	E	-60	DSS	-10	25	4-292
123	2SJ176	日立	Motor/Relay-D	MOS	P	E	-60	DSS	-15	30	4-292
124	2SJ177	日立	Motor/Relay-D	MOS	P	E	-60	DSS	-20	35	4-292
125	2SJ178	NEC	HS SW	MOS	P	E	-30	DSS	±1	0.75	4-53C
126	2SJ179	NEC	HS SW	MOS	P	E	-30	DSS	±1.5	2	4-216A
127	2SJ180	NEC	HS SW	MOS	P	E	-30	DSS	±1	1	4-217
128	2SJ181(L)	日立	SW-Reg, DDC	MOS	P	E	-600	DSS	-0.5	20	4-150
129	2SJ182(L)	日立	Motor/Relay-D	MOS	P	E	-60	DSS	-3	20	4-150
130	2SJ183	东芝	Relay-D, DDC	MOS	P	E	-60	DSS	-5	20	4-257
131	2SJ184	NEC	HS SW	MOS	P	E	-50	DSS	-100m	250m	4-104C
132	2SJ185	NEC	HS SW	MOS	P	E	-50	DSS	-100m	200m	4-275A
133	2SJ186	日立	SW-Reg, DDC	MOS	P	E	-200	DSS	-0.5	1	4-295
134	2SJ187	三洋	SW	MOS	P	E	-30	DSS	-1	3.5	4-252
135	2SJ188	三洋	SW	MOS	P	E	-30	DSS	-2	20	4-346
136	2SJ189	三洋	SW	MOS	P	E	-30	DSS	-4	30	4-346
137	2SJ190	三洋	SW	MOS	P	E	-60	DSS	-1	3.5	4-252
138	2SJ191	三洋	SW	MOS	P	E	-60	DSS	-2	20	4-346
139	2SJ192	三洋	SW	MOS	P	E	-60	DSS	-4	30	4-346
140	2SJ193	三洋	SW	MOS	P	E	-100	DSS	-1	3.5	4-252
141	2SJ194	三洋	SW	MOS	P	E	-100	DSS	-2	20	4-346
142	2SJ195	三洋	SW	MOS	P	E	-100	DSS	-4	30	4-346
143	2SJ196	NEC	SW	MOS	P	E	-60	DSS	±1	0.75	4-53C
144	2SJ197	NEC	SW	MOS	P	E	-60	DSS	±1	2	4-216A
145	2SJ198	NEC	SW	MOS	P	E	-100	DSS	±0.5	0.75	4-53D
146	2SJ199	NEC	SW	MOS	P	E	-100	DSS	±1	2	4-216A
147	2SJ200	东芝	LF PA	MOS	P	E	-180	DSS	-10	120	4-184
148	2SJ201	东芝	LF PA	MOS	P	E	-200	DSS	-12	150	4-337
149	2SJ202	NEC	SW	MOS	P	E	-16	DSS	-100m	150m	4-246C
150	2SJ203	NEC	SW	MOS	P	E	-16	DSS	-200m	200m	4-275A
151	2SJ204	NEC	SW	MOS	P	E	-30	DSS	-200m	200m	4-275A
152	2SJ205	NEC	SW	MOS	P	E	-16	DSS	±0.5	2	4-216A
153	2SJ206	NEC	SW	MOS	P	E	-30	DSS	±0.5	2	4-216A
154	2SJ207	NEC	SW	MOS	P	E	-16	DSS	±1	2	4-216A
155	2SJ208	NEC	SW	MOS	P	E	-16	DSS	±2	2	4-216A
156	2SJ209	NEC	SW	MOS	P	E	-100	DSS	-100m	200m	4-275A
157	2SJ210	NEC	SW	MOS	P	E	-60	DSS	-200m	200m	4-275A
158	2SJ211	NEC	SW	MOS	P	E	-100	DSS	-200m	200m	4-275A
159	2SJ212	NEC	SW	MOS	P	E	-60	DSS	±0.5	2	4-216A
160	2SJ213	NEC	SW	MOS	P	E	-100	DSS	±0.5	2	4-216A
161	2SJ214(L)	日立	Motor/Relay-D	MOS	P	E	-60	DSS	-105	40	4-294
162	2SJ215	日立	Motor/Relay-D	MOS	P	E	-60	DSS	-35	125	4-149
163	2SJ216	日立	Motor/Relay-D	MOS	P	E	-60	DSS	-35	60	4-293
164	2SJ217	日立	Motor/Relay-D	MOS	P	E	-60	DSS	-45	150	4-149
165	2SJ218	日立	Motor/Relay-D	MOS	P	E	-60	DSS	-45	75	4-293
166	2SJ219(L)	日立	Motor/Relay-D	MOS	P	E	-60	DSS	-15	50	4-294
167	2SJ220(L)	日立	Motor/Relay-D	MOS	P	E	-60	DSS	-20	75	4-294
168	2SJ221	日立	Motor/Relay-D	MOS	P	E	-100	DSS	-20	75	4-116B
169	2SJ222	日立	Motor/Relay-D	MOS	P	E	-100	DSS	-15	35	4-292
170	2SJ223(L)	日立	HS PSW	MOS	P	E	-60	DSS	-2	10	4-150
171	2SJ224	东芝	SW, DDC, Motor-D	MOS	P	E	-60	DSS	-12	80	4-341
172	2SJ225	三洋	HS SW	MOS	P	E	-30	DSS	-1	1	4-348
173	2SJ226	三洋	HS SW	MOS	P	E	-30	DSS	-2	1.5	4-347
174	2SJ227	三洋	HS SW	MOS	P	E	-30	DSS	-3	1.5	4-347
175	2SJ228	三洋	HS SW	MOS	P	E	-60	DSS	-0.8	1	4-348
176	2SJ229	三洋	HS SW	MOS	P	E	-60	DSS	-1.6	1.5	4-347
177	2SJ230	三洋	HS SW	MOS	P	E	-60	DSS	-2.5	1.5	4-347
178	2SJ231	三洋	HS SW	MOS	P	E	-100	DSS	-0.5	1	4-348

5000种场效应管参数

更多彩电维修资料请到《彩电维修资料网》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道	方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
179	2SJ232	三洋	HS SW	MOS	P	E	-100	DSS	-2.5	1.5	4-347
180	2SJ233	三洋	HS SW	MOS	P	E	-100	DSS	-2.5	1.5	4-347
181	2SJ234(L)	日立	HS PSW, DDC	MOS	P	E	-30	DSS	-2.5	10	4-150
182	2SJ235(L)	日立	HS PSW	MOS	P	E	-60	DSS	-3	20	4-150
183	2SJ236	日立	HS PSW	MOS	P	E	-60	DSS	-10	25	4-376
184	2SJ237	日立	HS PSW	MOS	P	E	-60	DSS	-15	30	4-376
185	2SJ238	东芝	SW, DDC, Motor-D	MOS	P	E	-60	DSS	-1	0.5	4-256
186	2SJ239	东芝	SW, DDC, Motor-D	MOS	P	E	-60	DSS	-5	20	4-257
187	2SJ240	东芝	SW, DDC, Motor-D	MOS	P	E	-60	DSS	-20	45	4-335
188	2SJ241	东芝	SW, DDC, Motor-D	MOS	P	E	-60	DSS	-20	100	4-341
189	2SJ243	NEC	SW	MOS	P	E	-30	DSS	±100m	200m	4-356
190	2SJ244	日立	HS PSW, DDC	MOS	P	E	-12	DSS	±2	1	4-295
191	2SJ245(L)	日立	HS PSW, DDC	MOS	P	E	-60	DSS	-5	20	4-150
192	2SJ246(L)	日立	HS PSW, DDC	MOS	P	E	-30	DSS	-7	20	4-150
193	2SJ247	日立	HS PSW	MOS	P	E	-100	DSS	-8	40	4-116B
194	2SJ248	日立	HS PSW, DDC	MOS	P	E	-100	DSS	-8	25	4-292
195	2SJ250	日立	HS PSW	MOS	P	E	-60	DSS	-10	12	4-363A
196	2SJ254	三洋	HS SW	MOS	P	E	-30	DSS	-8	25	4-284
197	2SJ255	三洋	HS SW	MOS	P	E	-30	DSS	-10	25	4-284
198	2SJ256	三洋	HS SW	MOS	P	E	-30	DSS	-18	30	4-284
199	2SJ257	三洋	HS SW	MOS	P	E	-30	DSS	-10	50	4-370
200	2SJ258	三洋	HS SW	MOS	P	E	-30	DSS	-12	60	4-370
201	2SJ259	三洋	HS SW	MOS	P	E	-30	DSS	-20	70	4-370
202	2SJ263	三洋	HS SW	MOS	P	E	-60	DSS	-6	25	4-284
203	2SJ264	三洋	HS SW	MOS	P	E	-60	DSS	-8	25	4-284
204	2SJ265	三洋	HS SW	MOS	P	E	-60	DSS	-15	30	4-284
205	2SJ266	三洋	HS SW	MOS	P	E	-60	DSS	-8	50	4-370
206	2SJ267	三洋	HS SW	MOS	P	E	-60	DSS	-10	60	4-370
207	2SJ268	三洋	HS SW	MOS	P	E	-60	DSS	-18	70	4-370
208	2SJ272	三洋	HS SW	MOS	P	E	-100	DSS	-4	25	4-284
209	2SJ273	三洋	HS SW	MOS	P	E	-100	DSS	-6	25	4-284
210	2SJ274	三洋	HS SW	MOS	P	E	-100	DSS	-12	30	4-284
211	2SJ275	三洋	HS SW	MOS	P	E	-100	DSS	-6	50	4-370
212	2SJ276	三洋	HS SW	MOS	P	E	-100	DSS	-8	60	4-370
213	2SJ277	三洋	HS SW	MOS	P	E	-100	DSS	-60	70	4-370
214	2SJ278	日立	HS PSW, DDC	MOS	P	E	-60	DSS	-1	1	4-295
215	2SJ279(L)	日立	HS PSW, DDC	MOS	P	E	-60	DSS	-5	20	4-150
216	2SJ280(L)	日立	HS PSW, DDC	MOS	P	E	-60	DSS	-30	75	4-294
217	2SJ281	三洋	HS SW	MOS	P	E	-250	DSS	-3	30	4-346
218	2SJ284	三洋	HS SW	MOS	P	E	-30	DSS	-0.3	250m	4-368
219	2SJ285	三洋	HS SW	MOS	P	E	-60	DSS	-0.2	250m	4-368
220	2SJ287	三洋	HS SW	MOS	P	E	-30	DSS	-0.5	3.5	4-252
221	2SJ288	三洋	HS SW	MOS	P	E	-60	DSS	-0.5	3.5	4-252
222	2SJ290	日立	HS PSW	MOS	P	E	-60	DSS	-15	50	4-116B
223	2SJ291	日立	HS PSW	MOS	P	E	-60	DSS	-20	60	4-116B
224	2SJ292	日立	HS PSW	MOS	P	E	-60	DSS	-30	75	4-116B
225	2SJ293	日立	HS PSW	MOS	P	E	-60	DSS	-15	30	4-292
226	2SJ294	日立	HS PSW	MOS	P	E	-60	DSS	-20	35	4-292
227	2SJ295	日立	HS PSW	MOS	P	E	-60	DSS	-30	35	4-292
228	2SJ296(L)	日立	HS PSW	MOS	P	E	-60	DSS	-15	50	4-294
229	2SJ297(L)	日立	HS PSW, DDC	MOS	P	E	-60	DSS	-20	60	4-294
230	2SJ298	日立	HS PSW	MOS	P	E	-20	DSS	-5	12	4-363A
231	2SJ299(L)	日立	HS PSW	MOS	P	E	-20	DSS	-5	20	4-150
232	2SJ300	日立	HS PSW	MOS	P	E	-20	DSS	-10	12	4-363A
233	2SJ302, 302	NEC	SW, DDC	MOS	P	E	-60	DSS	±16	75	4-287/Z:306
234	2SJ303	NEC	SW, DDC	MOS	P	E	-60	DSS	±14	35	4-304
235	2SJ304	东芝	HS, SW, DDC	MOS	P	E	-60	DSS	-14	40	4-335
236	2SJ306	三洋	HS SW	MOS	P	E	-250	DSS	-3	25	4-284
237	2SJ307	三洋	HS SW	MOS	P	E	-250	DSS	-6	30	4-284
238	2SJ308	三洋	HS SW	MOS	P	E	-250	DSS	-9	40	4-284
239	2SJ312	东芝	HS SW, DDC	MOS	P	E	-60	DSS	-14	40	4-341

5000种场效应管参数

更多彩电维修资料请到《彩电维修资料网》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道	方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
240	2SJ313	东芝	LF PA	MOS	P	E	-180	DSS	-1	25	4-335
241	2SJ314-01L	富士电机		MOS	P	E	-60	DSS	-5	20	4-391
242	2SJ315	东芝	DDC	MOS	P	E	-60	DSS	-5	20	4-257
243	2SJ316	三洋	HS SW	MOS	P	E	-12	DSS	-1	3.5	4-252
244	2SJ317	日立	SW, PA	MOS	P	E	-12	DSS	±2	1	4-295
245	2SJ318(L)	日立	HS PSW	MOS	P	E	-20	DSS	-5	20	4-150
246	2SJ319(L)	日立	HS PSW	MOS	P	E	-200	DSS	-3	20	4-150
247	2SJ320	三洋	HS SW	MOS	P	E	-250	DSS	-4	25	4-284
248	2SJ321	日立	HS PSW	MOS	P	E	-60	DSS	-15	30	4-376
249	2SJ322	日立	HS PSW	MOS	P	E	-60	DSS	-20	35	4-376
250	2SJ323	日立	HS PSW	MOS	P	E	-60	DSS	-30	35	4-376
251	2SJ324, 324	NEC	SW, DDC	MOS	P	E	-30	DSS	±2	20	4-276/Z:277
252	2SJ325, 325	NEC	SW, DDC	MOS	P	E	-30	DSS	±4	20	4-276/Z:277
253	2SJ326, 32	NEC	SW, DDC	MOS	P	E	-60	DSS	±2	20	4-276/Z:277
254	2SJ327, 32	NEC	SW, DDC	MOS	P	E	-60	DSS	±4	20	4-276/Z:277
255	2SJ328, 32	NEC	SW, DDC	MOS	P	E	-60	DSS	±20	75	4-287/Z:306
256	2SJ329	NEC	SW, DDC	MOS	P	E	-60	DSS	±15	35	4-304
257	2SJ330	NEC	SW, DDC	MOS	P	E	-60	DSS	±20	35	4-304
258	2SJ331	NEC	SW, DDC	MOS	P	E	-60	DSS	±30	150	4-253
259	2SJ332(L)	日立	HS PSW	MOS	P	E	-20	DSS	-10	20	4-377, 378
260	2SJ333(L)	日立	HS PSW	MOS	P	E	-30	DSS	-7	20	4-150
261	2SJ334	东芝	HS SW, DDC	MOS	P	E	-60	DSS	-30	45	4-335
262	2SJ337	三洋	HS SW	MOS	P	E	-12	DSS	-8	30	4-384
263	2SJ341	日立	HS PSW	MOS	P	E	-20	DSS	-5	12	4-363B
264	2SJ349	东芝	HS SW, DDC	MOS	P	E	-60	DSS	-20	35	4-335
265	2SJ350	日立	HS PSW	MOS	P	E	-120	DSS	-6	20	4-292
266	2SJ351	日立	LF/RF PA, HS PSW	MOS	P	E	-180	DSX	-8	100	4-149
267	2SJ352	日立	LF/RF PA, HS PSW	MOS	P	E	-200	DSX	-8	100	4-149
268	2SJ353	NEC		MOS	P	E	-60	DSS	±1.5	1	4-217
269	2SJ355	NEC		MOS	P	E	-30	DSS	±2	2	4-SC-62
270	2SJ356	NEC		MOS	P	E	-60	DSS	±2	2	4-SC-62
271	2SJ357	NEC		MOS	P	E	-30	DSS	±3	2	4-MP-2
272	2SJ358	NEC		MOS	P	E	-60	DSS	±3	2	4-MP-2
273	2SJ359	东芝	HS SW, DDC	MOS	P	E	-60	DSS	-5	1.2	4-387
274	2SJ360	东芝	HS SW, DDC	MOS	P	E	-60	DSS	-1	1.5	4-256
275	2SJ361	日立	HS PSW	MOS	P	E	-20	DSS	-2	1	4-295
276	2SJ363	日立	HS PSW	MOS	P	E	-30	DSS	-2	1	4-295
277	2SJ365	新电元	HS SW	MOS	P	E	-60	DSS	-2	10	4-290
278	2SJ366	新电元	HS SW	MOS	P	E	-60	DSS	-5	15	4-290
279	2SJ367	新电元	HS SW	MOS	P	E	-60	DSS	-5	30	4-383
280	2SJ368	新电元	HS SW	MOS	P	E	-60	DSS	-5	20	4-304
281	2SJ369	新电元	HS SW	MOS	P	E	-60	DSS	-10	40	4-383
282	2SJ370	新电元	HS SW	MOS	P	E	-60	DSS	-10	25	4-304
283	2SJ371	新电元	HS SW	MOS	P	E	-60	DSS	-15	50	4-383
284	2SJ372	新电元	HS SW	MOS	P	E	-60	DSS	-15	30	4-304
285	2SJ373	新电元	HS SW	MOS	P	E	-60	DSS	-20	60	4-383
286	2SJ374	新电元	HS SW	MOS	P	E	-60	DSS	-20	40	4-304
287	2SJ375	新电元	HS SW	MOS	P	E	-60	DSS	-30	60	4-383
288	2SJ376	新电元	HS SW	MOS	P	E	-60	DSS	-30	50	4-304
289	2SJ377	东芝	HS SW, DDC	MOS	P	E	-60	DSS	-5	20	4-257
290	2SJ378	东芝	HS SW, DDC	MOS	P	E	-60	DSS	-5	1.2	4-387
291	2SJ379	东芝	HS SW, DDC	MOS	P	E	-100	DSS	-8	15	4-342
292	2SJ380	东芝	HS SW, DDC	MOS	P	E	-100	DSS	-12	35	4-335
293	2SJ381	三洋		MOS	P	E	-12	DSS	-2	3.5	4-252
294	2SJ382	三洋		MOS	P	E	-12	DSS	-4	20	
295	2SJ383	三洋		MOS	P	E	-12	DSS	-8	30	
296	2SJ384(L)	日立	HS PSW	MOS	P	E	-60	DSS	-15	50	4-294
297	2SJ386	日立	HS PSW	MOS	P	E	-30	DSS	-3	0.9	4-97B
298	2SJ387(L)	日立	HS PSW	MOS	P	E	-20	DSS	-10	20	4-377, 378
299	2SJ388(L)	日立	HS PSW	MOS	P	E	-30	DSS	-10	20	4-377, 378
300	2SJ389(L)	日立	HS PSW	MOS	P	E	-60	DSS	-10	30	4-377, 378

5000种场效应管参数

更多彩电维修资料请到《彩电维修资料网》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道	方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
301	2SJ390	日立	HS PSW	MOS	P	E	-60	DSS	-10	25	4-292
302	2SJ399	日立	HS PSW	MOS	P	E	-30	DSS	-0.2	0.15	4-185B
303	2SJ408(L)	日立	HS PSW	MOS	P	E	-60	DSS	-50	100	4-379, 380
304	2SJ409(L)	日立	HS PSW	MOS	P	E	-100	DSS	-20	75	4-294
305	2SJ410	日立	HS PSW	MOS	P	E	-200	DSS	-6	30	4-292
306	2SJ128Z	NEC	SW	MOS	P	E	-100	DSS	±2	20	4-281
307	2SJ132Z	NEC	SW	MOS	P	E	-30	DSS	±2	20	4-281
308	2SJ133Z	NEC	SW	MOS	P	E	-60	DSS	±2	20	4-281
309	2SJ302Z	NEC	SW, DDC	MOS	P	E	-60	DSS	±16	75	4-306
310	2SJ324Z	NEC	SW, DDC	MOS	P	E	-30	DSS	±2	20	4-277
311	2SJ325Z	NEC	SW, DDC	MOS	P	E	-30	DSS	±4	20	4-277
312	2SJ326Z	NEC	SW, DDC	MOS	P	E	-60	DSS	±2	20	4-277
313	2SJ327Z	NEC	SW, DDC	MOS	P	E	-60	DSS	±4	20	4-277
314	2SJ328Z	NEC	SW, DDC	MOS	P	E	-60	DSS	±20	75	4-306
315	2SJ120(S)	日立	HS PSW, RF PA	MOS	P	E	-40	DSS	-2	10	4-150
316	2SK11	东芝	DC/LF A, Chop	J	N	D	-20	GDS	10m	100m	4-2
317	2SK12	东芝	DC/LF A, Chop	J	N	D	-20	GDS	10m	100m	4-2
318	2SK13	东芝	DC/LF A	J	N	D	-12	GDS	10m	100m	4-2
319	2SK15	东芝	DC/LF LN A	J	N	D	-20	GDS	10m	100m	4-2
320	2SK16(H)	日立	Hi - Imp A	J	N	D			10m	100m	4-3
321	2SK17	东芝	LF A	J	N	D	-20	GDS	10m	100m	4-7
322	2SK18	东芝	DC	J	N	D	-40	GDS	10m	200m	4-19
323	2SK18A	东芝	DC	J	N	D	-40	GDS	10m	200m	4-19
324	2SK19TM	东芝	FM/VHF RF	J	N	D	-18	GDO	10m	200m	4-82A
325	2SK1905	三洋	HS SW	MOS	N	E	100	DSS	12	25	4-284
326	2SK1908	三洋	HS SW	MOS	N	E	100	DSS	15	60	4-370
327	2SK23A-8		DC/VHF RF	J	N	D	-27	GDO	10m	250m	4-5
328	2SK23A-9		DC/VHF RF	J	N	D	-40	GDO	10m	250m	4-5
329	2SK24	三洋	LF A, AM RF	J	N	D	-40	GDS	10m	100m	4-6
330	2SK25	三洋	FM RF/MIX	J	N	D	-18	GDS	10m	100m	4-6
331	2SK30	东芝	LF A	J	N	D	-50	GDS	10m	100m	4-7
332	2SK30ATM	东芝	LF LN A	J	N	D	-50	GDS	10m	100m	4-82B
333	2SK33	三菱	FM/VHF RF	J	N	D	-20	GDO	10m	150m	4-153A
334	2SK34	三菱	LF LN A	J	N	D	-50	GDO	10m	150m	4-153B
335	2SK37	NEC	FM RF/MX	J	N	D	-20	GDO	10m	100m	4-10
336	2SK38	三菱	烟感知器, DC	MOS	N	DE	20	DSX	20m	100m	
337	2SK38A	三菱	烟感知器, DC	MOS	N	DE	20	DSX	20m	100m	4-11
338	2SK39		C-MIC	J	N		-20	GDO			4-12
339	2SK39A		C-MIC	J	N		-20	GDO	0.5m	10m	4-12
340	2SK40	日立	LF LN A	J	N	D	-50	GDS	10m	100m	4-13
341	2SK41	三洋	FM RF/MIX	J	N	D	-18	GDS	10m	200m	4-57A
342	2SK41(旧)	三洋	FM RF/MIX	J	N	D	-18	GDO	10m	150m	4-14
343	2SK42		FM/AM RF	J	N	D	-10	GDO	10m	50m	4-15
344	2SK43		LF LN A	J	N	D	-30	GDO	5m	300m	4-16A
345	2SK43(S)		DC, LF A, A-SW	J	N	D	-30	GDO	5m	300m	4-16A
346	2SK44	三洋	LF LN A	J	N	D	-20	GDS	10m	100m	4-58A
347	2SK44(旧)	三洋	LF LN A	J	N	D	-20	GDS	10m	100m	
348	2SK45	NEC	DC, RF	J	N	D	-22	GDO	10m	100m	4-30
349	2SK46	三菱	C-MIC	J	N	D	-30	GDO	10m	150m	4-20
350	2SK47	NEC	LF A, RF	J	N	D	-20	GDO	10m	200m	4-18
351	2SK48	东芝	LF LN A	J	N	D	-20	GDS	10m	100m	4-2
352	2SK49	NEC	FM RF	J	N	D	-20	GDO	10m	72m	4-40
353	2SK50	松下	C-MIC	J	N	D	-10	GDO	2m	20m	4-80D
354	2SK54	日立	VHF RF/MIX	J	N	D	-15	GDO	10m	150m	4-37A
355	2SK55	日立	VHF RF/MIX	J	N	D	-18	GDO	10m	150m	4-37A
356	2SK56	松下	VHF RF	J	N	D	-10	GDS	10m	100m	4-80D
357	2SK57	NEC	RF	J	N	D	-20	GDO	10m	100m	
358	2SK58		DC, VHF	J	N	D	-27	GDO	10m	270m	4-49
359	2SK59	日立	C-MIC	J	N	D	-30	GDS	10m	50m	4-50
360	2SK60		LF PA	J(V)	N		-170	GDO	5	63	4-45
361	2SK61-LV	东芝	FM/VHF RF	J	N	D	-18	GDO	10m	200m	4-82A

5000种场效应管参数

更多彩电维修资料请到《[彩电维修资料网](http://www.tv160.net)》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing	
362	2SK63		A	J(V)	N		-120	GDO	200m	470m	4-51
363	2SK65	松下	LF Imp-C, C-MIC	J	N	D	-12	GDO	2m	20m	4-52
364	2SK66	松下	LF LN A	J	N	D	-55	GDO	10m	100m	4-80D
365	2SK67	NEC	C-MIC	J	N	D	-20	GDO	10m	80m	4-60
366	2SK67A	NEC	C-MIC	J	N	D	-20	GDO	10m	80m	4-60
367	2SK68	NEC	LF A	J	N	D	-50	GDO	10m	250m	4-53A
368	2SK68A	NEC	LF LN A	J	N	D	-50	GDO	10m	250m	4-53A
369	2SK69	NEC	LF D	J(V)	N		-140	GDO	100m	800m	4-41
370	2SK70	NEC	LF PA	J(V)	N		-100	GDO	10	100	4-42
371	2SK72	东芝	DC	J	N	D	-20	GDS	10m	200m	4-43
372	2SK73	松下	HV LF A	J	N	D	-200	GDO	100m	5	4-54
373	2SK79		A	J(V)	N		-120	GDO	200m	750m	4-55
374	2SK83	松下	VHF RF	J	N	D	-25	GDO	15m	100m	4-80B
375	2SK84	松下	LF LN A	J	N	D	-55	GDO	10m	100m	4-52
376	2SK85	NEC	X-Band LN A/OSC	GaAs/SbN	D		-10	GDO	100m	500m	4-56
377	2SK87(H)	日立	LF LN A	J	N	D	-50	GDS	10m	100m	4-61
378	2SK89	日立	LF PA								
379	2SK92	NEC	C-MIC	J	N	D	-20	GDO	10m	80m	4-18
380	2SK93		C-MIC	J	N	D	-20	GDO	0.5m	10m	4-62A
381	2SK94	NEC	LF A, A-SW	J	N	D	-50	GDO	10m	150m	4-78
382	2SK97		DC, LF A	J	N	D	-30	GDO	5m	210m	4-49
383	2SK103	NEC	C-MIC	J	N	D	-20	GDO	10m	80m	4-63
384	2SK104	NEC	RF, LF A	J	N	D	-30	GDO	10m	250m	4-40
385	2SK105	NEC	LF A	J	N	D	-50	GDO	10m	250m	4-53A
386	2SK106	日立	LF LN A	J	N	D			10m	300m	4-79A
387	2SK107		DC, VHF RF	J	N	D	-27	GDO	10m	250m	4-16A
388	2SK108	三菱	LF LN A, A-SW	J	N	D	-50	GDO	10m	300m	4-153B
389	2SK109	三菱	LF LN A	J	N	D	-50	GDO	10m	15/CH	4-84
390	2SK109A	三菱	LF LN A	J	N	D	-50	GDO	10m	15/CH	4-84
391	2SK110	三菱	LF LN A	J	N	D	-30	GDO	10m	900m	4-154
392	2SK111	三菱	LF LN A	J	N	D	-30	GDO	10m	0.2/CH	4-84
393	2SK112	东芝	DC LN A, Chop, S	J	N	D	-50	GDS	10m	250m	4-69
394	2SK113	东芝	A-SW, Chop SW	J	N	D	-50	GDS	10m	250m	4-69
395	2SK117	东芝	LF LN A	J	N	D	-50	GDS	10m	300m	4-82C
396	2SK118	东芝	C-MIC	J	N	D	-50	GDS	10m	100m	4-70A
397	2SK119	NEC	DC, A-SW	J	N	D	-30	GDO	10m	250m	4-71
398	2SK120		VHF RF/MIX	J	N	D	-15	GDO	10m	200m	4-64
399	2SK121		DC/LF LN A	J	N	D	-30	GDO	5m	300m	4-62B
400	2SK123	松下	LF Imp-C,C-MIC	J	N	D	-20	GDO	2m	200m	4-131
401	2SK124	NEC	X-Band LN A/OSC	GaAs/SbN	D		-8	GDO	100m	500m	4-56
402	2SK125		UHF RF/MIX	J	N	D	-35	GDO	10m	300m	4-62B
403	2SK127	松下	LF A	J	N	D	-50	GDO	20m	250m	4-80
404	2SK127A	松下	LF A	J	N	D	-80	GDS	20m	250m	4-80
405	2SK128	松下	LF LN A	J	N	D	-30	GDO	10m	250m	4-80A
406	2SK130	NEC	LF A, A-SW	J	N	D	-30	GDO	10m	250m	4-53A
407	2SK130A	NEC	LF LN A	J	N	D	-30	GDO	10m	250m	4-53A
408	2SK131	NEC	LF LN A	J	N	D	-30	GDO	10m	25/CH	4-109
409	2SK132	日立	LF PA	MOS	N	E	100	DSX	7	100	4-28A
410	2SK133	日立	LF PA, HS PSW	MOS	N	E	120	DSX	7	100	4-28A
411	2SK134	日立	LF PA, HS PSW	MOS	N	E	140	DSX	7	100	4-28A
412	2SK134(H)	日立	HS PSW	MOS	N	E	140	DSX	7	100	4-28A
413	2SK135	日立	LF PA, HS PSW	MOS	N	E	160	DSX	7	100	4-28A
414	2SK135(H)	日立	HS PSW	MOS	N	E	160	DSX	7	100	4-28A
415	2SK136	松下	LF LN A	J	N	D	-30	GDO	10m	250m	4-80A
416	2SK137	松下	LF LN A	J	N	D	-15	GDO	50m	100m	4-83
417	2SK137A	松下	LF LN A	J	N	D	-15	GDO	50m	100m	4-83
418	2SK138	NEC	X-Band RF/OSC	GaAs/SbN	D		5	DSX	100m	300m	4-100
419	2SK140	NEC	X-Band RF/OSC	GaAs/SbN	D		5	DSX	100m	300m	4-100
420	2SK141	NEC	DC, A-SW	J	N	D	-30	GDO	10m	250m	4-73
421	2SK141A	NEC	DC, A-SW	J	N	D	-30	GDO	10m	250m	4-73
422	2SK146	东芝	LF LN A	J	N	D	-40	GDS	10m	0.6/CH	4-85

5000种场效应管参数

更多彩电维修资料请到《[彩电视维修资料网](http://www.tv160.net)》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing	
423	2SK147	东芝	LF LN A	J	N	D	-40	GDS	10m	600m	4-74A
424	2SK148	松下	VHF RF	J	N	D	-25	GDS	10m	100m	4-101
425	2SK149	NEC	UHF RF/MIX	J	N	D	-20	GDO	10m	350m	4-102A
426	2SK150	东芝	LF LN A	J	N	D	-50	GDS	10m	0.2/CH	4-75
427	2SK151	日立	LF LN A	J	N	D	-40	GDO	10m	800m	4-97A
428	2SK152		HF/LF LN A	J	N	D	-15	GDO	5m	300m	4-62C
429	2SK154	松下	VHF RF	J	N	D	-20	GDO	10m	350m	4-80B
430	2SK155	松下	LF LN A	J	N	D	-20	GDO	30m	400m	4-80A
431	2SK156	三洋	C-MIC	J	N	D	-20	GDO	10m	100m	4-58A
432	2SK157	日立	LF A	J	N	D			10m	150m	4-87A
433	2SK158	松下	LF A	J	N	D	-55	GDS	10m	70m	4-103
434	2SK160	NEC	LF/VHF A	J	N	D	-30	GDO	10m	150m	4-78A
435	2SK160A	NEC	LF/VHF A	J	N	D	-50	GDO	10m	150m	4-78A
436	2SK161	东芝	FM/VHF RF	J	N	D	-18	GDO	10m	200m	4-70C
437	2SK162	NEC	LF LN A	J	N	D	-40	GDO	10m	400m	4-53A
438	2SK163	NEC	LF LN A	J	N	D	-50	GDO	10m	400m	4-53A
439	2SK165	松下		J	N	D	-15	GDO	5m	300m	4-80C
440	2SK168	日立	VHF RF/MIX/OSC	J	N	D	-30	GDO	10m	200m	4-89
441	2SK169	松下	LF LN A	J	N	D	-15	GDS	50m	400m	
442	2SK170	东芝	LF LN A	J	N	D	-40	GDS	10m	400m	4-82C
443	2SK171	三菱	LF LN A	J	N	D	-20	GDO	10m	0.2/CH	4-84
444	2SK175	日立	LF PA, HS PSW	MOS	N	E	180	DSX	8	125	4-28A
445	2SK176	日立	LF PA, HS PSW	MOS	N	E	200	DSX	8	125	4-28A
446	2SK176(H)	日立	RF PA, HS PSW	MOS	N	E	200	DSS	8	125	4-28A
447	2SK180		SW, RF PA	SIT	N	D	600	GDO	20	300	4-269
448	2SK181		SW, RF PA	SIT	N	D	800	GDO	20	300	4-269
449	2SK182, 182E		SW, RF PA	SIT	N	D	600	GDO	60	1000	4-271/E:270
450	2SK183, 183E		SW, RF PA	SIT	N	D	800	GDO	60	1000	4-271/E:270
451	2SK183H, 183HE		SW, RF PA	SIT	N	D	1200	GDO	60	1000	4-271/HE:270
452	2SK183V, 183VE		SW, RF PA	SIT	N	D	1500	GDO	60	1000	4-271/VE:270
453	2SK184	东芝	LF LN A	J	N	D	-50	GDS	10m	200m	4-70B
454	2SK185		LF LN A, RF	J	N	D	-30	GDO	5m	320m	4-86
455	2SK186	日立	LF LN A	J	N	D	40	DSX	10m	300m	4-79A
456	2SK187	日立	LF LN A	J	N	D	40	DSX	10m	300m	4-79A
457	2SK189	日立	LF LN A								
458	2SK190	日立	LF LN A	J	N	D	-40	DGO	10m	800m	4-97A
459	2SK191	日立	LF LN A	J	N	D	-15	DGO	10m	1	4-97A
460	2SK192	东芝	FM/VHF RF	J	N	D	-18	GDO	10m	200m	4-70C
461	2SK192A	东芝	FM/VHF RF	J	N	D	-18	DGO	10m	200m	4-70C
462	2SK193	NEC	FM RF	J	N	D	-20	GDO	10m	250m	4-104A
463	2SK194	NEC	LF LN A	J	N	D	-40	GDO	10m	0.4/CH	4-109
464	2SK195	NEC	FM RF	J	N	D	-20	GDO	10m	250m	4-40
465	2SK196(H)	日立	HF PA, HS PSW	MOS	N		160	DSS	500m	800m	4-121A
466	2SK197	日立	VHF RF/MIX	J	N	D	-18	O	10m	150m	4-87B
467	2SK198	松下	LF A	J	N	D	-30	GDO	10m	150m	4-105A
468	2SK199	松下	VHF RF	J	N	D	15	DSX	15m	100m	4-103
469	2SK201	NEC	C-X-Band A/OSC	GaAs	N	D	10	DSX	400m	1.3	4-120
470	2SK203	NEC	C-X-Band A/OSC	GaAs	N	D	10	DSX	180m	800m	4-120
471	2SK208	东芝	C-MIC	J	N	D	-50	DSX	10m	100m	4-105A
472	2SK209	东芝	LF LN A	J	N	D	-50	GDS	10m	150m	4-105A
473	2SK210	东芝	VHF RF	J	N	D	-18	GDS	10m	100m	4-105B
474	2SK211	东芝	FM/VHF RF	J	N	D	-18	GDO	10m	150m	4-105B
475	2SK212	三洋	FM RF	J	N	D	-20	GDO	10m	200m	4-58B
476	2SK213	日立	LF/HF PA, HS PSW	MOS	N	E	140	DSX	500m	30	4-116A
477	2SK214	日立	LF/HF PA, HS PSW	MOS	N	E	160	DSX	500m	30	4-116A
478	2SK214(K)	日立	RF PA, HS PSW	MOS	N	E	160	DSS	500m	30	4-116A
479	2SK215	日立	LF PA, HS PSW	MOS	N	E	180	DSX	500m	30	4-116A
480	2SK216	日立	LF PA, HS PSW	MOS	N	E	200	DSX	500m	30	4-116A
481	2SK216(K)	日立	RF PA, HS PSW	MOS	N	E	200	DSX	500m	30	4-116A
482	2SK217	日立	VHF RF	J	N	D	-30	GDO	10m	150m	4-87B
483	2SK218	松下		J	N	D	-15	GDO	5m	200m	4-80C

5000种场效应管参数

更多彩电维修资料请到《[彩电维修资料网](http://www.tv160.net)》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道	方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
484	2SK220(H)	日立	HF PA, HS PSW	MOS	N	E	160	DSS	8	100	4-28A
485	2SK221(H)	日立	HF PA, HS PSW	MOS	N	E	200	DSS	8	100	4-28A
486	2SK222	三洋	LF LN A	J	N	D	-40	GDS	10m	300m	4-57B
487	2SK223	三洋	HV D	J	N	D	-80	GDS	10m	400m	4-57B
488	2SK225	日立	LF PA	MOS	N		120	DSX	7	100	4-117A
489	2SK226	日立	LF PA	MOS	N		140	DSX	7	100	4-117A
490	2SK227	日立	LF PA	MOS	N		160	DSX	7	100	4-117A
491	2SK238	NEC	FM Tuner	J	N	D	-20	GDO	10m	150m	4-78B
492	2SK240	东芝	LF LN A	J	N	D	-40	GDS	10m	0.4/CH	4-110
493	2SK241	东芝	FM/VHF RF	MOS	N	DE	20	DSX	30m	200m	4-70C
494	2SK242	三洋	RF	J	N	D	-20	GDO	10m	150m	4-126B
495	2SK246	东芝	DC, Imp-C, CC	J	N	D	-50	GDS	10m	300m	4-82B
496	2SK247	松下	LN RF	J	N	D	-15	GDO	5m	150m	4-105A
497	2SK258(H)	日立	HF PA, HS SW	MOS	N	E	250	DSS	8	125	4-28A
498	2SK259(H)	日立	LF PA, HS SW	MOS	N	E	350	DSS	5	125	4-28A
499	2SK260(H)	日立	HF PA, HS SW	MOS	N	E	400	DSS	5	125	4-28A
500	2SK261	日立	LF PA		N						
501	2SK262	日立	LF PA		N						
502	2SK263	日立	LF PA		N						
503	2SK264	日立	LF PA		N						
504	2SK266	东芝	C-MIC, Imp-C	J	N	D	-15	GDO	10m	100m	4-155
505	2SK270	东芝	LF LN A	J	N	D	-40	GDS	10m	0.3/CH	4-75
506	2SK271	东芝	LF PA	MOS	N		140	DSX	8	120	4-118
507	2SK272	东芝	LF PA	MOS	N		140	DSX	7	100	4-119
508	2SK273	三菱	S-X-Band LN A	GaAs	N	D	8	DSX	100m	300m	4-122
509	2SK274	三菱	S-X-Band LN A	GaAs	N	D	8	DSX	100m	300m	4-122
510	2SK275	三菱	S-X-Band LN A	GaAs	N	D	8	DSX	100m	300m	4-122
511	2SK276	三菱	S-X-Band LN A	GaAs	N	D	6	DSX	80m	200m	4-122
512	2SK277	NEC	HC SW	MOS	N		350	DSS	7	100	4-108
513	2SK278	NEC	HC SW	MOS	N		400	DSS	7	100	4-108
514	2SK279	三菱	S-X-Band PA	GaAs	N	D	8	DSX	250m	1	4-122
515	2SK280	NEC	X-Ku-Band LN A	GaAs	N	D	5	DSX	100m	270m	4-123
516	2SK281	NEC	VHF-C-Band LN A	GaAs	N	D	5	DSX	120m	300m	4-123
517	2SK283	三洋	HV D	J	N	D	-80	GDS	10m	150m	4-126A
518	2SK286	日立	LF/HF PA, HS PSW	MOS	N	E	60	DSX	8	100	4-117A
519	2SK287(K)	日立	RF PA	MOS	N	E	60	DSS	8	100	4-117A
520	2SK288(K)	日立	RF PA	MOS	N	E	80	DSS	8	100	4-117A
521	2SK289(H)	日立	RF PA	MOS	N	E	80	DSS	8	100	4-28A
522	2SK290(H)	日立	RF PA	MOS	N	E	100	DSS	8	100	4-28A
523	2SK291	日立	RF LN A	J	N	D	-15	GDO	5m	300m	4-37B
524	2SK292	NEC	FM Tuner	J	N	D	-20	GDO	10m	200m	4-104A
525	2SK293	NEC	HV HS HC SW	MOS	N	E	300	DSS	7	100	4-108
526	2SK293A	NEC	HV HS HC SW	MOS	N	E	300	DSS	7	100	4-108
527	2SK294	日立	HS PSW	MOS	N	E	80	DSS	5	30	4-116B
528	2SK295	日立	HS PSW	MOS	N	E	100	DSS	5	30	4-116B
529	2SK296	日立	HS PSW	MOS	N	E	300	DSS	1	30	4-116B
530	2SK298	日立	HS PSW	MOS	N	E	400	DSS	8	100	4-28B
531	2SK299	日立	HS PSW	MOS	N	E	450	DSS	8	100	4-28B
532	2SK300		Video A, VHF RF	J	N	D	-15	GDO	5m	150m	4-179
533	2SK301	松下	LF A, SW	J	N	D	-55	GDO	10m	250m	4-80A
534	2SK302	东芝	VHF RF	MOS	N	D	20	DSX	30m	150m	4-105B
535	2SK303	三洋	LF PA	J	N	D	-30	GDS	10m	150m	4-126A
536	2SK304	三洋	LF PA	J	N	D	-30	GDS	10m	150m	4-58A
537	2SK308	日立	HS PSW	MOS	N	E	120	DSS	10	100	4-28B
538	2SK310	日立	HS PSW	MOS	N	E	400	DSS	3	40	4-116B
539	2SK311	日立	HS PSW	MOS	N	E	450	DSS	3	40	4-116B
540	2SK312	日立	HS PSW	MOS	N	E	400	DSS	12	125	4-28B
541	2SK313	日立	HS PSW	MOS	N	E	450	DSS	12	125	4-28B
542	2SK314	NEC	LF LN A	J	N	D	-40	GDO	10m	250m	4-73
543	2SK315	三洋	FM Tuner	J	N	D	-20	GDO	10m	200m	4-58B
544	2SK316	松下		J	N	D	-10	GDO	5m	200m	4-105A

5000种场效应管参数

更多彩电维修资料请到《[彩电维修资料网](http://www.tv160.net)》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道	方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
545	2SK317	日立	HF/VHF PA	MOS	N	E	180	DSS	8	120	4-129
546	2SK318	日立	HF/VHF PA	MOS	N	E	180	DSS	4	70	4-129
547	2SK319	日立	HS PSW	MOS	N	E	400	DSS	5	50	4-116B
548	2SK320	日立	HS PSW	MOS	N	E	450	DSS	5	50	4-116B
549	2SK321	松下		J	N	D	-15	GDO	5m	200m	4-105A
550	2SK322	日立	HF A	J	N	D	-15	GDO	5m	150m	4-87A
551	2SK323	日立	LF A	J	N	D			10m	150m	4-87A
552	2SK324	东芝	HS HV SW	MOS	N	E	400	DSX	10	120	4-134
553	2SK325	东芝	HS HV SW	MOS	N	E	450	DSX	10	120	4-134
554	2SK330	东芝	HF A, CC, A-SW	J	N	D	-50	GDS	10m	200m	4-70A
555	2SK331	三洋	C-MIC	J	N	D	-20	GDO	10m	100m	4-127
556	2SK332	三洋	Diff	J	N	D	-40	GDS	10m	0.2/CH	4-107
557	2SK333	三洋	Diff	J	N	D	-80	GDS	10m	0.2/CH	4-107
558	2SK334	三洋	C-MIC	J	N	D	-20	GDO	10m	100m	4-106
559	2SK336	三洋	A-SW	MOS	N	E	50	DSS	400m	600m	4-57A
560	2SK337	NEC	HV SW	MOS	N	E	500	DSS	±0.1	10	4-135
561	2SK343	日立	LF PA, HS PSW	MOS	N	E	140	DSS	8	100	4-117B
562	2SK344	日立	LF PA, HS PSW	MOS	N	E	160	DSS	8	100	4-117B
563	2SK345	日立	LF PA, HS PSW	MOS	N	E	40	DSS	5	30	4-116B
564	2SK346	日立	HS PSW	MOS	N	E	60	DSS	5	30	4-116B
565	2SK347(L)	日立	PF PA, HS PSW	MOS	N	E	400	DSS	1	10	4-150
566	2SK349	日立	HS PSW	MOS	N	E	400	DSS	10	100	4-149
567	2SK350	日立	HS PSW	MOS	N	E	450	DSS	10	100	4-149
568	2SK351	日立	HS PSW	MOS	N	E	800	DSS	5	125	4-28B
569	2SK352	日立	HS PSW	MOS	N	E	250	DSS	300m	8	4-136A
570	2SK353	NEC	C-Ku-Band LN A	GaAs	N	D	5	DSX	120m	270m	4-123
571	2SK354	NEC	VHF-C-Band LN A	GaAs	N	D	5	DSX	150m	300m	4-137
572	2SK354A	NEC	VHF-C-Band LN A	GaAs	N	D	5	DSX	150m	300m	4-9
573	2SK355	东芝	HS HV SW	MOS	N	E	150	DSX	12	120	4-134
574	2SK356	东芝	HS HV SW	MOS	N	E	250	DSX	12	120	4-134
575	2SK357	东芝	HS HV SW	MOS	N	E	150	DSX	5	40	4-138
576	2SK358	东芝	HS HV SW	MOS	N	E	250	DSX	5	40	4-138
577	2SK359	日立	VHF RF	MOS	N	D	20	DSX	30m	400m	4-37A
578	2SK360	日立	VHF RF	MOS	N	D	20	DSX	30m	150m	4-87D
579	2SK362	东芝	LF A, A-SW	J	N	D	-50	GDS	10m	300m	4-82C
580	2SK363	东芝	LF A, A-SW	J	N	D	-40	GDS	10m	400m	4-82C
581	2SK364	东芝	LF A, A-SW	J	N	D	-40	GDS	10m	400m	4-82C
582	2SK365	东芝	LF A, A-SW	J	N	D	-50	GDS	10m	200m	4-70B
583	2SK366	东芝	LF A, A-SW	J	N	D	-40	GDS	10m	200m	4-70B
584	2SK367	东芝	LF HV A, CC	J	N	D	-100	GDS	10m	200m	4-70A
585	2SK368	东芝	LF HV A, CC	J	N	D	-100	GDS	10m	150m	4-105A
586	2SK369	东芝	LF LN A	J	N	D	-40	GDS	10m	400m	4-82C
587	2SK370	东芝	LF LN A	J	N	D	-40	GDS	10m	200m	4-70B
588	2SK371	东芝	LF LN A	J	N	D	-40	GDS	10m	200m	4-70B
589	2SK372	东芝	LF A, A-SW	J	N	D	-40	GDS	10m	200m	4-70B
590	2SK373	东芝	LF HV A, CC	J	N	D	-100	GDS	10m	400m	4-82B
591	2SK374	松下	LF A, SW	J	N	D	-55	GDO	10m	200m	4-105A
592	2SK375(L)	日立	HS PSW	MOS	N	D	300	DSS	1	10	4-150
593	2SK376	三洋	C-MIC	J	N	D	-20	GDO	10m	100m	4-156
594	2SK377	三洋	C-MIC	J	N	D	-20	GDO	10m	100m	4-127
595	2SK378	松下	UHF LN A	GaAs	N	D	5	DSX	130m	350m	4-91A
596	2SK379	松下	SW-Reg, DDC	MOS	N	E	400	DSS	8	100	4-140
597	2SK380	松下	SW Reg, DDC	MOS	N	E	450	DSS	8	100	4-140
598	2SK381	三菱	LF A, A-SW	J	N	D	-50	GDO	10m	300m	4-151
599	2SK382	日立	HS PSW	MOS	N	E	500	DSS	2	30	4-116B
600	2SK383	日立	HS PSW	MOS	N	E	100	DSS	10	50	4-116B
601	2SK384(L)	日立	HS PSW	MOS	N	E	500	DSS	300m	10	4-150
602	2SK385	东芝	HS HV SW	MOS	N	E	400	DSX	10	120	4-141
603	2SK386	东芝	HS HV SW	MOS	N	E	450	DSX	10	120	4-141
604	2SK387	东芝	HS HV SW	MOS	N	E	150	DSX	12	150	4-141
605	2SK388	东芝	HS HV SW	MOS	N	E	250	DSX	12	150	4-141

5000种场效应管参数

更多彩电维修资料请到《[彩电维修资料网](http://www.tv160.net)》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道	方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
606	2SK389	东芝	LF LN A,Diff	J	N	D	-50	GDS	10m	200m	4-148
607	2SK398	日立	RF PA, HS PSW	MOS	N	E	100	DSS	10	100	4-28B
608	2SK399	日立	HS PSW	MOS	N	E	100	DSS	10	100	4-149
609	2SK400	日立	HS PSW	MOS	N	E	200	DSS	8	100	4-149
610	2SK401	日立	HS PSW	MOS	N	E	250	DSS	10	100	4-28B
611	2SK402	日立	HS PSW	MOS	N	E	400	DSS	8	100	4-149
612	2SK403	日立	HS PSW	MOS	N	E	450	DSS	8	100	4-149
613	2SK404	三洋	LF/HF A	J	N	D	20	DSS	10m	200m	4-157A
614	2SK405	东芝	LF PA	MOS	N	E	160	DSS	8	100	4-119
615	2SK406	NEC	C-Ku-Band LN A	GaAs	N	D	5	DSX	120m	270m	4-123
616	2SK407	NEC	C-Ku-Band LN A	GaAs	N	D	5	DSX	120m	270m	4-123
617	2SK408	日立	HF/VHF PA	MOS	N	E	180	DSS	2	30	4-116A
618	2SK409	日立	HF/VHF PA	MOS	N	E	180	DSS	2	30	4-116C
619	2SK410	日立	HF/VHF PA	MOS	N	E	180	DSS	8	120	4-129
620	2SK411	日立	RF PA, HS PSW	MOS	N	E	600	DSS	5	100	4-28B
621	2SK412	日立	HS PSW	MOS	N	E	250	DSS	10	100	4-149
622	2SK413	日立	HS PSW	MOS	N	E	140	DSS	8	100	4-149
623	2SK414	日立	HS PSW	MOS	N	E	160	DSS	8	100	4-149
624	2SK415	日立	HS PSW	MOS	N	E	800	DSS	3	80	4-149
625	2SK416(L)	日立	HS PSW	MOS	N	E	40	DSS	2	10	4-150
626	2SK417	东芝	HS HC SW	MOS	N	E	60	DSX	10	60	4-142
627	2SK418	东芝	HS HV SW	MOS	N	E	400	DSX	2	50	4-142
628	2SK419	东芝	HS HV SW	MOS	N	E	450	DSX	2	50	4-142
629	2SK420	东芝	HS HV SW	MOS	N	E	400	DSX	5	60	4-142
630	2SK421	东芝	HS HV SW	MOS	N	E	450	DSX	5	60	4-142
631	2SK422	东芝	HS SW	MOS	N	E	60	DSX	700m	900m	4-74B
632	2SK423	东芝	HS SW	MOS	N	E	100	DSX	500m	900m	4-74B
633	2SK424	NEC	HV HC SW	MOS	N	E	600	DSS	3	100	4-108
634	2SK425	NEC	LF A	J	N	D	-50	GDO	10m	200m	4-78A
635	2SK426	NEC	LF A	J	N	D	-50	GDO	10m	200m	4-78A
636	2SK427	三洋	AM Tuner, RF	J	N	D	-15	GDS	10m	200m	4-157A
637	2SK428	日立	HS PSW	MOS	N	E	60	DSS	10	50	4-116B
638	2SK429(L)	日立	HS PSW	MOS	N	E	100	DSS	3	20	4-150
639	2SK430(L)	日立	HS PSW	MOS	N	E	150	DSS	3	20	4-150
640	2SK431	日立	LF LN A	J	N	D	40	DSX	10m	150m	4-87E
641	2SK433	三菱	LF A, A-SW	J	N	D	-50	GDO	10m	150m	4-152
642	2SK435	日立	LF/HF A	J	N	D	22	DSX	10m	300m	4-37B
643	2SK436	三洋	LF/HF A	J	N	D	-15	GDS	10m	150m	4-126A
644	2SK437	松下	SHF LN A	GaAs	N	D	-6	GDO	120m	270m	4-103
645	2SK437(H)	松下	SHF LN A	GaAs	N	D	-6	GDO	120m	270m	4-103
646	2SK438	松下	SHF LN A	GaAs	N	D	-6	GDO	150m	300m	4-103
647	2SK439	日立	VHF RF	MOS	N	D	20	DSX	±1m	300m	4-8A
648	2SK440	日立	HS PSW	MOS	N	E	200	DSS	6	40	4-116B
649	2SK441	日立	HS PSW	MOS	N	E	500	DSS	300m	750m	4-121B
650	2SK442	东芝	LF PA, HS SW	MOS	N	E	70	DSS	10	30	4-138
651	2SK443	三洋		J	N	D	-15	GDS	10m	200m	4-126A
652	2SK444	三洋		J	N	D	-15	GDS	10m	200m	4-157A
653	2SK445	三洋		J	N	D	-15	GDS	10m	300m	4-57A
654	2SK446	NEC	SW	MOS	N	E	20	DSS	±2	20	4-158
655	2SK447	东芝	HS PSW, Motor-D	MOS	N	E	250	DSS	±15	150	4-141
656	2SK448	NEC	HC SW	MOS	N	E	250	DSS	±10	120	4-108
657	2SK449	NEC	HC SW	MOS	N	E	450	DSS	±8	120	4-108
658	2SK453	NEC	RF PA	MOS	N	E	100	DSS	±10	120	4-159
659	2SK454	NEC	RF PA	MOS	N	E	200	DSS	±8	120	4-159
660	2SK455	东芝	C-MIC, Imp-C	J	N	D	-20	GDO	10m	100m	4-160
661	2SK456	东芝	C-MIC, Imp-C	J	N	D	-20	GDO	10m	100m	4-155
662	2SK457	日立	SHF/UHF LN A	GaAs/M	N	D	6	DSX	100m	200m	4-175B
663	2SK458	NEC	SW	MOS	N	E	150	DSS	±1	16	4-161
664	2SK459	NEC	SW	MOS	N	E	200	DSS	±10	60	4-162
665	2SK462	NEC	SW	MOS	N	E	60	DSS	±2	20	4-163
666	2SK463	NEC	SW	MOS	N	E	60	DSS	±5	40	4-164

5000种场效应管参数

更多彩电维修资料请到《彩电维修资料网》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道	方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
667	2SK464	NEC	SW	MOS	N	E	60	DSS	±10	60	4-164
668	2SK468	NEC	SW	MOS	N	E	100	DSS	±2	20	4-163
669	2SK470	NEC	SW	MOS	N	E	100	DSS	±10	60	4-164
670	2SK477	NEC	SW	MOS	N	E	250	DSS	±8	60	4-162
671	2SK479	NEC	SW	MOS	N	E	250	DSS	±15	100	4-180
672	2SK482	NEC	SW	MOS	N	E	450	DSS	±5	40	4-164
673	2SK484	NEC	SW	MOS	N	E	450	DSS	±8	100	4-180
674	2SK490	NEC	SW	MOS	N	E	400	DSS	±10	100	4-180
675	2SK492	三菱	LF A,A-SW	J	N	D	-50	GDO	10m	150m	4-152
676	2SK493	三洋		J	N	D	-15	GDS	10m	300m	4-165A
677	2SK494	日立	LF/HF A	J	N	D	22	DSX	10m	300m	4-8B
678	2SK505	NEC		J	N	D	-15	GDO	5m	400m	4-53B
679	2SK507	NEC		J	N	D	-15	GDO	5m	350m	4-104B
680	2SK508	NEC		J	N	D	-15	GDO	5m	200m	4-78A
681	2SK511	日立	HS PSW, RF PA	MOS	N	E	250	DSS	300m	8	4-136
682	2SK512	日立	HS PSW	MOS	N	E	500	DSS	12	125	4-28B
683	2SK513	日立	HS PSW	MOS	N	E	800	DSS	3	60	4-116B
684	2SK514	NEC	LF A,A-SW, VR	J	N	D	-50	GDO	10m	250m	4-104B
685	2SK515	NEC	LF A, VR, A-SW	J	N	D	-50	GDO	10m	150m	4-275B
686	2SK518	NEC	RF	J	N	D	-30	GDO	10m	400m	4-53A
687	2SK519	NEC	RF	J	N	D	-30	GDO	10m	350m	4-104B
688	2SK520	NEC	RF	J	N	D	-30	GDO	10m	200m	4-78A
689	2SK521	日立	VHF RF/MIX/OSC	J	N	D	-18	GDO	10m	150m	4-181
690	2SK522	日立	VHF RF/MIX/OSC	J	N	D	-30	GDO	10m	200m	4-181
691	2SK523	NEC	LF LN A	J	N	D	-50	GDO	10m	400m	4-53B
692	2SK525	东芝	HS HV SW	MOS	N	E	150	DSX	10	40	4-182
693	2SK526	东芝	HS HV SW	MOS	N	E	250	DSX	10	40	4-182
694	2SK527	东芝	DDC	MOS	N	E	60	DSX	10	40	4-182
695	2SK528	东芝	HS HV SW	MOS	N	E	400	DSX	2	30	4-182
696	2SK529	东芝	DDC	MOS	N	E	450	DSX	2	30	4-182
697	2SK530	东芝	DDC	MOS	N	E	400	DSX	5	40	4-182
698	2SK531	东芝	DDC	MOS	N	E	450	DSX	5	40	4-182
699	2SK532	东芝	DDC	MOS	N	E	60	DSX	12	40	4-182
700	2SK533	NEC	LF LN A	J	N	D	-50	GDO	10m	400m	4-53B
701	2SK534	日立	HS PSW	MOS	N	E	800	DSS	5	100	4-149
702	2SK535(L)	日立	HS PSW	MOS	N	E	400	DSS	1.5	20	4-150
703	2SK536	三洋	A-SW	MOS	N	E	50	DSX	100m	200m	4-126B
704	2SK537	东芝	HS HV SW	MOS	N	E	900	DSX	1	60	4-183
705	2SK538	东芝	SW Reg	MOS	N	E	900	DSX	3	100	4-184
706	2SK539	东芝	SW Reg	MOS	N	E	900	DSX	5	150	4-141
707	2SK541	日立		J	N	D	12	DSX	±1m	150m	4-185A
708	2SK542	NEC	SW	MOS	N	E	150	DSS	±2	25	4-164
709	2SK543	三洋	FM Tuner, VHF RF	MOS	N	DE	20	DS	20m	200m	4-126A
710	2SK544	三洋	FM Tuner, VHF RF	MOS	N	DE	20	DS	30m	300m	4-157B
711	2SK545	三洋		J	N	D	-40	GDS	10m	100m	4-126A
712	2SK546	三洋		J	N	D	-40	GDS	10m	100m	4-157A
713	2SK549	日立	HS PSW	MOS	N	E	60	DSS	10	50	4-116B
714	2SK551	日立	HS PSW	MOS	N	E	120	DSS	10	50	4-116B
715	2SK552	日立	HS PSW	MOS	N	E	450	DSS	5	50	4-116B
716	2SK553	日立	HS PSW	MOS	N	E	500	DSS	5	50	4-116B
717	2SK554	日立	HS PSW	MOS	N	E	450	DSS	7	60	4-116B
718	2SK555	日立	HS PSW	MOS	N	E	500	DSS	7	60	4-116B
719	2SK556	日立	HS PSW	MOS	N	E	450	DSS	12	100	4-149
720	2SK557	日立	HS PSW	MOS	N	E	500	DSS	12	100	4-149
721	2SK559	日立	HS PSW	MOS	N	E	450	DSS	15	100	4-149
722	2SK560	日立	HS PSW	MOS	N	E	500	DSS	15	100	4-149
723	2SK561	日立	HS PSW	MOS	N	E					
724	2SK562	富士电	SW Reg, DDC	MOS	N	E	50	DSX	39	125	4-186
725	2SK564	富士电	SW Reg, DDC	MOS	N	E	100	DSX	32	125	4-186
726	2SK565	富士电	SW Reg, DDC	MOS	N	E	500	DSX	9.6	125	4-186
727	2SK566	富士电	SW Reg, DDC	MOS	N	E	800	DSX	2.9	78	4-186

5000种场效应管参数

更多彩电维修资料请到《[彩电维修资料网](http://www.tv160.net)》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道	方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
728	2SK568	东芝	HS PSW	MOS	N	E	450	DSS	±8	150	4-141
729	2SK569	NEC	C-Ku-Band LN A	GaAs	N	D	-6	GDO	60m	270m	4-123
730	2SK570	NEC	C-Ku-Band LN A	GaAs	N	D	-6	GDO	0.3m	240m	4-123
731	2SK570S	NEC	C-Ku-Band LN A	GaAs	N	D	-6	GDO	0.3m	240m	4-123
732	2SK572	东芝	DDC	MOS	N	E	150	DSS		100	
733	2SK573	东芝	DDC	MOS	N	E	250	DSS		100	
734	2SK575		~Ku-Band LN A	GaAs	N	D	5	DSX	80m	270m	4-187
735	2SK578	东芝	HS PSW	MOS	N	E	150	DSS	±15	120	4-141
736	2SK579(L)(日立	HS PSW	MOS	N	E	450	DSS	1.5	20	4-150
737	2SK580(L)(日立	HS PSW	MOS	N	E	500	DSS	1.5	20	4-150
738	2SK581		HF/LF LN A	J	N	D	-30	GDO	5m	300m	4-72
739	2SK582		V/UHF RF/MIX	J	N	D	-30	GDO	10m	300m	4-72
740	2SK583	三洋	A-SW, LPF	MOS	N	D	50	DS	200m	600m	4-165A
741	2SK585		~X-Band LN A	GaAs	N	D	5	DSX	120m	300m	4-188
742	2SK586		~Ku-Band LN A	GaAs	N	D	5	DSX	80m	270m	4-187
743	2SK587		~X-Band LN A	GaAs	N	D	5	DSX	80m	270m	4-188
744	2SK590	东芝	V/UHF LN A	GaAs	N	D	10	DSX	80m	200m	4-125B
745	2SK591	NEC	SW	MOS	N	E	60	DSS	±15	35	4-274
746	2SK593	松下	RF LN A	GaAs	N	D	5	DSX	1m	350m	4-139A
747	2SK595	三洋	C-MIC	J	N	D	-20	GDO	10m	100m	4-106
748	2SK596	三洋	C-MIC	J	N	D	-20	GDO	10m	100m	4-156
749	2SK597	三洋	C-MIC	J	N	D	-20	GDO	10m	100m	4-127
750	2SK600	日立	HS PSW	MOS	N	D	60	DSS	25	75	4-116B
751	2SK601	松下	SW	MOS	N	E	80	DS	500m	1	4-189
752	2SK602	松下	RF PA, SW	MOS	N	E	800	DSS	1	40	4-190
753	2SK603	松下	RF PA, SW	MOS	N	E	800	DSS	3	80	4-191
754	2SK604	松下	RF PA, SW	MOS	N	E	800	DSS	5	80	4-191
755	2SK606	松下	RF	J	N	D	-30	GDO	10m	400m	4-80B
756	2SK607	松下	RF	J	N	D	-30	GDO	10m	200m	4-192A
757	2SK608	松下	RF	J	N	D	-30	GDO	10m	200m	4-193A
758	2SK609	NEC	C-Ku-Band LN A	GaAs	N	D	-6	GDO	120m	270m	4-194
759	2SK610	松下	RF PA, SW	MOS	N	E	400	DSS	3	80	4-191
760	2SK611, 61	NEC	SW	MOS	N	E	100	DSS	±1	10	4-276/Z:281
761	2SK612, 612	NEC	SW	MOS	N	E	100	DSS	±2	20	4-276/Z:281
762	2SK613			J	N	D	-15	GDO	5m	150m	4-179
763	2SK614	松下	SW	MOS	N	E	80	DS	500m	750m	4-132
764	2SK615	松下	SW	MOS	N	E	80	DS	500m	1	4-195
765	2SK616	富士电	SW Reg, DDC	MOS	N	E	200	DSX	22	125	4-186
766	2SK617	松下	RF PA, SW	MOS	N	E	800	DSS	1	40	
767	2SK618	东芝	V/UHF LN A	GaAs	N	D	10	DSX	80m	150m	4-105C
768	2SK619	日立		MOS	N	E	70	DSS	300m	1	4-136B
769	2SK620	松下	SW	MOS	N	E	50	DSS	100m	150m	4-193B
770	2SK621	松下	SW	MOS	N	E	20	DS	100m	150m	4-193B
771	2SK622	日立	HS PSW	MOS	N	E	150	DSS	20	120	4-149
772	2SK623	日立	HS PSW	MOS	N	E	250	DSS	20	120	4-149
773	2SK624	松下	LF Imp-C	J	N	D	-20	GDO	2m	200m	4-192B
774	2SK625	东芝	C-MIC, Imp-C	J	N	D	-20	GDO	10m	100m	4-105A
775	2SK626	松下	RF PA, SW	MOS	N	E	30	DSS	20	80	4-191
776	2SK627	松下	RF PA, SW	MOS	N	E	50	DSS	20	80	4-191
777	2SK628	松下	RF PA, SW	MOS	N	E	100	DSS	5	40	4-190
778	2SK629	松下	RF PA, SW	MOS	N	E	100	DSS	20	80	4-191
779	2SK630	松下	RF PA, SW	MOS	N	E	160	DSS	5	40	4-191
780	2SK631	松下	RF PA, SW	MOS	N	E	160	DSS	10	80	4-191
781	2SK632	松下	RF PA, SW	MOS	N	E	200	DSS	5	40	4-191
782	2SK633	松下	RF PA, SW	MOS	N	E	200	DSS	10	80	4-191
783	2SK634	松下	RF PA, SW	MOS	N	E	400	DSS	10	80	4-191
784	2SK635	松下	RF PA, SW	MOS	N	E	500	DSS	3	40	4-191
785	2SK636	松下	RF PA, SW	MOS	N	E	500	DSS	8	80	4-191
786	2SK637	松下	RF PA, SW	MOS	N	E	500	DSS	10	80	4-191
787	2SK638	松下	RF PA, SW	MOS	N	E	800	DSS	3	80	4-196
788	2SK641	日立	HS PSW	MOS	N	E	450	DSS	10	100	4-149

5000种场效应管参数

更多彩电维修资料请到《[彩电视维修资料网](http://www.tv160.net)》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道	方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
789	2SK642	日立	HS PSW	MOS	N	E	500	DSS	10	100	4-149
790	2SK643	东芝	HS SW, DDC	MOS	N	E	450	DSX	10	125	4-184
791	2SK644	东芝	HS SW, DDC	MOS	N	E	500	DSX	10	125	4-184
792	2SK645	东芝	C-MIC, Imp-C	J	N	D	-15	GDO	10m	100m	4-155
793	2SK646	日立	HS PSW, Hout	MOS	N	E	1200	DSS	4	125	4-28B
794	2SK647	松下	RF LN A	SB	N	D	-6	GDO	120m	270m	4-209
795	2SK648	松下	Ku-Band LN	GaAs/MI	N	D	-6	GDO	120m	200m	4-210
796	2SK649	松下	Ku-Band PA/OSC	GaAs/MI	N	D	-6	GDO	100m	200m	4-210
797	2SK650	松下	RF LN A	SB	N	D	-6	GDO	120m	200m	4-211
798	2SK651	松下	RF LN A	SB	N	D	-6	GDO	150m	200m	4-211
799	2SK652	松下	LF A, SW	J	N	D	-55	GDO	10m	300m	4-213B
800	2SK653	松下		GaAs/MI	N	D	5	DS	50m	200m	4-212
801	2SK654, 65	NEC	SW	MOS	N	E	100	DSS	±1	10	4-276/Z:281
802	2SK655	松下	SW	MOS	N	E	50	DSS	100m	200m	4-213A
803	2SK656	松下	SW	MOS	N	E	50	DS	100m	200m	4-213A
804	2SK657	松下	SW	MOS	N	E	50	DSS	100m	400m	4-214
805	2SK658	松下	SW	MOS	N	E	20	DS	100m	400m	4-214
806	2SK659	NEC	SW	MOS	N	E	60	DSS	±12	35	4-274
807	2SK660	NEC	ECM Imp-C	J	N	D	-20	GDO	10m	100m	4-104B
808	2SK661	NEC	C-MIC Imp-C	J	N	D	-20	GDO	10m	80m	4-88
809	2SK662	松下	LF A	J	N	D	-30	GDO	10m	150m	4-233
810	2SK663	松下	LF A, SW	J	N	D	-55	GDO	10m	150m	4-233
811	2SK664	松下	SW	MOS	N	E	50	DSS	100m	150m	4-233
812	2SK665	松下	SW	MOS	N	E	20	DS	100m	150m	4-233
813	2SK666	日立	V/UHF A	GaAs/MI	N	D	4	DS	150m	200m	4-175B
814	2SK667	松下	SW	MOS	N	E	400	DSS	8	80	4-191
815	2SK668	日立	U/SHF LN A	GaAs/MI	N	D	6	DS	100m	150m	4-199B
816	2SK669	三洋	HS SW, A-SW, LPI	MOS	N	D	50	DS	100m	200m	4-157A
817	2SK671		~X-Band RF/MIX	GaAs	N	D	5.5	DSX	120m	300m	4-188
818	2SK672	东芝	HS SW, DDC	MOS	N	E	60	DSX	10	40	4-183
819	2SK673	东芝	HS SW, DDC	MOS	N	E	60	DSX	15	75	4-183
820	2SK674	东芝	HS SW, DDC	MOS	N	D	60	DSX	25	100	4-183
821	2SK676		~X-Band RF/MIX	GaAs	N	D	5	DSX	70m	340m	4-187
822	2SK676H5		MW LN A	GaAsHE	N	D	5	DS	70m		
823	2SK677		~X-Band RF/MIX	GaAs	N	D	5	DSX	100m	340m	4-187
824	2SK677H5		MW LN A	GaAsHE	N	D	5	DS	100m		
825	2SK678	东芝	HS SW, DDC	MOS	N	E	500	DSX	13	150	4-141
826	2SK679	NEC	SW	MOS	N	E	30	DSS	±0.5	750m	4-53C
827	2SK679A	NEC	HS SW, Motor-D	MOS	N	E	30	DSS	±0.5	750m	4-53C
828	2SK680	NEC	SW	MOS	N	E	30	DSS	±1	1	4-216A
829	2SK680A	NEC	HS SW, Motor-D	MOS	N	E	30	DSS	±1	2	4-216
830	2SK681	NEC	SW	MOS	N	E	30	DSS	±1	1	4-217
831	2SK681A	NEC	HS SW, Motor-D	MOS	N	E	30	DSS	±1	1	4-217
832	2SK682	日立	HS PSW	MOS	N	E	450	DSS	12	100	4-149
833	2SK683	日立	HS PSW	MOS	N	E	500	DSS	12	100	4-149
834	2SK684	日立	HS PSW	MOS	N	E	800	DSS	7	100	4-149
835	2SK685	日立	HS PSW	MOS	N	E	1000	DSS	5	100	4-149
836	2SK686	三洋	HS PSW	MOS	N	E	60	DSX	5	40	4-242
837	2SK687	三洋	HS PSW	MOS	N	E	60	DSX	10	60	4-242
838	2SK688	三洋	HS PSW	MOS	N	E	60	DSX	15	60	4-242
839	2SK689	松下	RF LN A	SB	N	D	-6	GDO	70m	200m	4-218
840	2SK690	松下	UHF PA	GaAs/MI	N	D	10	DS	500m	1	4-189
841	2SK691	松下	RF PA	SB	N	D	-20	GDO	3	6	4-219
842	2SK692	NEC	C-MIC Imp-C	J	N	D	-20	GDO	10m	100m	4-104B
843	2SK693	东芝	HS SW, DDC	MOS	N	E	450	DSX	13	150	4-141
844	2SK694	东芝	HS SW, DDC	MOS	N	E	500	DSX	12	150	4-141
845	2SK695	日立	HS PSW	MOS	N	E	800	DSS	5	100	4-149
846	2SK696	日立	HS PSW	MOS	N	E	1000	DSS	3	100	4-149
847	2SK697	松下	RF LN A	SB	N	D	-5	GDO	50m	200m	4-212
848	2SK698	NEC	SW	MOS	N	E	450	DSS	±10	120	4-180
849	2SK699	NEC	SW	MOS	N	E	100	DSS	±2	15	4-135

5000种场效应管参数

更多彩电维修资料请到《[彩电视维修资料网](http://www.tv160.net)》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道	方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
850	2SK700	NEC	SW	MOS	N	E	80	DSS	±2	15	4-135
851	2SK701	NEC	SW	MOS	N	E	60	DSS	±2	15	4-135
852	2SK702	NEC	SW	MOS	N	E	100	DSS	±5	50	4-164
853	2SK703	NEC	SW	MOS	N	E	100	DSS	±5	35	4-274
854	2SK704	NEC	SW	MOS	N	E	60	DSS	±5	50	4-164
855	2SK705	NEC	SW	MOS	N	E	60	DSS	±5	35	4-274
856	2SK707	NEC	SW	MOS	N	E	250	DSS	±25	120	4-180
857	2SK708	东芝									
858	2SK709	东芝	LF/HF A	J	N	D	-20	GDS	10m	300m	4-82A
859	2SK710	东芝	LF/HF A	J	N	D	-20	GDS	10m	200m	4-70B
860	2SK711	东芝	LF/HF A	J	N	D	-20	GDS	10m	150m	4-105A
861	2SK712	日立	HS PSW	MOS	N	E	120	DSS	10	25	4-236
862	2SK713	日立	HS PSW	MOS	N	E	450	DSS	4	25	4-236
863	2SK714	日立	HS PSW	MOS	N	E	500	DSS	4	25	4-236
864	2SK715	三洋	AM Tuner, RF	J	N	D	-15	GDS	10m	300m	4-157A
865	2SK719	NEC	SW	MOS	N	E	900	DSS	±5	120	4-180
866	2SK720A	NEC	SW	MOS	N	E	250	DSS	±20	120	4-180
867	2SK722		SW	MOS	N	E	170	DSS	10	100	4-207
868	2SK723	富士电	SW-Reg, UPS, DDC	MOS	N	E	500	DSS	7	125	4-186
869	2SK724	富士电	SW-Reg, UPS, DDC	MOS	N	E	500	DSS	10	100	4-186
870	2SK725	富士电	SW-Reg, UPS, DDC	MOS	N	E	500	DSS	15	125	4-186
871	2SK726	富士电	SW-Reg, UPS, DDC	MOS	N	E	900	DSS	3	100	4-186
872	2SK727	富士电	SW-Reg, UPS, DDC	MOS	N	E	900	DSS	5	125	4-186
873	2SK732	三菱	HS PSW	MOS	N	E	450	DSS	10	45	4-215
874	2SK733	三菱	HS PSW	MOS	N	E	450	DSS	10	120	4-250
875	2SK734	三菱	HS PSW	MOS	N	E	450	DSS	15	150	4-250
876	2SK735	NEC	SW	MOS	N	E	450	DSS	±10	100	4-253
877	2SK736	NEC	SW	MOS	N	E	100	DSS	±15	35	4-274
878	2SK737	NEC	SW	MOS	N	E	100	DSS	±12	35	4-274
879	2SK738, 738	NEC	SW	MOS	N	E	30	DSS	±2	20	4-276/Z:281
880	2SK739, 739	NEC	SW	MOS	N	E	60	DSS	±2	20	4-276/Z:281
881	2SK740	日立	HS PSW	MOS	N	E	150	DSS	10	50	4-116B
882	2SK741	日立	HS, PSW	MOS	N	E	250	DSS	7	50	4-116B
883	2SK742	松下	RF PA, SW	MOS	N	E	50	DSS	5	30	4-190
884	2SK743	松下	RF PA, SW	MOS	N	E	50	DSS	8	40	4-190
885	2SK744	松下	RF PA, SW	MOS	N	E	50	DSS	10	50	4-190
886	2SK745	松下	RF PA, SW	MOS	N	E	50	DSS	20	100	4-196
887	2SK746	松下	RF PA, SW	MOS	N	E	50	DSS	20	100	4-191
888	2SK747	松下	RF PA, SW	MOS	N	E	100	DSS	5	30	4-190
889	2SK748	松下	RF PA, SW	MOS	N	E	100	DSS	8	40	4-190
890	2SK749	松下	RF PA, SW	MOS	N	E	100	DSS	10	50	4-190
891	2SK750	松下	RF PA, SW	MOS	N	E	100	DSS	20	100	4-196
892	2SK751	松下	RF PA, SW	MOS	N	E	100	DSS	20	100	4-191
893	2SK752	松下	RF PA, SW	MOS	N	E	160	DSS	3	30	4-190
894	2SK753	松下	RF PA, SW	MOS	N	E	160	DSS	5	40	4-190
895	2SK754	松下	RF PA, SW	MOS	N	E	160	DSS	10	50	4-190
896	2SK755	松下	DDC, Motor-D	MOS	N	E	200	DSS	5	40	4-190
897	2SK756	松下	DDC, Motor-D	MOS	N	E	200	DSS	8	40	4-190
898	2SK757	松下	DDC, Motor-D	MOS	N	E	200	DSS	10	50	4-190
899	2SK758	松下	DDC, Motor-D	MOS	N	E	250	DSS	5	40	4-190
900	2SK759	松下	DDC, Motor-D	MOS	N	E	250	DSS	8	50	4-190
901	2SK760	松下	DDC, Motor-D	MOS	N	E	250	DSS	15	100	4-196
902	2SK761	松下	DDC, Motor-D	MOS	N	E	250	DSS	15	100	4-191
903	2SK762	松下	Motor-D, SW-Reg	MOS	N	E	400	DSS	3	40	4-190
904	2SK763	松下	Motor-D, SW-Reg	MOS	N	E	400	DSS	5	50	4-190
905	2SK764	松下	Motor-D, SW-Reg	MOS	N	E	400	DSS	10	100	4-196
906	2SK765	松下	Motor-D, SW-Reg	MOS	N	E	400	DSS	10	100	4-191
907	2SK766	松下	Motor-D, SW-Reg	MOS	N	E	500	DSS	3	40	4-190
908	2SK767	松下	Motor-D, SW-Reg	MOS	N	E	500	DSS	5	50	4-190
909	2SK768	松下	Motor-D, SW-Reg	MOS	N	E	500	DSS	10	100	4-196
910	2SK769	松下	Motor-D, SW-Reg	MOS	N	E	500	DSS	10	100	4-191

5000种场效应管参数

更多彩电维修资料请到《[彩电维修资料网](http://www.tv160.net)》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing	
911	2SK770	松下	Motor-D, SW-Reg	MOS	N	E	600	DSS	2	40	4-190
912	2SK771	三洋	A-SW, CC, LF A	J	N	D	-40	GDS	10m	200m	4-126A
913	2SK772	三洋	LF A, VR, A-SW	J	N	D	-40	GDS	10m	300m	4-157A
914	2SK773	NEC	SW	MOS	N	E	500	DSS	±12	120	4-180
915	2SK774	NEC	SW	MOS	N	E	500	DSS	±18	120	4-180
916	2SK775	三洋	HS SW	MOS	N	E	450	DSS	2	50	4-242
917	2SK776	三洋	HS SW	MOS	N	E	450	DSS	5	60	4-242
918	2SK777	三洋	HS SW	MOS	N	E	450	DSS	10	120	4-243
919	2SK778	三洋	HS SW	MOS	N	E	250	DSS	500m	10	4-242
920	2SK779	日立	SHF RF	GaAs/M	N	D	5	DSX	120m	200m	4-222
921	2SK780	日立	SHF RF	GaAs/M	N	D	5	DSX	120m	200m	4-220
922	2SK782	松下	DDC, Motor-D	MOS	N	E	200	DSS	5	40	4-249
923	2SK783	富士电	SW	MOS	N	E	500	DSX	12	125	
924	2SK784	NEC	SW	MOS	N	E	450	DSS	±20	150	4-253
925	2SK785	NEC	SW	MOS	N	E	500	DSS	±20	150	4-253
926	2SK786	NEC	SW	MOS	N	E	900	DSS	±3	60	4-164
927	2SK787	NEC	SW	MOS	N	E	900	DSS	±8	150	4-253
928	2SK788	东芝	HS SW, DDC	MOS	N	E	500	DSS	13	150	4-184
929	2SK789	东芝	HS SW, DDC	MOS	N	E	450	DSS	15	150	4-184
930	2SK790	东芝	HS SW, DDC	MOS	N	E	500	DSS	15	150	4-184
931	2SK791	东芝	HV SW, Motor-D	MOS	N	E	850	DSS	3	100	4-222
932	2SK792	东芝	HV SW, Motor-D	MOS	N	E	900	DSS	3	100	4-222
933	2SK793	东芝	HV SW, Motor-D	MOS	N	E	850	DSS	5	150	4-184
934	2SK794	东芝	HV SW, Motor-D	MOS	N	E	900	DSS	5	150	4-184
935	2SK795	松下	Motor-D, SW-Reg	MOS	N	E	600	DSS	2	15	4-221
936	2SK796	松下	Motor-D, SW-Reg	MOS	N	E	800	DSS	3	90	4-191
937	2SK797	NEC	SW	MOS	N	E	60	DSS	±40	150	4-253
938	2SK798	NEC	SW	MOS	N	E	100	DSS	±40	150	4-253
939	2SK799	NEC	SW	MOS	N	E	450	DSS	±12	120	4-180
940	2SK800	NEC	SW	MOS	N	E	450	DSS	±18	120	4-180
941	2SK801, 801	NEC	SW	MOS	N	E	30	DSS	±2	12	4-276/Z:281
942	2SK802	NEC	SW	MOS	N	E	30	DSS	±2	15	4-135
943	2SK803	松下	SW	MOS	N	E	160	DSS	8	40	4-190
944	2SK804	松下	DDC, Motor-D	MOS	N	E	150	DSS	20	100	4-191
945	2SK805	松下	DDC, Motor-D	MOS	N	E	200	DSS	20	100	4-191
946	2SK806	松下	Motor-D, SW-Reg	MOS	N	E	600	DSS	3	50	4-190
947	2SK807	松下	Motor-D, SW-Reg	MOS	N	E	600	DSS	5	100	4-191
948	2SK808	松下	Motor-D, SW-Reg	MOS	N	E	800	DSS	1	45	4-190
949	2SK809	松下	Motor-D, SW-Reg	MOS	N	E	800	DSS	5	100	4-191
950	2SK810	NEC	SW	MOS	N	E	100	DSS	±14	60	4-164
951	2SK811	NEC	SW	MOS	N	E	100	DSS	±12	35	4-274
952	2SK812	NEC	SW	MOS	N	E	60	DSS	±27	60	4-164
953	2SK813	NEC	SW	MOS	N	E	60	DSS	±21	35	4-274
954	2SK814	NEC	SW	MOS	N	E	30	DSS	±15	35	4-274
955	2SK815	NEC	SW	MOS	N	E	100	DSS	±21	35	4-274
956	2SK817	NEC	SW	MOS	N	E	60	DSS	±26	35	4-274
957	2SK818	松下	Motor-D, SW-Reg	MOS	N	E	800	DSS	5	100	4-196
958	2SK819	NEC	SW	MOS	N	E	500	DSS	±10	100	4-253
959	2SK820	NEC	SW	MOS	N	E	250	DSS	±18	80	4-251
960	2SK821	NEC	SW	MOS	N	E	250	DSS	±20	150	4-253
961	2SK822	NEC	SW	MOS	N	E	250	DSS	±22	90	4-251
962	2SK823	NEC	SW	MOS	N	E	250	DSS	±25	150	4-253
963	2SK824	NEC	SW	MOS	N	E	450	DSS	±12	90	4-251
964	2SK825	NEC	SW	MOS	N	E	450	DSS	±15	150	4-253
965	2SK826	NEC	SW	MOS	N	E	450	DSS	±15	95	4-251
966	2SK827	NEC	SW	MOS	N	E	450	DSS	±18	150	4-253
967	2SK828	NEC	SW	MOS	N	E	500	DSS	±12	90	4-251
968	2SK829	NEC	SW	MOS	N	E	500	DSS	±15	150	4-253
969	2SK830	NEC	SW	MOS	N	E	500	DSS	±15	95	4-251
970	2SK831	NEC	SW	MOS	N	E	500	DSS	±18	150	4-253
971	2SK832	NEC	SW	MOS	N	E	900	DSS	±4	85	4-251

5000种场效应管参数

更多彩电维修资料请到《[彩电维修资料网](http://www.tv160.net)》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道	方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
972	2SK833	NEC	SW	MOS	N	E	900	DSS	±5	150	4-253
973	2SK834	NEC	SW	MOS	N	E	900	DSS	±8	100	4-251
974	2SK839	松下		MOS	N		40	DSS	2	1.4	
975	2SK840	松下		MOS	N		40	DSS	2	1.4	
976	2SK841	松下		MOS	N		250	DSS	1	1.4	
977	2SK842	松下		MOS	N		400	DSS	500m	1.4	
978	2SK843	三菱	HS PSW	MOS	N	E	60	DSS	10	40	4-215
979	2SK844	三菱	HS PSW	MOS	N	E	100	DSS	8	40	4-215
980	2SK845	三菱	HS PSW	MOS	N	E	450	DSS	5	40	4-215
981	2SK846	三菱	HS PSW	MOS	N	E	900	DSS	3	45	4-215
982	2SK847	三菱	HS PSW	MOS	N	E	900	DSS	3	120	4-250
983	2SK848	三洋	HS SW	MOS	N	E	250	DSX	0.5	3.5	4-252
984	2SK849	东芝	HS SW, DDC	MOS	N	E	60	DSX	40	150	4-184
985	2SK850	东芝	HS SW, DDC	MOS	N	E	100	DSX	40	125	4-184
986	2SK851	东芝	HS SW, DDC	MOS	N	E	200	DSX	30	150	4-184
987	2SK852	NEC	LF A, A-SW	J	N	D	-50	GDO	10m	150m	4-246
988	2SK853	NEC	LF/RF A, A-SW, V	J	N	D	-30	GDO	10m	150m	4-246
989	2SK853A	NEC	LF/RF A, A-SW, V	J	N	D	-50	GDO	10m	150m	4-246
990	2SK854	NEC	SW	MOS	N	E	450	DSS	±5	50	4-164
991	2SK855	NEC	SW	MOS	N	E	500	DSS	±5	50	4-164
992	2SK856	东芝	HS SW, DDC	MOS	N	E	60	DSX	45	125	4-183
993	2SK857	东芝	HS SW, DDC	MOS	N	E	60	DSX	45	125	4-184
994	2SK858	东芝	HS HV SW, Motor	MOS	N	E	600	DSS	2	40	4-222
995	2SK859	富士电	SW	MOS	N	E	500	DSX	9	125	4-186
996	2SK863	松下									
997	2SK864	松下									
998	2SK865	松下									
999	2SK866	松下									
###	2SK867	松下	Motor-D, SW-Reg	MOS	N	E	400	DSS	15	120	4-196
###	2SK868, 86	松下	Motor-D, SW-Reg	MOS	N	E	400	DSS	20	130	4-196
###	2SK869	松下	Motor-D, SW-Reg	MOS	N	E	500	DSS	15	120	4-196
###	2SK870	松下	Motor-D, SW-Reg	MOS	N	E	500	DSS	20	130	4-196
###	2SK871	NEC	SW	MOS	N	E	900	DSS	±4	120	4-253
###	2SK872	NEC	SW	MOS	N	E	900	DSS	±6	150	4-253
###	2SK873	NEC	SW	MOS	N	E	450	DSS	±8	100	4-253
###	2SK874	NEC	SW	MOS	N	E	500	DSS	±8	100	4-253
###	2SK875	NEC	SW	MOS	N	E	450	DSS	±12	120	4-253
###	2SK876	NEC	SW	MOS	N	E	500	DSS	±12	120	4-253
###	2SK879	东芝	C-MIC, Imp-C	J	N	D	-50	DSS	10m	100m	4-246B
###	2SK880	东芝	LF LN	J	N	D	-50	GDS	10m	100m	4-246B
###	2SK881	东芝	FM Tuner, VHF	J	N	D	-18	GDO	10m	100m	4-246A
###	2SK882	东芝	FM Tuner, VHF	MOS	N	DE	20	DS	30m	100m	4-246A
###	2SK888	东芝	DDC, Motor-D	MOS	N	E	-100	GDR	15	75	4-231
###	2SK889	东芝	DDC, Motor-D	MOS	N	E	-100	GDR	27	125	4-231
###	2SK890	东芝	DDC, Motor-D	MOS	N	E	-200	GDR	10	75	4-231
###	2SK891	东芝	DDC, Motor-D	MOS	N	E	-200	GDR	18	125	4-231
###	2SK892	东芝	SW-Reg, DDC	MOS	N	E	500	DSS	2.5	40	4-231
###	2SK893	东芝	SW-Reg, DDC	MOS	N	E	500	DSS	5	75	4-231
###	2SK894	东芝	SW-Reg, DDC	MOS	N	E	500	DSS	8	125	4-231
###	2SK895	东芝	HS HV SW	MOS	N	E	-450	GDR	12	125	4-184
###	2SK896	东芝	HS HV SW	MOS	N	E	-550	GDR	12	125	4-184
###	2SK897	富士电	SW-Reg, UPS, DDC	MOS	N	E	550	DSS	4	40	4-235
###	2SK899	富士电	SW-Reg, UPS, DDC	MOS	N	E	500	DSS	18	125	4-186
###	2SK900	富士电	UPS, DDC, PA	MOS	N	E	250	DSS	12	80	4-234
###	2SK901	富士电	UPS, DDC, PA	MOS	N	E	250	DSS	20	125	4-186
###	2SK902	富士电	UPS, DDC, PA	MOS	N	E	250	DSS	30	150	4-186
###	2SK903	富士电	SW-Reg, UPS, DDC	MOS	N	E	800	DSS	3	40	4-235
###	2SK904	富士电	SW-Reg, UPS, DDC	MOS	N	E	800	DSS	3	80	4-234
###	2SK905	富士电机		MOS	N	E	50	DSS	45	125	4-186
###	2SK906	富士电机		MOS	N	E	100	DSS	32	125	4-186
###	2SK926	NEC	SW	MOS	N	E	250	DSS	±10	60	4-164

5000种场效应管参数

更多彩电维修资料请到《彩电维修资料网》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道	方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
###	2SK928	NEC	SW	MOS	N	E	450	DSS	±5	35	4-208
###	2SK929	NEC	SW	MOS	N	E	500	DSS	±5	35	4-208
###	2SK930	三菱	LF A,A-SW	J	N	D	-50	GDO	10m	150m	
###	2SK931	三洋	RF LN A	J	N	D	-30	GDS	10m	200m	4-126A
###	2SK932	三洋	RF LN A	J	N	D	-15	GDS	10m	200m	4-126A
###	2SK933	三洋	HS SW	MOS	N	E	60	DS	±15	35	4-284
###	2SK934	三菱	HS SW	MOS	N	E	250	DSS	8	40	4-215
###	2SK935	三菱	HS SW	MOS	N	E	300	DSS	8	40	4-215
###	2SK936	三菱	HS SW	MOS	N	E	50	DSS	30	45	
###	2SK937	三洋	RF	J	N	D	-40	GDS	10m	300m	4-165B
###	2SK940	东芝		MOS	N	E	60	DSS	800m	900m	4-74B
###	2SK941	东芝	SW, DDC, Motor-D	MOS	N	E	100	DSS	600m	900m	4-74B
###	2SK942	东芝		MOS	N	E	60	DSS	25	75	4-231
###	2SK943	东芝	DDC, Motor-D	MOS	N	E	60	DSS	25	40	4-335
###	2SK944	东芝	SW, DDC, Motor-D	MOS	N	E	250	DSS	22	150	4-184
###	2SK945	东芝	SW, DDC, Motor-D	MOS	N	E	400	DSS	1	10	4-257
###	2SK946	NEC	SW	MOS	N	E	900	DSS	±3	40	4-208
###	2SK947	富士电	USP, DDC, PA	MOS	N	E	250	DSS	12	40	4-235
###	2SK948	富士电	USP, DDC, PA	MOS	N	E	250	DSS	12	100	4-286
###	2SK949	富士电	SW-Reg, UPS, DDC	MOS	N	E	500	DSS	6	40	4-235
###	2SK950	富士电	SW-Reg, UPS, DDC	MOS	N	E	500	DSS	6	80	4-234
###	2SK951	富士电	SW-Reg, USP, DDC	MOS	N	E	800	DSS	2.5	40	4-235
###	2SK952	富士电	SW-Reg, USP, DDC	MOS	N	E	800	DSS	2.5	45	4-234
###	2SK953	富士电	SW-Reg, USP, DDC	MOS	N	E	800	DSS	2.5	80	4-186
###	2SK954	富士电	SW-Reg, UPS, DDC	MOS	N	E	800	DSS	3	100	4-186
###	2SK955	富士电	SW-Reg, UPS, DDC	MOS	N	E	800	DSS	5	125	4-186
###	2SK956	富士电	SW-Reg, USP, DDC	MOS	N	E	800	DSS	9	150	4-186
###	2SK957	富士电	SW-Reg, USP, DDC	MOS	N	E	900	DSS	6	40	4-235
###	2SK958	富士电	SW-Reg, USP, DDC	MOS	N	E	900	DSS	2	45	4-234
###	2SK959	富士电	SW-Reg, USP, DDC	MOS	N	E	900	DSS	2	80	4-186
###	2SK960	富士电	SW-Reg, USP, DDC	MOS	N	E	900	DSS	3	40	4-235
###	2SK961	富士电	SW-Reg, USP, DDC	MOS	N	E	900	DSS	3	80	4-234
###	2SK962	富士电	SW-Reg, USP, DDC	MOS	N	E	900	DSS	8	150	4-186
###	2SK963	松下	DDC, Motor-D	MOS	N	E	250	DSS	5	15	4-221
###	2SK968	三洋	RF	J	N	D	-20	GDO	10m	200m	4-126C
###	2SK970	日立	HS PSW	MOS	N	E	60	DSS	10	30	4-116B
###	2SK971	日立	HS PSW	MOS	N	E	60	DSS	15	40	4-116B
###	2SK972	日立	HS PSW	MOS	N	E	60	DSS	25	50	4-116B
###	2SK973(L)	日立	HS PSW	MOS	N	E	60	DSS	2	10	4-150
###	2SK974(L)	日立	HS PSW	MOS	N	E	60	DSS	3	20	4-150
###	2SK975	日立	HS PSW	MOS	N	E	60	DSS	1.5	900m	4-97B
###	2SK976	日立	HS PSW	MOS	N	E	60	DSS	10	20	4-236
###	2SK977	日立	HS PSW	MOS	N	E	60	DSS	15	25	4-236
###	2SK978	日立	HS PSW	MOS	N	E	60	DSS	25	30	4-236
###	2SK980	日立	Video-Band LN A	J	N	D	12	DSX	±1m	150m	4-185A
###	2SK981, 98	松下	Motor-D, SW-Reg	MOS	N	E	400	DSS	3	15	4-221
###	2SK982	东芝	HS SW, A-SW	MOS	N	E	60	DS	200m	400m	4-82D
###	2SK987	三菱	HS PSW	MOS	N	E	500	DSS	5	40	4-215
###	2SK988	三菱	HS PSW	MOS	N	E	500	DSS	10	45	4-215
###	2SK989	三菱	HS PSW	MOS	N	E	500	DSS	10	120	4-250
###	2SK990	三菱	HS PSW	MOS	N	E	500	DSS	15	150	4-250
###	2SK991	NEC	SW	MOS	N	E	100	DSS	±4	35	4-164
###	2SK992	NEC	SW	MOS	N	E	100	DSS	±4	30	4-274
###	2SK993	NEC	SW	MOS	N	E	60	DSS	±8	35	4-164
###	2SK994	NEC	SW	MOS	N	E	60	DSS	±7	30	4-274
###	2SK995	松下	Motor-D, SW-Reg	MOS	N	E	550	DSS	5	60	4-191
###	2SK996	松下	Motor-D, SW-Reg	MOS	N	E	600	DSS	4	50	4-190
###	2SK997	NEC	ECM Imp-C	J	N	D	-20	GDO	10m	100m	4-104B
###	2SK998	NEC	RF/MIX	J	N	D	-20	GDO	10m	350m	4-53B
###	2SK1000	NEC	AM Tuner, LF A	J	N	D	-22	GDO	10m	250m	4-104B
###	2SK1001	NEC	AM Tuner, LF A	J	N	D	-22	GDO	10m	250m	4-275B

5000种场效应管参数

更多彩电维修资料请到《彩电维修资料网》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道	方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
###	2SK1002	NEC	RF	J	N	D	-20	GDO	10m	250m	4-104B
###	2SK1006	富士电	SW-Reg, USP, DDC	MOS	N	E	450	DSS	5	40	4-235
###	2SK1007	富士电	SW-Reg, USP, DDC	MOS	N	E	450	DSS	5	60	4-234
###	2SK1008	富士电	SW-Reg, USP, DDC	MOS	N	E	500	DSS	4.5	60	4-234
###	2SK1009	富士电	SW-Reg, USP, DDC	MOS	N	E	450	DSS	7	80	4-234
###	2SK1010	富士电	SW-Reg, USP, DDC	MOS	N	E	500	DSS	6	80	4-234
###	2SK1011	富士电	SW-Reg, USP, DDC	MOS	N	E	450	DSS	10	100	4-186
###	2SK1012	富士电	SW-Reg, USP, DDC	MOS	N	E	500	DSS	10	100	4-186
###	2SK1013	富士电	SW-Reg, USP, DDC	MOS	N	E	450	DSS	13	125	4-186
###	2SK1014	富士电	SW-Reg, USP, DDC	MOS	N	E	500	DSS	12	125	4-186
###	2SK1015	富士电	SW-Reg, USP, DDC	MOS	N	E	450	DSS	18	125	4-186
###	2SK1016	富士电	SW-Reg, USP, DDC	MOS	N	E	500	DSS	15	125	4-186
###	2SK1017	富士电	SW-Reg, USP, DDC	MOS	N	E	450	DSS	20	150	4-186
###	2SK1018	富士电	SW-Reg, USP, DDC	MOS	N	E	500	DSS	18	125	4-186
###	2SK1019	富士电	SW-Reg, USP, DDC	MOS	N	E	450	DSS	35	300	4-326
###	2SK1020	富士电	SW-Reg, USP, DDC	MOS	N	E	500	DSS	30	300	4-326
###	2SK1021	富士电	SW-Reg, USP, DDC	MOS	N	E	800	DSS	3	60	4-234
###	2SK1022	富士电	SW-Reg, USP, DDC	MOS	N	E	900	DSS	2.5	60	4-234
###	2SK1023	富士电	SW-Reg, USP, DDC	MOS	N	E	800	DSS	4	60	4-234
###	2SK1024	富士电	SW-Reg, USP, DDC	MOS	N	E	900	DSS	3.5	60	4-234
###	2SK1025	三菱	HS PSW	MOS	N	E	50	DSS	20	45	4-215
###	2SK1026	三菱	HS PSW	MOS	N	E	250	DSS	20	150	4-250
###	2SK1027	三菱	HS PSW	MOS	N	E	300	DSS	20	150	4-250
###	2SK1029	东芝	SW	MOS	N	E	500	DSX	±10	200	4-141
###	2SK1030	松下	Motor-D, SW-Reg	MOS	N	E	800	DSS	3	50	4-190
###	2SK1031	日立	LF A	J	N	D	-50	GDO	10m	100m	4-185A
###	2SK1032	松下	Motor-D, SW-Reg	MOS	N	E	800	DSS	8	120	4-196
###	2SK1033	松下	DDC, Motor-D	MOS	N	E	60	DSS	20	45	4-190
###	2SK1034	松下	DDC, Motor-D	MOS	N	E	100	DSS	15	45	4-190
###	2SK1035	松下	DDC, Motor-D	MOS	N	E	150	DSS	12	45	4-190
###	2SK1036	松下	DDC, Motor-D	MOS	N	E	250	DSS	10	50	4-190
###	2SK1037	松下	SW	MOS	N	E	250	DSS		50	4-190
###	2SK1038	松下	SW	MOS	N	E	400	DSS	5	50	4-190
###	2SK1039	松下	SW	MOS	N	E	400	DSS	8	50	4-190
###	2SK1040	松下	SW	MOS	N	E	400	DSS	10	100	4-191
###	2SK1041	松下	SW	MOS	N	E	400	DSS	15	120	
###	2SK1042	松下	SW	MOS	N	E	400	DSS	20	130	
###	2SK1043	NEC	X-K-Band LN A	GaAs	N	D	4	DSX	10m	200m	4-254
###	2SK1044	三菱	HS PSW	MOS	N	E	800	DSS	5	150	4-250
###	2SK1045	三菱	HS PSW	MOS	N	E	900	DSS	5	150	4-250
###	2SK1046	NEC	C-K-Band LN A	GaAs	N	D	4	DSX	70m	200m	4-254
###	2SK1047	三菱		MOS	N	E	250	DSS	20	150	4-250
###	2SK1048	三菱		MOS	N	E	300	DSS	20	150	4-250
###	2SK1049	三菱		MOS	N	E	450	DSS	15	150	4-250
###	2SK1050	三菱		MOS	N	E	500	DSS	15	150	4-250
###	2SK1051	三菱	HS PSW	MOS	N	E	50	DSS	40	120	4-250
###	2SK1052	三洋	HS SW	MOS	N	E	450	DSS	0.5	30	4-242
###	2SK1053	三洋	HS SW	MOS	N	E	450	DSS	1	40	4-242
###	2SK1056	日立	LF PA	MOS	N	E	120	DSX	7	100	4-149
###	2SK1057	日立	LF PA	MOS	N	E	140	DSX	7	100	4-149
###	2SK1058	日立	LF PA	MOS	N	E	160	DSX	7	100	4-149
###	2SK1059, 1	NEC	SW	MOS	N	E	60	DSS	±5	20	4-276/Z:277
###	2SK1060, 10	NEC	SW	MOS	N	E	100	DSS	±5	20	276/Z:277
###	2SK1061	东芝	HS SW, A-SW	MOS	N	E	60	DS	200m	300m	4-70D
###	2SK1062	东芝	HS SW, A-SW	MOS	N	E	60	DS	200m	200m	4-105D
###	2SK1063	日立	HS PSW	MOS	N	E	450	DSS	15	125	4-28B
###	2SK1064	日立	HS PSW	MOS	N	E	500	DSS	15	125	4-28B
###	2SK1065	三洋	RF	J	N	D	-20	GDO	10m	150m	4-255A
###	2SK1066	三洋	RF	J	N	D	-15	GDS	10m	150m	4-255B
###	2SK1067	三洋	FM Tuner, VHF RF	MOS	N	DE	16	DS	30m	150m	4-255B
###	2SK1068	三洋		J	N	D	-40	GDS	10m	100m	4-255B

5000种场效应管参数

更多彩电维修资料请到《[彩电维修资料网](http://www.tv160.net)》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道	方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
###	2SK1069	三洋	LF A	J	N	D	-40	GDS	10m	150m	4-255B
###	2SK1070	日立	LF/HF A	J	N	D	-22	GDO	10m	150m	4-185A
###	2SK1073	三菱	HS PSW	MOS	N	E	800	DSS	3	45	4-215
###	2SK1074	三菱	HS PSW	MOS	N	E	800	DSS	3	120	4-250
###	2SK1078	东芝	HS PSW, DDC	MOS	N	E	60	DSS	800m	500m	4-256
###	2SK1079	东芝		MOS	N	E	100	DSS	600m	500m	4-256
###	2SK1081	富士电	SW-Reg, USP, DDC	MOS	N	E	800	DSS	7	125	4-186
###	2SK1082	富士电	SW-Reg, USP, DDC	MOS	N	E	900	DSS	6	125	4-186
###	2SK1083	富士电机		MOS	N	E	60	DSS	8	20	4-235
###	2SK1084	富士电机		MOS	N	E	100	DSS	5	20	4-235
###	2SK1085	富士电机		MOS	N	E	150	DSS	3	20	4-235
###	2SK1086	富士电机		MOS	N	E	60	DSS	20	35	4-235
###	2SK1087	富士电机		MOS	N	E	100	DSS	12	35	4-235
###	2SK1088	富士电机		MOS	N	E	150	DSS	9	35	4-235
###	2SK1089	富士电机		MOS	N	E	60	DSS	35	80	4-235
###	2SK1090	富士电机		MOS	N	E	100	DSS	20	80	4-186
###	2SK1091	富士电机		MOS	N	E	150	DSS	15	80	4-186
###	2SK1092	日立	V/UHF A	GaAs/Me	N	D	4	DS	150m	150m	4-199C
###	2SK1093	日立	Motor/Relay-D	MOS	N	E	60	DSS	10	20	4-292
###	2SK1094	日立	Motor/Relay-D	MOS	N	E	60	DSS	15	25	4-292
###	2SK1095	日立	Motor/Relay-D	MOS	N	E	60	DSS	25	30	4-292
###	2SK1096	富士电机		MOS	N	E	60	DSS	13	30	4-235
###	2SK1097	富士电机		MOS	N	E	100	DSS	8	30	4-235
###	2SK1098	富士电机		MOS	N	E	150	DSS	6	30	4-235
###	2SK1099	富士电	SW-Reg, UPS, DDC	MOS	N	E	500	DSS	10	80	4-327
###	2SK1100	松下	~Ku-Band LN A	HEMT	N	D	-4	GDO	60m	200m	4-218
###	2SK1101	富士电	SW-Reg, UPS, DDC	MOS	N	E	450	DSS	10	50	4-235
###	2SK1102	富士电	SW-Reg, UPS, DDC	MOS	N	E	500	DSS	10	50	4-235
###	2SK1103	松下	SW	J	N	D	-65	GDS	10m	150m	4-193D
###	2SK1104	松下	SW	J	N	D	-65	GDS	10m	300m	4-213C
###	2SK1105	富士电	SW-Reg, UPS, DDC	MOS	N	E	800	DSS	3	80	4-327
###	2SK1108	NEC	C-MIC, Imp-C	J	N	D	20	DSX	10m	100m	4-104B
###	2SK1109	NEC	ECM Imp-C	J	N	D	-20	GDO	10m	80m	4-88
###	2SK1112	东芝		MOS	N	E	-60	GDR	5	20	4-257
###	2SK1113	东芝		MOS	N	E	-120	GDR	3	20	4-257
###	2SK1114	东芝		MOS	N	E	-60	GDR	12	40	4-231
###	2SK1115	东芝	DDC, Motor-D	MOS	N	E	60	DSS	20	60	4-231
###	2SK1116	东芝	DDC, Motor-D	MOS	N	E	100	DSS	25	100	4-231
###	2SK1117	东芝	SW-Reg	MOS	N	E	-600	GDR	6	100	4-231
###	2SK1118	东芝	SW-Reg	MOS	N	E	600	DSS	6	45	4-335
###	2SK1119	东芝	SW Reg	MOS	N	E	-1000	GDR	4	100	4-231
###	2SK1120	东芝	SW Reg	MOS	N	E	-1000	GDR	8	150	4-184
###	2SK1121	三菱	HS PSW	MOS	N	E	50	DSS	25	45	4-215
###	2SK1122	NEC	SW	MOS	N	E	100	DSS	±40	100	4-253
###	2SK1123	NEC	SW, Motor-D	MOS	N	E	60	DSS	±40	100	4-253
###	2SK1124	东芝	DDC, HC SW	MOS	N	E	-60	GDR	45	125	4-184
###	2SK1132	NEC	HS SW	MOS	N	E	50	DSS	±100m	250m	4-104C
###	2SK1133	NEC	HS SW	MOS	N	E	50	DSS	±100m	200m	4-275A
###	2SK1134	富士电机		MOS	N	E	50	DSS	45	80	4-327
###	2SK1135	日立	SW-Reg, DDC	MOS	N	E	250	DSS	15	100	4-149
###	2SK1136	三菱	HS PSW	MOS	N	E	50	DSS	10	30	4-215
###	2SK1137	三菱	HS PSW	MOS	N	E	50	DSS	16	40	4-215
###	2SK1138	三菱	HS PSW	MOS	N	E	150	DSS	7	30	4-215
###	2SK1139	三菱	HS PSW	MOS	N	E	150	DSS	13	40	4-215
###	2SK1142	三菱	HS PSW	MOS	N	E	800	DSS	2	35	4-215
###	2SK1143	三菱	HS PSW	MOS	N	E	900	DSS	2	35	4-215
###	2SK1149	NEC	SW, Motor-D, DDC	MOS	N	E	100	DSS	±40	75	4-251B
###	2SK1150	NEC	SW, Motor-D, DDC	MOS	N	E	60	DSS	±40	75	4-251B
###	2SK1151(L)	日立	SW-Reg, DDC	MOS	N	E	450	DSS	1.5	20	4-150
###	2SK1152(L)	日立	SW-Reg, DDC	MOS	N	E	500	DSS	1.5	20	4-150
###	2SK1153	日立	SW-Reg, DDC	MOS	N	E	450	DSS	3	30	4-116B

5000种场效应管参数

更多彩电维修资料请到《彩电维修资料网》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道	方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
###	2SK1154	日立	SW-Reg, DDC	MOS	N	E	500	DSS	3	30	4-116B
###	2SK1155	日立	SW-Reg, DDC	MOS	N	E	450	DSS	5	50	4-116B
###	2SK1156	日立	SW-Reg, DDC	MOS	N	E	500	DSS	5	50	4-116B
###	2SK1157	日立	SW-Reg, DDC	MOS	N	E	450	DSS	7	60	4-116B
###	2SK1158	日立	SW-Reg, DDC	MOS	N	E	500	DSS	7	60	4-116B
###	2SK1159	日立	SW-Reg, DDC	MOS	N	E	450	DSS	8	60	4-116B
###	2SK1160	日立	SW-Reg, DDC	MOS	N	E	500	DSS	8	60	4-116B
###	2SK1161	日立	SW-Reg, DDC	MOS	N	E	450	DSS	10	100	4-149
###	2SK1162	日立	SW-Reg, DDC	MOS	N	E	500	DSS	10	100	4-149
###	2SK1163	日立	SW-Reg, DDC	MOS	N	E	450	DSS	10	100	4-149
###	2SK1164	日立	SW-Reg, DDC	MOS	N	E	500	DSS	11	100	4-149
###	2SK1165	日立	SW-Reg, DDC	MOS	N	E	450	DSS	12	100	4-149
###	2SK1166	日立	SW-Reg, DDC	MOS	N	E	500	DSS	12	100	4-149
###	2SK1167	日立	SW-Reg, DDC	MOS	N	E	450	DSS	15	100	4-149
###	2SK1168	日立	SW-Reg, DDC	MOS	N	E	500	DSS	15	100	4-149
###	2SK1169	日立	SW-Reg, DDC	MOS	N	E	450	DSS	20	120	4-149
###	2SK1170	日立	SW-Reg, DDC	MOS	N	E	500	DSS	20	120	4-149
###	2SK1171	富士电	SW-Reg, UPS, DDC	MOS	N	E	800	DSS	4	80	4-186
###	2SK1172	富士电	SW-Reg, UPS, DDC	MOS	N	E	900	DSS	3.5	80	4-186
###	2SK1173	松下		MOS	N		50	DSS	500m	200m	
###	2SK1194	新电元	DDC	MOS	N	E	230	DSS	500m	6	4-381
###	2SK1195	新电元	DDC	MOS	N	E	230	DSS	1.5	10	4-381
###	2SK1196	松下	Ku-Band LN A	GaAs/M	N	D	-6	GDO	70m	200m	4-218
###	2SK1197	日立	RF PA	MOS	N	E	100	DSS	0.5	20	4-136B
###	2SK1198	NEC	SW	MOS	N	E	700	DSS	±2	35	4-208
###	2SK1199	日立	SW-Reg, DDC	MOS	N	E	900	DSS	2	50	4-116B
###	2SK1200	日立	SW-Reg, DDC	MOS	N	E	900	DSS	3	80	4-149
###	2SK1201	日立	SW-Reg, DDC	MOS	N	E	900	DSS	4	80	4-149
###	2SK1202	日立	SW-Reg, DDC	MOS	N	E	900	DSS	5	100	4-149
###	2SK1203	日立	SW-Reg, DDC	MOS	N	E	900	DSS	6	100	4-149
###	2SK1204	日立	SW-Reg, DDC	MOS	N	E	900	DSS	8	100	4-149
###	2SK1205	日立	SW-Reg, DDC	MOS	N	E	1000	DSS	5	100	4-149
###	2SK1206	日立	SW-Reg, DDC	MOS	N	E	500	DSS	12	60	4-149
###	2SK1211	富士电	SW-Reg, UPS, DDC	MOS	N	E	800	DSS	2.5	40	4-327
###	2SK1212	富士电	SW-Reg, UPS, DDC	MOS	N	E	900	DSS	5	80	4-327
###	2SK1213	东芝	SW-Reg	MOS	N	E	600	DSS	6	125	4-184
###	2SK1214	松下	DDC, Motor-D	MOS	N	E	80	DSS	20	45	4-190
###	2SK1215	日立	VHF RF	MOS	N	D	20	DSX	30m	100m	4-CMPAK
###	2SK1216	松下		J	N	D	-10	GDO	5m	200m	4-268
###	2SK1217	富士电	SW-Reg, UPS, DDC	MOS	N	E	900	DSS	8	100	4-327
###	2SK1221	富士电	SW-Reg, UPS, DDC	MOS	N	E	250	DSS	10	80	4-234
###	2SK1222	富士电	SW-Reg, UPS, DDC	MOS	N	E	450	DSS	15	125	4-186
###	2SK1223	松下	DDC, Motor D	MOS	N	E	60	DSS	50	130	4-258
###	2SK1224	富士电	SW-Reg, UPS, DDC	MOS	N	E	800	DSS	4	50	4-327
###	2SK1225	日立	SW-Reg, UPS, DDC	MOS	N	E	450	DSS	12	60	4-293
###	2SK1227	东芝	C-MIC, Imp-C	J	N	D	-15	GDO	10m	100m	4-70B
###	2SK1228	松下	SW	MOS	N	E	50	DS	50m	150m	4-193B
###	2SK1229	日立	SHF LN A	GaAsHE	N	D	4	DS	60m	160m	
###	2SK1230	日立	SW-Reg, DDC	MOS	N	E	120	DSS	10	25	4-292
###	2SK1231	日立	SW-Reg, DDC	MOS	N	E	450	DSS	5	30	4-292
###	2SK1232	日立	SW-Reg, DDC	MOS	N	E	500	DSS	5	30	4-292
###	2SK1233	三洋	4GHz OSC/A	GaAs/M	N	D	6	DS	100m	300m	4-332
###	2SK1234	三洋	4GHz OSC/A	GaAs/M	N	D	5	DS	100m	270m	4-332
###	2SK1235	三洋	12GHz, OSC/A	GaAs/M	N	D	6	DS	100m	300m	4-332
###	2SK1236	三洋	12GHz, OSC/A	GaAs/M	N	D	6	DS	100m	300m	4-333
###	2SK1237	三洋	12GHz OSC/A	GaAs/M	N	D	5	DS	70m	270m	4-333
###	2SK1238	三洋	12GHz OSC/A	GaAs/M	N	D	5	DS	70m	270m	4-333
###	2SK1239	三洋	12GHz OSC/A	GaAs/M	N	D	5	DS	70m	270m	4-334
###	2SK1240	三洋	X-Band LN A	GaAsHE	N	D	4	DS	60m	180m	4-333
###	2SK1241	三洋	X-Band LN A	GaAsHE	N	D	4	DS	60m	180m	4-333
###	2SK1242	三洋	X-Band LN A	GaAsHE	N	D	4	DS	60m	180m	4-334

5000种场效应管参数

更多彩电维修资料请到《彩电维修资料网》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道	方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
###	2SK1243	三洋	X-Band LN A	GaAsHE	N	D	4	DS	60m	180m	4-334
###	2SK1244	新电元	SW-Reg	MOS	N	E	500	DSS	3	40	4-288
###	2SK1245	新电元	SW-Reg	MOS	N	E	500	DSS	3	25	4-289
###	2SK1246	新电元	SW-Reg	MOS	N	E	500	DSS	5	50	4-288
###	2SK1247	新电元	SW-Reg	MOS	N	E	500	DSS	5	30	4-289
###	2SK1248	新电元	SW-Reg	MOS	N	E	500	DSS	10	100	4-290
###	2SK1249	新电元	SW-Reg	MOS	N	E	500	DSS	15	130	4-290
###	2SK1250	新电元	SW Reg	MOS	N	E	500	DSS	20	150	4-290
###	2SK1251	东芝	Relay-D, DDC	MOS	N	E	60	DSS	5	10	4-336
###	2SK1252	东芝	Relay-D, DDC	MOS	N	E	120	DSS	3	10	4-336
###	2SK1253	日立	SW-Reg, DDC	MOS	N	E	30	DSS	30	35	4-292
###	2SK1254(L)	日立	Motor/Relay-D	MOS	N	E	120	DSS	3	20	4-150
###	2SK1255	松下	DDC, Motor-D	MOS	N	E	60	DSS	5	30	4-190
###	2SK1256	松下	DDC, Motor-D	MOS	N	E	60	DSS	10	40	4-190
###	2SK1257	松下	DDC, Motor-D	MOS	N	E	60	DSS	40	45	4-190
###	2SK1258	松下	DDC, Motor-D	MOS	N	E	60	DSS	50	100	4-196
###	2SK1259	松下	DDC, Motor-D	MOS	N	E	60	DSS	100	150	4-258
###	2SK1260	松下	DDC, Motor-D	MOS	N	E	100	DSS	5	30	4-190
###	2SK1261	松下	DDC, Motor-D	MOS	N	E	100	DSS	8	40	4-190
###	2SK1262	松下	DDC, Motor-D	MOS	N	E	100	DSS	30	45	4-190
###	2SK1263	松下	DDC, Motor-D	MOS	N	E	100	DSS	40	100	4-196
###	2SK1264	松下	DDC, Motor-D	MOS	N	E	150	DSS	3	30	4-190
###	2SK1265	松下	DDC, Motor-D	MOS	N	E	150	DSS	6	40	4-190
###	2SK1266	松下	DDC, Motor-D	MOS	N	E	150	DSS	20	45	4-190
###	2SK1267	松下	DDC, Motor-D	MOS	N	E	150	DSS	25	100	4-196
###	2SK1268	日立	SW-Reg, DDC	MOS	N	E	450	DSS	15	60	4-293
###	2SK1269	日立	SW-Reg, DDC	MOS	N	E	500	DSS	15	60	4-293
###	2SK1270	日立	SW-Reg, DDC	MOS	N	E	60	DSS	2	10	4-136A
###	2SK1271	NEC	SW, HV	MOS	N	E	1400	DSS	±5	240	4-308
###	2SK1272	NEC	HS SW	MOS	N	E	60	DSS	±1	0.75	4-53C
###	2SK1273	NEC	HS SW	MOS	N	E	60	DSS	±2	2	4-216A
###	2SK1274	NEC	HS SW	MOS	N	E	60	DSS	±1.5	1	4-217
###	2SK1275	日立	SW-Reg, DDC	MOS	N	E	900	DSS	2	30	4-292
###	2SK1276	富士电机		MOS	N	E	250	DSS	20	100	4-186
###	2SK1277	富士电机		MOS	N	E	250	DSS	30	150	4-186
###	2SK1278	富士电机		MOS	N	E	500	DSS	10	100	4-186
###	2SK1279	富士电机		MOS	N	E	500	DSS	15	125	4-186
###	2SK1280	富士电机		MOS	N	E	500	DSS	18	150	4-186
###	2SK1281	NEC	SW	MOS	N	E	700	DSS	±4	120	4-253
###	2SK1282, 1	NEC	SW, Motor-D	MOS	N	E	60	DSS	±3	20	4-276/Z:277
###	2SK1283	NEC	SW, Motor-D	MOS	N	E	60	DSS	±3	20	4-135
###	2SK1284, 1	NEC	SW, Motor-D	MOS	N	E	100	DSS	±3	20	4-276/Z:277
###	2SK1285	NEC	SW, Motor-D	MOS	N	E	100	DSS	±3	20	4-135
###	2SK1286	NEC	SW, Motor-D	MOS	N	E	60	DSS	±15	30	4-304
###	2SK1287	NEC	SW, Motor-D	MOS	N	E	60	DSS	±20	60	4-164
###	2SK1288	NEC	SW, Motor-D	MOS	N	E	100	DSS	±15	30	4-304
###	2SK1289	NEC	SW, Motor-D	MOS	N	E	100	DSS	±20	60	4-164
###	2SK1290	NEC	SW, Motor-D	MOS	N	E	60	DSS	±25	35	4-304
###	2SK1291	NEC	SW, Motor-D	MOS	N	E	60	DSS	±30	75	4-164
###	2SK1292	NEC	SW, Motor-D	MOS	N	E	100	DSS	±20	35	4-304
###	2SK1293	NEC	SW, Motor-D	MOS	N	E	100	DSS	±30	75	4-164
###	2SK1294	NEC	SW, Motor-D	MOS	N	E	100	DSS	±30	35	4-304
###	2SK1295	NEC	SW, Motor-D	MOS	N	E	100	DSS	±30	35	4-304
###	2SK1296	日立	Motor/Relay-D	MOS	N	E	60	DSS	30	75	4-116B
###	2SK1297	日立	Motor/Relay-D	MOS	N	E	60	DSS	40	100	4-149
###	2SK1298	日立	Motor/Relay-D	MOS	N	E	60	DSS	40	50	4-293
###	2SK1299(L)	日立	Motor/Relay-D	MOS	N	E	100	DSS	3	20	4-150
###	2SK1300	日立	Motor/Relay-D	MOS	N	E	100	DSS	10	40	4-116B
###	2SK1301	日立	Motor/Relay-D	MOS	N	E	100	DSS	15	50	4-116B
###	2SK1302	日立	Motor/Relay-D	MOS	N	E	100	DSS	20	50	4-116B
###	2SK1303	日立	Motor/Relay-D	MOS	N	E	100	DSS	30	100	4-149

5000种场效应管参数

更多彩电维修资料请到《[彩电视维修资料网](http://www.tv160.net)》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道	方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
###	2SK1304	日立	Motor/Relay-D	MOS	N	E	100	DSS	40	100	4-149
###	2SK1305	日立	Motor/Relay-D	MOS	N	E	100	DSS	10	25	4-292
###	2SK1306	日立	Motor/Relay-D	MOS	N	E	100	DSS	15	30	4-292
###	2SK1307	日立	Motor/Relay-D	MOS	N	E	100	DSS	20	35	4-292
###	2SK1308, 1	松下	Motor-D, SW-Reg	MOS	N	E	400	DSS	5	40	4-249
###	2SK1311	三洋	HS SW	MOS	N	E	60	DSS	2	3.5	4-252
###	2SK1313(L)	日立	SW-Reg, DDC	MOS	N	E	450	DSS	5	50	4-294
###	2SK1314(L)	日立	SW-Reg, DDC	MOS	N	E	500	DSS	5	50	4-294
###	2SK1315(L)	日立	SW-Reg, DDC	MOS	N	E	450	DSS	8	60	4-294
###	2SK1316(L)	日立	SW-Reg, DDC	MOS	N	E	500	DSS	8	60	4-294
###	2SK1317	日立	SW-Reg, DDC	MOS	N	E	1500	DSS	2.5	100	4-149
###	2SK1318	日立	Motor/Relay-D	MOS	N	E	120	DSS	20	35	4-292
###	2SK1319	三菱	HS PSW	MOS	N	E	250	DSS	8	75	4-267
###	2SK1319S	三菱	HS PSW	MOS	N	E	250	DSS	8	75	4-330
###	2SK1320	三菱	HS PSW	MOS	N	E	300	DSS	8	75	4-267
###	2SK1320S	三菱	HS PSW	MOS	N	E	300	DSS	8	75	4-330
###	2SK1321	三菱	HS PSW	MOS	N	E	450	DSS	5	75	4-267
###	2SK1321S	三菱	HS PSW	MOS	N	E	450	DSS	5	75	4-330
###	2SK1322	三菱	HS PSW	MOS	N	E	500	DSS	5	75	4-267
###	2SK1322S	三菱	HS PSW	MOS	N	E	500	DSS	5	75	4-330
###	2SK1323	三菱	HS PSW	MOS	N	E	800	DSS	2	75	4-267
###	2SK1323S	三菱	HS PSW	MOS	N	E	800	DSS	2	75	4-330
###	2SK1324	三菱	HS PSW	MOS	N	E	900	DSS	2	75	4-267
###	2SK1324S	三菱	HS PSW	MOS	N	E	900	DSS	2	75	4-330
###	2SK1325	东芝	SHF LN A	GaAs/M	N	D	-6	GDO	120m	200m	4-338
###	2SK1326	日立	Video-Band LN A	J	N	D	10	DSX	±1m	150m	4-185A
###	2SK1327(L)	日立	SW-Reg, DDC	MOS	N	E	600	DSS	1	20	4-150
###	2SK1328	日立	SW-Reg, DDC	MOS	N	E	450	DSS	12	60	4-293
###	2SK1329	日立	SW-Reg, DDC	MOS	N	E	500	DSS	12	60	4-293
###	2SK1330	松下	Motor-D, SW-Reg	MOS	N	E	800	DSS	8	100	4-191
###	2SK1330A	松下	Motor-D, SW-Reg	MOS	N	E	900	DSS	8	100	4-191
###	2SK1331	松下	Motor-D, SW-Reg	MOS	N	E	500	DSS	15	100	4-291
###	2SK1332	三洋	LF A	J	N	D	-30	GDS	10m	150m	4-255B
###	2SK1333	东芝	Motor-D, DDC	MOS	N	E	500	DSS	±15	200	4-337
###	2SK1334	日立	SW-Reg, DDC	MOS	N	E	200	DSS	1	1	4-295
###	2SK1335(L)	日立	SW-Reg, DDC	MOS	N	E	200	DSS	3	20	4-150
###	2SK1336	日立	Motor/Relay-D	MOS	N	E	60	DSS	0.3	400m	4-79B
###	2SK1337	日立	Motor/Relay-D	MOS	N	E	100	DSS	0.3	400m	4-79B
###	2SK1338	日立	SW-Reg, DDC	MOS	N	E	900	DSS	2	50	4-116B
###	2SK1339	日立	SW-Reg, DDC	MOS	N	E	900	DSS	3	80	4-149
###	2SK1340	日立	SW-Reg, DDC	MOS	N	E	900	DSS	5	100	4-149
###	2SK1341	日立	SW-Reg, DDC	MOS	N	E	900	DSS	6	100	4-149
###	2SK1342	日立	SW-Reg, DDC	MOS	N	E	900	DSS	8	100	4-149
###	2SK1344	东芝	Relay-D, DDC	MOS	N	E	60	DSS	12	30	4-335
###	2SK1345	东芝	Relay-D, DDC	MOS	N	E	60	DSS	20	40	4-335
###	2SK1346	东芝	SW-Reg, DDC	MOS	N	E	60	DSS	25	40	4-335
###	2SK1347	东芝	DDC, Motor-D	MOS	N	E	100	DSS	20	75	4-231
###	2SK1348	东芝	DDC, Motor-D	MOS	N	E	100	DSS	20	40	4-335
###	2SK1349	东芝	DDC, Motor-D	MOS	N	E	100	DSS	25	45	4-335
###	2SK1350	东芝	SW-Reg, DDC	MOS	N	E	200	DSS	15	45	4-335
###	2SK1351	东芝	SW-Reg, DDC	MOS	N	E	500	DSS	5	40	4-335
###	2SK1352	东芝	SW-Reg, DDC	MOS	N	E	500	DSS	7	45	4-335
###	2SK1356	东芝	SW-Reg, Motor-D	MOS	N	E	900	DSS	3	40	4-335
###	2SK1357	东芝	SW-Reg	MOS	N	E	900	DSS	5	125	4-184
###	2SK1358	东芝	SW-Reg	MOS	N	E	900	DSS	9	150	4-184
###	2SK1359	东芝	SW-Reg	MOS	N	E	1000	DSS	5	125	4-184
###	2SK1362	东芝	HS SW, SW-Reg	MOS	N	E	900	DSS	5	85	4-388
###	2SK1363	东芝	HS SW, SW-Reg	MOS	N	E	900	DSS	8	90	4-388
###	2SK1365	东芝	HS SW, SW-Reg	MOS	N	E	1000	DSS	7	90	4-388
###	2SK1371	日立	SW-Reg, DDC	MOS	N	E	450	DSS	20	125	4-28B
###	2SK1372	日立	SW-Reg, DDC	MOS	N	E	500	DSS	20	125	4-28B

5000种场效应管参数

更多彩电维修资料请到《彩电维修资料网》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道	方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
###	2SK1373	日立	SW-Reg, DDC	MOS	N	E	550	DSS	12	100	4-149
###	2SK1374	松下	SW	MOS	N	E	50	DS	50m	150m	4-233
###	2SK1375	三洋	C-MIC	J	N	D	-20	GDO	10m	100m	4-255B
###	2SK1377	东芝	SW-Reg, DDC	MOS	N	E	400	DSS	5.5	40	4-335
###	2SK1378	东芝	SW-Reg, DDC	MOS	N	E	400	DSS	10	125	4-231
###	2SK1379	东芝	DDC, Motor-D	MOS	N	E	60	DSS	50	150	4-184
###	2SK1380	东芝	DDC, Motor-D	MOS	N	E	60	DSS	60	200	4-337
###	2SK1381	东芝	DDC, Motor-D	MOS	N	E	100	DSS	50	150	4-184
###	2SK1382	东芝	DDC, Motor-D	MOS	N	E	100	DSS	60	200	4-337
###	2SK1383			SIT	N	E	200	DSS	3	8	4-305
###	2SK1384	富士电	SW-Reg, UPS, DDC	MOS	N	E	800	DSS	5	80	4-327
###	2SK1385	富士电	SW-Reg, UPS, DDC	MOS	N	E	800	DSS	9	100	4-327
###	2SK1386	富士电	SW-Reg, UPS, DDC	MOS	N	E	450	DSS	7	100	4-186
###	2SK1387	富士电机		MOS	N	E	60	DSS	35	40	4-235
###	2SK1388	富士电机		MOS	N	E	30	DSS	35	60	4-234
###	2SK1389	富士电机		MOS	N	E	60	DSS	50	125	4-186
###	2SK1390	富士电机		MOS	N	E	60	DSS	50	80	4-327
###	2SK1391	新电元		MOS	N	E	250	DSS	6	40	4-287
###	2SK1392	新电元		MOS	N		250	DSS	6	25	4-288
###	2SK1393	新电元		MOS	N		250	DSS	10	50	4-287
###	2SK1394	新电元		MOS	N		250	DSS	10	30	4-288
###	2SK1395	新电元		MOS	N		250	DSS	20	100	4-289
###	2SK1396	新电元		MOS	N		250	DSS	30	120	4-289
###	2SK1397	新电元		MOS	N		250	DSS	40	130	4-289
###	2SK1398	NEC	HS SW	MOS	N	E	50	DSS	100m	250m	4-104C
###	2SK1399	NEC	HS SW	MOS	N	E	50	DSS	100m	200m	4-275A
###	2SK1400	日立	SW-Reg, DDC	MOS	N	E	300	DSS	7	50	4-116B
###	2SK1400A	日立	SW-Reg, DDC	MOS	N	E	350	DSS	7	50	4-116B
###	2SK1401	日立	SW-Reg, DDC	MOS	N	E	300	DSS	15	100	4-149
###	2SK1401A	日立	SW-Reg, DDC	MOS	N	E	350	DSS	15	100	4-149
###	2SK1402	日立	SW-Reg, DDC	MOS	N	E	600	DSS	4	50	4-116B
###	2SK1402A	日立	SW-Reg, DDC	MOS	N	E	650	DSS	4	50	4-116B
###	2SK1403	日立	SW-Reg, DDC	MOS	N	E	600	DSS	8	100	4-149
###	2SK1403A	日立	SW-Reg, DDC	MOS	N	E	650	DSS	8	100	4-149
###	2SK1404	日立	SW-Reg, DDC	MOS	N	E	600	DSS	5	35	4-292
###	2SK1405	日立	SW-Reg, DDC	MOS	N	E	600	DSS	15	60	4-293
###	2SK1406	松下	Motor-D, SW-Reg	MOS	N	E	500	DSS	±20	100	4-291
###	2SK1407		MW A	HEMT	N	D	4	DSX	60m	200m	4-266
###	2SK1408	三菱	HS PSW	MOS	N	E	450	DSS	16	200	4-250
###	2SK1409	三菱	HS PSW	MOS	N	E	450	DSS	20	250	4-250
###	2SK1410	三菱	HS PSW	MOS	N	E	500	DSS	16	200	4-250
###	2SK1411	三菱	HS PSW	MOS	N	E	500	DSS	20	250	4-250
###	2SK1412	三洋	HV HS SW	MOS	N	E	1500	DSS	0.1	20	4-345
###	2SK1413	三洋	HV HS SW	MOS	N	E	1500	DSS	2	60	4-343
###	2SK1414	三洋	HV HS SW	MOS	N	E	1500	DSS	6	200	4-344
###	2SK1415	日立	SHF RF	GaAsHE	N	D	3.5	DS	60m	160m	
###	2SK1416	三洋	HS SW	MOS	N	E	60	DSS	15	40	4-242
###	2SK1417	三洋	HS SW	MOS	N	E	60	DSS	25	60	4-242
###	2SK1418	三洋	HS SW	MOS	N	E	60	DSS	40	70	4-242
###	2SK1419	三洋	HS SW	MOS	N	E	60	DSS	15	25	4-242
###	2SK1420	三洋	HS SW	MOS	N	E	60	DSS	25	30	4-284
###	2SK1421	三洋	HS SW	MOS	N	E	60	DSS	40	40	4-284
###	2SK1422	三洋	HS SW	MOS	N	E	60	DSS	50	100	4-243
###	2SK1423	三洋	HS SW	MOS	N	E	60	DSS	80	150	4-243
###	2SK1424	三洋	HS SW	MOS	N	E	60	DSS	40	60	4-343
###	2SK1425	三洋	HS SW	MOS	N	E	60	DSS	60	80	4-343
###	2SK1426	三洋	HS SW	MOS	N	E	60	DSS	100	200	4-344
###	2SK1427	三洋	HS SW	MOS	N	E	100	DSS	10	40	4-242
###	2SK1428	三洋	HS SW	MOS	N	E	100	DSS	20	60	4-242
###	2SK1429	三洋	HS SW	MOS	N	E	100	DSS	30	70	4-242
###	2SK1430	三洋	HS SW	MOS	N	E	100	DSS	10	25	4-284

5000种场效应管参数

更多彩电维修资料请到《[彩电维修资料网](http://www.tv160.net)》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道	方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
###	2SK1431	三洋	HS SW	MOS	N	E	100	DSS	15	30	4-284
###	2SK1432	三洋	HS SW	MOS	N	E	100	DSS	25	40	4-284
###	2SK1433	三洋	HS SW	MOS	N	E	100	DSS	30	100	4-243
###	2SK1434	三洋	HS SW	MOS	N	E	100	DSS	60	150	4-243
###	2SK1435	三洋	HS SW	MOS	N	E	100	DSS	30	60	4-343
###	2SK1436	三洋	HS SW	MOS	N	E	100	DSS	50	80	4-343
###	2SK1437	三洋	HS SW	MOS	N	E	100	DSS	70	200	4-344
###	2SK1438	三洋	HS SW	MOS	N	E	450	DSS	0.3	20	4-242
###	2SK1439	三洋	HS SW	MOS	N	E	450	DSS	3	50	4-242
###	2SK1440	三洋	HS SW	MOS	N	E	450	DSS	5	60	4-242
###	2SK1441	三洋	HS SW	MOS	N	E	450	DSS	8	70	4-242
###	2SK1442	三洋	HS SW	MOS	N	E	450	DSS	12	70	4-242
###	2SK1443	三洋	HS SW	MOS	N	E	450	DSS	1	20	4-345
###	2SK1444	三洋	HS SW	MOS	N	E	450	DSS	3	25	4-345
###	2SK1445	三洋	HS SW	MOS	N	E	450	DSS	5	30	4-345
###	2SK1446	三洋	HS SW	MOS	N	E	450	DSS	7	35	4-345
###	2SK1447	三洋	HS SW	MOS	N	E	450	DSS	9	40	4-345
###	2SK1448	三洋	HS SW	MOS	N	E	450	DSS	8	100	4-243
###	2SK1449	三洋	HS SW	MOS	N	E	450	DSS	12	120	4-243
###	2SK1450	三洋	HS SW	MOS	N	E	450	DSS	20	150	4-243
###	2SK1451	三洋	HS SW	MOS	N	E	450	DSS	8	50	4-343
###	2SK1452	三洋	HS SW	MOS	N	E	450	DSS	10	60	4-343
###	2SK1453	三洋	HS SW	MOS	N	E	450	DSS	16	70	4-343
###	2SK1454	三洋	HS SW	MOS	N	E	450	DSS	30	250	4-344
###	2SK1455	三洋	HS SW	MOS	N	E	900	DSS	0.2	30	4-242
###	2SK1456	三洋	HS SW	MOS	N	E	900	DSS	3	60	4-242
###	2SK1457	三洋	HS SW	MOS	N	E	900	DSS	5	70	4-242
###	2SK1458	三洋	HS SW	MOS	N	E	900	DSS	0.2	20	4-345
###	2SK1459	三洋	HS SW	MOS	N	E	900	DSS	2.5	30	4-345
###	2SK1460	三洋	HS SW	MOS	N	E	900	DSS	3.5	40	4-345
###	2SK1461	三洋	HS SW	MOS	N	E	900	DSS	5	120	4-243
###	2SK1462	三洋	HS SW	MOS	N	E	900	DSS	8	150	4-243
###	2SK1463	三洋	HS SW	MOS	N	E	900	DSS	4.5	60	4-343
###	2SK1464	三洋	HS SW	MOS	N	E	900	DSS	8	80	4-343
###	2SK1465	三洋	HS SW	MOS	N	E	900	DSS	8	200	4-344
###	2SK1466	三洋	HS SW	MOS	N	E	900	DSS	16	250	4-344
###	2SK1467	三洋	HS SW	MOS	N	E	30	DSS	2	3.5	4-252
###	2SK1468	三洋	HS SW	MOS	N	E	30	DSS	4	20	4-346
###	2SK1469	三洋	HS SW	MOS	N	E	30	DSS	8	30	4-346
###	2SK1470	三洋	HS SW	MOS	N	E	60	DSS	2	3.5	4-252
###	2SK1471	三洋	HS SW	MOS	N	E	60	DSS	4	20	4-346
###	2SK1472	三洋	HS SW	MOS	N	E	60	DSS	8	30	4-346
###	2SK1473	三洋	HS SW	MOS	N	E	100	DSS	2	3.5	4-252
###	2SK1474	三洋	HS SW	MOS	N	E	100	DSS	4	20	4-346
###	2SK1475	三洋	HS SW	MOS	N	E	100	DSS	8	30	4-346
###	2SK1476	三菱	HS PSW	MOS	N	E	450	DSS	12	150	4-250
###	2SK1477	三菱	HS PSW	MOS	N	E	500	DSS	12	150	4-250
###	2SK1478	松下	Motor-D, SW-Reg	MOS	N	E	250	DSS	8	40	4-190
###	2SK1479	日立	LF, CC	J	N	D	-25	GDO	5m	100m	4-185A
###	2SK1480	NEC	FM/VHS, TV Tune	MOS	N	D	20	DSX	±30m	200m	4-275
###	2SK1482	NEC	SW, Motor-D	MOS	N	E	30	DSS	±1.5	0.75	4-53C
###	2SK1483	NEC	SW, Motor-D	MOS	N	E	30	DSS	±2	2	4-216A
###	2SK1484	NEC	SW, DDC	MOS	N	E	100	DSS	±0.5	0.75	4-53D
###	2SK1485	NEC	SW, DDC	MOS	N	E	100	DSS	±1	2	4-216A
###	2SK1486	东芝	SW-Reg, DDC	MOS	N	E	300	DSS	32	200	4-337
###	2SK1487	东芝	SW-Reg, DDC	MOS	N	E	450	DSS	10	125	4-184
###	2SK1488	东芝	SW-Reg, DDC	MOS	N	E	500	DSS	10	125	4-184
###	2SK1489	东芝	SW-Reg, HS, HC S	MOS	N	E	1000	DSS	12	200	4-337
###	2SK1491	NEC	SW, SW-Reg, DDC	MOS	N	E	250	DSS	±25	120	4-308
###	2SK1492	NEC	SW, SW-Reg, DDC	MOS	N	E	250	DSS	±35	140	4-253
###	2SK1493, 1	NEC	SW, SW-Reg, DDC	MOS	N	E	450	DSS	±3	50	4-164/Z:306

5000种场效应管参数

更多彩电维修资料请到《彩电维修资料网》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道	方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
###	2SK1494, 1	NEC	SW, SW-Reg, DDC	MOS	N	E	500	DSS	±3	50	4-164/Z:306
###	2SK1495, 1	NEC	SW, SW-Reg, DDC	MOS	N	E	450	DSS	±7	70	4-164/Z:306
###	2SK1496, 1	NEC	SW, SW-Reg, DDC	MOS	N	E	500	DSS	±7	70	4-164/Z:306
###	2SK1497	NEC	SW, SW-Reg, DDC	MOS	N	E	450	DSS	±20	120	4-253
###	2SK1498	NEC	SW, SW-Reg, DDC	MOS	N	E	500	DSS	±20	120	4-253
###	2SK1499	NEC	SW, SW-Reg, DDC	MOS	N	E	450	DSS	±25	160	4-253
###	2SK1500	NEC	SW, SW-Reg, DDC	MOS	N	E	500	DSS	±25	160	4-253
###	2SK1501, 1	NEC	SW, DDC	MOS	N	E	900	DSS	±4	70	4-164/Z:306
###	2SK1502	NEC	SW, DDC	MOS	N	E	900	DSS	±7	120	4-253
###	2SK1503	富士电	SW-Reg, UPS, DDC	MOS	N	E	500	DSS	10	80	4-234
###	2SK1504-L,	富士电	SW-Reg, UPS, DDC	MOS	N	E	500	DSS	10	80	4-389
###	2SK1505	富士电机		MOS	N	E	30	DSS	35	40	4-235
###	2SK1506	富士电	SW-Reg, UPS, DDC	MOS	N	E	120	DSS	50	150	4-186
###	2SK1507	富士电	SW-Reg, UPS, DDC	MOS	N	E	600	DSS	9	50	4-390
###	2SK1508	富士电机		MOS	N	E	60	DSS	35	60	4-234
###	2SK1509	富士电机		MOS	N	E	100	DSS	20	60	4-234
###	2SK1510-L,	富士电	SW-Reg, UPS, DDC	MOS	N	E	900	DSS	3.5	60	4-389
###	2SK1511	富士电机		MOS	N	E	1000	DSS	5	100	
###	2SK1512	富士电机		MOS	N	E	900	DSS	10	150	
###	2SK1513	东芝	Motor-D, DDC	MOS	N	E	500	DSS	±8	150	4-337
###	2SK1514	日立	Motor/Relay-D	MOS	N	E	60	DSS	40	125	4-149
###	2SK1515	日立	Motor-D, SW-Reg	MOS	N	E	450	DSS	10	100	4-149
###	2SK1516	日立	Motor-D, SW-Reg	MOS	N	E	500	DSS	10	100	4-149
###	2SK1517	日立	Motor-D, SW-Reg	MOS	N	E	450	DSS	20	120	4-149
###	2SK1518	日立	Motor-D, SW-Reg	MOS	N	E	500	DSS	20	120	4-149
###	2SK1519	日立	Motor-D, SW-Reg	MOS	N	E	450	DSS	30	200	4-296
###	2SK1520	日立	Motor-D, SW-Reg	MOS	N	E	500	DSS	30	200	4-296
###	2SK1521	日立	Motor-D, SW-Reg	MOS	N	E	450	DSS	50	250	4-296
###	2SK1522	日立	Motor-D, SW-Reg	MOS	N	E	500	DSS	50	250	4-296
###	2SK1523	新电元	HS SW	MOS	N	E	500	DSS	10	55	4-384
###	2SK1524	新电元	HS SW	MOS	N	E	500	DSS	15	65	4-384
###	2SK1525	新电元	HS SW	MOS	N	E	500	DSS	20	70	4-384
###	2SK1526	日立	HS PSW, DDC	MOS	N	E	450	DSS	40	250	4-296
###	2SK1527	日立	HS PSW, DDC	MOS	N	E	500	DSS	40	250	4-296
###	2SK1528(L)	日立	SW-Reg, DDC	MOS	N	E	900	DSS	4	60	4-294
###	2SK1529	东芝	LF PA	MOS	N		180	DSS	±10	120	4-184
###	2SK1530	东芝	LF PA	MOS	N		200	DSS	±12	150	4-337
###	2SK1531	东芝	SW-Reg, DDC	MOS	N	E	500	DSS	15	150	4-184
###	2SK1532	日立	LF A, A-SW	J	N	D	-50	GDO	10m	100m	4-CMPAK
###	2SK1533	新电元		MOS	N		900	DSS	1	10	4-381
###	2SK1534	新电元		MOS	N		900	DSS	3	50	4-287
###	2SK1535	新电元		MOS	N		900	DSS	3	30	4-288
###	2SK1536	新电元		MOS	N		900	DSS	3	70	4-289
###	2SK1537	新电元		MOS	N		900	DSS	5	100	4-289
###	2SK1538	新电元		MOS	N		900	DSS	7	130	4-289
###	2SK1539	新电元		MOS	N		900	DSS	10	150	4-289
###	2SK1540(L)	日立	SW-Reg, DDC	MOS	N	E	450	DSS	7	60	4-294
###	2SK1541(L)	日立	SW-Reg, DDC	MOS	N	E	500	DSS	7	60	4-294
###	2SK1542	东芝	Motor-D, DDC	MOS	N	E	60	DSS	45	125	4-231
###	2SK1544	东芝	SW-Reg, DDC	MOS	N	E	500	DSS	25	200	4-337
###	2SK1545	富士电机		MOS	N	E	800	DSS	3	40	
###	2SK1546	富士电机		MOS	N	E	900	DSS	2.5	40	
###	2SK1547	富士电	SW-Reg, UPS, DDC	MOS	N	E	800	DSS	4	40	4-390
###	2SK1548	富士电	SW-Reg, UPS, DDC	MOS	N	E	900	DSS	3.5	40	4-390
###	2SK1549	富士电	SW-Reg, UPS, DDC	MOS	N	E	250	DSS	20	80	4-327
###	2SK1550	富士电机		MOS	N	E	600	DSS	4	40	
###	2SK1552-L,	富士电	SW-Reg, UPS, DDC	MOS	N	E	800	DSS	4	60	4-389
###	2SK1553	富士电	SW-Reg, UPS, DDC	MOS	N	E	650	DSS	5	40	4-390
###	2SK1554	富士电机		MOS	N	E	650	DSS	3	30	
###	2SK1555, 1	三菱	HS PSW	MOS	N	E	50	DSS	16	75	4-267/S:330
###	2SK1556	三菱	HS PSW	MOS	N	E	100	DSS	8	30	4-215

5000种场效应管参数

更多彩电维修资料请到《[彩电视维修资料网](http://www.tv160.net)》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道	方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
###	2SK1557	三菱	HS PSW	MOS	N	E	100	DSS	8	45	4-331
###	2SK1558	三菱	HS PSW	MOS	N	E	100	DSS	15	40	4-215
###	2SK1559, 1	三菱	HS PSW	MOS	N	E	100	DSS	16	75	4-267/S:330
###	2SK1560	三菱	HS PSW	MOS	N	E	150	DSS	7	45	4-331
###	2SK1561	三菱	HS PSW	MOS	N	E	150	DSS	16	75	4-267
###	2SK1561S	三菱	HS PSW	MOS	N	E	150	DSS	16	75	4-330
###	2SK1562	三菱	HS PSW	MOS	N	E	450	DSS	12	150	4-267
###	2SK1562S	三菱	HS PSW	MOS	N	E	450	DSS	12	150	4-330
###	2SK1563	三菱	HS PSW	MOS	N	E	500	DSS	12	150	4-267
###	2SK1563S	三菱	HS PSW	MOS	N	E	500	DSS	12	150	4-330
###	2SK1564	三菱	HS PSW	MOS	N	E	800	DSS	3	150	4-267
###	2SK1564S	三菱	HS PSW	MOS	N	E	800	DSS	3	150	4-330
###	2SK1565	三菱	HS PSW	MOS	N	E	900	DSS	3	150	4-267
###	2SK1565S	三菱	HS PSW	MOS	N	E	900	DSS	3	150	4-330
###	2SK1566	日立	SW-Reg, DDC	MOS	N	E	450	DSS	7	35	4-292
###	2SK1567	日立	SW-Reg, DDC	MOS	N	E	500	DSS	7	35	4-292
###	2SK1568	三菱	HS PSW, Inverter	MOS	N	E	250	DSS	8	40	4-215
###	2SK1569	三菱	HS PSW, Inverter	MOS	N	E	300	DSS	8	40	4-215
###	2SK1570	三菱	HS PSW Inverter	MOS	N	E	450	DSS	12	150	4-250
###	2SK1571	三菱	HS PSW Inverter	MOS	N	E	500	DSS	12	150	4-250
###	2SK1572	日立	SW-Reg, DDC	MOS	N	E	600	DSS	3	25	4-292
###	2SK1573	日立	SW-Reg, DDC	MOS	N	E	600	DSS	15	125	4-149
###	2SK1574	东芝	SW-Reg, DDC	MOS	N	E	500	DSS	8	125	4-231
###	2SK1575	日立	VHF A	MOS	N	E	180	DSS	16	200	4-381
###	2SK1576		LF LN A, RF, LPP	J	N	D	30	DGO	5m	150m	4-307
###	2SK1577		UHF LN A	J	N	D	35	DGO	10m	150m	4-307
###	2SK1578	三洋	C-Mic	M	N	D	-20	GDO	10m	100m	4-157A
###	2SK1579	日立	HS PSW, D	MOS	N	E	12	DSS	2	1	4-295
###	2SK1580	NEC	SW	MOS	N	E	16	DSS	±100m	150m	4-246C
###	2SK1581	NEC	SW	MOS	N	E	16	DSS	±200m	200m	4-275A
###	2SK1582	NEC	SW	MOS	N	E	30	DSS	±200m	200m	4-275A
###	2SK1583	NEC	SW	MOS	N	E	16	DSS	±0.5	2	4-216A
###	2SK1584	NEC	SW	MOS	N	E	30	DSS	±0.5	2	4-216A
###	2SK1585	NEC	SW	MOS	N	E	16	DSS	±1	2	4-216A
###	2SK1586	NEC	SW	MOS	N	E	30	DSS	±1	2	4-216A
###	2SK1587	NEC	SW	MOS	N	E	16	DSS	±2	2	4-216B
###	2SK1588	NEC	SW	MOS	N	E	16	DSS	±3	2	4-216A
###	2SK1589	NEC	SW	MOS	N	E	100	DSS	100m	200m	4-275A
###	2SK1590	NEC	SW	MOS	N	E	60	DSS	200m	200m	4-275A
###	2SK1591	NEC	SW	MOS	N	E	100	DSS	200m	200m	4-275A
###	2SK1592	NEC	SW, Motor-D	MOS	N	E	60	DSS	±0.5	2	4-216A
###	2SK1593	NEC	SW, Motor-D	MOS	N	E	100	DSS	±0.5	2	4-216A
###	2SK1594	NEC	SW, Motor-D	MOS	N	E	30	DSS	±20	30	4-304
###	2SK1595	NEC	SW, Motor-D	MOS	N	E	30	DSS	±30	35	4-304
###	2SK1596	NEC	SW, Motor-D	MOS	N	E	30	DSS	±40	35	4-304
###	2SK1600	东芝	SW-Reg, DDC	MOS	N	E	800	DSS	3	75	4-231
###	2SK1601	东芝	SW-Reg, DDC	MOS	N	E	900	DSS	3	75	4-231
###	2SK1602	东芝	SW-Reg, DDC	MOS	N	E	800	DSS	2.8	40	4-335
###	2SK1603	东芝	SW-Reg, DDC	MOS	N	E	900	DSS	2.5	40	4-335
###	2SK1605	松下	SW, RF PA	MOS	N	E	450	DSS	5	50	4-190
###	2SK1606	松下	SW, RF PA	MOS	N	E	450	DSS	8	50	4-190
###	2SK1607	松下	SW, RF PA	MOS	N	E	450	DSS	13	120	4-196
###	2SK1608	松下	SW, RF PA	MOS	N	E	500	DSS	5	50	4-190
###	2SK1609	松下	SW, RF PA	MOS	N	E	500	DSS	8	50	4-190
###	2SK1610	松下	SW, RF PA	MOS	N	E	500	DSS	13	120	4-196
###	2SK1611	松下	SW, RF PA	MOS	N	E	800	DSS	3	50	4-190
###	2SK1612	松下	SW, RF PA	MOS	N	E	900	DSS	3	50	4-190
###	2SK1613	松下	SW, RF PA	MOS	N	E	900	DSS	5	100	4-191
###	2SK1614	松下	SW, RF PA	MOS	N	E	900	DSS	8	120	4-196
###	2SK1615	日立	SHF LN A	GaAsHE	N	D	3.5	DS	60m	160m	
###	2SK1616	日立	SHF LN A	GaAsHE	N	D	3.5	DS	70m	180m	4- μ FPAK

5000种场效应管参数

更多彩电维修资料请到《彩电维修资料网》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道	方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing	
###	2SK1617	日立	SHF LN A	GaAsHE	N	D	3.5	DS	60m	160m	4-μ FPAK	
###	2SK1618(L)	日立	SW-Reg, DDC	MOS	N	E	600	DSS	3	30	4-294	
###	2SK1619	东芝	SHF LN A	GaAs	N	D	-3	GDO	60m	150m	4-338	
###	2SK1620(L)	日立	SW-Reg, DDC	MOS	N	E	150	DSS	10	50	4-294	
###	2SK1621(L)	日立	SW-Reg, DDC	MOS	N	E	250	DSS	7	50	4-294	
###	2SK1622(L)	日立	Motor/Relay-D	MOS	N	E	60	DSS	25	50	4-294	
###	2SK1623(L)	日立	Motor/Relay-D	MOS	N	E	100	DSS	20	50	4-294	
###	2SK1624(L)	日立	SW-Reg, DDC	MOS	N	E	600	DSS	4	50	4-294	
###	2SK1625(L)	日立	SW-Reg, DDC	MOS	N	E	600	DSS	7	75	4-294	
###	2SK1626	日立	SW-Reg, DDC	MOS	N	E	450	DSS	5	35	4-292	
###	2SK1627	日立	SW-Reg, DDC	MOS	N	E	500	DSS	5	35	4-292	
###	2SK1628	日立	SW-Reg, DDC	MOS	N	E	450	DSS	30	200	4-296	
###	2SK1629	日立	SW-Reg, DDC	MOS	N	E	500	DSS	30	200	4-296	
###	2SK1630, 1	三菱	HS PSW, SW-Reg	MOS	N	E	700	DSS	3	75	4-267/S:330	
###	2SK1631	三菱	HS PSW, SW-Reg	MOS	N	E	700	DSS	3	35	4-215	
###	2SK1632, 1	三菱	HS PSW, SW-Reg	MOS	N	E	700	DSS	5	150	4-267/S:330	
###	2SK1633	三菱	HS PSW, SW-Reg	MOS	N	E	700	DSS	5	45	4-215	
###	2SK1634	三菱	HS PSW, SW-Reg	MOS	N	E	700	DSS	5	150	4-250	
###	2SK1635	松下	HS SW, RF PA	MOS	N	E	60	DSS	50	130	4-258	
###	2SK1636(L)	日立	SW-Reg, DDC	MOS	N	E	250	DSS	15	75	4-294	
###	2SK1637	日立	SW-Reg, DDC	MOS	N	E	600	DSS	4	35	4-292	
###	2SK1638	日立	SW-Reg, DDC	MOS	N	E	900	DSS	3	60	4-116B	
###	2SK1639	日立	SW-Reg, DDC	MOS	N	E	900	DSS	4	75	4-116B	
###	2SK1641	东芝	SW-Reg, DDC	MOS	N	E	250	DSS	20	150	4-184	
###	2SK1642	东芝	SW-Reg, DDC	MOS	N	E	400	DSS	9	45	4-235	
###	2SK1643	东芝	SW-Reg, DDC	MOS	N	E	900	DSS	5	125	4-231	
###	2SK1647(L)	日立	SW-Reg, DDC	MOS	N	E	900	DSS	2	50	4-294	
###	2SK1648(L)	日立	Motor/Relay-D	MOS	N	E	60	DSS	15	40	4-294	
###	2SK1649	东芝	SW-Reg, HS HC SW	MOS	N	E	900	DSS	6	150	4-184	
###	2SK1650	东芝	SW-Reg, HS, HC SW	MOS	N	E	900	DSS	4	125	4-184	
###	2SK1651	东芝	HS SW, SW-Reg, D	MOS	N	E	500	DSS	8	80	4-388	
###	2SK1653	东芝	Motor-D, DDC	MOS	N	E	60	DSS	45	45	4-235	
###	2SK1654	三菱		MOS	N		250	DSS	16		4-TO-220	
###	2SK1655	三菱		MOS	N		300	DSS	16		4-TO-220	
###	2SK1656	NEC		MOS	N	E	30	DSS	±100m	250m	4-104A	
###	2SK1657	NEC		MOS	N	E	30	DSS	±100m	200m	4-275B	
###	2SK1658	NEC		MOS	N	E	30	DSS	±100m	150m	4-255	
###	2SK1659-L	富士电机	SW-Reg, UPS, DDC	MOS	N	E	900	DSS	3	80	4-389	
###	2SK1660	富士电机		MOS	N	E	450	DSS	10	80		
###	2SK1661	富士电机		MOS	N	E	200	DSS	20	80		
###	2SK1662	富士电机		MOS	N	E	700	DSS	3	40		
###	2SK1663-L	富士电机	SW-Reg, UPS, DDC	MOS	N	E	800	DSS	3	80	4-389	
###	2SK1664	NEC	SW, SW-Reg, DDC	MOS	N	E	700	DSS	±2	30	4-304	
###	2SK1665	日立	Motor/Relay-D	MOS	N	E	60	DSS	45	125	4-149	
###	2SK1666	日立	Motor/Relay-D	MOS	N	E	60	DSS	45	60	4-293	
###	2SK1667	日立	HS PSW	MOS	N	E	250	DSS	7	50	4-116B	
###	2SK1668	日立	HS PSW, DDC	MOS	N	E	250	DSS	7	30	4-292	
###	2SK1669	日立	Motor-D, SW-Reg	MOS	N	E	250	DSS	30	125	4-149	
###	2SK1670	日立	Motor-D, SW-Reg	MOS	N	E	250	DSS	30	70	4-293	
###	2SK1671	日立	SW-Reg, DDC	MOS	N	E	250	DSS	30	125	4-149	
###	2SK1672	新电元	HS SW	MOS	N	E	500	DSS	1	10	4-381	
###	2SK1673	三菱	HS PSW, Motor-D	MOS	N	E	250	DSS	24	200	4-250	
###	2SK1674	三菱	HS PSW, Motor-D	MOS	N	E	300	DSS	24	200	4-250	
###	2SK1675	三菱	HS PSW, Motor-D	MOS	N	E	250	DSS	30	250	4-250	
###	2SK1676	三菱	HS PSW, Motor-D	MOS	N	E	300	DSS	30	250	4-250	
###	2SK1677	三菱	HS PSW, Motor-D	MOS	N	E	450	DSS	16	200	4-250	
###	2SK1678	三菱	HS PSW, Motor-D	MOS	N	E	500	DSS	16	200	4-250	
###	2SK1679	三菱	HS PSW, Motor-D	MOS	N	E	450	DSS	20	250	4-250	
###	2SK1680	三菱	HS PSW, Motor-D	MOS	N	E	500	DSS	20	250	4-250	
###	2SK1681	新电元	HS SW	MOS	N	E	500	DSS	30	300	4-385	
###	2SK1682		RF/LF A, CC, Imp	J	N	D	28	30	DGO	10m	150m	4-307

5000种场效应管参数

更多彩电维修资料请到《彩电维修资料网》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道	方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
###	2SK1683	新电元	HS SW	MOS	N	E	900	DSS	3	50	4-384
###	2SK1684	新电元	HS SW	MOS	N	E	900	DSS	5	55	4-384
###	2SK1685	新电元	HS SW	MOS	N	E	900	DSS	7	65	4-384
###	2SK1686	新电元	HS SW	MOS	N	E	900	DSS	10	70	4-384
###	2SK1687	松下	X-Ku-Band, LN A	HEMT	N	D	-4	GDO	60m	200m	4-218
###	2SK1688	松下	X-Ku-Band, LN A	HEMT	N	D	-4	GDO	60m	200m	4-218
###	2SK1689	松下	X-Ku-Band LN A	GaAs	N	D	-6	GDO	70m	200m	4-218
###	2SK1690	三洋	HS SW	MOS	N	E	450	DSS	3	50	4-370
###	2SK1691	三洋	HS SW	MOS	N	E	450	DSS	5	60	4-370
###	2SK1692	东芝	SW-Reg, HS HC SW	MOS	N	E	900	DSS	7	150	4-184
###	2SK1693	新电元	HS SW	MOS	N	E	500	DSS	8	60	4-287
###	2SK1694	新电元	HS SW	MOS	N	E	500	DSS	8	35	4-288
###	2SK1695	新电元	HS SW	MOS	N	E	500	DSS	10	80	4-359
###	2SK1696	新电元	HS SW	MOS	N	E	500	DSS	10	50	4-384
###	2SK1697	日立	HS PSW	MOS	N	E	60	DSS	0.5	1	4-295
###	2SK1698	日立	HS PSW, DDC	MOS	N	E	100	DSS	0.3	1	4-295
###	2SK1699	三菱	HS PSW, SW-Reg	MOS	N	E	450	DSS	5	75	4-267
###	2SK1699S	三菱	HS PSW, SW-Reg	MOS	N	E	450	DSS	5	75	4-330
###	2SK1700	三菱	HS PSW, SW-Reg	MOS	N	E	450	DSS	5	35	4-215
###	2SK1701	三菱		MOS	N		450	DSS	8		4-TO-220
###	2SK1702	三菱		MOS	N		450	DSS	8		4-TO-220F
###	2SK1703	三菱	HS PSW, SW-Reg	MOS	N	E	500	DSS	5	75	4-267
###	2SK1703S	三菱	HS PSW, SW-Reg	MOS	N	E	500	DSS	5	75	4-330
###	2SK1704	三菱	HS PSW, SW-Reg	MOS	N	E	500	DSS	5	35	4-215
###	2SK1705	三菱		MOS	N		500	DSS	8		4-TO-3P
###	2SK1706	三菱		MOS	N		500	DSS	8		4-TO-220F
###	2SK1707	三菱		MOS	N		600	DSS	4		4-TO-220
###	2SK1708	三菱		MOS	N		600	DSS	4		4-TO-220F
###	2SK1709	三菱		MOS	N		600	DSS	6		4-TO-220
###	2SK1710	三菱		MOS	N		600	DSS	6		4-TO-220F
###	2SK1716	东芝	Motor-D, DDC	MOS	N	E	60	DSS	2	20	4-235
###	2SK1717	东芝	Motor-D, DDC	MOS	N	E	60	DSS	2	1.5	4-256
###	2SK1718	东芝	Motor-D, DDC	MOS	N	E	60	DSS	6	25	4-235
###	2SK1719	东芝	Motor-D, DDC	MOS	N	E	60	DSS	5	20	4-257
###	2SK1720	东芝	SW-Reg, DDC	MOS	N	E	60	DSS	45	100	4-341
###	2SK1721	东芝	SW-Reg, DDC	MOS	N	E	500	DSS	3	40	4-341
###	2SK1722	东芝	SW-Reg, DDC	MOS	N	E	500	DSS	5	60	4-341
###	2SK1723	东芝	SW-Reg, DDC	MOS	N	E	600	DSS	12	150	4-184
###	2SK1724	三洋	HS SW	MOS	N	E	30	DSS	1	3.5	4-252
###	2SK1725	三洋	HS SW	MOS	N	E	30	DSS	1	1	4-348
###	2SK1726	三洋	HS SW	MOS	N	E	60	DSS	1	3.5	4-252
###	2SK1727	三洋	HS SW	MOS	N	E	60	DSS	0.8	1	4-348
###	2SK1728	三洋	HS SW	MOS	N	E	100	DSS	1	3.5	4-252
###	2SK1729	三洋	HS SW	MOS	N	E	100	DSS	0.5	3.5	4-348
###	2SK1730	三洋	HS SW	MOS	N	E	30	DSS	1.8	1	4-348
###	2SK1731	三洋	HS SW	MOS	N	E	30	DSS	3	1.5	4-347
###	2SK1732	三洋	HS SW	MOS	N	E	30	DSS	4.5	1.5	4-347
###	2SK1733	三洋	HS SW	MOS	N	E	60	DSS	1.5	1	4-348
###	2SK1734	三洋	HS SW	MOS	N	E	60	DSS	2.5	1.5	4-347
###	2SK1735	三洋	HS SW	MOS	N	E	60	DSS	4	1.5	4-347
###	2SK1736	三洋	HS SW	MOS	N	E	100	DSS	1	1	4-348
###	2SK1737	三洋	HS SW	MOS	N	E	100	DSS	1.8	1.5	4-347
###	2SK1738	三洋	HS SW	MOS	N	E	100	DSS	3	1.5	4-347
###	2SK1740	三洋	RF/LF A, A-SW	J	N	D	-40	GDS	10m	250m	4-126A
###	2SK1741	三洋	HS SW	MOS	N	E	100	DSS	10	40	4-369
###	2SK1745	东芝	Motor-D, DDC	MOS	N	E	500	DSS	18	150	4-184
###	2SK1746	东芝	SW-Reg, DDC	MOS	N	E	600	DSS	2	40	4-341
###	2SK1747	三洋	RF/LF A, A-SW	J	N	D	-40	GDS	10m	400m	4-107
###	2SK1748, 1	NEC	SW, Motor-D	MOS	N	E	60	DSS	±8	1	4-276/Z:277
###	2SK1749	NEC		MOS	N	E	60	DSS	±50	150	4-308
###	2SK1750, 1	NEC	RF SW, DDC	MOS	N	E	450	DSS	±5	50	4-287/Z:306

5000种场效应管参数

更多彩电维修资料请到《彩电维修资料网》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道	方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
###	2SK1751, 1	NEC	RF SW, DDC	MOS	N	E	500	DSS	±5	50	4-287/Z:306
###	2SK1752	NEC	SW, SW-Reg, DDC	MOS	N	E	450	DSS	±10	100	4-308
###	2SK1753	NEC	SW, SW-Reg, DDC	MOS	N	E	500	DSS	±10	100	4-308
###	2SK1754	三菱	HS PSW	MOS	N	E	50	DSS	10	45	4-331
###	2SK1756	NEC	RF SW, DDC	MOS	N	E	450	DSS	±15	120	4-253
###	2SK1757	NEC	RF SW, DDC	MOS	N	E	500	DSS	±15	120	4-253
###	2SK1758	NEC	RF SW, DDC	MOS	N	E	600	DSS	±2	30	4-253
###	2SK1760	NEC	RF SW, DDC	MOS	N	E	900	DSS	±5	100	4-253
###	2SK1761	日立	HS PSW	MOS	N	E	250	DSS	12	75	4-116B
###	2SK1762	日立	HS PSW	MOS	N	E	250	DSS	12	35	4-292
###	2SK1763(L)	日立	HS PSW	MOS	N	E	30	DSS	2.5	10	4-150
###	2SK1764	日立	HS PSW	MOS	N	E	60	DSS	2	1	4-295
###	2SK1766	东芝	HS SW, SW-Reg, DDC	MOS	N	E	250	DSS	10	40	4-335
###	2SK1767	东芝	Motor-D, DDC	MOS	N	E	600	DSS	3.5	40	4-335
###	2SK1768	东芝	Motor-D, DDC	MOS	N	E	60	DSS	12	15	4-342
###	2SK1769	东芝	SW-Reg, DDC	MOS	N	E	600	DSS	2	15	4-342
###	2SK1770	日立	HS PSW, SW-Reg	MOS	N	E	1000	DSS	5	60	4-293
###	2SK1772	日立	HS PSW, DDC	MOS	N	E	30	DSS	1	1	4-295
###	2SK1773	日立	HS PSW, SW-Reg	MOS	N	E	1000	DSS	5	100	4-149
###	2SK1774	日立	HS PSW	MOS	N	E	800	DSS	7	60	4-293
###	2SK1775	日立	HS PSW	MOS	N	E	900	DSS	8	60	4-293
###	2SK1776	日立	HS PSW	MOS	N	E	60	DSS	10	20	4-292
###	2SK1777	日立	HS PSW	MOS	N	E	60	DSS	15	25	4-292
###	2SK1778	日立	HS PSW	MOS	N	E	100	DSS	10	25	4-292
###	2SK1784	NEC	RF SW, DDC	MOS	N	E	450	DSS	±12	100	4-253
###	2SK1785	NEC	RF SW, DDC	MOS	N	E	500	DSS	±12	100	4-253
###	2SK1792	东芝	Motor-D, DDC	MOS	N	E	60	DSS	45	100	4-341
###	2SK1793, 1	NEC	RF SW, DDC	MOS	N	E	900	DSS	±3	75	4-164/Z:306
###	2SK1794	NEC	RF SW, DDC	MOS	N	E	900	DSS	±6	100	4-253
###	2SK1795	NEC	RF SW, DDC	MOS	N	E	900	DSS	±8	140	4-253
###	2SK1796	NEC	RF SW, DDC	MOS	N	E	900	DSS	±10	150	4-253
###	2SK1803	松下	Motor/Relay-D, S	MOS	N	E	900	DSS	8	100	4-291
###	2SK1804	东芝	Motor-D, DDC	MOS	N	E	100	DSS	5	20	4-257
###	2SK1805	东芝	Motor-D, DDC	MOS	N	E	500	DSS	7	45	4-335
###	2SK1806	三洋	LF A, Imp-C	J	N	D	-30	GDS	10m	250m	4-127
###	2SK1807	日立	HS PSW	MOS	N	E	900	DSS	4	60	4-116B
###	2SK1808	日立	HS PSW	MOS	N	E	900	DSS	4	35	4-292
###	2SK1809	日立	HS PSW, SW-Reg	MOS	N	E	600	DSS	5	60	4-116B
###	2SK1810	新电元	HS SW	MOS	N	E	300	DSS	10	50	4-287
###	2SK1811	新电元	HS SW	MOS	N	E	300	DSS	20	100	4-359
###	2SK1812	新电元	HS SW	MOS	N	E	300	DSS	30	120	4-359
###	2SK1813	三洋	HS SW	MOS	N	E	100	DSS	30	70	4-359
###	2SK1814	富士电机		MOS	N	E	60	DSS	20	45	4-234
###	2SK1815	富士电机		MOS	N	E	60	DSS	35	50	4-327
###	2SK1816	富士电机		MOS	N	E	100	DSS	5	20	
###	2SK1817	富士电机		MOS	N	E	100	DSS	20	40	4-390
###	2SK1818	富士电机		MOS	N	E	250	DSS	20	50	4-390
###	2SK1819	富士电机		MOS	N	E	450	DSS	5	35	4-390
###	2SK1820-L,	富士电机		MOS	N	E	500	DSS	6	80	4-389
###	2SK1821	富士电机		MOS	N	E	600	DSS	2	30	4-390
###	2SK1822	富士电机		MOS	N	E	60	DSS	20	35	4-390
###	2SK1823	富士电机		MOS	N	E	60	DSS	50	80	4-327
###	2SK1824	NEC		MOS	N	E	30	DSS	±0.1	0.2	4-356
###	2SK1831	日立	HS PSW	MOS	N	E	450	DSS	10	50	4-293
###	2SK1832	日立	HS PSW	MOS	N	E	500	DSS	10	50	4-293
###	2SK1833	松下	Motor/Relay-D, S	MOS	N	E	500	DSS	2.5	40	4-190
###	2SK1834	松下	Motor/Relay-D, S	MOS	N	E	800	DSS	2	40	4-190
###	2SK1835	日立	HS PSW	MOS	N	E	1500	DSS	4	125	4-149
###	2SK1836	日立	HS PSW, SW-Reg	MOS	N	E	450	DSS	50	250	4-296
###	2SK1837	日立	HS PSW, SW-Reg	MOS	N	E	500	DSS	50	250	4-296
###	2SK1838(L)	日立	HS PSW, DDC	MOS	N	E	250	DSS	1	10	4-150

5000种场效应管参数

更多彩电维修资料请到《[彩电维修资料网](http://www.tv160.net)》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道	方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
###	2SK1839	三洋	A-SW	MOS	N	E	30	DSS	100m	150m	4-255A
###	2SK1840	三洋	A-SW	MOS	N	E	30	DSS	100m	200m	4-126B
###	2SK1841	三洋	A-SW	MOS	N	E	30	DSS	100m	200m	4-157B
###	2SK1842	松下	Imp-C, IR	J	N	D	-40	GDO	10m	150m	4-193D
###	2SK1846	松下	Motor/Relay-D, S	MOS	N	E	800	DSS	3	40	4-249
###	2SK1847	三洋	HS SW	MOS	N	E	30	DSS	0.5	250m	4-368
###	2SK1848	三洋	HS SW	MOS	N	E	60	DSS	0.4	250m	4-368
###	2SK1849	三洋	HS SW	MOS	N	E	100	DSS	0.25	250m	4-368
###	2SK1850	NEC	SW, Motor-D	MOS	N	E	60	DSS	±10	1.8	4-365
###	2SK1851	NEC	SW, Motor-D	MOS	N	E	60	DSS	±15	1.8	4-365
###	2SK1852	NEC	SW, Motor-D	MOS	N	E	100	DSS	±10	1.8	4-365
###	2SK1853	NEC	SW, Motor-D	MOS	N	E	100	DSS	±15	1.8	4-365
###	2SK1854	东芝	HS SW, SW-Reg, D	MOS	N	E	400	DSS	6	40	4-335
###	2SK1855	东芝	HS SW, DDC	MOS	N	E	500	DSS	12	125	4-184
###	2SK1858	东芝	HS SW, SW-Reg, D	MOS	N	E	800	DSS	3	60	4-341
###	2SK1859	日立	HS PSW	MOS	N	E	900	DSS	6	60	4-293
###	2SK1861	新电元	HS SW	MOS	N	E	150	DSS	4	10	4-381
###	2SK1862	日立	HS PSW, SW-Reg	MOS	N	E	450	DSS	3	25	4-292
###	2SK1863	日立	HS PSW, SW-Reg	MOS	N	E	500	DSS	3	25	4-292
###	2SK1864	东芝	HS SW, SW-Reg, D	MOS	N	E	500	DSS	8	100	4-341
###	2SK1865	东芝	HS SW, SW-Reg, D	MOS	N	E	500	DSS	12	100	4-341
###	2SK1867	松下	Motor/Relay-D, S	MOS	N	E	900	DSS	2	15	4-349
###	2SK1868	松下	Motor/Relay-D, S	MOS	N	E	60	DSS	3	15	4-349
###	2SK1869(L)	日立	HS PSW, SW-Reg	MOS	N	E	350	DSS	7	50	4-294
###	2SK1876	富士电机		MOS	N	E	450	DSS	10	80	
###	2SK1877	日立	HS PSW	MOS	N	E	60	DSS	10	12	4-363A
###	2SK1878	日立	HS PSW	MOS	N	E	100	DSS	10	12	4-363A
###	2SK1879	东芝	HS SW, SW-Reg, D	MOS	N	E	60	DSS	45	125	4-184
###	2SK1880(L)	日立	HS PSW, SW-Reg	MOS	N	E	600	DSS	1.5	20	4-150
###	2SK1881-L,	富士电机		MOS	N	E	60	DSS	20	45	4-389
###	2SK1882	东芝	HS SW, SW-Reg, D	MOS	N	E	60	DSS	25	40	4-335
###	2SK1886	三洋	HS SW	MOS	N	E	30	DSS	15	25	4-284
###	2SK1887	三洋	HS SW	MOS	N	E	30	DSS	20	25	4-284
###	2SK1888	三洋	HS SW	MOS	N	E	30	DSS	30	30	4-284
###	2SK1889	三洋	HS SW	MOS	N	E	30	DSS	18	50	4-370
###	2SK1890	三洋	HS SW	MOS	N	E	30	DSS	22	60	4-370
###	2SK1891	三洋	HS SW	MOS	N	E	30	DSS	35	70	4-370
###	2SK1895	三洋	HS SW	MOS	N	E	60	DSS	12	25	4-284
###	2SK1896	三洋	HS SW	MOS	N	E	60	DSS	15	25	4-284
###	2SK1897	三洋	HS SW	MOS	N	E	60	DSS	25	30	4-284
###	2SK1898	三洋	HS SW	MOS	N	E	60	DSS	15	50	4-370
###	2SK1899	三洋	HS SW	MOS	N	E	60	DSS	18	60	4-370
###	2SK1900	三洋	HS SW	MOS	N	E	60	DSS	30	70	4-370
###	2SK1904	三洋	HS SW	MOS	N	E	100	DSS	10	25	4-284
###	2SK1906	三洋	HS SW	MOS	N	E	100	DSS	20	30	4-284
###	2SK1907	三洋	HS SW	MOS	N	E	100	DSS	12	50	4-370
###	2SK1909	三洋	HS SW	MOS	N	E	100	DSS	25	70	4-370
###	2SK1910	日立	HS PSW	MOS	N	E	60	DSS	25	50	4-116B
###	2SK1911	日立	HS PSW, DDC	MOS	N	E	60	DSS	40	75	4-116B
###	2SK1913	东芝	HS SW, SW-Reg, D	MOS	N	E	600	DSS	4	40	4-335
###	2SK1915	东芝	HS SW, SW-Reg, D	MOS	N	E	600	DSS	6	100	4-341
###	2SK1916	富士电	SW-Reg, UPS, DDC	MOS	N	E	450	DSS	18	80	4-327
###	2SK1917-M	富士电	SW-Reg, UPS, DDC	MOS	N	E	250	DSS	10	50	4-390
###	2SK1918(L)	日立	HS PSW, DDC	MOS	N	E	60	DSS	25	50	4-294
###	2SK1919(L)	日立	HS PSW, DDC	MOS	N	E	60	DSS	40	75	4-294
###	2SK1920	三洋	HS SW	MOS	N	E	250	DSS	4	30	4-346
###	2SK1921	三洋	HS SW	MOS	N	E	250	DSS	4	50	4-242
###	2SK1922	三洋	HS SW	MOS	N	E	600	DSS	2	50	4-242
###	2SK1923	三洋	HS SW	MOS	N	E	600	DSS	4	60	4-242
###	2SK1924	三洋	HS SW	MOS	N	E	600	DSS	6	70	4-242
###	2SK1925	三洋	HS SW	MOS	N	E	600	DSS	8	120	4-243

5000种场效应管参数

更多彩电维修资料请到《彩电维修资料网》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道	方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
###	2SK1927	东芝	HS SW, SW-Reg, D	MOS	N	E	100	DSS	15	60	4-341
###	2SK1928	东芝	HS SW, SW-Reg, D	MOS	N	E	100	DSS	27	80	4-341
###	2SK1929	东芝	HS SW, SW-Reg, D	MOS	N	E	900	DSS	5	100	4-341
###	2SK1930	东芝	HS SW, SW-Reg, D	MOS	N	E	1000	DSS	4	80	4-341
###	2SK1931	新电元	HS SW	MOS	N	E	200	DSS	5	20	4-381
###	2SK1933	日立	HS PSW, SW-Reg	MOS	N	E	900	DSS	10	150	4-149
###	2SK1934	日立	HS PSW, SW-Reg	MOS	N	E	1000	DSS	8	150	4-149
###	2SK1936-01	富士电	SW-Reg, UPS, DDC	MOS	N	E	500	DSS	10	100	4-186
###	2SK1937-01	富士电	SW-Reg, UPS, DDC	MOS	N	E	500	DSS	15	125	4-186
###	2SK1938-01	富士电	SW-Reg, UPS, DDC	MOS	N	E	500	DSS	18	100	4-327
###	2SK1939-01	富士电	SW-Reg, UPS, DDC	MOS	N	E	600	DSS	8	100	4-186
###	2SK1940-01	富士电	SW-Reg, UPS, DDC	MOS	N	E	600	DSS	12	125	4-186
###	2SK1941-01	富士电	SW-Reg, UPS, DDC	MOS	N	E	600	DSS	16	100	4-327
###	2SK1942-01	富士电	SW-Reg, UPS, DDC	MOS	N	E	900	DSS	3	80	4-186
###	2SK1943-01	富士电	SW-Reg, UPS, DDC	MOS	N	E	900	DSS	5	80	4-234
###	2SK1944-01	富士电	SW-Reg, UPS, DDC	MOS	N	E	900	DSS	5	100	4-186
###	2SK1945-01	富士电	SW-Reg, UPS, DDC	MOS	N	E	900	DSS	5	80	4-389
###	2SK1946-01	富士电机		MOS	N	E	60	DSS	45	50	4-390
###	2SK1947	日立	HS PSW	MOS	N	E	250	DSS	50	200	4-296
###	2SK1948	日立	HS PSW, DDC	MOS	N	E	250	DSS	50	200	4-296
###	2SK1949(L)	日立	HS PSW, DDC	MOS	N	E	60	DSS	5	20	4-150
###	2SK1950(L)	日立	HS PSW	MOS	N	E	60	DSS	3	10	4-150
###	2SK1951	日立	HS PSW, DDC	MOS	N	E	60	DSS	25	35	4-292
###	2SK1952	日立	HS PSW, DDC	MOS	N	E	60	DSS	40	35	4-292
###	2SK1953	NEC	SW, SW-Reg, DDC	MOS	N	E	600	DSS	±2	25	4-304
###	2SK1954, 1	NEC	SW, SW-Reg, DDC	MOS	N	E	180	DSS	±4	20	4-276/Z:277
###	2SK1957	日立	HS PSW, DDC	MOS	N	E	200	DSS	7	30	4-292
###	2SK1958	NEC	HS SW, 低电压用	MOS	N	E	16	DSS	±0.1	0.15	4-246C
###	2SK1959	NEC	HS SW, 低电压用	MOS	N	E	16	DSS	±2	2	4-216
###	2SK1960	NEC	HS SW, 低电压用	MOS	N	E	16	DSS	±3	2	4-216
###	2SK1961	三洋	RF UHF A/MIX/OSC	J	N	D	15	DSX	10m	500m	4-57B
###	2SK1962	松下	BS 受信用	MEMT	N	E	-4	GDO	60m	200	4-218
###	2SK1963	松下	BS受信用	MEMT	N	E	-4	GDO	60m	200	4-218
###	2SK1964	松下	BS受信用	MEMT	N	E	-4	GDO	60m	200	4-218
###	2SK1967	松下	Motor-D, SW-Reg	MOS	N	E	60	DSS	20	45	4-249
###	2SK1968	日立	HS PSW, SW-Reg	MOS	N	E	600	DSS	12	100	4-149
###	2SK1969-01	富士电机		MOS	N	E	60	DSS	50	125	4-186
###	2SK1971	日立	HS PSW	MOS	N	E	500	DSS	35	200	4-296
###	2SK1973	罗姆	SW-Reg, Motor-D	MOS	N	E	60	DSS	2	10	4-357
###	2SK1974	罗姆	SW-Reg, Motor-D	MOS	N	E	60	DSS	10	30	4-358
###	2SK1975	罗姆	SW-Reg, Motor-D	MOS	N	E	450	DSS	10	80	4-359
###	2SK1976	罗姆	SW-Reg, Motor-D	MOS	N	E	450	DSS	5	30	4-358
###	2SK1980	松下	Motor-D, SW-Reg	MOS	N	E	800	DSS	2	40	4-249
###	2SK1981-01	富士电	SW-Reg, UPS, DDC	MOS	N	E	500	DSS	10	80	4-234
###	2SK1982-01	富士电	SW-Reg, UPS, DDC	MOS	N	E	500	DSS	10	50	4-390
###	2SK1983-01	富士电	SW-Reg, UPS, DDC	MOS	N	E	900	DSS	3	60	4-234
###	2SK1984-01	富士电	SW-Reg, UPS, DDC	MOS	N	E	900	DSS	3	40	4-390
###	2SK1985-01	富士电	SW-Reg, UPS, DDC	MOS	N	E	900	DSS	5	50	4-390
###	2SK1986-01	富士电	SW-Reg, UPS, DDC	MOS	N	E	1000	DSS	4	80	4-234
###	2SK1987	NEC	SW, SW-Reg, DDC	MOS	N	E	250	DSS	±7	30	4-304
###	2SK1988	NEC	SW, SW-Reg, DDC	MOS	N	E	450	DSS	±4.5	30	4-304
###	2SK1989	NEC	SW, SW-Reg, DDC	MOS	N	E	500	DSS	±4.5	30	4-304
###	2SK1990	NEC	SW, SW-Reg, DDC	MOS	N	E	450	DSS	±2.5	30	4-304
###	2SK1991	NEC	SW, SW-Reg, DDC	MOS	N	E	500	DSS	±2.5	30	4-304
###	2SK1992	NEC	SW, SW-Reg, DDC	MOS	N	E	450	DSS	±6	35	4-304
###	2SK1993	NEC	SW, SW-Reg, DDC	MOS	N	E	500	DSS	±6	35	4-304
###	2SK1994	NEC	SW, SW-Reg, DDC	MOS	N	E	900	DSS	±2	30	4-304
###	2SK1995	NEC	SW, SW-Reg, DDC	MOS	N	E	900	DSS	±3	35	4-304
###	2SK1997	东芝	HS SW, SW-Reg, D	MOS	N	E	60	DSS	36	40	4-335
###	2SK1998	东芝	HS SW, SW-Reg, D	MOS	N	E	60	DSS	45	125	4-184
###	2SK1999	日立	VHF A	MOS	N	E	32	DSS	12	180	4-381

5000种场效应管参数

更多彩电维修资料请到《[彩电维修资料网](http://www.tv160.net)》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道	方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
###	2SK2002-01	富士电	SW-Reg, UPS, DDC	MOS	N	E	600	DSS	3	30	4-390
###	2SK2003-01	富士电	SW-Reg, UPS, DDC	MOS	N	E	600	DSS	4	40	4-390
###	2SK2004-01	富士电	SW-Reg, UPS, DDC	MOS	N	E	1000	DSS	4	80	4-389
###	2SK2005	新电元	HS SW	MOS	N	E	900	DSS	3	50	4-382, 383
###	2SK2006	新电元	HS SW	MOS	N	E	900	DSS	5	65	4-382, 383
###	2SK2007	日立	HS PSW	MOS	N	E	250	DSS	20	100	4-149
###	2SK2008	日立	HS PSW	MOS	N	E	250	DSS	20	60	4-293
###	2SK2010	三洋	HS SW	MOS	N	E	250	DSS	4	25	4-284
###	2SK2011	三洋	HS SW	MOS	N	E	250	DSS	12	30	4-284
###	2SK2012	三洋	HS SW	MOS	N	E	250	DSS	18	40	4-284
###	2SK2013	东芝	LF PA	MOS	N	E	180	DSS	1	25	4-335
###	2SK2014	松下	Motor-D, DDC	MOS	N	E	100	DSS	1	10	4-277
###	2SK2015	松下	Motor-D, DDC	MOS	N	E	150	DSS	3	10	4-277
###	2SK2016	松下	Motor-D, DDC	MOS	N	E	100	DSS	5	10	4-277
###	2SK2017	松下	Motor-D	MOS	N	E	550	DSS	1	10	4-277
###	2SK2018-01	富士电机		MOS	N	E	60	DSS	10	20	4-391
###	2SK2019-01	富士电	SW-Reg, UPS, DDC	MOS	N	E	500	DSS	3.5	40	4-234
###	2SK2020-01	富士电	SW-Reg, UPS, DDC	MOS	N	E	500	DSS	3.5	30	4-390
###	2SK2021-01	富士电	SW-Reg, UPS, DDC	MOS	N	E	500	DSS	5	60	4-234
###	2SK2022-01	富士电	SW-Reg, UPS, DDC	MOS	N	E	500	DSS	5	40	4-390
###	2SK2023-01	富士电	SW-Reg, UPS, DDC	MOS	N	E	600	DSS	3	40	4-234
###	2SK2024-01	富士电	SW-Reg, UPS, DDC	MOS	N	E	600	DSS	3	50	4-186
###	2SK2025-01	富士电	SW-Reg, UPS, DDC	MOS	N	E	600	DSS	4	60	4-234
###	2SK2026-01	富士电	SW-Reg, UPS, DDC	MOS	N	E	600	DSS	4	60	4-186
###	2SK2027-01	富士电	SW-Reg, UPS, DDC	MOS	N	E	600	DSS	8	80	4-234
###	2SK2028-01	富士电	SW-Reg, UPS, DDC	MOS	N	E	600	DSS	8	50	4-390
###	2SK2029-01	富士电	SW-Reg, UPS, DDC	MOS	N	E	900	DSS	3	60	4-389
###	2SK2030	东芝	DDC	MOS	N	E	60	DSS	5	20	4-257
###	2SK2032	松下	Motor-D, SW-Reg	MOS	N	E	450	DSS	13	100	4-371
###	2SK2038	东芝	HS SW, SW-Reg	MOS	N	E	800	DSS	5	125	4-184
###	2SK2039	东芝	HS SW, SW-Reg	MOS	N	E	900	DSS	5	150	4-184
###	2SK2040, 2	NEC	SW, SW-Reg, DDC	MOS	N	E	600	DSS	±2	20	4-276/Z:277
###	2SK2043	三洋	HS SW	MOS	N	E	600	DSS	2	25	4-345
###	2SK2044	三洋	HS SW	MOS	N	E	600	DSS	4	30	4-345
###	2SK2045	三洋	HS SW	MOS	N	E	600	DSS	5.5	35	4-345
###	2SK2046	三洋	HS SW	MOS	N	E	30	DSS	12	30	4-346
###	2SK2047	松下	Motor-D, SW-Reg	MOS	N	E	550	DSS	1.2	15	4-221
###	2SK2048-01	富士电机		MOS	N	E	30	DSS	35	60	4-389
###	2SK2049	富士电机		MOS	N	E	60	DSS	50	80	4-234
###	2SK2050	富士电机		MOS	N	E	100	DSS	30	80	4-234
###	2SK2051-L,	富士电	SW-Reg, UPS, DDC	MOS	N	E	250	DSS	10	80	4-389
###	2SK2052	富士电机		MOS	N	E	500	DSS	10	80	4-327
###	2SK2053	NEC	SW, 低电压用	MOS	N	E	16	DSS	±5	2	4-366
###	2SK2054	NEC	SW, DDC	MOS	N	E	60	DSS	±3	2	4-366
###	2SK2055	NEC	SW, DDC	MOS	N	E	100	DSS	±2	2	4-366
###	2SK2056	东芝	HS SW, SW-Reg	MOS	N	E	800	DSS	4	40	4-335
###	2SK2057	东芝	HS SW, SW-Reg, D	MOS	N	E	500	DSS	20	150	4-184
###	2SK2058	三洋	HS SW	MOS	N	E	250	DSS	25	120	4-243
###	2SK2059(L)	日立	HS PSW	MOS	N	E	600	DSS	3	20	4-150
###	2SK2062	新电元	HS SW	MOS	N	E	250	DSS	10	50	4-382, 383
###	2SK2063	新电元	HS SW	MOS	N	E	250	DSS	20	60	4-382, 383
###	2SK2064	新电元	HS SW	MOS	N	E	300	DSS	10	50	4-382, 383
###	2SK2065	新电元	HS SW	MOS	N	E	300	DSS	20	60	4-382, 383
###	2SK2070	NEC	SW, DDC	MOS	N	E	100	DSS	±1.5	1	4-367
###	2SK2071-01	富士电	SW-Reg, UPS, DDC	MOS	N	E	600	DSS	2	20	4-391
###	2SK2072-01	富士电	SW-Reg, UPS, DDC	MOS	N	E	800	DSS	6	80	4-380
###	2SK2073	三洋		J	N	D	15	DSX	10m	200m	4-126A
###	2SK2074	三洋		J	N	D	15	DSX	10m	300m	4-157A
###	2SK2075	日立	HS PSW	MOS	N	E	250	DSS	20	100	4-149
###	2SK2076	三洋	LF A, Imp-C, IR	J	N	D	30	DSX	10m	150m	4-126A
###	2SK2077	东芝	HS SW, SW-Reg, D	MOS	N	E	800	DSS	7	150	4-184

5000种场效应管参数

更多彩电维修资料请到《彩电维修资料网》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道	方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
###	2SK2078	东芝	HS SW, SW-Reg	MOS	N	E	800	DSS	9	150	4-184
###	2SK2080-01	富士电	SW-Reg, UPS, DDC	MOS	N	E	500	DSS	15	80	4-327
###	2SK2081-01	富士电	SW-Reg, UPS, DDC	MOS	N	E	500	DSS	12	125	4-186
###	2SK2082-01	富士电	SW-Reg, UPS, DDC	MOS	N	E	900	DSS	9	150	4-186
###	2SK2083	三洋	HS SW	MOS	N	E	900	DSS	5	70	4-370
###	2SK2084(L)	日立	HS PSW	MOS	N	E	20	DSS	7	20	4-377, 378
###	2SK2085	日立	HS PSW	MOS	N	E	100	DSS	1	0.9	4-97B
###	2SK2088	东芝	HS SW, SW-Reg, D	MOS	N	E	200	DSS	10	60	4-341
###	2SK2089	东芝	HS SW, SW-Reg, D	MOS	N	E	800	DSS	5	100	4-341
###	2SK2090	NEC		MOS	N	E	50	DSS	±0.1	0.15	4-255C
###	2SK2091	三洋	LF A, Imp-C, IR	J	N	D	30	DSX	10m	150m	4-255B
###	2SK2096	日立	HS PSW	MOS	N	E	60	DSS	45	100	4-149
###	2SK2097	日立	HS PSW	MOS	N	E	600	DSS	4	35	4-376
###	2SK2098-01	富士电	SW-Reg, UPS, DDC	MOS	N	E	150	DSS	20	50	4-390
###	2SK2099-01	富士电	SW-Reg, UPS, DDC	MOS	N	E	250	DSS	6	20	4-391
###	2SK2100	富士电	SW-Reg, UPS, DDC	MOS	N	E	800	DSS	4	40	4-390
###	2SK2101-01	富士电	SW-Reg, UPS, DDC	MOS	N	E	800	DSS	6	50	4-390
###	2SK2107	东芝	HS SW, SW-Reg, D	MOS	N	E	200	DSS	20	100	4-341
###	2SK2108	三洋	HS SW	MOS	N	E	250	DSS	6	25	4-284
###	2SK2109	NEC		MOS	N	E	60	DSS	±0.5	2	4-216A
###	2SK2110	NEC		MOS	N	E	100	DSS	±0.5	2	4-216A
###	2SK2111	NEC		MOS	N	E	60	DSS	±1	2	4-216A
###	2SK2112	NEC		MOS	N	E	100	DSS	±1	2	4-216A
###	2SK2114	日立	HS PSW	MOS	N	E	450	DSS	5	35	4-376
###	2SK2115	日立	HS PSW	MOS	N	E	500	DSS	5	35	4-376
###	2SK2116	日立	HS PSW	MOS	N	E	450	DSS	7	35	4-376
###	2SK2117	日立	HS PSW	MOS	N	E	500	DSS	7	35	4-376
###	2SK2118	日立	HS PSW	MOS	N	E	600	DSS	5	35	4-376
###	2SK2119	日立	HS PSW	MOS	N	E	60	DSS	25	30	4-376
###	2SK2120	日立	HS PSW	MOS	N	E	60	DSS	40	35	4-376
###	2SK2121	日立	HS PSW	MOS	N	E	60	DSS	50	100	4-149
###	2SK2122	松下	Motor-D, SW-Reg	MOS	N	E	250	DSS	8	40	4-372
###	2SK2123	松下	Motor-D, SW-Reg	MOS	N	E	450	DSS	5	50	4-372
###	2SK2124	松下	Motor-D, SW-Reg	MOS	N	E	450	DSS	8	50	4-372
###	2SK2125	松下	Motor-D, SW-Reg	MOS	N	E	500	DSS	2.5	40	4-372
###	2SK2126	松下	Motor-D, SW-Reg	MOS	N	E	500	DSS	5	50	4-372
###	2SK2127	松下	Motor-D, SW-Reg	MOS	N	E	500	DSS	8	50	4-372
###	2SK2128	松下	Motor-D, SW-Reg	MOS	N	E	800	DSS	2	40	4-372
###	2SK2129	松下	Motor-D, SW-Reg	MOS	N	E	800	DSS	3	50	4-372
###	2SK2130	松下	Motor-D, SW-Reg	MOS	N	E	900	DSS	3	50	4-372
###	2SK2131	NEC	SW	MOS	N	E	150	DSS	±15	35	4-304
###	2SK2132	NEC	SW, SW-Reg, DDC	MOS	N	E	180	DSS	±4	1.8	4-365
###	2SK2133, 2	NEC	SW-Reg, DDC	MOS	N	E	250	DSS	±16	75	4-287/Z:306
###	2SK2134	NEC		MOS	N	E	200	DSS	±13	70	4-287
###	2SK2135	NEC		MOS	N	E	200	DSS	±14	35	4-304
###	2SK2136	NEC		MOS	N	E	200	DSS	±20	75	4-287
###	2SK2137	NEC		MOS	N	E	600	DSS	±4	30	4-304
###	2SK2138	NEC		MOS	N	E	600	DSS	±5	70	4-287
###	2SK2139	NEC		MOS	N	E	600	DSS	±5	35	4-304
###	2SK2140	NEC		MOS	N	E	600	DSS	±7	75	4-287
###	2SK2141	NEC		MOS	N	E	600	DSS	±6	35	4-304
###	2SK2144	日立	HS PSW	MOS	N	E	600	DSS	3	25	4-376
###	2SK2146	东芝	HS SW, SW-Reg, D	MOS	N	E	250	DSS	2	25	4-335
###	2SK2147-01	富士电	SW-Reg, UPS, DDC	MOS	N	E	900	DSS	6	80	4-327
###	2SK2148-01	富士电	SW-Reg, UPS, DDC	MOS	N	E	600	DSS	12	80	4-327
###	2SK2149	东芝	HS SW, SW-Reg, D	MOS	N	E	500	DSS	10	125	4-184
###	2SK2150	东芝	HS SW, SW-Reg, D	MOS	N	E	500	DSS	15	150	4-184
###	2SK2151	三洋	HS SW	MOS	N	E	20	DSS	1	3.5	4-252
###	2SK2152	三洋	HS SW	MOS	N	E	20	DSS	2	3.5	4-252
###	2SK2157	NEC		MOS	N	E	30	DSS	±5	2	4-366
###	2SK2158	NEC		MOS	N	E	50	DSS	±0.1	0.2	4-275A

5000种场效应管参数

更多彩电维修资料请到《彩电维修资料网》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道	方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
###	2SK2159	NEC		MOS	N	E	60	DSS	±2	2	4-216A
###	2SK2160	三洋	HS SW	MOS	N	E	200	DSS	7	25	4-284
###	2SK2161	三洋	HS SW	MOS	N	E	200	DSS	9	25	4-284
###	2SK2165-01	富士电机		MOS	N	E	60	DSS	40	100	4-186
###	2SK2166-01	富士电机		MOS	N	E	60	DSS	40	80	4-327
###	2SK2167	三洋	HS SW	MOS	N	E	250	DSS	0.4	3.5	4-252
###	2SK2168	三洋	HS SW	MOS	N	E	250	DSS	0.8	3.5	4-252
###	2SK2169	三洋	HS SW	MOS	N	E	250	DSS	0.4	1	4-348
###	2SK2173	东芝	HS SW, DDC	MOS	N	E	60	DSS	50	125	4-184
###	2SK2174(L)	日立	HS PSW	MOS	N	E	500	DSS	20	120	4-379, 380
###	2SK2175	日立	HS PSW	MOS	N	E	60	DSS	15	30	4-116B
###	2SK2177	新电元	HS SW	MOS	N	E	500	DSS	1	10	4-290
###	2SK2178	新电元	HS SW	MOS	N	E	500	DSS	2	15	4-381
###	2SK2179	新电元	HS SW	MOS	N	E	500	DSS	3	20	4-290
###	2SK2180	新电元	HS SW	MOS	N	E	500	DSS	3	40	4-287
###	2SK2181	新电元	HS SW	MOS	N	E	500	DSS	3	40	4-383
###	2SK2182	新电元	HS SW	MOS	N	E	500	DSS	3	25	4-304
###	2SK2183	新电元	HS SW	MOS	N	E	500	DSS	5	50	4-287
###	2SK2184	新电元	HS SW	MOS	N	E	500	DSS	5	50	4-383
###	2SK2185	新电元	HS SW	MOS	N	E	500	DSS	5	30	4-304
###	2SK2186	新电元	HS SW	MOS	N	E	500	DSS	10	60	4-287
###	2SK2187	新电元	HS SW	MOS	N	E	500	DSS	10	60	4-383
###	2SK2188	新电元	HS SW	MOS	N	E	500	DSS	10	40	4-304
###	2SK2189	新电元	HS SW	MOS	N	E	500	DSS	10	70	4-359
###	2SK2190	新电元	HS SW	MOS	N	E	500	DSS	10	40	4-384
###	2SK2191	新电元	HS SW	MOS	N	E	500	DSS	12	60	4-383
###	2SK2192	新电元	HS SW	MOS	N	E	500	DSS	12	80	4-359
###	2SK2193	新电元	HS SW	MOS	N	E	500	DSS	12	50	4-384
###	2SK2194	新电元	HS SW	MOS	N	E	500	DSS	15	110	4-359
###	2SK2195	新电元	HS SW	MOS	N	E	500	DSS	15	60	4-384
###	2SK2196	新电元	HS SW	MOS	N	E	500	DSS	20	125	4-359
###	2SK2197	新电元	HS SW	MOS	N	E	500	DSS	20	70	4-384
###	2SK2198	新电元	HS SW	MOS	N	E	500	DSS	30	220	4-385
###	2SK2199	三洋	HS SW	MOS	N	E	250	DSS	0.8	15	4-346
###	2SK2200	东芝	HS SW, DDC	MOS	N	E	100	DSS	3	1.2	4-378
###	2SK2201	东芝	HS SW, DDC	MOS	N	E	100	DSS	3	20	4-257
###	2SK2202	日立	HS PSW	MOS	N	E	120	DSS	7	20	4-292
###	2SK2203	日立	HS PSW	MOS	N	E	60	DSS	50	60	4-293
###	2SK2204(L)	日立	HS PSW	MOS	N	E	30	DSS	45	75	4-294
###	2SK2205	日立	HS PSW	MOS	N	E	30	DSS	45	75	4-116B
###	2SK2206	日立	HS PSW	MOS	N	E	30	DSS	45	35	4-376
###	2SK2207		SW-Reg	MOS	N	E	900	DSS	±3	35	4-375
###	2SK2208		SW-Reg	MOS	N	E	900	DSS	±5	75	4-376
###	2SK2212	日立	HS PSW	MOS	N	E	200	DSS	10	30	4-292
###	2SK2213-01	富士电	SW-Reg, UPS, DDC	MOS	N	E	500	DSS	10	80	4-389
###	2SK2215-01	富士电	SW-Reg, UPS, DDC	MOS	N	E	600	DSS	8	80	4-389
###	2SK2219	三洋	C-MIC	J	N	D	-20	GDO	10m	100m	4-255B
###	2SK2220	日立	LF/RF A, HS SW	MOS	N	E	180	DSX	8	100	4-149
###	2SK2221	日立	LF/RF A, HS SW	MOS	N	E	200	DSX	8	100	4-149
###	2SK2222	东芝	HS SW, SW-Reg, D	MOS	N	E	800	DSS	5	80	4-388
###	2SK2223-01	富士电	SW-Reg, UPS, DDC	MOS	N	E	500	DSS	10	80	4-327
###	2SK2224-01	富士电	SW-Reg, UPS, DDC	MOS	N	E	900	DSS	3	50	4-327
###	2SK2225	日立	HS PSW	MOS	N	E	1500	DSS	2	50	4-293
###	2SK2228	东芝	HS SW, DDC	MOS	N	E	60	DSS	5	1.2	4-387
###	2SK2229	东芝	HS SW, DDC	MOS	N	E	60	DSS	5	1.2	4-387
###	2SK2230	东芝	HS SW, DDC	MOS	N	E	250	DSS	2	1.2	4-387
###	2SK2231	东芝	HS SW, DDC	MOS	N	E	60	DSS	5	20	4-257
###	2SK2232	东芝	HS SW, DDC	MOS	N	E	60	DSS	25	35	4-335
###	2SK2233	东芝	HS SW, DDC	MOS	N	E	60	DSS	45	100	4-184
###	2SK2234	NEC		MOS	N	E	500	DSS	±8	40	4-304
###	2SK2235	东芝	HS SW, SW-Reg	MOS	N	E	250	DSS	2	20	4-257

5000种场效应管参数

更多彩电维修资料请到《彩电维修资料网》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道	方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
###	2SK2236	东芝	HS SW, SW-Reg, D	MOS	N	E	500	DSS	5	40	4-335
###	2SK2237	东芝	HS SW, SW-Reg, D	MOS	N	E	500	DSS	7	45	4-335
###	2SK2247	日立	HS PSW	MOS	N	E	30	DSS	±2	1	4-295
###	2SK2250-01	富士电	SW-Reg, UPS, DDC	MOS	N	E	250	DSS	2	10	4-391
###	2SK2251-01	富士电	SW-Reg, UPS, DDC	MOS	N	E	250	DSS	2	20	4-234
###	2SK2252-01	富士电	SW-Reg, UPS, DDC	MOS	N	E	250	DSS	8	50	4-389
###	2SK2253-01	富士电	SW-Reg, UPS, DDC	MOS	N	E	250	DSS	8	20	4-390
###	2SK2254-01	富士电	SW-Reg, UPS, DDC	MOS	N	E	250	DSS	18	80	4-389
###	2SK2255-01	富士电	SW-Reg, UPS, DDC	MOS	N	E	250	DSS	18	50	4-390
###	2SK2256-01	富士电	SW-Reg, UPS, DDC	MOS	N	E	250	DSS	18	80	4-234
###	2SK2257-01	富士电	SW-Reg, UPS, DDC	MOS	N	E	500	DSS	17	150	4-186
###	2SK2258-01	富士电	SW-Reg, UPS, DDC	MOS	N	E	1000	DSS	4	100	4-186
###	2SK2259-01	富士电机		MOS	N	E	60	DSS	40	40	4-390
###	2SK2264	日立	LF/RF A, HS SW	MOS	N	E	350	DSX	5	100	4-149
###	2SK2265	日立	LF/RF A, HS SW	MOS	N	E	400	DSX	5	100	4-149
###	2SK2266	东芝	HS SW, DDC	MOS	N	E	60	DSS	45	65	4-341
###	2SK2267	东芝	HS SW, DDC	MOS	N	E	60	DSS	60	150	4-337
###	2SK2274	东芝	HS, SW-Reg, DDC	MOS	N	E	700	DSS	5	45	4-335
###	2SK2275	NEC		MOS	N	E	900	DSS	±3.5	35	4-304
###	2SK2278(L)	日立	HS PSW	MOS	N	E	1500	DSS	2.5	100	4-379, 380
###	2SK2279	新电元	HS SW	MOS	N	E	60	DSS	2	10	4-290
###	2SK2280	新电元	HS SW	MOS	N	E	60	DSS	5	10	4-290
###	2SK2281	新电元	HS SW	MOS	N	E	60	DSS	10	15	4-290
###	2SK2282	新电元	HS SW	MOS	N	E	60	DSS	10	30	4-383
###	2SK2283	新电元	HS SW	MOS	N	E	60	DSS	10	20	4-304
###	2SK2284	新电元	HS SW	MOS	N	E	60	DSS	15	40	4-383
###	2SK2285	新电元	HS SW	MOS	N	E	60	DSS	15	25	4-304
###	2SK2286	新电元	HS SW	MOS	N	E	60	DSS	20	50	4-383
###	2SK2287	新电元	HS SW	MOS	N	E	60	DSS	20	30	4-304
###	2SK2288	新电元	HS SW	MOS	N	E	60	DSS	30	60	4-383
###	2SK2289	新电元	HS SW	MOS	N	E	60	DSS	30	40	4-304
###	2SK2290	新电元	HS SW	MOS	N	E	60	DSS	45	60	4-383
###	2SK2291	新电元	HS SW	MOS	N	E	60	DSS	45	50	4-304
###	2SK2311	东芝	HS SW, SW-Reg, D	MOS	N	E	60	DSS	25	40	4-341
###	2SK2312	东芝	HS SW, DDC	MOS	N	E	60	DSS	45	45	4-335
###	2SK2313	东芝	HS SW, DDC	MOS	N	E	60	DSS	60	150	4-184
###	2SK2315	日立	HS PSW	MOS	N	E	60	DSS	±2	1	4-295
###	2SK2316	三洋		MOS	N	E	20	DSS	2	3.5	4-252
###	2SK2317	三洋		MOS	N	E	20	DSS	4	20	
###	2SK2318	三洋		MOS	N	E	20	DSS	12	30	
###	2SK2319	东芝	HS SW, SW-Reg, D	MOS	N	E	800	DSS	7	90	4-388
###	2SK2320	东芝	HS SW, SW-Reg, D	MOS	N	E	800	DSS	8.5	90	4-388
###	2SK2322(L)	日立	HS PSW	MOS	N	E	60	DSS	15	50	4-294
###	2SK2328	日立	HS PSW	MOS	N	E	650	DSS	7	75	4-116B
###	2SK2329(L)	日立	HS PSW	MOS	N	E	30	DSS	10	20	4-377, 378
###	2SK2330(L)	日立	HS PSW	MOS	N	E	500	DSS	15	100	4-379, 380
###	2SK2333	新电元	HS SW	MOS	N	E	700	DSS	6	50	4-304
###	2SK2334(L)	日立	HS PSW	MOS	N	E	60	DSS	20	30	4-377, 378
###	2SK2341	NEC		MOS	N	E	250	DSS	±11	35	4-304
###	2SK2344	三洋	HS SW	MOS	N	E	20	DSS	7	2	4-386
###	2SK2345	日立	HS PSW	MOS	N	E	350	DSS	6	35	4-292
###	2SK2346	日立	HS PSW	MOS	N	E	60	DSS	20	25	4-292
###	2SK2353	NEC		MOS	N	E	450	DSS	±4.5	30	4-304
###	2SK2354	NEC		MOS	N	E	500	DSS	±4.5	30	4-304
###	2SK2355	NEC		MOS	N	E	450	DSS	±5	50	4-287
###	2SK2356	NEC		MOS	N	E	500	DSS	±5	50	4-287
###	2SK2357	NEC		MOS	N	E	450	DSS	±6	35	4-304
###	2SK2358	NEC		MOS	N	E	500	DSS	±6	35	4-304
###	2SK2359	NEC		MOS	N	E	450	DSS	±7	75	4-287
###	2SK2360	NEC		MOS	N	E	500	DSS	±7	75	4-287
###	2SK2361	NEC		MOS	N	E	450	DSS	±10	100	4-253

5000种场效应管参数

更多彩电维修资料请到《彩电视维修资料网》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道	方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
###	2SK2362	NEC		MOS	N	E	500	DSS	±10	100	4-253
###	2SK2363	NEC		MOS	N	E	450	DSS	±10	35	4-304
###	2SK2364	NEC		MOS	N	E	500	DSS	±10	35	4-304
###	2SK2365	NEC		MOS	N	E	450	DSS	±12	75	4-287
###	2SK2366	NEC		MOS	N	E	500	DSS	±12	75	4-287
###	2SK2367	NEC		MOS	N	E	450	DSS	±15	120	4-253
###	2SK2368	NEC		MOS	N	E	500	DSS	±15	120	4-253
###	2SK2369	NEC		MOS	N	E	450	DSS	±20	120	4-253
###	2SK2370	NEC		MOS	N	E	500	DSS	±20	120	4-253
###	2SK2371	NEC		MOS	N	E	450	DSS	±25	160	4-253
###	2SK2372	NEC		MOS	N	E	500	DSS	±25	160	4-253
###	2SK2373	日立	HS PSW	MOS	N	E	30	DSS	0.2	0.15	4-185B
###	2SK2376	东芝	HS SW, DDC	MOS	N	E	60	DSS	45	100	4-341
###	2SK2390	日立	HS PSW	MOS	N	E	60	DSS	12	20	4-376
###	2SK2393	日立	HS PSW	MOS	N	E	1500	DSS	8	200	4-296
###	2SK2394	三洋	RF LN A	J	N	D	15	DSX	10m	200m	4-126A
###	2SK2395	三洋	RF LN A	J	N	D	15	DSX	10m	300m	4-157A
###	2SK2408	日立	HS PSW	MOS	N	E	500	DSS	7	60	4-116B
###	2SK2418(L)	日立	HS PSW	MOS	N	E	20	DSS	7	20	4-377, 378
###	2SK2423	日立	HS PSW	MOS	N	E	450	DSS	7	35	4-376
###	2SK2424	日立	HS PSW	MOS	N	E	450	DSS	8	35	4-376
###	2SK2425	日立	HS PSW	MOS	N	E	250	DSS	7	30	4-376
###	2SK2426	日立	HS PSW	MOS	N	E	250	DSS	12	35	4-376
###	2SK2431	日立	HS PSW	MOS	N	E	450	DSS	3	25	4-376
###	2SK2441	三洋	HS SW	MOS	N	E	20	DSS	7	2	4-385
###	2SK254	NEC	CATV Tuner	MOS	N	DE	18	DSX	25m	130m	4-352
###	IRC150	IR				N	100		30		(TO-204AE)
###	IRC250	IR				N	200		29		(TO-204AE)
###	IRC254	IR				N	250		22.2		(TO-204AE)
###	IRC350	IR				N	400		14.5		(TO-204AA)
###	IRC450	IR				N	500		12.2		(TO-204AA)
###	IRC530	IR				N	100		14	75	IRH-7(TO-220)
###	IRC530	IR				N	100		14	1.7	TO-204AA
###	IRC531	IR				N	80		14	79	IRH-7(TO-220)
###	IRC533	IR				N	60		12	75	IRH-7(TO-220)
###	IRC540	IR				N	100		28		IRH-7(TO-220)
###	IRC540	IR				N	100		29	1	TO-204AA
###	IRC630	IR				N	200		9.3		IRH-7(TO-220)
###	IRC630	IR				N	200		9	1.7	TO-204AA
###	IRC634	IR				N	250		8.7		IRH-7(TO-220)
###	IRC634	IR				N	250		8.1	1.7	TO-204AA
###	IRC640	IR				N	200		18		IRH-7(TO-220)
###	IRC640	IR				N	200		18	1	TO-204AA
###	IRC644	IR				N	250		14		IRH-7(TO-220)
###	IRC644	IR				N	250		14	1	TO-204AA
###	IRC730	IR				N	400		5.6		IRH-7(TO-220)
###	IRC730	IR				N	400		5.5	1.7	TO-204AA
###	IRC740	IR				N	400		9.8		IRH-7(TO-220)
###	IRC740	IR				N	400		10	1	TO-204AA
###	IRC830	IR				N	500		4.4	75	IRH-7(TO-220)
###	IRC830	IR				N	500		4.5	1.7	TO-204AA
###	IRC832	IR				N	500		4.0	74	IRH-7(TO-220)
###	IRC833	IR				N	450		3.8	75	IRH-7(TO-220)
###	IRC840	IR				N	500		7.7		IRH-7(TO-220)
###	IRC840	IR				N	500		8	1	TO-204AA
###	IRCC024	IR					60				
###	IRCC034	IR					60				
###	IRCC044	IR					60				
###	IRCC054	IR					60				
###	IRCC130	IR					100				
###	IRCC140	IR					100				

5000种场效应管参数

更多彩电维修资料请到《[彩电视维修资料网](http://www.tv160.net)》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
###	IRCC150	IR				100				
###	IRCC230	IR				200				
###	IRCC234	IR				250				
###	IRCC240	IR				200				
###	IRCC244	IR				250				
###	IRCC250	IR				200				
###	IRCC254	IR				250				
###	IRCC330	IR				400				
###	IRCC340	IR				400				
###	IRCC350	IR				400				
###	IRCC430	IR				500				
###	IRCC440	IR				500				
###	IRCC450	IR				500				
###	IRCP054	IR			N	60	70	0.5		TO-247AC
###	IRCZ24	IR			N	60	16			IRH-7(TO-220)
###	IRCZ24	IR			N	60	17	2.5		TO-204AA
###	IRCZ34	IR			N	60	27			IRH-7(TO-220)
###	IRCZ34	IR			N	60	30	1.7		TO-204AA
###	IRCZ44	IR			N	60	35			IRH-7(TO-220)
###	IRCZ44	IR			N	60	50	1		TO-204AA
###	IRF9Z10	IR			P	-50	-4.7	20		TO-220AB
###	IRF9Z12	IR			P	-50	-4	20		TO-220AB
###	IRF9Z14	IR			P	-60	-6.7	43		TO-220AB
###	IRF9Z20	IR			P	-50	-9.7	40		TO-220AB
###	IRF9Z22	IR			P	-50	-8.9	40		TO-220AB
###	IRF9Z24	IR			P	-60	-11	60		TO-220AB
###	IRF9Z30	IR			P	-50	-18	74		TO-220AB
###	IRF9Z32	IR			P	-50	-15	74		TO-220AB
###	IRF9Z34	IR			P	-60	-18	88		TO-220AB
###	IRF48	IR			N	60	50	190		TO-220AB
###	IRF024	IR			N	60	17	60		TO-204AA
###	IRF034	IR			N	60	30	90		TO-204AE
###	IRF035	IR			N	60	25	90		TO-204AE
###	IRF044	IR			N	60	30	150		TO-204AE
###	IRF045	IR			N	60	30	150		TO-204AE
###	IRF054	IR			N	60	30	180		TO-204AA
###	IRF120	IR			N	100	8.0	40		TO-3
###	IRF121	IR			N	60	8.0	40		TO-3
###	IRF122	IR			N	100	7.0	40		TO-3
###	IRF123	IR			N	60	7.0	40		TO-3
###	IRF130	IR			N	100	14	75		TO-3
###	IRF131	IR			N	60	14	75		TO-3
###	IRF132	IR			N	100	12	75		TO-3
###	IRF133	IR			N	60	12	75		TO-3
###	IRF140	IR			N	100	27	125		TO-204AE
###	IRF141	IR			N	60	27	125		TO-204AE
###	IRF142	IR			N	100	24	125		TO-204AE
###	IRF143	IR			N	60	24	125		TO-204AE
###	IRF150	IR			N	100	40	150		TO-204AE
###	IRF151	IR			N	60	40	150		TO-204AE
###	IRF152	IR			N	100	33	150		TO-204AE
###	IRF153	IR			N	60	33	150		TO-204AE
###	IRF220	IR			N	200	5.0	40		TO-3
###	IRF221	IR			N	150	5.0	40		TO-3
###	IRF222	IR			N	200	4.0	4.0		TO-3
###	IRF223	IR			N	150	4.0	40		TO-3
###	IRF224	IR			N	250	3.8	40		TO-204AA
###	IRF225	IR			N	250	3.3	40		TO-204AA
###	IRF230	IR			N	200	9.0	75		TO-3
###	IRF231	IR			N	150	9.0	75		TO-3
###	IRF232	IR			N	200	8.0	75		TO-3

5000种场效应管参数

更多彩电维修资料请到《[彩电视修资料网](http://www.tv160.net)》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
###	IRF233	IR			N	150		8.0	75	T0-3
###	IRF234	IR			N	250		8.1	75	T0-204AA
###	IRF235	IR			N	250		6.5	75	T0-204AA
###	IRF240	IR			N	200		18	125	T0-204AE
###	IRF241	IR			N	150		18	125	T0-204AE
###	IRF242	IR			N	200		16	125	T0-204AE
###	IRF243	IR			N	150		16	125	T0-204AE
###	IRF244	IR			N	250		14	125	T0-204AA
###	IRF245	IR			N	250		13	125	T0-204AA
###	IRF250	IR			N	200		30	150	T0-204AE
###	IRF251	IR			N	150		30	150	T0-204AE
###	IRF252	IR			N	200		25	150	T0-204AE
###	IRF253	IR			N	150		25	150	T0-204AE
###	IRF254	IR			N	250		22	150	T0-204AE
###	IRF255	IR			N	250		20	150	T0-204AE
###	IRF320	IR			N	400		3.0	40	T0-3
###	IRF321	IR			N	350		3.0	40	T0-3
###	IRF322	IR			N	400		2.5	40	T0-3
###	IRF323	IR			N	350		2.5	40	T0-3
###	IRF330	IR			N	400		5.5	75	T0-3
###	IRF331	IR			N	350		5.5	75	T0-3
###	IRF332	IR			N	400		4.5	75	T0-3
###	IRF333	IR			N	350		4.5	75	T0-3
###	IRF340	IR			N	400		10	125	T0-3
###	IRF341	IR			N	350		10	125	T0-3
###	IRF342	IR			N	400		8.0	125	T0-3
###	IRF343	IR			N	350		8.0	125	T0-3
###	IRF350	IR			N	400		15	150	T0-3
###	IRF351	IR			N	350		15	150	T0-3
###	IRF352	IR			N	400		13	150	T0-3
###	IRF353	IR			N	350		13	150	T0-3
###	IRF360	IR			N	400		25	300	T0-204AE
###	IRF362	IR			N	400		22	300	T0-204AE
###	IRF420	IR			N	500		2.5	50	T0-3
###	IRF421	IR			N	450		2.5	50	T0-3
###	IRF422	IR			N	500		2.0	50	T0-3
###	IRF423	IR			N	450		2.0	50	T0-3
###	IRF430	IR			N	500		4.5	75	T0-3
###	IRF431	IR			N	450		4.5	75	T0-3
###	IRF432	IR			N	500		4.0	75	T0-3
###	IRF433	IR			N	450		4.0	75	T0-3
###	IRF440	IR			N	500		8.0	125	T0-3
###	IRF441	IR			N	450		8.0	125	T0-3
###	IRF442	IR			N	500		7.0	125	T0-3
###	IRF443	IR			N	450		7.0	125	T0-3
###	IRF448	IR			N	500		9.6	130	T0-204AA
###	IRF449	IR			N	500		8.6	130	T0-204AA
###	IRF450	IR			N	500		13	150	T0-3
###	IRF451	IR			N	450		13	150	T0-3
###	IRF452	IR			N	500		12	150	T0-3
###	IRF453	IR			N	450		12	150	T0-3
###	IRF460	IR			N	500		21	300	T0-204AE
###	IRF462	IR			N	500		19	300	T0-204AE
###	IRF510	IR			N	100		5.6	43	T0-220AB
###	IRF511	IR			N	80		5.6	43	T0-220AB
###	IRF512	IR			N	100		4.9	43	T0-220AB
###	IRF513	IR			N	80		4.9	43	T0-220AB
###	IRF520	IR			N	100		9.2	60	T0-220AB
###	IRF521	IR			N	80		9.2	60	T0-220AB
###	IRF522	IR			N	100		8	60	T0-220AB
###	IRF523	IR			N	80		8	60	T0-220AB

5000种场效应管参数

更多彩电维修资料请到《[彩电视维修资料网](http://www.tv160.net)》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
###	IRF530	IR			N	100		14	79	TO-220AB
###	IRF531	IR			N	80		14	79	TO-220AB
###	IRF532	IR			N	100		12	79	TO-220AB
###	IRF533	IR			N	80		12	79	TO-220AB
###	IRF540	IR			N	100		28	150	TO-220AB
###	IRF541	IR			N	80		28	150	TO-220AB
###	IRF542	IR			N	100		25	150	TO-220AB
###	IRF543	IR			N	80		25	150	TO-220AB
###	IRF610	IR			N	200		3.3	43	TO-220AB
###	IRF611	IR			N	150		3.3	43	TO-220AB
###	IRF612	IR			N	200		2.6	43	TO-220AB
###	IRF613	IR			N	150		2.6	43	TO-220AB
###	IRF614	IR			N	250		2.0	20	TO-220AB
###	IRF615	IR			N	250		1.6	20	TO-220AB
###	IRF620	IR			N	200		5	40	TO-220AB
###	IRF621	IR			N	150		5	40	TO-220AB
###	IRF622	IR			N	200		4	40	TO-220AB
###	IRF623	IR			N	150		4	40	TO-220AB
###	IRF624	IR			N	250		3.8	40	TO-220AB
###	IRF625	IR			N	250		3.3	40	TO-220AB
###	IRF630	IR			N	200		9	75	TO-220AB
###	IRF631	IR			N	150		9	75	TO-220AB
###	IRF632	IR			N	200		8	75	TO-220AB
###	IRF633	IR			N	150		8	75	TO-220AB
###	IRF634	IR			N	250		8.1	75	TO-220AB
###	IRF635	IR			N	250		6.5	75	TO-220AB
###	IRF640	IR			N	200		18	125	TO-220AB
###	IRF641	IR			N	150		18	125	TO-220AB
###	IRF642	IR			N	200		16	125	TO-220AB
###	IRF643	IR			N	150		16	125	TO-220AB
###	IRF644	IR			N	250		14	125	TO-220AB
###	IRF645	IR			N	250		13	125	TO-220AB
###	IRF710	IR			N	400		2.0	36	TO-220AB
###	IRF711	IR			N	350		2.0	36	TO-220AB
###	IRF712	IR			N	400		1.7	36	TO-220AB
###	IRF713	IR			N	350		1.7	36	TO-220AB
###	IRF720	IR			N	400		3.3	50	TO-220AB
###	IRF721	IR			N	350		3.3	50	TO-220AB
###	IRF722	IR			N	400		2.8	50	TO-220AB
###	IRF723	IR			N	350		2.8	50	TO-220AB
###	IRF730	IR			N	400		5.5	74	TO-220AB
###	IRF731	IR			N	350		5.5	74	TO-220AB
###	IRF732	IR			N	400		4.5	74	TO-220AB
###	IRF733	IR			N	350		4.5	74	TO-220AB
###	IRF740	IR			N	400		10	125	TO-220AB
###	IRF741	IR			N	350		10	125	TO-220AB
###	IRF742	IR			N	400		8.3	125	TO-220AB
###	IRF743	IR			N	350		8.3	125	TO-220AB
###	IRF820	IR			N	500		2.5	50	TO-220AB
###	IRF821	IR			N	450		2.5	50	TO-220AB
###	IRF822	IR			N	500		2.2	50	TO-220AB
###	IRF823	IR			N	450		2.2	50	TO-220AB
###	IRF830	IR			N	500		4.5	74	TO-220AB
###	IRF831	IR			N	450		4.5	74	TO-220AB
###	IRF832	IR			N	500		4.0	74	TO-220AB
###	IRF833	IR			N	450		4.0	74	TO-220AB
###	IRF840	IR			N	500		8.0	125	TO-220AB
###	IRF841	IR			N	450		8.0	125	TO-220AB
###	IRF842	IR			N	500		7.0	125	TO-220AB
###	IRF843	IR			N	450		7.0	125	TO-220AB
###	IRF9130	IR			N	-100		-12	75	TO-3

5000种场效应管参数

更多彩电维修资料请到《[彩电视维修资料网](http://www.tv160.net)》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
###	IRF9131	IR			P	-60		-12	75	T0-3
###	IRF9132	IR			P	-100		-10	75	T0-3
###	IRF9133	IR			P	-60		-10	75	T0-3
###	IRF9140	IR			P	-100		-19	125	T0-3
###	IRF9141	IR			P	-60		-19	125	T0-3
###	IRF9142	IR			P	-100		-15	125	T0-3
###	IRF9143	IR			P	-60		-15	125	T0-3
###	IRF9230	IR			P	-200		-6.5	75	T0-3
###	IRF9231	IR			P	-150		-6.5	75	T0-3
###	IRF9232	IR			P	-200		-5.5	75	T0-3
###	IRF9233	IR			P	-150		-5.5	75	T0-3
###	IRF9240	IR			P	-200		-11	125	T0-3
###	IRF9241	IR			P	-150		-11	125	T0-3
###	IRF9242	IR			P	-200		-9.0	125	T0-3
###	IRF9243	IR			P	-150		-9.0	125	T0-3
###	IRF9510	IR			P	-100		-3.0	20	T0-220AB
###	IRF9511	IR			P	-60		-3.0	20	T0-220AB
###	IRF9512	IR			P	-100		-2.5	20	T0-220AB
###	IRF9513	IR			P	-60		-2.5	20	T0-220AB
###	IRF9520	IR			P	-100		-6.0	40	T0-220AB
###	IRF9521	IR			P	-60		-6.0	40	T0-220AB
###	IRF9522	IR			P	-100		-5.0	40	T0-220AB
###	IRF9523	IR			P	-60		-5.0	40	T0-220AB
###	IRF9530	IR			P	-100		-12	75	T0-220AB
###	IRF9531	IR			P	-60		-12	75	T0-220AB
###	IRF9532	IR			P	-100		-10	75	T0-220AB
###	IRF9533	IR			P	-60		-10	75	T0-220AB
###	IRF9540	IR			P	-100		-19	125	T0-220AB
###	IRF9541	IR			P	-60		-19	125	T0-220AB
###	IRF9542	IR			P	-100		-15	125	T0-220AB
###	IRF9543	IR			P	-60		-15	125	T0-220AB
###	IRF9610	IR			P	-200		-1.75	20	T0-220AB
###	IRF9611	IR			P	-150		-1.75	20	T0-220AB
###	IRF9612	IR			P	-200		-1.5	20	T0-220AB
###	IRF9613	IR			P	-150		-1.5	20	T0-220AB
###	IRF9620	IR			P	-200		-3.5	40	T0-220AB
###	IRF9621	IR			P	-150		-3.5	40	T0-220AB
###	IRF9622	IR			P	-200		-3.0	40	T0-220AB
###	IRF9623	IR			P	-150		-3.0	40	T0-220AB
###	IRF9630	IR			P	-200		-6.5	75	T0-220AB
###	IRF9631	IR			P	-150		-6.5	75	T0-220AB
###	IRF9632	IR			P	-200		-5.5	75	T0-220AB
###	IRF9633	IR			P	-150		-5.5	75	T0-220AB
###	IRF9640	IR			P	-200		-11	125	T0-220AB
###	IRF9641	IR			P	-150		-11	125	T0-220AB
###	IRF9642	IR			P	-200		-9	125	T0-220AB
###	IRF9643	IR			P	-150		-9	125	T0-220AB
###	IRFAC30	IR			N	600		3.6	74	T0-204AA
###	IRFAC32	IR			N	600		3.2	74	T0-204AA
###	IRFAC40	IR			N	600		6.2	125	T0-204AA
###	IRFAC42	IR			N	600		5.4	125	T0-204AA
###	IRFAE20	IR			N	800		3.1	74	T0-204AA
###	IRFAE30	IR			N	800		3.1	74	T0-204AA
###	IRFAE40	IR			N	800		4.8	125	T0-204AA
###	IRFAE42	IR			N	800		4.4	125	T0-204AA
###	IRFAE50	IR			N	800		7.1	150	T0-204AA
###	IRFAE52	IR			N	800		6.6	150	T0-204AA
###	IRFAF20	IR			N	900		1.6	50	T0-204AA
###	IRFAF30	IR			N	900		2.8	74	T0-204AA
###	IRFAF40	IR			N	900		4.3	125	T0-204AA
###	IRFAF42	IR			N	900		3.9	125	T0-204AA

5000种场效应管参数

更多彩电维修资料请到《[彩电视维修资料网](http://www.tv160.net)》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
###	IRFAF50	IR			N	900		6.2	150	TO-204AA
###	IRFAF52	IR			N	900		5.7	150	TO-204AA
###	IRFAG20	IR			N	1000		1.3	50	TO-204AA
###	IRFAG30	IR			N	1000		2.3	74	TO-204AA
###	IRFAG40	IR			N	1000		3.9	125	TO-204AA
###	IRFAG42	IR			N	1000		3.6	125	TO-204AA
###	IRFAG50	IR			N	1000		5.6	150	TO-204AA
###	IRFAG52	IR			N	1000		5.1	150	TO-204AA
###	IRFBC20	IR			N	600		2.2	50	TO-220AB
###	IRFBC30	IR			N	600		3.6	74	TO-220AB
###	IRFBC32	IR			N	600		3.2	74	TO-220AB
###	IRFBC40	IR			N	600		6.2	125	TO-220AB
###	IRFBC42	IR			N	600		5.4	125	TO-220AB
###	IRFBE20	IR			N	800		2	63	TO-220AB
###	IRFBE30	IR			N	800		5.2	210	TO-220AB
###	IRFBF20	IR			N	900		1.8	63	TO-220AB
###	IRFBF30	IR			N	900		4.7	210	TO-220AB
###	IRFBG20	IR			N	1000		1.3	50	TO-220AB
###	IRFBG30	IR			N	1000		4	210	TO-220AB
###	IRFC1Z0	IR			N	100				
###	IRFC014	IR			N	60				
###	IRFC024	IR			N	60				
###	IRFC034	IR			N	60				
###	IRFC044	IR			N	60				
###	IRFC054	IR			N	60				
###	IRFC110	IR			N	100				
###	IRFC120	IR			N	100				
###	IRFC130	IR			N	100				
###	IRFC140	IR			N	100				
###	IRFC150	IR			N	100				
###	IRFC210	IR			N	200				
###	IRFC214	IR			N	250				
###	IRFC220	IR			N	200				
###	IRFC224	IR			N	250				
###	IRFC230	IR			N	200				
###	IRFC234	IR			N	250				
###	IRFC240	IR			N	200				
###	IRFC244	IR			N	250				
###	IRFC250	IR			N	200				
###	IRFC254	IR			N	250				
###	IRFC260	IR			N	200				
###	IRFC310	IR			N	400				
###	IRFC320	IR			N	400				
###	IRFC330	IR			N	400				
###	IRFC340	IR			N	400				
###	IRFC350	IR			N	400				
###	IRFC360	IR			N	400				
###	IRFC420	IR			N	500				
###	IRFC430	IR			N	500				
###	IRFC440	IR			N	500				
###	IRFC448	IR			N	500				
###	IRFC450	IR			N	500				
###	IRFC460	IR			N	500				
###	IRFC9014	IR			P	-60				
###	IRFC9024	IR			P	-60				
###	IRFC9034	IR			P	-60				
###	IRFC9044	IR			P	-60				
###	IRFC9110	IR			P	-100				
###	IRFC9120	IR			P	-100				
###	IRFC9130	IR			P	-100				
###	IRFC9140	IR			P	-100				

5000种场效应管参数

更多彩电维修资料请到《[彩电视维修资料网](http://www.tv160.net)》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
###	IRFC9210	IR			P	-200				
###	IRFC9220	IR			P	-200				
###	IRFC9230	IR			P	-200				
###	IRFC9240	IR			P	-200				
###	IRFCC20	IR			N	600				
###	IRFCC30	IR			N	600				
###	IRFCC40	IR			N	600				
###	IRFCC50	IR			N	600				
###	IRFCE20	IR			N	800				
###	IRFCE30	IR			N	800				
###	IRFCE40	IR			N	800				
###	IRFCE50	IR			N	800				
###	IRFCF20	IR			N	900				
###	IRFCF30	IR			N	900				
###	IRFCF40	IR			N	900				
###	IRFCF50	IR			N	900				
###	IRFCG20	IR			N	1000				
###	IRFCG30	IR			N	1000				
###	IRFCG40	IR			N	1000				
###	IRFCG50	IR			N	1000				
###	IRFD1Z0	IR			N	100		0.5	1	P-DIP4PIN
###	IRFD1Z3	IR			N	60		0.4	1	P-DIP4PIN
###	IRFD010	IR			N	50		1.7	1	P-DIP4PIN
###	IRFD012	IR			N	50		1.4	1	P-DIP4PIN
###	IRFD014	IR			N	60		1.7	1.3	HD-1
###	IRFD020	IR			N	50		2.4	1	P-DIP4PIN
###	IRFD022	IR			N	50		2.2	1	P-DIP4PIN
###	IRFD024	IR			N	60		2.5	1.3	HD-1
###	IRFD110	IR			N	100		1.0	1	P-DIP4PIN
###	IRFD113	IR			N	60		0.8	1	P-DIP4PIN
###	IRFD120	IR			N	100		1.3	1	P-DIP4PIN
###	IRFD123	IR			N	60		1.1	1	P-DIP4PIN
###	IRFD210	IR			N	200		0.6	1	P-DIP4PIN
###	IRFD213	IR			N	150		0.45	1	P-DIP4PIN
###	IRFD220	IR			N	200		0.8	1	P-DIP4PIN
###	IRFD223	IR			N	150		0.7	1	P-DIP4PIN
###	IRFD9010	IR			P	-50		-1.1	1	P-DIP4PIN
###	IRFD9012	IR			P	-50		-0.91	1	P-DIP4PIN
###	IRFD9014	IR			P	-60		-1.1	1.3	HD-1
###	IRFD9020	IR			P	-50		-1.6	1	P-DIP4PIN
###	IRFD9022	IR			P	-50		-1.4	1	P-DIP4PIN
###	IRFD9024	IR			P	-60		-1.6	1.3	HD-1
###	IRFD9110	IR			P	-100		-0.7	1	P-DIP4PIN
###	IRFD9113	IR			P	-60		-0.6	1	P-DIP4PIN
###	IRFD9120	IR			P	-100		-1.0	1	P-DIP4PIN
###	IRFD9123	IR			P	-150		-0.8	1	P-DIP4PIN
###	IRFD9210	IR			P	-200		-0.4	1	P-DIP4PIN
###	IRFD9213	IR			P	-150		-0.3	1	P-DIP4PIN
###	IRFD9220	IR			P	-200		-0.6	1	P-DIP4PIN
###	IRFD9223	IR			P	-150		-0.45	1	P-DIP4PIN
###	IRFF110	IR			N	100		3.5	15	TO-205AF
###	IRFF111	IR			N	60		3.5	15	TO-205AF
###	IRFF112	IR			N	100		3.0	15	TO-205AF
###	IRFF113	IR			N	60		3.0	15	TO-205AF
###	IRFF120	IR			N	100		6.0	20	TO-205AF
###	IRFF121	IR			N	60		6.0	20	TO-205AF
###	IRFF122	IR			N	100		5.0	20	TO-205AF
###	IRFF123	IR			N	60		5.0	20	TO-205AF
###	IRFF130	IR			N	100		8.0	25	TO-205AF
###	IRFF131	IR			N	60		8.0	25	TO-205AF
###	IRFF132	IR			N	100		7.0	25	TO-205AF

5000种场效应管参数

更多彩电维修资料请到《彩电视修资料网》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
###	IRFF133	IR			N	60		7.0	25	TO-205AF
###	IRFF210	IR			N	200		2.2	15	TO-205AF
###	IRFF211	IR			N	150		2.2	15	TO-205AF
###	IRFF212	IR			N	200		1.8	15	TO-205AF
###	IRFF213	IR			N	150		1.8	15	TO-205AF
###	IRFF220	IR			N	200		3.5	20	TO-205AF
###	IRFF221	IR			N	150		3.5	20	TO-205AF
###	IRFF222	IR			N	200		3.0	20	TO-205AF
###	IRFF223	IR			N	150		3.0	20	TO-205AF
###	IRFF230	IR			N	200		5.5	25	TO-205AF
###	IRFF231	IR			N	150		5.5	25	TO-205AF
###	IRFF232	IR			N	200		4.5	25	TO-205AF
###	IRFF233	IR			N	150		4.5	25	TO-205AF
###	IRFF310	IR			N	400		1.35	15	TO-205AF
###	IRFF311	IR			N	350		1.35	15	TO-205AF
###	IRFF312	IR			N	400		1.15	15	TO-205AF
###	IRFF313	IR			N	350		1.15	15	TO-205AF
###	IRFF320	IR			N	400		2.5	20	TO-205AF
###	IRFF321	IR			N	350		2.5	20	TO-205AF
###	IRFF322	IR			N	400		2.0	20	TO-205AF
###	IRFF323	IR			N	350		2.0	20	TO-205AF
###	IRFF330	IR			N	400		3.5	25	TO-205AF
###	IRFF331	IR			N	350		3.5	25	TO-205AF
###	IRFF332	IR			N	400		3.0	25	TO-205AF
###	IRFF333	IR			N	350		3.0	25	TO-205AF
###	IRFF420	IR			N	500		1.6	20	TO-205AF
###	IRFF421	IR			N	450		1.6	20	TO-205AF
###	IRFF422	IR			N	500		1.4	20	TO-205AF
###	IRFF423	IR			N	450		1.4	20	TO-205AF
###	IRFF430	IR			N	500		2.75	25	TO-205AF
###	IRFF431	IR			N	450		2.75	25	TO-205AF
###	IRFF432	IR			N	500		2.25	25	TO-205AF
###	IRFF433	IR			N	450		2.25	25	TO-205AF
###	IRFF9110	IR			P	-100		-2.6	15	TO-205AF
###	IRFF9111	IR			P	-60		-2.6	15	TO-205AF
###	IRFF9112	IR			P	-100		-2.3	15	TO-205AF
###	IRFF9113	IR			P	-60		-2.3	15	TO-205AF
###	IRFF9120	IR			P	-100		-4.0	20	TO-205AF
###	IRFF9121	IR			P	-60		-4.0	20	TO-205AF
###	IRFF9122	IR			P	-100		-3.5	20	TO-205AF
###	IRFF9123	IR			P	-60		-3.5	20	TO-205AF
###	IRFF9130	IR			P	-100		-6.5	25	TO-205AF
###	IRFF9131	IR			P	-60		-6.5	25	TO-205AF
###	IRFF9132	IR			P	-100		-5.5	25	TO-205AF
###	IRFF9133	IR			P	-60		-5.5	25	TO-205AF
###	IRFF9210	IR			P	-200		-1.6	15	TO-205AF
###	IRFF9211	IR			P	-150		-1.6	15	TO-205AF
###	IRFF9212	IR			P	-200		-1.3	15	TO-205AF
###	IRFF9213	IR			P	-150		-1.3	15	TO-205AF
###	IRFF9220	IR			P	-200		-2.5	20	TO-205AF
###	IRFF9221	IR			P	-150		-2.5	20	TO-205AF
###	IRFF9222	IR			P	-200		-2.0	20	TO-205AF
###	IRFF9223	IR			P	-150		-2.0	20	TO-205AF
###	IRFF9230	IR			P	-200		-4.0	25	TO-205AF
###	IRFF9231	IR			P	-150		-4.0	25	TO-205AF
###	IRFF9232	IR			P	-200		-3.5	25	TO-205AF
###	IRFF9233	IR			P	-150		-3.5	25	TO-205AF
###	IRFG1Z0	IR			N	100		0.40*	1.0*	2SK×4
###	IRFG1Z3	IR			N	60		0.35*	1.0*	2SK×4
###	IRFG110	IR			N	100		0.95*	1.4/U	2SK×4
###	IRFG113	IR			N	60		0.85*	1.4*	2SK×4

5000种场效应管参数

更多彩电维修资料请到《[彩电视维修资料网](http://www.tv160.net)》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
###	IRFG6110	IR			*	±100		+0.95*	1.4*	2SK×2+2SJ×2
###	IRFG6113	IR			*	±60		+0.85*	1.4*	2SK×2+2SJ×2
###	IRFG9110	IR			P	-100		-0.75*	1.4*	2SJ×4
###	IRFG9113	IR			P	-60		-0.65*	1.4*	2SJ×4
###	IRFH150	IR			N	100		30	150	TO-210AC
###	IRFH250	IR			N	200		30	150	TO-210AC
###	IRFH350	IR			N	400		15	150	TO-210AC
###	IRFH450	IR			N	500		13	150	TO-210AC
###	IRFI530	IR			N	100		9.7	39	Iso TO-220
###	IRFI540	IR			N	100		17	48	Iso TO-220
###	IRFI630	IR			N	200		5.9	32	Iso TO-220
###	IRFI634	IR			N	250		5.6	32	Iso TO-220
###	IRFI640	IR			N	200		9.8	40	Iso TO-220
###	IRFI644	IR			N	250		7.9	40	Iso TO-220
###	IRFI730	IR			N	400		3.5	32	Iso TO-220
###	IRFI740	IR			N	400		5.4	40	Iso TO-220
###	IRFI820	IR			N	500		2.1	30	Iso TO-220
###	IRFI830	IR			N	500		3.1	32	Iso TO-220
###	IRFI840	IR			N	500		4.6	40	Iso TO-220
###	IRFIP044	IR			N	60		43	100	Iso TO-247
###	IRFIP054	IR			N	60		64	120	Iso TO-247
###	IRFIP140	IR			N	100		23	100	Iso TO-247
###	IRFIP150	IR			N	100		31	120	Iso TO-247
###	IRFIP240	IR			N	200		14	83	Iso TO-247
###	IRFIP244	IR			N	250		11	83	Iso TO-247
###	IRFIP250	IR			N	200		22	96	Iso TO-247
###	IRFIP254	IR			N	250		17	96	Iso TO-247
###	IRFIP340	IR			N	400		8	83	Iso TO-247
###	IRFIP350	IR			N	400		11	96	Iso TO-247
###	IRFIP440	IR			N	500		6.4	83	Iso TO-247
###	IRFIP448	IR			N	500		7.4	89	Iso TO-247
###	IRFIP450	IR			N	500		10	96	Iso TO-247
###	IRFIZ24	IR			N	60		14	37	Iso TO-220
###	IRFIZ34	IR			N	60		20	38	Iso TO-220
###	IRFIZ44	IR			N	60		30	48	Iso TO-220
###	IRFJ120	IR			N	100		8.0	40	TO-213AA
###	IRFJ121	IR			N	60		8.0	40	TO-213AA
###	IRFJ122	IR			N	100		7.0	40	TO-213AA
###	IRFJ123	IR			N	60		7.0	40	TO-213AA
###	IRFJ130	IR			N	100		10	50	TO-213AA
###	IRFJ131	IR			N	60		10	50	TO-213AA
###	IRFJ132	IR			N	100		10	50	TO-213AA
###	IRFJ133	IR			N	60		10	50	TO-213AA
###	IRFJ140	IR			N	100		15	70	TO-213AA
###	IRFJ141	IR			N	60		15	70	TO-213AA
###	IRFJ142	IR			N	100		10	70	TO-213AA
###	IRFJ143	IR			N	60		10	70	TO-213AA
###	IRFJ220	IR			N	200		5.0	40	TO-213AA
###	IRFJ221	IR			N	150		5.0	40	TO-213AA
###	IRFJ222	IR			N	200		4.0	40	TO-213AA
###	IRFJ223	IR			N	150		4.0	40	TO-213AA
###	IRFJ230	IR			N	200		8.0	50	TO-213AA
###	IRFJ231	IR			N	150		8.0	50	TO-213AA
###	IRFJ232	IR			N	200		6.5	50	TO-213AA
###	IRFJ233	IR			N	150		6.5	50	TO-213AA
###	IRFJ240	IR			N	200		13	70	TO-213AA
###	IRFJ241	IR			N	150		13	70	TO-213AA
###	IRFJ242	IR			N	200		11	70	TO-213AA
###	IRFJ243	IR			N	150		11	70	TO-213AA
###	IRFJ320	IR			N	400		3.0	40	TO-213AA
###	IRFJ321	IR			N	350		3.0	40	TO-213AA

5000种场效应管参数

更多彩电维修资料请到《彩电视修资料网》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
###	IRFJ322	IR			N	400		2.5	40	TO-213AA
###	IRFJ323	IR			N	350		2.5	40	TO-213AA
###	IRFJ330	IR			N	400		4.5	50	TO-213AA
###	IRFJ331	IR			N	350		4.5	50	TO-213AA
###	IRFJ332	IR			N	400		4.0	50	TO-213AA
###	IRFJ333	IR			N	350		4.0	50	TO-213AA
###	IRFJ340	IR			N	400		7.5	70	TO-213AA
###	IRFJ341	IR			N	350		7.5	70	TO-213AA
###	IRFJ342	IR			N	400		6.0	70	TO-213AA
###	IRFJ343	IR			N	350		6.0	70	TO-213AA
###	IRFJ420	IR			N	500		2.5	40	TO-213AA
###	IRFJ421	IR			N	450		2.5	40	TO-213AA
###	IRFJ422	IR			N	500		2.0	40	TO-213AA
###	IRFJ423	IR			N	450		2.0	40	TO-213AA
###	IRFJ430	IR			N	500		4.0	50	TO-213AA
###	IRFJ431	IR			N	450		4.0	50	TO-213AA
###	IRFJ432	IR			N	500		3.0	50	TO-213AA
###	IRFJ433	IR			N	450		3.0	50	TO-213AA
###	IRFJ440	IR			N	500		6.0	70	TO-213AA
###	IRFJ441	IR			N	450		6.0	70	TO-213AA
###	IRFJ442	IR			N	500		5.0	70	TO-213AA
###	IRFJ443	IR			N	450		5.0	70	TO-213AA
###	IRFK2D054	IR			N	60		120	500	TO-240AA
###	IRFK2D150	IR			N	100		72	500	TO-240AA
###	IRFK2D250	IR			N	200		54	500	TO-240AA
###	IRFK2D350	IR			N	400		25	500	TO-240AA
###	IRFK2D450	IR			N	500		22	500	TO-240AA
###	IRFK2DC50	IR			N	600		18	500	TO-240AA
###	IRFK2DE50	IR			N	800		12	500	TO-240AA
###	IRFK2F054	IR			N	60		120	500	TO-240AA
###	IRFK2F150	IR			N	100		72	500	TO-240AA
###	IRFK2F250	IR			N	200		54	500	TO-240AA
###	IRFK2F350	IR			N	400		25	500	TO-240AA
###	IRFK2F450	IR			N	500		22	500	TO-240AA
###	IRFK2FC50	IR			N	600		16	500	TO-240AA
###	IRFK2FE50	IR			N	800		12	500	TO-240AA
###	IRFK3D150	IR			N	100		125	625	TO-240AA
###	IRFK3D250	IR			N	200		70	625	TO-240AA
###	IRFK3D350	IR			N	400		37	625	TO-240AA
###	IRFK3D450	IR			N	500		33	625	TO-240AA
###	IRFK3DC50	IR			N	600		24	625	TO-240AA
###	IRFK3F150	IR			N	100		125	625	TO-240AA
###	IRFK3F250	IR			N	200		70	625	TO-240AA
###	IRFK3F350	IR			N	400		37	625	TO-240AA
###	IRFK3F450	IR			N	500		33	625	TO-240AA
###	IRFK3FC50	IR			N	600		24	625	TO-240AA
###	IRFK4H054	IR			N	60		150	500	TO-240AA
###	IRFK4H150	IR			N	100		137	500	TO-240AA
###	IRFK4H250	IR			N	200		108	500	TO-240AA
###	IRFK4H350	IR			N	400		50	500	TO-240AA
###	IRFK4H450	IR			N	500		44	500	TO-240AA
###	IRFK4HC50	IR			N	600		35	500	TO-240AA
###	IRFK4HE50	IR			N	800		26	500	TO-240AA
###	IRFK4J054	IR			N	60		150	500	TO-240AA
###	IRFK4J150	IR			N	100		137	500	TO-240AA
###	IRFK4J250	IR			N	200		108	500	TO-240AA
###	IRFK4J350	IR			N	400		50	500	TO-240AA
###	IRFK4J450	IR			N	500		44	500	TO-240AA
###	IRFK4JC50	IR			N	600		35	500	TO-240AA
###	IRFK4JE50	IR			N	800		26	500	TO-240AA
###	IRFK6H150	IR			N	100		150	625	TO-240AA

5000种场效应管参数

更多彩电维修资料请到《[彩电维修资料网](http://www.tv160.net)》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
###	IRFK6H250	IR			N	200		140	625	TO-240AA
###	IRFK6H350	IR			N	400		75	625	TO-240AA
###	IRFK6H450	IR			N	500		66	625	TO-240AA
###	IRFK6HC50	IR			N	600		48	625	TO-240AA
###	IRFK6J150	IR			N	100		150	625	TO-240AA
###	IRFK6J250	IR			N	200		140	625	TO-240AA
###	IRFK6J350	IR			N	400		75	625	TO-240AA
###	IRFK6J450	IR			N	500		66	625	TO-240AA
###	IRFK6JC50	IR			N	600		48	625	TO-240AA
###	IRFM040	IR			N	50		25	96	TO-254AA
###	IRFM140	IR			N	100		23	96	TO-254AA
###	IRFM150	IR			N	100		25	125	TO-254AA
###	IRFM240	IR			N	200		15	96	TO-254AA
###	IRFM250	IR			N	200		24	125	TO-254AA
###	IRFM340	IR			N	400		8.5	96	TO-254AA
###	IRFM350	IR			N	400		14	125	TO-254AA
###	IRFM440	IR			N	500		6.9	96	TO-254AA
###	IRFM450	IR			N	500		11	125	TO-254AA
###	IRFM9140	IR			P	-100		-15	96	TO-254AA
###	IRFM9240	IR			P	-200		-9.3	96	TO-254AA
###	IRFP040	IR			N	40		40	150	TO-247AC
###	IRFP042	IR			N	40		40	150	TO-247AC
###	IRFP044	IR			N	60		40	180	TO-247AC
###	IRFP045	IR			N	60		40	180	TO-247AC
###	IRFP054	IR			N	60		70	300	TO-247AC
###	IRFP064	IR			N	60		70	300	TO-247AC
###	IRFP140	IR			N	100		29	150	TO-247AC
###	IRFP141	IR			N	60		29	150	TO-247AC
###	IRFP142	IR			N	100		26	150	TO-247AC
###	IRFP143	IR			N	60		26	150	TO-247AC
###	IRFP150	IR			N	100		41	180	TO-247AC
###	IRFP151	IR			N	60		41	180	TO-247AC
###	IRFP152	IR			N	100		34	180	TO-247AC
###	IRFP153	IR			N	60		34	180	TO-247AC
###	IRFP240	IR			N	200		19	150	TO-247AC
###	IRFP241	IR			N	150		19	150	TO-247AC
###	IRFP242	IR			N	200		17	150	TO-247AC
###	IRFP243	IR			N	150		17	150	TO-247AC
###	IRFP244	IR			N	250		15	150	TO-247AC
###	IRFP245	IR			N	250		14	150	TO-247AC
###	IRFP250	IR			N	200		31	180	TO-247AC
###	IRFP251	IR			N	150		31	180	TO-247AC
###	IRFP252	IR			N	200		26	180	TO-247AC
###	IRFP253	IR			N	150		26	180	TO-247AC
###	IRFP254	IR			N	250		23	180	TO-247AC
###	IRFP255	IR			N	250		21	180	TO-247AC
###	IRFP260	IR			N	200		38	250	TO-247AC
###	IRFP264	IR			N	250		32	250	TO-247AC
###	IRFP340	IR			N	400		10	150	TO-247AC
###	IRFP341	IR			N	350		10	150	TO-247AC
###	IRFP342	IR			N	400		8.4	150	TO-247AC
###	IRFP343	IR			N	350		8.4	150	TO-247AC
###	IRFP350	IR			N	400		16	180	TO-247AC
###	IRFP351	IR			N	350		16	180	TO-247AC
###	IRFP352	IR			N	400		14	180	TO-247AC
###	IRFP353	IR			N	350		14	180	TO-247AC
###	IRFP360	IR			N	400		23	250	TO-247AC
###	IRFP362	IR			N	400		20	250	TO-247AC
###	IRFP440	IR			N	500		8.1	150	TO-247AC
###	IRFP441	IR			N	450		8.1	150	TO-247AC
###	IRFP442	IR			N	500		7.1	150	TO-247AC

5000种场效应管参数

更多彩电维修资料请到《彩电视修资料网》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
###	IRFP443	IR			N	450		7.1	150	TO-247AC
###	IRFP450	IR			N	500		14	180	TO-247AC
###	IRFP451	IR			N	450		14	180	TO-247AC
###	IRFP452	IR			N	500		12	180	TO-247AC
###	IRFP453	IR			N	450		12	180	TO-247AC
###	IRFP460	IR			N	500		20	250	TO-247AC
###	IRFP462	IR			N	500		17	250	TO-247AC
###	IRFP9140	IR			P	-100		-19	150	TO-247AC
###	IRFP9141	IR			P	-60		-19	150	TO-247AC
###	IRFP9142	IR			P	-100		-16	150	TO-247AC
###	IRFP9143	IR			P	-60		-16	150	TO-247AC
###	IRFP9240	IR			P	-200		-12	150	TO-247AC
###	IRFP9241	IR			P	-150		-12	150	TO-247AC
###	IRFP9242	IR			P	-200		-10	150	TO-247AC
###	IRFP9243	IR			P	-150		-10	150	TO-247AC
###	IRFPC30	IR			N	600		4.3	100	TO-247AC
###	IRFPC40	IR			N	600		6.8	150	TO-247AC
###	IRFPC42	IR			N	600		5.9	150	TO-247AC
###	IRFPC50	IR			N	600		13	250	TO-247AC
###	IRFPE30	IR			N	800		5.2	210	TO-247AC
###	IRFPE40	IR			N	800		5.3	150	TO-247AC
###	IRFPE42	IR			N	800		4.8	150	TO-247AC
###	IRFPE50	IR			N	800		7.8	180	TO-247AC
###	IRFPE52	IR			N	800		7.2	180	TO-247AC
###	IRFPF30	IR			N	900		4.7	210	TO-247AC
###	IRFPF40	IR			N	900		4.7	150	TO-247AC
###	IRFPF42	IR			N	900		4.3	150	TO-247AC
###	IRFPF50	IR			N	900		6.8	180	TO-247AC
###	IRFPF52	IR			N	900		6.2	180	TO-247AC
###	IRFPG30	IR			N	1000		4	210	TO-247AC
###	IRFPG40	IR			N	1000		4.3	150	TO-247AC
###	IRFPG42	IR			N	1000		3.9	150	TO-247AC
###	IRFPG50	IR			N	1000		6.1	180	TO-247AC
###	IRFPG52	IR			N	1000		5.5	180	TO-247AC
###	IRFR010	IR			N	50		8.2	25	TO-251AA
###	IRFR012	IR			N	50		6.7	25	TO-251AA
###	IRFR014	IR			N	60		8.4	30	TO-252AA
###	IRFR020	IR			N	50		15	42	TO-251AA
###	IRFR022	IR			N	50		14	42	TO-251AA
###	IRFR024	IR			N	60		16	50	TO-252AA
###	IRFR110	IR			N	100		4.7	30	TO-251AA
###	IRFR111	IR			N	80		4.7	30	TO-251AA
###	IRFR120	IR			N	100		8.4	50	TO-251AA
###	IRFR121	IR			N	80		8.4	50	TO-251AA
###	IRFR210	IR			N	200		2.7	25	TO-251AA
###	IRFR212	IR			N	200		2.1	25	TO-251AA
###	IRFR214	IR			N	250		2.2	25	TO-252AA
###	IRFR220	IR			N	200		4.6	42	TO-251AA
###	IRFR222	IR			N	200		3.8	42	TO-251AA
###	IRFR224	IR			N	250		3.8	42	TO-252AA
###	IRFR310	IR			N	400		1.7	25	TO-252AA
###	IRFR320	IR			N	400		3.1	42	TO-252AA
###	IRFR420	IR			N	500		2.4	42	TO-252AA
###	IRFR9010	IR			P	-50		-5.3	25	TO-251AA
###	IRFR9012	IR			P	-50		-4.5	25	TO-251AA
###	IRFR9014	IR			P	-60		-5.6	30	TO-252AA
###	IRFR9020	IR			P	-50		-9.9	42	TO-251AA
###	IRFR9022	IR			P	-50		-9.0	42	TO-251AA
###	IRFR9024	IR			P	-60		-9.6	50	TO-252AA
###	IRFR9110	IR			P	-100		-3.2	25	TO-251AA
###	IRFR9111	IR			P	-80		-3.2	25	TO-251AA

5000种场效应管参数

更多彩电维修资料请到《彩电视修资料网》查询吧：<http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
###	IRFR9120	IR			P	-100		-5.9	42	T0-251AA
###	IRFR9121	IR			P	-80		-5.9	42	T0-251AA
###	IRFR9210	IR			P	-200		-2.0	25	T0-251AA
###	IRFR9212	IR			P	-200		-1.6	25	T0-251AA
###	IRFR9220	IR			P	-200		-3.6	42	T0-251AA
###	IRFR9222	IR			P	-200		-2.8	42	T0-251AA
###	IRFRC20	IR			N	600		2	42	T0-252AA
###	IRFS1Z0	IR			N	100		0.9	3.5	T0-243AA
###	IRFS1Z3	IR			N	60		0.75	3.5	T0-243AA
###	IRFT001	IR			*	100		3.6		2SK×3, 2SJ×3
###	IRFT002	IR			*	60		6.1		2SK×3, 2SJ×3
###	IRFT003	IR			*	60		6.1		2SK×2, 2SJ×2
###	IRFU010	IR			N	50		8.2	25	T0-251AA
###	IRFU012	IR			N	50		6.7	25	T0-251AA
###	IRFU014	IR			N	60		8.4	30	T0-251AA
###	IRFU020	IR			N	50		15	42	T0-251AA
###	IRFU022	IR			N	50		14	42	T0-251AA
###	IRFU024	IR			N	60		16	50	T0-251AA
###	IRFU110	IR			N	100		4.7	30	T0-251AA
###	IRFU111	IR			N	80		4.7	30	T0-251AA
###	IRFU120	IR			N	100		8.4	50	T0-251AA
###	IRFU121	IR			N	80		8.4	50	T0-251AA
###	IRFU210	IR			N	200		2.7	25	T0-251AA
###	IRFU212	IR			N	200		2.1	25	T0-251AA
###	IRFU214	IR			N	250		2.2	25	T0-251AA
###	IRFU220	IR			N	200		4.6	42	T0-251AA
###	IRFU222	IR			N	200		3.8	42	T0-251AA
###	IRFU224	IR			N	250		3.8	42	T0-251AA
###	IRFU310	IR			N	400		1.7	25	T0-251AA
###	IRFU320	IR			N	400		3.1	42	T0-251AA
###	IRFU420	IR			N	500		2.4	42	T0-251AA
###	IRFU9010	IR			P	-50		-5.3	25	T0-251AA
###	IRFU9012	IR			P	-50		-4.5	25	T0-251AA
###	IRFU9014	IR			P	-60		-5.6	30	T0-251AA
###	IRFU9020	IR			P	-50		-9.9	42	T0-251AA
###	IRFU9022	IR			P	-50		-9.0	42	T0-251AA
###	IRFU9024	IR			P	-60		-9.6	50	T0-251AA
###	IRFU9110	IR			P	-100		-3.2	25	T0-251AA
###	IRFU9111	IR			P	-80		-3.2	25	T0-251AA
###	IRFU9120	IR			P	-100		-5.9	42	T0-251AA
###	IRFU9121	IR			P	-80		-5.9	42	T0-251AA
###	IRFU9210	IR			P	-200		-2.0	25	T0-251AA
###	IRFU9220	IR			P	-200		-3.6	42	T0-251AA
###	IRFU9222	IR			P	-200		-2.8	42	T0-251AA
###	IRFUC20	IR			N	600		2	42	T0-251AA
###	IRFZ10	IR			N	50		7.2	20	T0-220AB
###	IRFZ12	IR			N	50		5.9	20	T0-220AB
###	IRFZ14	IR			N	60		10	36	T0-220AB
###	IRFZ15	IR			N	60		8.3	36	T0-220AB
###	IRFZ20	IR			N	50		15	40	T0-220AB
###	IRFZ22	IR			N	50		14	40	T0-220AB
###	IRFZ24	IR			N	60		17	60	T0-220AB
###	IRFZ30	IR			N	50		30	75	T0-220AB
###	IRFZ32	IR			N	50		25	75	T0-220AB
###	IRFZ34	IR			N	60		30	90	T0-220AB
###	IRFZ35	IR			N	60		25	90	T0-220AB
###	IRFZ40	IR			N	50		35	125	T0-220AB
###	IRFZ42	IR			N	50		35	125	T0-220AB
###	IRFZ44	IR			N	60		35	150	T0-220AB
###	IRFZ45	IR			N	60		35	150	T0-220AB
###	IRFZ48	IR			N	60		50	250	T0-220AB

5000种场效应管参数

更多彩电维修资料请到《[彩电视维修资料网](http://www.tv160.net)》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
###	IRH150	IR			N	100		38	150	TO-204AE
###	IRH254	IR			N	250		19	150	TO-204AE
###	IRH450	IR			N	500		10	150	TO-204AE
###	IRL510	IR			N	100		4.8		TO-220AB
###	IRL510	IR			N	100		5.6	43	TO-220AB
###	IRL520	IR			N	100		7.9		TO-220AB
###	IRL520	IR			N	100		9.2	60	TO-220AB
###	IRL530	IR			N	100		13		TO-220AB
###	IRL530	IR			N	100		15	88	TO-220AB
###	IRL540	IR			N	100		24		TO-220AB
###	IRL540	IR			N	100		28	150	TO-220AB
###	IRLC014	IR				60				
###	IRLC024	IR				60				
###	IRLC034	IR				60				
###	IRLC044	IR				60				
###	IRLC110	IR				100				
###	IRLC120	IR				100				
###	IRLC130	IR				100				
###	IRLC140	IR				100				
###	IRLD014	IR			N	60		1.7	1	HD-1
###	IRLD024	IR			N	60		2.5	1	HD-1
###	IRLD110	IR			N	100		1	1	HD-1
###	IRLD120	IR			N	100		1.3	1	HD-1
###	IRLR014	IR			N	60		8.5	30	TO-252AA
###	IRLR024	IR			N	60		16	50	TO-252AA
###	IRLR110	IR			N	100		4.6	30	TO-252AA
###	IRLR120	IR			N	100		8.4	50	TO-252AA
###	IRLU014	IR			N	60		8.5	30	TO-251AA
###	IRLU024	IR			N	60		16	50	TO-251AA
###	IRLU110	IR			N	100		4.6	30	TO-251AA
###	IRLU120	IR			N	100		8.4	50	TO-251AA
###	IRLZ14	IR			N	60		7.8		TO-220AB
###	IRLZ14	IR			N	60		10	43	TO-220AB
###	IRLZ24	IR			N	60		13		TO-220AB
###	IRLZ24	IR			N	60		17	60	TO-220AB
###	IRLZ34	IR			N	60		23		TO-220AB
###	IRLZ34	IR			N	60		30	88	TO-220AB
###	IRLZ44	IR			N	60		35		TO-220AB
###	IRLZ44	IR			N	60		50	150	TO-220AB
###	IRF120	MOT			N	100		8	40	TO-204AA
###	IRF121	MOT			N	60		8	40	TO-204AA
###	IRF122	MOT			N	100		7	40	TO-204AA
###	IRF123	MOT			N	60		7	40	TO-204AA
###	IRF130	MOT			N	100		14	75	TO-220AB
###	IRF131	MOT			N	60		14	75	TO-220AB
###	IRF132	MOT			N	100		12	75	TO-220AB
###	IRF133	MOT			N	60		12	75	TO-220AB
###	IRF140	MOT			N	100		27	125	TO-204AE
###	IRF141	MOT			N	60		27	125	TO-204AE
###	IRF142	MOT			N	100		24	125	TO-204AE
###	IRF143	MOT			N	60		24	125	TO-204AE
###	IRF150	MOT			N	100		40	150	TO-204AE
###	IRF151	MOT			N	60		40	150	TO-204AE
###	IRF152	MOT			N	100		33	150	TO-204AE
###	IRF153	MOT			N	60		33	150	TO-204AE
###	IRF220	MOT			N	200		5	40	TO-204AA
###	IRF221	MOT			N	150		5	40	TO-204AA
###	IRF222	MOT			N	200		4	40	TO-204AA
###	IRF223	MOT			N	150		4	40	TO-204AA
###	IRF230	MOT			N	200		9	75	TO-204AA
###	IRF231	MOT			N	150		9	75	TO-204AA

5000种场效应管参数

更多彩电维修资料请到《[彩电视维修资料网](http://www.tv160.net)》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
###	IRF232	MOT			N	200		8	75	TO-204AA
###	IRF233	MOT			N	150		8	75	TO-204AA
###	IRF240	MOT			N	200		18	125	TO-204AE
###	IRF241	MOT			N	150		18	125	TO-204AE
###	IRF242	MOT			N	200		16	125	TO-204AE
###	IRF243	MOT			N	150		16	125	TO-204AE
###	IRF250	MOT			N	200		30	150	TO-204AE
###	IRF251	MOT			N	150		30	150	TO-204AE
###	IRF252	MOT			N	200		25	150	TO-204AE
###	IRF253	MOT			N	150		25	150	TO-204AE
###	IRF330	MOT			N	400		5.5	75	TO-204AA
###	IRF331	MOT			N	350		5.5	75	TO-204AA
###	IRF332	MOT			N	400		4.5	75	TO-204AA
###	IRF333	MOT			N	350		4.5	75	TO-204AA
###	IRF340	MOT			N	400		10	125	TO-204AA
###	IRF350	MOT			N	400		15	150	TO-204AA
###	IRF351	MOT			N	350		15	150	TO-204AA
###	IRF352	MOT			N	400		13	150	TO-204AA
###	IRF430	MOT			N	500		4.5	75	TO-204AA
###	IRF431	MOT			N	450		4.5	75	TO-204AA
###	IRF432	MOT			N	500		4	75	TO-204AA
###	IRF433	MOT			N	450		4	75	TO-204AA
###	IRF440	MOT			N	500		8	125	TO-204AA
###	IRF450	MOT			N	500		13	150	TO-204AA
###	IRF451	MOT			N	450		13	150	TO-204AA
###	IRF452	MOT			N	500		12	150	TO-204AA
###	IRF510	MOT			N	100		5.6	43	TO-220AB
###	IRF511	MOT			N	80		5.6	43	TO-220AB
###	IRF512	MOT			N	100		4.9	43	TO-220AB
###	IRF513	MOT			N	80		4.9	43	TO-220AB
###	IRF520	MOT			N	100		8	40	TO-220AB
###	IRF521	MOT			N	60		8	40	TO-220AB
###	IRF522	MOT			N	100		7	40	TO-220AB
###	IRF523	MOT			N	60		7	40	TO-220AB
###	IRF530	MOT			N	100		14	75	TO-220AB
###	IRF531	MOT			N	60		14	75	TO-220AB
###	IRF532	MOT			N	100		12	75	TO-220AB
###	IRF533	MOT			N	60		12	75	TO-220AB
###	IRF540	MOT			N	100		28	150	TO-220AB
###	IRF541	MOT			N	80		28	150	TO-220AB
###	IRF542	MOT			N	100		25	150	TO-220AB
###	IRF543	MOT			N	80		25	150	TO-220AB
###	IRF610	MOT			N	200		3.3	43	TO-220AB
###	IRF611	MOT			N	150		3.3	43	TO-220AB
###	IRF612	MOT			N	200		2.6	43	TO-220AB
###	IRF613	MOT			N	150		2.6	43	TO-220AB
###	IRF620	MOT			N	200		5	40	TO-220AB
###	IRF621	MOT			N	150		5	40	TO-220AB
###	IRF622	MOT			N	200		4	40	TO-220AB
###	IRF623	MOT			N	150		4	40	TO-220AB
###	IRF630	MOT			N	200		9	75	TO-220AB
###	IRF631	MOT			N	150		9	75	TO-220AB
###	IRF632	MOT			N	200		8	75	TO-220AB
###	IRF633	MOT			N	150		8	75	TO-220AB
###	IRF640	MOT			N	200		18	125	TO-220AB
###	IRF641	MOT			N	150		18	125	TO-220AB
###	IRF642	MOT			N	200		16	125	TO-220AB
###	IRF643	MOT			N	150		16	125	TO-220AB
###	IRF710	MOT			N	400		2	36	TO-220AB
###	IRF720	MOT			N	400		3.3	50	TO-220AB
###	IRF722	MOT			N	400		2.8	50	TO-220AB

5000种场效应管参数

更多彩电维修资料请到《[彩电视维修资料网](http://www.tv160.net)》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
###	IRF730	MOT			N	400		5.5	75	TO-220AB
###	IRF731	MOT			N	350		5.5	75	TO-220AB
###	IRF732	MOT			N	400		4.5	75	TO-220AB
###	IRF733	MOT			N	350		4.5	75	TO-220AB
###	IRF740	MOT			N	400		10	125	TO-220AB
###	IRF741	MOT			N	350		10	125	TO-220AB
###	IRF820	MOT			N	500		2.5	50	TO-220AB
###	IRF821	MOT			N	450		2.5	50	TO-220AB
###	IRF823	MOT			N	450		2.2	50	TO-220AB
###	IRF830	MOT			N	500		4.5	75	TO-220AB
###	IRF831	MOT			N	450		4.5	75	TO-220AB
###	IRF832	MOT			N	500		4	75	TO-220AB
###	IRF833	MOT			N	450		4	75	TO-220AB
###	IRF840	MOT			N	500		8	125	TO-220AB
###	IRF841	MOT			N	450		8	125	TO-220AB
###	IRF842	MOT			N	500		7	125	TO-220AB
###	IRF843	MOT			N	450		7	125	TO-220AB
###	IRF9630	MOT			P	-200		-6.5	75	TO-220AB
###	IRF9640	MOT			P	-200		-11	125	TO-220AB
###	IRFD1Z0	MOT			N	100		0.5	1	CASE370-01
###	IRFD1Z3	MOT			N	60		0.4	1	CASE370-01
###	IRFD110	MOT			N	100		1	1	CASE370-01
###	IRFD113	MOT			N	60		0.8	1	CASE370-01
###	IRFD120	MOT			N	100		1.3	1	CASE370-01
###	IRFD121	MOT			N	60		1.3	1	CASE370-01
###	IRFD122	MOT			N	100		1.1	1	CASE370-01
###	IRFD123	MOT			N	60		1.1	1	CASE370-01
###	IRFD210	MOT			N	200		0.6	1	CASE370-01
###	IRFD211	MOT			N	150		0.6	1	CASE370-01
###	IRFD212	MOT			N	200		0.45	1	CASE370-01
###	IRFD213	MOT			N	150		0.45	1	CASE370-01
###	IRFD220	MOT			N	200		0.8	1	CASE370-01
###	IRFD221	MOT			N	150		0.8	1	CASE370-01
###	IRFD222	MOT			N	200		0.7	1	CASE370-01
###	IRFD223	MOT			N	150		0.7	1	CASE370-01
###	IRFF110	MOT			N	100		3.5	15	CASE79-05
###	IRFF113	MOT			N	60		3	15	CASE79-05
###	IRFF120	MOT			N	100		6	20	CASE79-05
###	IRFF123	MOT			N	60		5	20	CASE79-05
###	IRFF220	MOT			N	200		3.5	20	CASE79-05
###	IRFF223	MOT			N	150		3	20	CASE79-05
###	IRFZ20	MOT			N	50		15	40	TO-220AB
###	IRFZ22	MOT			N	50		14	40	TO-220AB
###	IRFZ30	MOT			N	50		30	75	TO-220AB
###	IRFZ32	MOT			N	50		25	75	TO-220AB
###	IRFZ40	MOT			N	50		35	125	TO-220AB
###	IRFZ42	MOT			N	50		35	125	TO-220AB
###	IRFZ44	MOT			N	60				TO-220AB
###	IRF9Z10	SAMSUNG			P	-50				TO-220
###	IRF9Z12	SAMSUNG			P	-50				TO-220
###	IRF9Z20	SAMSUNG			P	-50				TO-220
###	IRF9Z22	SAMSUNG			P	-50				TO-220
###	IRF9Z30	SAMSUNG			P	-50				TO-220
###	IRF9Z32	SAMSUNG			P	-50				TO-220
###	IRF120	SAMSUNG			N	100				TO-3
###	IRF121	SAMSUNG			N	80				TO-3
###	IRF122	SAMSUNG			N	100				TO-3
###	IRF123	SAMSUNG			N	80				TO-3
###	IRF130	SAMSUNG			N	100				TO-3
###	IRF131	SAMSUNG			N	80				TO-3
###	IRF132	SAMSUNG			N	100				TO-3

5000种场效应管参数

更多彩电维修资料请到《[彩电维修资料网](http://www.tv160.net)》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
###	IRF133	SAMSUNG			N	80				T0-3
###	IRF140	SAMSUNG			N	100				T0-3
###	IRF141	SAMSUNG			N	80				T0-3
###	IRF142	SAMSUNG			N	100				T0-3
###	IRF143	SAMSUNG			N	80				T0-3
###	IRF150	SAMSUNG			N	100				T0-3
###	IRF151	SAMSUNG			N	80				T0-3
###	IRF152	SAMSUNG			N	100				T0-3
###	IRF153	SAMSUNG			N	80				T0-3
###	IRF220	SAMSUNG			N	200				T0-3
###	IRF221	SAMSUNG			N	150				T0-3
###	IRF222	SAMSUNG			N	200				T0-3
###	IRF223	SAMSUNG			N	150				T0-3
###	IRF230	SAMSUNG			N	200				T0-3
###	IRF231	SAMSUNG			N	150				T0-3
###	IRF232	SAMSUNG			N	200				T0-3
###	IRF233	SAMSUNG			N	150				T0-3
###	IRF240	SAMSUNG			N	200				T0-3
###	IRF241	SAMSUNG			N	150				T0-3
###	IRF242	SAMSUNG			N	200				T0-3
###	IRF243	SAMSUNG			N	150				T0-3
###	IRF250	SAMSUNG			N	200				T0-3
###	IRF251	SAMSUNG			N	150				T0-3
###	IRF252	SAMSUNG			N	200				T0-3
###	IRF253	SAMSUNG			N	150				T0-3
###	IRF254	SAMSUNG			N	250				T0-3
###	IRF255	SAMSUNG			N	250				T0-3
###	IRF320	SAMSUNG			N	400				T0-3
###	IRF321	SAMSUNG			N	350				T0-3
###	IRF322	SAMSUNG			N	400				T0-3
###	IRF323	SAMSUNG			N	350				T0-3
###	IRF330	SAMSUNG			N	400				T0-3
###	IRF331	SAMSUNG			N	350				T0-3
###	IRF332	SAMSUNG			N	400				T0-3
###	IRF333	SAMSUNG			N	350				T0-3
###	IRF340	SAMSUNG			N	400				T0-3
###	IRF341	SAMSUNG			N	350				T0-3
###	IRF342	SAMSUNG			N	400				T0-3
###	IRF343	SAMSUNG			N	350				T0-3
###	IRF350	SAMSUNG			N	400				T0-3
###	IRF351	SAMSUNG			N	350				T0-3
###	IRF352	SAMSUNG			N	400				T0-3
###	IRF353	SAMSUNG			N	350				T0-3
###	IRF420	SAMSUNG			N	500				T0-3
###	IRF421	SAMSUNG			N	450				T0-3
###	IRF422	SAMSUNG			N	500				T0-3
###	IRF423	SAMSUNG			N	450				T0-3
###	IRF430	SAMSUNG			N	500				T0-3
###	IRF431	SAMSUNG			N	450				T0-3
###	IRF432	SAMSUNG			N	500				T0-3
###	IRF433	SAMSUNG			N	450				T0-3
###	IRF440	SAMSUNG			N	500				T0-3
###	IRF441	SAMSUNG			N	450				T0-3
###	IRF442	SAMSUNG			N	500				T0-3
###	IRF443	SAMSUNG			N	450				T0-3
###	IRF450	SAMSUNG			N	500				T0-3
###	IRF451	SAMSUNG			N	450				T0-3
###	IRF452	SAMSUNG			N	500				T0-3
###	IRF453	SAMSUNG			N	450				T0-3
###	IRF510	SAMSUNG			N	100				T0-220
###	IRF511	SAMSUNG			N	80				T0-220

5000种场效应管参数

更多彩电维修资料请到《[彩电维修资料网](http://www.tv160.net)》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
###	IRF512	SAMSUNG			N	100				T0-220
###	IRF513	SAMSUNG			N	80				T0-220
###	IRF520	SAMSUNG			N	100				T0-220
###	IRF521	SAMSUNG			N	80				T0-220
###	IRF522	SAMSUNG			N	100				T0-220
###	IRF523	SAMSUNG			N	80				T0-220
###	IRF530	SAMSUNG			N	100				T0-220
###	IRF531	SAMSUNG			N	80				T0-220
###	IRF532	SAMSUNG			N	100				T0-220
###	IRF533	SAMSUNG			N	80				T0-220
###	IRF540	SAMSUNG			N	100				T0-220
###	IRF541	SAMSUNG			N	80				T0-220
###	IRF542	SAMSUNG			N	100				T0-220
###	IRF543	SAMSUNG			N	80				T0-220
###	IRF610	SAMSUNG			N	200				T0-220
###	IRF611	SAMSUNG			N	150				T0-220
###	IRF612	SAMSUNG			N	200				T0-220
###	IRF613	SAMSUNG			N	150				T0-220
###	IRF614	SAMSUNG			N	250				T0-220
###	IRF615	SAMSUNG			N	250				T0-220
###	IRF620	SAMSUNG			N	200				T0-220
###	IRF621	SAMSUNG			N	150				T0-220
###	IRF622	SAMSUNG			N	200				T0-220
###	IRF623	SAMSUNG			N	150				T0-220
###	IRF624	SAMSUNG			N	250				T0-220
###	IRF625	SAMSUNG			N	250				T0-220
###	IRF630	SAMSUNG			N	200				T0-220
###	IRF631	SAMSUNG			N	150				T0-220
###	IRF632	SAMSUNG			N	200				T0-220
###	IRF633	SAMSUNG			N	150				T0-220
###	IRF634	SAMSUNG			N	250				T0-220
###	IRF635	SAMSUNG			N	250				T0-220
###	IRF640	SAMSUNG			N	200				T0-220
###	IRF641	SAMSUNG			N	150				T0-220
###	IRF642	SAMSUNG			N	200				T0-220
###	IRF643	SAMSUNG			N	150				T0-220
###	IRF644	SAMSUNG			N	250				T0-220
###	IRF645	SAMSUNG			N	250				T0-220
###	IRF710	SAMSUNG			N	400				T0-220
###	IRF711	SAMSUNG			N	350				T0-220
###	IRF712	SAMSUNG			N	400				T0-220
###	IRF713	SAMSUNG			N	350				T0-220
###	IRF720	SAMSUNG			N	400				T0-220
###	IRF721	SAMSUNG			N	350				T0-220
###	IRF722	SAMSUNG			N	400				T0-220
###	IRF723	SAMSUNG			N	350				T0-220
###	IRF730	SAMSUNG			N	400				T0-220
###	IRF731	SAMSUNG			N	350				T0-220
###	IRF732	SAMSUNG			N	400				T0-220
###	IRF733	SAMSUNG			N	350				T0-220
###	IRF740	SAMSUNG			N	400				T0-220
###	IRF741	SAMSUNG			N	350				T0-220
###	IRF742	SAMSUNG			N	400				T0-220
###	IRF743	SAMSUNG			N	350				T0-220
###	IRF820	SAMSUNG			N	500				T0-220
###	IRF821	SAMSUNG			N	450				T0-220
###	IRF822	SAMSUNG			N	500				T0-220
###	IRF823	SAMSUNG			N	450				T0-220
###	IRF830	SAMSUNG			N	500				T0-220
###	IRF831	SAMSUNG			N	450				T0-220
###	IRF832	SAMSUNG			N	500				T0-220

5000种场效应管参数

更多彩电维修资料请到《[彩电视维修资料网](http://www.tv160.net)》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
###	IRF833	SAMSUNG			N	450				T0-220
###	IRF840	SAMSUNG			N	500				T0-220
###	IRF841	SAMSUNG			N	450				T0-220
###	IRF842	SAMSUNG			N	500				T0-220
###	IRF843	SAMSUNG			N	450				T0-220
###	IRF9120	SAMSUNG			P	-100		-6	40	T0-3
###	IRF9121	SAMSUNG			P	-60		-6	40	T0-3
###	IRF9122	SAMSUNG			P	-100		-5	40	T0-3
###	IRF9123	SAMSUNG			P	-60		-5	40	T0-3
###	IRF9130	SAMSUNG			P	-100		-12	75	T0-3
###	IRF9131	SAMSUNG			P	-60		-12	75	T0-3
###	IRF9132	SAMSUNG			P	-100		-10	75	T0-3
###	IRF9133	SAMSUNG			P	-60		-10	75	T0-3
###	IRF9140	SAMSUNG			P	-100		-19	125	T0-3
###	IRF9141	SAMSUNG			P	-60		-19	125	T0-3
###	IRF9142	SAMSUNG			P	-100		-15	125	T0-3
###	IRF9143	SAMSUNG			P	-60		-15	125	T0-3
###	IRF9220	SAMSUNG			P	-200		-3.5	40	T0-3
###	IRF9221	SAMSUNG			P	-150		-3.5	40	T0-3
###	IRF9222	SAMSUNG			P	-200		-3	40	T0-3
###	IRF9223	SAMSUNG			P	-150		-3	40	T0-3
###	IRF9230	SAMSUNG			P	-200		-6.5	75	T0-3
###	IRF9231	SAMSUNG			P	-150		-6.5	75	T0-3
###	IRF9232	SAMSUNG			P	-200		-5.5	75	T0-3
###	IRF9233	SAMSUNG			P	-150		-5.5	75	T0-3
###	IRF9240	SAMSUNG			P	-200		-11	125	T0-3
###	IRF9241	SAMSUNG			P	-150		-11	125	T0-3
###	IRF9242	SAMSUNG			P	-200		-9.0	125	T0-3
###	IRF9243	SAMSUNG			P	-150		-9.0	125	T0-3
###	IRF9510	SAMSUNG			P	-100				T0-220
###	IRF9511	SAMSUNG			P	-60				T0-220
###	IRF9512	SAMSUNG			P	-100				T0-220
###	IRF9513	SAMSUNG			P	-60				T0-220
###	IRF9520	SAMSUNG			P	-100				T0-220
###	IRF9521	SAMSUNG			P	-60				T0-220
###	IRF9522	SAMSUNG			P	-100				T0-220
###	IRF9523	SAMSUNG			P	-60				T0-220
###	IRF9530	SAMSUNG			P	-100				T0-220
###	IRF9531	SAMSUNG			P	-60				T0-220
###	IRF9532	SAMSUNG			P	-100				T0-220
###	IRF9533	SAMSUNG			P	-60				T0-220
###	IRF9540	SAMSUNG			P	-100				T0-220
###	IRF9541	SAMSUNG			P	-60				T0-220
###	IRF9542	SAMSUNG			P	-100				T0-220
###	IRF9543	SAMSUNG			P	-60				T0-220
###	IRF9610	SAMSUNG			P	-200				T0-220
###	IRF9611	SAMSUNG			P	-150				T0-220
###	IRF9612	SAMSUNG			P	-200				T0-220
###	IRF9613	SAMSUNG			P	-150				T0-220
###	IRF9620	SAMSUNG			P	-200				T0-220
###	IRF9621	SAMSUNG			P	-150				T0-220
###	IRF9622	SAMSUNG			P	-200				T0-220
###	IRF9623	SAMSUNG			P	-150				T0-220
###	IRF9630	SAMSUNG			P	-200				T0-220
###	IRF9631	SAMSUNG			P	-150				T0-220
###	IRF9632	SAMSUNG			P	-200				T0-220
###	IRF9633	SAMSUNG			P	-150				T0-220
###	IRF9640	SAMSUNG			P	-200				T0-220
###	IRF9641	SAMSUNG			P	-150				T0-220
###	IRF9642	SAMSUNG			P	-200				T0-220
###	IRF9643	SAMSUNG			P	-150				T0-220

5000种场效应管参数

更多彩电维修资料请到《[彩电视维修资料网](http://www.tv160.net)》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
###	IRFA1Z0	SAMSUNG			N	100				T0-126
###	IRFA1Z3	SAMSUNG			N	60				T0-126
###	IRFP120	SAMSUNG			N	100				T0-3P
###	IRFP121	SAMSUNG			N	80				T0-3P
###	IRFP122	SAMSUNG			N	100				T0-3P
###	IRFP123	SAMSUNG			N	80				T0-3P
###	IRFP130	SAMSUNG			N	100				T0-3P
###	IRFP131	SAMSUNG			N	80				T0-3P
###	IRFP132	SAMSUNG			N	100				T0-3P
###	IRFP133	SAMSUNG			N	80				T0-3P
###	IRFP140	SAMSUNG			N	100				T0-3P
###	IRFP141	SAMSUNG			N	80				T0-3P
###	IRFP142	SAMSUNG			N	100				T0-3P
###	IRFP143	SAMSUNG			N	80				T0-3P
###	IRFP150	SAMSUNG			N	100				T0-3P
###	IRFP151	SAMSUNG			N	80				T0-3P
###	IRFP152	SAMSUNG			N	100				T0-3P
###	IRFP153	SAMSUNG			N	80				T0-3P
###	IRFP220	SAMSUNG			N	200				T0-3P
###	IRFP221	SAMSUNG			N	150				T0-3P
###	IRFP222	SAMSUNG			N	200				T0-3P
###	IRFP223	SAMSUNG			N	150				T0-3P
###	IRFP230	SAMSUNG			N	200				T0-3P
###	IRFP231	SAMSUNG			N	150				T0-3P
###	IRFP232	SAMSUNG			N	200				T0-3P
###	IRFP233	SAMSUNG			N	150				T0-3P
###	IRFP240	SAMSUNG			N	200				T0-3P
###	IRFP241	SAMSUNG			N	150				T0-3P
###	IRFP242	SAMSUNG			N	200				T0-3P
###	IRFP243	SAMSUNG			N	150				T0-3P
###	IRFP244	SAMSUNG			N	250				T0-3P
###	IRFP245	SAMSUNG			N	250				T0-3P
###	IRFP250	SAMSUNG			N	200				T0-3P
###	IRFP251	SAMSUNG			N	150				T0-3P
###	IRFP252	SAMSUNG			N	200				T0-3P
###	IRFP253	SAMSUNG			N	150				T0-3P
###	IRFP254	SAMSUNG			N	250				T0-3P
###	IRFP255	SAMSUNG			N	250				T0-3P
###	IRFP320	SAMSUNG			N	400				T0-3P
###	IRFP321	SAMSUNG			N	350				T0-3P
###	IRFP322	SAMSUNG			N	400				T0-3P
###	IRFP323	SAMSUNG			N	350				T0-3P
###	IRFP330	SAMSUNG			N	400				T0-3P
###	IRFP331	SAMSUNG			N	350				T0-3P
###	IRFP332	SAMSUNG			N	400				T0-3P
###	IRFP333	SAMSUNG			N	350				T0-3P
###	IRFP340	SAMSUNG			N	400				T0-3P
###	IRFP341	SAMSUNG			N	350				T0-3P
###	IRFP342	SAMSUNG			N	400				T0-3P
###	IRFP343	SAMSUNG			N	350				T0-3P
###	IRFP350	SAMSUNG			N	400				T0-3P
###	IRFP351	SAMSUNG			N	350				T0-3P
###	IRFP352	SAMSUNG			N	400				T0-3P
###	IRFP353	SAMSUNG			N	350				T0-3P
###	IRFP420	SAMSUNG			N	500				T0-3P
###	IRFP421	SAMSUNG			N	450				T0-3P
###	IRFP422	SAMSUNG			N	500				T0-3P
###	IRFP423	SAMSUNG			N	450				T0-3P
###	IRFP430	SAMSUNG			N	500				T0-3P
###	IRFP431	SAMSUNG			N	450				T0-3P
###	IRFP432	SAMSUNG			N	500				T0-3P

5000种场效应管参数

更多彩电维修资料请到《[彩电视维修资料网](http://www.tv160.net)》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
###	IRFP433	SAMSUNG			N	450				T0-3P
###	IRFP440	SAMSUNG			N	500				T0-3P
###	IRFP441	SAMSUNG			N	450				T0-3P
###	IRFP442	SAMSUNG			N	500				T0-3P
###	IRFP443	SAMSUNG			N	450				T0-3P
###	IRFP450	SAMSUNG			N	500				T0-3P
###	IRFP451	SAMSUNG			N	450				T0-3P
###	IRFP452	SAMSUNG			N	500				T0-3P
###	IRFP453	SAMSUNG			N	450				T0-3P
###	IRFP9120	SAMSUNG			P	-100		-6	40	T0-3P
###	IRFP9121	SAMSUNG			P	-60		-6	40	T0-3P
###	IRFP9122	SAMSUNG			P	-100		-5	40	T0-3P
###	IRFP9123	SAMSUNG			P	-60		-5	40	T0-3P
###	IRFP9130	SAMSUNG			P	-100		-12	75	T0-3P
###	IRFP9131	SAMSUNG			P	-60		-12	75	T0-3P
###	IRFP9132	SAMSUNG			P	-100		-10	75	T0-3P
###	IRFP9133	SAMSUNG			P	-60		-10	75	T0-3P
###	IRFP9140	SAMSUNG			P	-100		-19	150	T0-3P
###	IRFP9141	SAMSUNG			P	-60		-19	150	T0-3P
###	IRFP9142	SAMSUNG			P	-100		-16	150	T0-3P
###	IRFP9143	SAMSUNG			P	-60		-16	150	T0-3P
###	IRFP9220	SAMSUNG			P	-200		-3.5	40	T0-3P
###	IRFP9221	SAMSUNG			P	-150		-3.5	40	T0-3P
###	IRFP9222	SAMSUNG			P	-200		-3	40	T0-3P
###	IRFP9223	SAMSUNG			P	-150		-3	40	T0-3P
###	IRFP9230	SAMSUNG			P	-200		-6.5	75	T0-3P
###	IRFP9231	SAMSUNG			P	-150		-6.5	75	T0-3P
###	IRFP9232	SAMSUNG			P	-200		-5.5	75	T0-3P
###	IRFP9233	SAMSUNG			P	-150		-5.5	75	T0-3P
###	IRFP9240	SAMSUNG			P	-200		-12	150	T0-3P
###	IRFP9241	SAMSUNG			P	-150		-12	150	T0-3P
###	IRFP9242	SAMSUNG			P	-200		-10	150	T0-3P
###	IRFP9243	SAMSUNG			P	-150		-10	150	T0-3P
###	IRFP9510	SAMSUNG			P	-100		-3	20	T0-220
###	IRFP9511	SAMSUNG			P	-60		-3	20	T0-220
###	IRFP9512	SAMSUNG			P	-100		-2.5	20	T0-220
###	IRFP9513	SAMSUNG			P	-60		-2.5	20	T0-220
###	IRFP9520	SAMSUNG			P	-100		-6	40	T0-220
###	IRFP9521	SAMSUNG			P	-60		-6	40	T0-220
###	IRFP9522	SAMSUNG			P	-100		-5	40	T0-220
###	IRFP9523	SAMSUNG			P	-60		-5	40	T0-220
###	IRFP9530	SAMSUNG			P	-100		-12	75	T0-220
###	IRFP9531	SAMSUNG			P	-60		-12	75	T0-220
###	IRFP9532	SAMSUNG			P	-100		-10	75	T0-220
###	IRFP9533	SAMSUNG			P	-60		-10	75	T0-220
###	IRFP9540	SAMSUNG			P	-100		-19	125	T0-220
###	IRFP9541	SAMSUNG			P	-60		-19	125	T0-220
###	IRFP9542	SAMSUNG			P	-100		-15	125	T0-220
###	IRFP9543	SAMSUNG			P	-60		-15	125	T0-220
###	IRFP9610	SAMSUNG			P	-200		-1.75	20	T0-220
###	IRFP9611	SAMSUNG			P	-150		-1.75	20	T0-220
###	IRFP9612	SAMSUNG			P	-200		-1.5	20	T0-220
###	IRFP9613	SAMSUNG			P	-150		-1.5	20	T0-220
###	IRFP9620	SAMSUNG			P	-200		-3.5	40	T0-220
###	IRFP9621	SAMSUNG			P	-150		-3.5	40	T0-220
###	IRFP9622	SAMSUNG			P	-200		-3	40	T0-220
###	IRFP9623	SAMSUNG			P	-150		-3	40	T0-220
###	IRFP9630	SAMSUNG			P	-200		-6.5	75	T0-220
###	IRFP9631	SAMSUNG			P	-150		-6.5	75	T0-220
###	IRFP9632	SAMSUNG			P	-200		-5.5	75	T0-220
###	IRFP9633	SAMSUNG			P	-150		-5.5	75	T0-220

5000种场效应管参数

更多彩电维修资料请到《[彩电视维修资料网](http://www.tv160.net)》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
###	IRFP9640	SAMSUNG			P	-200		-11	125	T0-220
###	IRFP9641	SAMSUNG			P	-150		-11	125	T0-220
###	IRFP9642	SAMSUNG			P	-200		-9	125	T0-220
###	IRFP9643	SAMSUNG			P	-150		-9	125	T0-220
###	IRFR010	SAMSUNG			N	50				D-PAK
###	IRFR012	SAMSUNG			N	50				D-PAK
###	IRFR020	SAMSUNG			N	50				D-PAK
###	IRFR022	SAMSUNG			N	50				D-PAK
###	IRFR110	SAMSUNG			N	100				D-PAK
###	IRFR111	SAMSUNG			N	80				D-PAK
###	IRFR120	SAMSUNG			N	100				D-PAK
###	IRFR121	SAMSUNG			N	80				D-PAK
###	IRFR210	SAMSUNG			N	200				D-PAK
###	IRFR212	SAMSUNG			N	200				D-PAK
###	IRFR220	SAMSUNG			N	200				D-PAK
###	IRFR222	SAMSUNG			N	200				D-PAK
###	IRFR310	SAMSUNG			N	400				D-PAK
###	IRFR320	SAMSUNG			N	400				D-PAK
###	IRFR411	SAMSUNG			N	450				D-PAK
###	IRFR420	SAMSUNG			N	500				D-PAK
###	IRFR9010	SAMSUNG			P	-50				D-PAK
###	IRFR9012	SAMSUNG			P	-50				D-PAK
###	IRFR9020	SAMSUNG			P	-50				D-PAK
###	IRFR9022	SAMSUNG			P	-50				D-PAK
###	IRFR9110	SAMSUNG			P	-100				D-PAK
###	IRFR9111	SAMSUNG			P	-80				D-PAK
###	IRFR9120	SAMSUNG			P	-100				D-PAK
###	IRFR9121	SAMSUNG			P	-80				D-PAK
###	IRFR9210	SAMSUNG			P	-200				D-PAK
###	IRFR9212	SAMSUNG			P	-200				D-PAK
###	IRFR9220	SAMSUNG			P	-200				D-PAK
###	IRFR9222	SAMSUNG			P	-200				D-PAK
###	IRFS130	SAMSUNG			N	100				T0-247
###	IRFS131	SAMSUNG			N	80				T0-247
###	IRFS132	SAMSUNG			N	100				T0-247
###	IRFS133	SAMSUNG			N	80				T0-247
###	IRFS140	SAMSUNG			N	100				T0-247
###	IRFS141	SAMSUNG			N	80				T0-247
###	IRFS142	SAMSUNG			N	100				T0-247
###	IRFS143	SAMSUNG			N	80				T0-247
###	IRFS150	SAMSUNG			N	100				T0-247
###	IRFS151	SAMSUNG			N	80				T0-247
###	IRFS152	SAMSUNG			N	100				T0-247
###	IRFS153	SAMSUNG			N	80				T0-247
###	IRFS230	SAMSUNG			N	200				T0-247
###	IRFS231	SAMSUNG			N	150				T0-247
###	IRFS232	SAMSUNG			N	200				T0-247
###	IRFS233	SAMSUNG			N	150				T0-247
###	IRFS240	SAMSUNG			N	200				T0-247
###	IRFS241	SAMSUNG			N	150				T0-247
###	IRFS242	SAMSUNG			N	200				T0-247
###	IRFS243	SAMSUNG			N	150				T0-247
###	IRFS250	SAMSUNG			N	200				T0-247
###	IRFS251	SAMSUNG			N	150				T0-247
###	IRFS252	SAMSUNG			N	200				T0-247
###	IRFS253	SAMSUNG			N	150				T0-247
###	IRFS330	SAMSUNG			N	400				T0-247
###	IRFS331	SAMSUNG			N	350				T0-247
###	IRFS332	SAMSUNG			N	400				T0-247
###	IRFS333	SAMSUNG			N	350				T0-247
###	IRFS340	SAMSUNG			N	400				T0-247

5000种场效应管参数

更多彩电维修资料请到《[彩电视维修资料网](http://www.tv160.net)》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
###	IRFS341	SAMSUNG			N	350				T0-247
###	IRFS342	SAMSUNG			N	400				T0-247
###	IRFS343	SAMSUNG			N	350				T0-247
###	IRFS350	SAMSUNG			N	400				T0-247
###	IRFS351	SAMSUNG			N	350				T0-247
###	IRFS352	SAMSUNG			N	400				T0-247
###	IRFS353	SAMSUNG			N	350				T0-247
###	IRFS430	SAMSUNG			N	500				T0-247
###	IRFS431	SAMSUNG			N	450				T0-247
###	IRFS432	SAMSUNG			N	500				T0-247
###	IRFS433	SAMSUNG			N	450				T0-247
###	IRFS440	SAMSUNG			N	500				T0-247
###	IRFS441	SAMSUNG			N	450				T0-247
###	IRFS442	SAMSUNG			N	500				T0-247
###	IRFS443	SAMSUNG			N	450				T0-247
###	IRFS450	SAMSUNG			N	500				T0-247
###	IRFS451	SAMSUNG			N	450				T0-247
###	IRFS452	SAMSUNG			N	500				T0-247
###	IRFS453	SAMSUNG			N	450				T0-247
###	IRFS530	SAMSUNG			N	100				T0-220
###	IRFS531	SAMSUNG			N	80				T0-220
###	IRFS532	SAMSUNG			N	100				T0-220
###	IRFS533	SAMSUNG			N	80				T0-220
###	IRFS540	SAMSUNG			N	100				T0-220
###	IRFS541	SAMSUNG			N	80				T0-220
###	IRFS542	SAMSUNG			N	100				T0-220
###	IRFS543	SAMSUNG			N	80				T0-220
###	IRFS630	SAMSUNG			N	200				T0-220
###	IRFS631	SAMSUNG			N	150				T0-220
###	IRFS632	SAMSUNG			N	200				T0-220
###	IRFS633	SAMSUNG			N	150				T0-220
###	IRFS634	SAMSUNG			N	250				T0-220
###	IRFS635	SAMSUNG			N	250				T0-220
###	IRFS640	SAMSUNG			N	200				T0-220
###	IRFS641	SAMSUNG			N	150				T0-220
###	IRFS642	SAMSUNG			N	200				T0-220
###	IRFS643	SAMSUNG			N	150				T0-220
###	IRFS644	SAMSUNG			N	250				T0-220
###	IRFS645	SAMSUNG			N	250				T0-220
###	IRFS730	SAMSUNG			N	400				T0-220
###	IRFS731	SAMSUNG			N	350				T0-220
###	IRFS732	SAMSUNG			N	400				T0-220
###	IRFS733	SAMSUNG			N	350				T0-220
###	IRFS740	SAMSUNG			N	400				T0-220
###	IRFS741	SAMSUNG			N	350				T0-220
###	IRFS742	SAMSUNG			N	400				T0-220
###	IRFS743	SAMSUNG			N	350				T0-220
###	IRFS830	SAMSUNG			N	500				T0-220
###	IRFS831	SAMSUNG			N	450				T0-220
###	IRFS832	SAMSUNG			N	500				T0-220
###	IRFS833	SAMSUNG			N	450				T0-220
###	IRFS840	SAMSUNG			N	500				T0-220
###	IRFS841	SAMSUNG			N	450				T0-220
###	IRFS842	SAMSUNG			N	500				T0-220
###	IRFS843	SAMSUNG			N	450				T0-220
###	IRFS9130	SAMSUNG			P	-100				T0-247
###	IRFS9131	SAMSUNG			P	-60				T0-247
###	IRFS9132	SAMSUNG			P	-100				T0-247
###	IRFS9133	SAMSUNG			P	-60				T0-247
###	IRFS9140	SAMSUNG			P	-100				T0-247
###	IRFS9141	SAMSUNG			P	-60				T0-247

5000种场效应管参数

更多彩电维修资料请到《[彩电视维修资料网](http://www.tv160.net)》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
###	IRFS9142	SAMSUNG			P	-100				T0-247
###	IRFS9143	SAMSUNG			P	-60				T0-247
###	IRFS9230	SAMSUNG			P	-200				T0-247
###	IRFS9231	SAMSUNG			P	-150				T0-247
###	IRFS9232	SAMSUNG			P	-200				T0-247
###	IRFS9233	SAMSUNG			P	-150				T0-247
###	IRFS9240	SAMSUNG			P	-200				T0-247
###	IRFS9241	SAMSUNG			P	-150				T0-247
###	IRFS9242	SAMSUNG			P	-200				T0-247
###	IRFS9243	SAMSUNG			P	-150				T0-247
###	IRFS9530	SAMSUNG			P	-100				T0-220
###	IRFS9531	SAMSUNG			P	-60				T0-220
###	IRFS9532	SAMSUNG			P	-100				T0-220
###	IRFS9533	SAMSUNG			P	-60				T0-220
###	IRFS9540	SAMSUNG			P	-100				T0-220
###	IRFS9541	SAMSUNG			P	-60				T0-220
###	IRFS9542	SAMSUNG			P	-100				T0-220
###	IRFS9543	SAMSUNG			P	-60				T0-220
###	IRFS9630	SAMSUNG			P	-200				T0-220
###	IRFS9631	SAMSUNG			P	-150				T0-220
###	IRFS9632	SAMSUNG			P	-200				T0-220
###	IRFS9633	SAMSUNG			P	-150				T0-220
###	IRFS9640	SAMSUNG			P	-200				T0-220
###	IRFS9641	SAMSUNG			P	-150				T0-220
###	IRFS9642	SAMSUNG			P	-200				T0-220
###	IRFS9643	SAMSUNG			P	-150				T0-220
###	IRFU010	SAMSUNG			N	50				I-PAK
###	IRFU012	SAMSUNG			N	50				I-PAK
###	IRFU020	SAMSUNG			N	50				I-PAK
###	IRFU022	SAMSUNG			N	50				I-PAK
###	IRFU110	SAMSUNG			N	100				I-PAK
###	IRFU111	SAMSUNG			N	80				I-PAK
###	IRFU120	SAMSUNG			N	100				I-PAK
###	IRFU121	SAMSUNG			N	80				I-PAK
###	IRFU210	SAMSUNG			N	200				I-PAK
###	IRFU212	SAMSUNG			N	200				I-PAK
###	IRFU220	SAMSUNG			N	200				I-PAK
###	IRFU222	SAMSUNG			N	200				I-PAK
###	IRFU310	SAMSUNG			N	400				I-PAK
###	IRFU320	SAMSUNG			N	400				I-PAK
###	IRFU411	SAMSUNG			N	450				I-PAK
###	IRFU420	SAMSUNG			N	500				I-PAK
###	IRFU9010	SAMSUNG			P	-50				I-PAK
###	IRFU9012	SAMSUNG			P	-50				I-PAK
###	IRFU9020	SAMSUNG			P	-50				I-PAK
###	IRFU9022	SAMSUNG			P	-50				I-PAK
###	IRFU9110	SAMSUNG			P	-100				I-PAK
###	IRFU9111	SAMSUNG			P	-80				I-PAK
###	IRFU9120	SAMSUNG			P	-100				I-PAK
###	IRFU9121	SAMSUNG			P	-80				I-PAK
###	IRFU9210	SAMSUNG			P	-200				I-PAK
###	IRFU9212	SAMSUNG			P	-200				I-PAK
###	IRFU9220	SAMSUNG			P	-200				I-PAK
###	IRFU9222	SAMSUNG			P	-200				I-PAK
###	IRFZ10	SAMSUNG			N	50				T0-220
###	IRFZ12	SAMSUNG			N	50				T0-220
###	IRFZ14	SAMSUNG			N	60				T0-220
###	IRFZ15	SAMSUNG			N	60				T0-220
###	IRFZ20	SAMSUNG			N	50				T0-220
###	IRFZ22	SAMSUNG			N	50				T0-220
###	IRFZ30	SAMSUNG			N	50				T0-220

5000种场效应管参数

更多彩电维修资料请到《[彩电视维修资料网](http://www.tv160.net)》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
###	IRFZ32	SAMSUNG			N	50				TO-220
###	IRFZ34	SAMSUNG			N	60				TO-220
###	IRFZ35	SAMSUNG			N	60				TO-220
###	IRFZ40	SAMSUNG			N	50				TO-220
###	IRFZ42	SAMSUNG			N	50				TO-220
###	IRFZ44	SAMSUNG			N	60				TO-220
###	IRFZ45	SAMSUNG			N	60				TO-220
###	IRL510	SAMSUNG			N	100				TO-220
###	IRL511	SAMSUNG			N	80				TO-220
###	IRL520	SAMSUNG			N	100				TO-220
###	IRL521	SAMSUNG			N	80				TO-220
###	IRL530	SAMSUNG			N	100				TO-220
###	IRL531	SAMSUNG			N	80				TO-220
###	IRL540	SAMSUNG			N	100				TO-220
###	IRL541	SAMSUNG			N	80				TO-220
###	IRL610	SAMSUNG			N	200				TO-220
###	IRL611	SAMSUNG			N	150				TO-220
###	IRL620	SAMSUNG			N	200				TO-220
###	IRL621	SAMSUNG			N	150				TO-220
###	IRL630	SAMSUNG			N	200				TO-220
###	IRL631	SAMSUNG			N	150				TO-220
###	IRL640	SAMSUNG			N	200				TO-220
###	IRL641	SAMSUNG			N	150				TO-220
###	IRLZ10	SAMSUNG			N	50				TO-220
###	IRLZ14	SAMSUNG			N	60				TO-220
###	IRLZ20	SAMSUNG			N	50				TO-220
###	IRLZ24	SAMSUNG			N	60				TO-220
###	IRLZ30	SAMSUNG			N	50				TO-220
###	IRLZ34	SAMSUNG			N	60				TO-220
###	IRLZ40	SAMSUNG			N	50				TO-220
###	IRLZ44	SAMSUNG			N	60				TO-220
###	IRFR214	SAUMSUNG			N	250		2.2	25	D-PACK
###	IRFR215	SAUMSUNG			N	250		1.7	25	D-PACK
###	IRFR312	SAUMSUNG			N	400		1	25	D-PACK
###	IRFR322	SAUMSUNG			N	400		2.3	42	D-PACK
###	IRFR422	SAUMSUNG			N	500		2.2	42	D-PACK
###	IRFS624	SAUMSUNG			N	250		3.3	30	TO-220F
###	IRFS625	SAUMSUNG			N	250		2.9	30	TO-220F
###	IRFS720	SAUMSUNG			N	400		2.5	30	TO-220F
###	IRFS721	SAUMSUNG			N	350		2.5	30	TO-220F
###	IRFS722	SAUMSUNG			N	400		2	30	TO-220F
###	IRFS723	SAUMSUNG			N	350		2	30	TO-220F
###	IRFS820	SAUMSUNG			N	500		2	30	TO-220F
###	IRFS821	SAUMSUNG			N	450		2	30	TO-220F
###	IRFS822	SAUMSUNG			N	500		1.5	30	TO-220F
###	IRFS823	SAUMSUNG			N	450		1.5	30	TO-220F
###	IRFSZ20	SAUMSUNG			N	50		12.9	30	TO-220F
###	IRFSZ22	SAUMSUNG			N	50		12	30	TO-220F
###	IRFSZ24	SAUMSUNG			N	60		12.9	30	TO-220F
###	IRFSZ25	SAUMSUNG			N	60		12	30	TO-220F
###	IRFSZ30	SAUMSUNG			N	50		18.7	35	TO-220F
###	IRFSZ32	SAUMSUNG			N	50		15.6	35	TO-220F
###	IRFSZ34	SAUMSUNG			N	60		18.7	35	TO-220F
###	IRFSZ35	SAUMSUNG			N	60		15.6	35	TO-220F
###	IRFSZ40	SAUMSUNG			N	50		34	65	TO-220F
###	IRFSZ42	SAUMSUNG			N	50		30	65	TO-220F
###	IRFSZ44	SAUMSUNG			N	60		34	65	TO-220F
###	IRFSZ45	SAUMSUNG			N	60		30	65	TO-220F
###	IRFU214	SAUMSUNG			N	250		2.2	25	I-PACK
###	IRFU215	SAUMSUNG			N	250		1.7	25	I-PACK
###	IRFU312	SAUMSUNG			N	400		1	25	I-PACK

5000种场效应管参数

更多彩电维修资料请到《[彩电视维修资料网](http://www.tv160.net)》查询吧：<http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
###	IRFU322	SAUMSUNG			N	400		2.3	42	I-PACK
###	IRFU422	SAUMSUNG			N	500		2.2	42	I-PACK
###	IRFZ24	SAUMSUNG			N	60		15	40	TO-220
###	IRFZ25	SAUMSUNG			N	60		14	40	TO-220
###	IRF120	SILICONIX			N	100		8.0	40	TO-204AA
###	IRF121	SILICONIX			N	60		8.0	40	TO-204AA
###	IRF122	SILICONIX			N	100		7.0	40	TO-204AA
###	IRF123	SILICONIX			N	60		7.0	40	TO-204AA
###	IRF130	SILICONIX			N	100		14	75	TO-204AA
###	IRF131	SILICONIX			N	60		14	75	TO-204AA
###	IRF132	SILICONIX			N	100		12	75	TO-204AA
###	IRF133	SILICONIX			N	60		12	75	TO-204AA
###	IRF140	SILICONIX			N	100		27	125	TO-204AE
###	IRF141	SILICONIX			N	60		27	125	TO-204AE
###	IRF142	SILICONIX			N	100		24	125	TO-204AE
###	IRF143	SILICONIX			N	60		24	125	TO-204AE
###	IRF150	SILICONIX			N	100		40	150	TO-204AE
###	IRF151	SILICONIX			N	60		40	150	TO-204AE
###	IRF152	SILICONIX			N	100		33	150	TO-204AE
###	IRF153	SILICONIX			N	60		33	150	TO-204AE
###	IRF220	SILICONIX			N	200		5.0	40	TO-204AA
###	IRF221	SILICONIX			N	150		5.0	40	TO-204AA
###	IRF222	SILICONIX			N	200		4.0	40	TO-204AA
###	IRF223	SILICONIX			N	150		4.0	40	TO-204AA
###	IRF230	SILICONIX			N	200		9.0	75	TO-204AA
###	IRF231	SILICONIX			N	150		9.0	75	TO-204AA
###	IRF232	SILICONIX			N	200		8.0	75	TO-204AA
###	IRF233	SILICONIX			N	150		8.0	75	TO-204AA
###	IRF240	SILICONIX			N	200		18	125	TO-204AE
###	IRF241	SILICONIX			N	150		18	125	TO-204AE
###	IRF242	SILICONIX			N	200		16	125	TO-204AE
###	IRF243	SILICONIX			N	150		16	125	TO-204AE
###	IRF250	SILICONIX			N	200		30	150	TO-204AE
###	IRF251	SILICONIX			N	150		30	150	TO-204AE
###	IRF252	SILICONIX			N	200		25	150	TO-204AE
###	IRF253	SILICONIX			N	150		25	150	TO-204AE
###	IRF320	SILICONIX			N	400		3.0	40	TO-204AA
###	IRF321	SILICONIX			N	350		3.0	40	TO-204AA
###	IRF322	SILICONIX			N	400		2.5	40	TO-204AA
###	IRF323	SILICONIX			N	350		2.5	40	TO-204AA
###	IRF330	SILICONIX			N	400		5.5	75	TO-204AA
###	IRF331	SILICONIX			N	350		5.5	75	TO-204AA
###	IRF332	SILICONIX			N	400		4.5	75	TO-204AA
###	IRF333	SILICONIX			N	350		4.5	75	TO-204AA
###	IRF340	SILICONIX			N	400		10	125	TO-204AA
###	IRF341	SILICONIX			N	350		10	125	TO-204AA
###	IRF342	SILICONIX			N	400		8.0	125	TO-204AA
###	IRF343	SILICONIX			N	350		8.0	125	TO-204AA
###	IRF350	SILICONIX			N	400		15	150	TO-204AA
###	IRF351	SILICONIX			N	350		15	150	TO-204AA
###	IRF352	SILICONIX			N	400		13	150	TO-204AA
###	IRF353	SILICONIX			N	350		13	150	TO-204AA
###	IRF420	SILICONIX			N	500		2.5	50	TO-204AA
###	IRF421	SILICONIX			N	450		2.5	50	TO-204AA
###	IRF422	SILICONIX			N	500		2.0	50	TO-204AA
###	IRF423	SILICONIX			N	450		2.0	50	TO-204AA
###	IRF430	SILICONIX			N	500		4.5	75	TO-204AA
###	IRF431	SILICONIX			N	450		4.5	75	TO-204AA
###	IRF432	SILICONIX			N	500		4.0	75	TO-204AA
###	IRF433	SILICONIX			N	450		4.0	75	TO-204AA
###	IRF440	SILICONIX			N	500		8.0	125	TO-204AA

5000种场效应管参数

更多彩电维修资料请到《彩电视修资料网》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
###	IRF441	SILICONIX			N	450		8.0	125	TO-204AA
###	IRF442	SILICONIX			N	500		7.0	125	TO-204AA
###	IRF443	SILICONIX			N	450		7.0	125	TO-204AA
###	IRF450	SILICONIX			N	500		13	150	TO-204AA
###	IRF451	SILICONIX			N	450		13	150	TO-204AA
###	IRF452	SILICONIX			N	500		12	150	TO-204AA
###	IRF453	SILICONIX			N	450		12	150	TO-204AA
###	IRF510	SILICONIX			N	100		5.6	43	TO-220AB
###	IRF511	SILICONIX			N	80		5.6	43	TO-220AB
###	IRF512	SILICONIX			N	100		4.9	43	TO-220AB
###	IRF513	SILICONIX			N	80		4.9	43	TO-220AB
###	IRF520	SILICONIX			N	100		8	40	TO-220AB
###	IRF521	SILICONIX			N	60		8	40	TO-220AB
###	IRF522	SILICONIX			N	100		7	40	TO-220AB
###	IRF523	SILICONIX			N	60		7	40	TO-220AB
###	IRF530	SILICONIX			N	100		14	75	TO-220AB
###	IRF531	SILICONIX			N	60		14	75	TO-220AB
###	IRF532	SILICONIX			N	100		12	75	TO-220AB
###	IRF533	SILICONIX			N	60		12	75	TO-220AB
###	IRF540	SILICONIX			N	100		28	150	TO-220AB
###	IRF541	SILICONIX			N	80		28	150	TO-220AB
###	IRF542	SILICONIX			N	100		25	150	TO-220AB
###	IRF543	SILICONIX			N	80		25	150	TO-220AB
###	IRF610	SILICONIX			N	200		3.3	43	TO-220AB
###	IRF611	SILICONIX			N	150		3.3	43	TO-220AB
###	IRF612	SILICONIX			N	200		2.6	43	TO-220AB
###	IRF613	SILICONIX			N	150		2.6	43	TO-220AB
###	IRF620	SILICONIX			N	200		5	40	TO-220AB
###	IRF621	SILICONIX			N	150		5	40	TO-220AB
###	IRF622	SILICONIX			N	200		4	40	TO-220AB
###	IRF623	SILICONIX			N	150		4	40	TO-220AB
###	IRF630	SILICONIX			N	200		9	75	TO-220AB
###	IRF631	SILICONIX			N	150		9	75	TO-220AB
###	IRF632	SILICONIX			N	200		8	75	TO-220AB
###	IRF633	SILICONIX			N	150		8	75	TO-220AB
###	IRF640	SILICONIX			N	200		18	125	TO-220AB
###	IRF641	SILICONIX			N	150		18	125	TO-220AB
###	IRF642	SILICONIX			N	200		16	125	TO-220AB
###	IRF643	SILICONIX			N	150		16	125	TO-220AB
###	IRF710	SILICONIX			N	400		2.0	36	TO-220AB
###	IRF711	SILICONIX			N	350		2.0	36	TO-220AB
###	IRF712	SILICONIX			N	400		1.7	36	TO-220AB
###	IRF713	SILICONIX			N	350		1.7	36	TO-220AB
###	IRF720	SILICONIX			N	400		3.3	50	TO-220AB
###	IRF721	SILICONIX			N	350		3.3	50	TO-220AB
###	IRF722	SILICONIX			N	400		2.8	50	TO-220AB
###	IRF723	SILICONIX			N	350		2.8	50	TO-220AB
###	IRF730	SILICONIX			N	400		5.5	74	TO-220AB
###	IRF731	SILICONIX			N	350		5.5	74	TO-220AB
###	IRF732	SILICONIX			N	400		4.5	74	TO-220AB
###	IRF733	SILICONIX			N	350		4.5	74	TO-220AB
###	IRF740	SILICONIX			N	400		10	125	TO-220AB
###	IRF741	SILICONIX			N	350		10	125	TO-220AB
###	IRF742	SILICONIX			N	400		8.3	125	TO-220AB
###	IRF743	SILICONIX			N	350		8.3	125	TO-220AB
###	IRF820	SILICONIX			N	500		2.5	50	TO-220AB
###	IRF821	SILICONIX			N	450		2.5	50	TO-220AB
###	IRF822	SILICONIX			N	500		2.2	50	TO-220AB
###	IRF823	SILICONIX			N	450		2.2	50	TO-220AB
###	IRF830	SILICONIX			N	500		4.5	74	TO-220AB
###	IRF831	SILICONIX			N	450		4.5	74	TO-220AB

5000种场效应管参数

更多彩电维修资料请到《彩电视修资料网》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道	方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
###	IRF832	SILICONIX				N	500		4.0	74	TO-220AB
###	IRF833	SILICONIX				N	450		4.0	74	TO-220AB
###	IRF840	SILICONIX				N	500		8.0	125	TO-220AB
###	IRF841	SILICONIX				N	450		8.0	125	TO-220AB
###	IRF842	SILICONIX				N	500		7.0	125	TO-220AB
###	IRF843	SILICONIX				N	450		7.0	125	TO-220AB
###	IRF9530	SILICONIX				P	-100		-12	75	TO-220AB
###	IRFD020	SILICONIX				N	50		2.4	1	4-Pin DIP
###	IRFD120	SILICONIX				N	100		1.3	1	P-DIP4P
###	IRFD123	SILICONIX				N	60		1.1	1	P-DIP4P
###	IRFD9020	SILICONIX				P	-50		-1.6	1	4-Pin DIP
###	IRFD9120	SILICONIX				P	-100		-1.0	1	P-DIP4P
###	IRFD9123	SILICONIX				P	-60		-0.8	1	P-DIP4P
###	IRFF110	SILICONIX				N	100		3.5	15	TO-205AF
###	IRFF111	SILICONIX				N	60		3.5	15	TO-205AF
###	IRFF112	SILICONIX				N	100		3.0	15	TO-205AF
###	IRFF113	SILICONIX				N	60		3.0	15	TO-205AF
###	IRFF120	SILICONIX				N	100		6.0	20	TO-205AF
###	IRFF121	SILICONIX				N	60		6.0	20	TO-205AF
###	IRFF122	SILICONIX				N	100		5.0	20	TO-205AF
###	IRFF123	SILICONIX				N	60		5.0	20	TO-205AF
###	IRFF130	SILICONIX				N	100		8.0	25	TO-205AF
###	IRFF131	SILICONIX				N	60		8.0	25	TO-205AF
###	IRFF132	SILICONIX				N	100		7.0	25	TO-205AF
###	IRFF133	SILICONIX				N	60		7.0	25	TO-205AF
###	IRFF210	SILICONIX				N	200		2.2	15	TO-205AF
###	IRFF211	SILICONIX				N	150		2.2	15	TO-205AF
###	IRFF212	SILICONIX				N	200		1.8	15	TO-205AF
###	IRFF213	SILICONIX				N	150		1.8	15	TO-205AF
###	IRFF220	SILICONIX				N	200		3.5	20	TO-205AF
###	IRFF221	SILICONIX				N	150		3.5	20	TO-205AF
###	IRFF222	SILICONIX				N	200		3.0	20	TO-205AF
###	IRFF223	SILICONIX				N	150		3.0	20	TO-205AF
###	IRFF230	SILICONIX				N	200		5.5	25	TO-205AF
###	IRFF231	SILICONIX				N	150		5.5	25	TO-205AF
###	IRFF232	SILICONIX				N	200		4.5	25	TO-205AF
###	IRFF233	SILICONIX				N	150		4.5	25	TO-205AF
###	IRFF310	SILICONIX				N	400		1.35	15	TO-205AF
###	IRFF311	SILICONIX				N	350		1.35	15	TO-205AF
###	IRFF312	SILICONIX				N	400		1.15	15	TO-205AF
###	IRFF313	SILICONIX				N	350		1.15	15	TO-205AF
###	IRFF320	SILICONIX				N	400		2.5	20	TO-205AF
###	IRFF321	SILICONIX				N	350		2.5	20	TO-205AF
###	IRFF322	SILICONIX				N	400		2.0	20	TO-205AF
###	IRFF323	SILICONIX				N	350		2.0	20	TO-205AF
###	IRFF330	SILICONIX				N	400		3.5	25	TO-205AF
###	IRFF331	SILICONIX				N	350		3.5	25	TO-205AF
###	IRFF332	SILICONIX				N	400		3.0	25	TO-205AF
###	IRFF333	SILICONIX				N	350		3.0	25	TO-205AF
###	IRFF430	SILICONIX				N	500		2.75	25	TO-205AF
###	IRFF431	SILICONIX				N	450		2.75	25	TO-205AF
###	IRFF432	SILICONIX				N	500		2.25	25	TO-205AF
###	2SK254	NEC	CATV Tuner	MOS	N	DE	18	DSX	25m	130m	4-352
###	3SK35	东芝	VHF RF/MIX	MOS	N	DE	20	DS	30m	300m	4-33
###	3SK37		VHF RF/MIX	MOS	N	DE	20	DS	25m	230m	4-34
###	3SK39	松下	VHF RF/MIX	MOS	N	DE	20	DS	24m	250m	4-39
###	3SK40	NEC	VHF RF/MIX	MOS	N	DE	20	DS	25m	250m	4-21
###	3SK41	NEC	VHF RF/MIX	MOS	N	DE	20	DS	25m	250m	4-21
###	3SK44	东芝	VHF RF/MIX	MOS	N	DE	20	DS	45m	300m	4-33
###	3SK45	日立	VHF RF/MIX	MOS	N	DE	22	DS	35m	330m	4-46
###	3SK47	NEC	VHF RF/MIX, VR	MOS	N	DE	20	DS	25m	300m	4-102B

5000种场效应管参数

更多彩电维修资料请到《[彩电维修资料网](http://www.tv160.net)》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing	
###	3SK48		UHF RF/MIX	MOS	N	DE	18	DS	30m	240m	4-34
###	3SK49	松下	VHF RF/MIX	MOS	N	DE	20	DS	30m	350m	4-39
###	3SK49(Z)	松下	VHF RF/MIX	MOS	N	DE	20	DS	30m	350m	4-39
###	3SK49NC	松下	VHF RF/MIX	MOS	N	DE	20	DS	30m	350m	4-39
###	3SK51	日立	VHF RF/MIX	MOS	N	DE	20	DS	35m	330m	4-46
###	3SK53	日立	UHF RF	MOS	N	DE	15	DS	33m	330m	4-46
###	3SK55	东芝	VHF RF/MIX	MOS	N	DE	20	DS	30m	300m	4-33
###	3SK59	东芝	VHF RF/MIX	MOS	N	DE	20	DS	30m	300m	4-33
###	3SK60	日立	VHF RF	MOS	N	DE	15	DS	33m	330m	4-46
###	3SK61		VHF RF/MIX	MOS	N	DE	20	DS	25m	230m	4-34
###	3SK63	东芝	VHF RF	MOS	N	DE	20	DS	30m	300m	4-33
###	3SK66	松下	UHF RF	MOS	N	DE	20	DS	30m	350m	4-39
###	3SK70	日立	UHF RF	MOS	N	DE	20	DS	50m	360m	4-46
###	3SK72	松下	VHF RF	MOS	N	DE	20	DS	30m	350m	4-91B
###	3SK73	东芝	VHF RF/MIX	MOS	N	DE	20	DS	30m	300m	4-17
###	3SK74	NEC	VHF RF/MIX	MOS	N	DE	20	DS	25m	200m	4-114
###	3SK77	东芝	VHF RF	MOS	N	DE	20	DS	30m	300m	4-92
###	3SK78	东芝	UHF RF	MOS	N	DE	20	DS	30m	300m	4-93
###	3SK79	松下	UHF RF	MOS	N	DE	20	DS	30m	350m	4-91
###	3SK80	日立	UHF RF	MOS	N	DE	20	DS	50m	200m	4-115
###	3SK81	日立	VHF RF	MOS	N	DE	20	DS	35m	200m	4-115
###	3SK82	日立	UHF RF	MOS	N	DE	15	DS	33m	200m	4-115
###	3SK83	日立	VHF RF	MOS	N	DE	15	DS	33m	200m	4-115
###	3SK85	日立	VHF RF	MOS	N	DE	22	DS	35m	200m	4-115
###	3SK87	NEC	UHF RF	MOS	N	DE	20	DS	25m	200m	4-114
###	3SK88	NEC	UHF RF	MOS	N	DE	20	DS	25m	200m	4-114
###	3SK90	东芝	A-SW, Chop	MOS	N	E	20	DS	20m	300m	4-197
###	3SK95	日立	UHF RF	MOS	N	DE	15	DS	35m	200m	4-115
###	3SK96	日立	VHF RF	MOS	N	DE	15	DS	35m	200m	4-115
###	3SK97	松下	UHF RF	GaAs	N	D	13	DS	80m	350m	4-91B
###	3SK100	松下	UHF LN A	MOS	N	DE	15	DS	30m	250m	4-91B
###	3SK101	东芝	VHF RF/MIX	MOS	N	DE	20	DS	30m	200m	4-125A
###	3SK102	东芝	VHF RF/MIX	MOS	N	DE	20	DS	30m	200m	4-125A
###	3SK103	日立	UHF RF	MOS	N	DE	15	DS	35m	200m	4-115
###	3SK104	日立	UHF TV Tuner	MOS	N	DE	15	DS	35m	200m	4-175A
###	3SK104V	日立	VHF TV Tuner	MOS	N	DE	15	DS	35m	200m	4-175A
###	3SK107	三洋	VHF RF	MOS	N	DE	20	DS	30m	250m	4-128
###	3SK108	三洋	VHF RF	MOS	N	DE	20	DS	30m	250m	4-128
###	3SK112	东芝	UHF RF/MIX	GaAs	N	D	10	DS	50m	200m	4-125A
###	3SK113	日立	UHF TV Tuner	GaAs/MOS	N	D	12	DS	80m	200m	4-175A
###	3SK114	东芝	VHF RF/MIX	MOS	N	DE	15	DS	30m	200m	4-125A
###	3SK115	东芝	UHF RF/MIX	MOS	N	DE	15	DS	30m	200m	4-125A
###	3SK116	松下	VHF RF	MOS	N	DE	20	DS	30m	200m	4-147A
###	3SK118	松下	UHF LN A	MOS	N	DE	15	DS	30m	250m	4-139B
###	3SK119	松下	VHF LN A	MOS	N	DE	15	DS	30m	250m	4-139B
###	3SK120	松下	VHF RF/MIX	MOS	N	DE	15	DS	30m	250m	4-139B
###	3SK121	东芝	UHF RF/MIX	GaAs	N	D	10	DS	50m	200m	4-125A
###	3SK122	NEC	VHF RF/MIX	MOS	N	DE	20	DS	25m	200m	4-114
###	3SK123	NEC	UHF TV Tuner	MOS	N	DE	18	DS	25m	200m	4-114
###	3SK125	松下	U/VHF LN A	MOS	N	DE	15	DS	30m	350m	4-139B
###	3SK126	东芝	VHF RF/MIX	MOS	N	DE	15	DS	30m	150m	4-176
###	3SK127	东芝	UHF RF/MIX	MOS	N	DE	15	DS	30m	150m	4-176
###	3SK128	松下	UHF LN A	MOS	N	DE	15	DS	30m	200m	4-147C
###	3SK129	松下	UHF RF	GaAs	N	D	13	DS	50m	350m	4-91B
###	3SK131	NEC	VHF RF/MIX	MOS	N	DE	20	DS	25m	200m	4-177
###	3SK132	NEC	UHF Tuner	MOS	N	DE	20	DS	25m	200m	4-177
###	3SK132A	NEC	UHF Tuner	MOS	N	DE	20	DS	25m	200m	4-177
###	3SK133	NEC	UHF TV Tuner	MOS	N	DE	20	DS	25m	200m	4-177
###	3SK133A	NEC	UHF TV Tuner	MOS	N	DE	20	DS	25m	200m	4-177
###	3SK134	NEC	UHF RF	MOS	N	DE	15	DS	25m	200m	4-177
###	3SK134A	NEC	UHF Tuner	MOS	N	DE	18	DSX	25m	200m	4-177

5000种场效应管参数

更多彩电维修资料请到《彩电维修资料网》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
###	3SK135	NEC	UHF RF	MOS	N	18	DS	25m	200m	4-177
###	3SK135A	NEC	UHF TV Tuner	MOS	N	DE 20	DS	25m	200m	4-177
###	3SK136	日立	VHF TV Tuner	MOS	N	DE 20	DS	35m	150m	4-178
###	3SK137	日立	UHF TV Tuner	MOS	N	DE 15	DS	35m	150m	4-178
###	3SK137V	日立	VHF TV Tuner	MOS	N	DE 15	DS	35m	150m	4-199A
###	3SK138	日立	UHF TV Tuner	MOS	N	DE 15	DS	35m	150m	4-178
###	3SK139	松下	U/VHF LN A	MOS	N	DE 15	DS	30m	150m	4-147B
###	3SK140	东芝	UHF RF/MIX	GaAs	N	D 10	DS	50m	150m	4-176
###	3SK141	松下	UHF RF	GaAs	N	D 13	DS	50m	200m	4-147B
###	3SK142	松下	UHF LN A	MOS	N	DE 15	DS	30m	250m	4-139C
###	3SK143	松下	UHF LN A	MOS	N	DE 15	DS	30m	200m	4-147B
###	3SK144	松下	VHF LN A	MOS	N	DE 15	DS	30m	150m	4-147B
###	3SK145	东芝	UHF RF/MIX	MOS	N	DE 13.5	DS	30m	200m	4-125A
###	3SK146	东芝	UHF RF/MIX	MOS	N	DE 13.5	DS	30m	150m	4-176
###	3SK150	东芝	UHF RF/MIX	MOS	N	DE 15	DS	30m	200m	4-125A
###	3SK151	东芝	VHF RF/MIX	MOS	N	DE 15	DS	30m	150m	4-176
###	3SK152	东芝	V/UHF RF	MOS	N	DE 13.5	DS	30m	200m	4-125A
###	3SK153	东芝	V/UHF RF	MOS	N	DE 13.5	DS	30m	150m	4-176
###	3SK154	日立	VHF TV Tuner	MOS	N	DE 15	DSX	35m	150m	4-199A
###	3SK156	日立	UHF TV Tuner	MOS	N	DE 12	DS	35m	200m	4-175A
###	3SK159	东芝	V/UHF RF	MOS	N	DE 13.5	DS	30m	200m	4-125A
###	3SK160	东芝	V/UHF RF	MOS	N	DE 13.5	DS	30m	150m	4-176
###	3SK162	日立	UHF TV Tuner	MOS	N	DE 12	DS	35m	150m	4-178
###	3SK164		UHF RF/MIX/OSC	GaAs	N	D 12	DS	55m	150m	4-198
###	3SK165		UHF RF/MIX/OSC	GaAs	N	D 8	DS	80m	150m	4-198
###	3SK166		UHF RF/OSC	GaAs	N	D 8	DS	80m	150m	4-198
###	3SK168	三洋	UHF RF/MIX	GaAs	N	D 12	DS	55m	250m	4-244
###	3SK169	松下	VHF LN RF/MIX	MOS	N	DE 15	DS	30m	150m	4-147B
###	3SK171	日立	UHF TV Tuner	MOS	N	DE 12	DS	80m	150m	4-199A
###	3SK173	NEC	CATV TV Tuner	MOS	N	DE 18	DSX	25m	200m	4-114
###	3SK174	NEC	UHF TV Tuner	GaAs/M	N	D 13	DSX	40m	200m	4-114
###	3SK176	NEC	CATV TV Tuner	MOS	N	DE 18	DSX	25m	200m	4-177
###	3SK176A	NEC	CATV TV Tuner	MOS	N	DE 18	DSX	25m	200m	4-177
###	3SK177	NEC	UHF TV Tuner	GaAs/M	N	D 13	DSX	40m	200m	4-177
###	3SK179	NEC	VHF RF/MIX	MOS	N	DE 20	DS	25m	200m	4-177
###	3SK180	三洋	FM/VHF Tuner	MOS	N	DE 15	DS	30m	200m	4-232
###	3SK181	三洋	FM/VHF Tuner	MOS	N	E 15	DS	30m	200m	4-232
###	3SK182	日立	UHF TV Tuner	MOS	N	DE 20	DS	50m	150m	4-199A
###	3SK183	松下	UHF LN A	GaAs/M	N	D 13	DS	50m	350m	4-139B
###	3SK184	松下	UHF LN A	GaAs/M	N	D 13	DS	50m	200m	4-147B
###	3SK186	日立	UHF TV Tuner	MOS	N	DE 15	DS	35m	150m	4-199A
###	3SK187	松下	RF LN A	SB	N	DE -20	GDS	130m	200m	4-212
###	3SK188	日立	VHF TV Tuner	MOS	N	DE 22	DS	35m	150m	4-199A
###	3SK189	三洋	UHF RF/MIX	GaAs	N	D 13	DS	50m	200m	4-232
###	3SK191	日立	UHF TV Tuner	GaAs/M	N	D 12	DS	80m	150m	4-178
###	3SK192	松下	U/VHF LN A	MOS	N	DE 15	DS	30m	150m	4-212
###	3SK193	松下	U/VHF LN A	MOS	N	DE 15	DS	30m	150m	4-212
###	3SK194	日立	V/UHF TV Tuner	MOS	N	DE 15	DS	35m	150m	4-199A
###	3SK195	东芝	VHF RF	MOS	N	DE 13.5	DS	30m	150m	4-176
###	3SK196	日立	V/UHF TV Tuner	MOS	N	DE 12	DSX	35m	150m	4-199D
###	3SK197	日立	VHF TV Tuner	MOS	N	DE 12	DSX	35m	150m	4-199D
###	3SK198	东芝	UHF RF	MOS	N	DE 13.5	DS	30m	200m	4-125A
###	3SK199	东芝	UHF RF	MOS	N	DE 13.5	DS	30m	150m	4-176
###	3SK200	松下	UHF RF	MOS	N	DE 15	DS	30m	150m	4-212
###	3SK201	松下	U/VHF RF	GaAs/M	N	D 13	DS	50m	200m	4-212
###	3SK202	松下	VHF LN RF	MOS	N	DE 15	DS	30m	250m	4-240
###	3SK203	NEC	UHF RF	GaAs/M	N	D 10	DSX	60m	200m	4-114
###	3SK204	NEC	UHF RF	GaAs/M	N	D 10	DSX	60m	200m	4-177
###	3SK205	NEC	UHF RF	GaAs/M	N	D 10	DSX	80m	200m	4-114
###	3SK206	NEC	UHF RF	GaAs/M	N	D 10	DSX	80m	200m	4-177
###	3SK207	东芝	UHF RF	MOS	N	DE 13.5	DS	30m	150m	4-176

5000种场效应管参数

更多彩电维修资料请到《[彩电维修资料网](http://www.tv160.net)》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道	方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
###	3SK212	罗姆	UHF TV Tuner	GaAs/M	N	D	10	DS	50m	150m	4-259
###	3SK217	日立	UHF TV Tuner	MOS	N	DE	12	DS	35m	100m	4-CMPAK-4
###	3SK219	松下	VHF RF	MOS	N	DE	15	DS	30m	150m	4-147B
###	3SK220	松下	U/VHF RF	MOS	N	DE	15	DS	30m	150m	4-147B
###	3SK222	NEC	VHF RF	MOS	N		18	DSX	25m	200m	4-177
###	3SK223	NEC	CATV Tuner	MOS	N		18	DSX	25m	200m	4-177
###	3SK224	NEC	CATV TV Tuner	MOS	N	D	18	DSX	25m	200m	4-177
###	3SK225	东芝	V/UHF TV Tuner	MOS	N	DE	13.5	DS	30m	150m	4-176
###	3SK226	东芝	VHF TV/FM Tuner	MOS	N	DE	13.5	DS	30m	150m	4-176
###	3SK227	松下	UHF RF	MOS	N	DE	15	DS	30m	150m	4-147B
###	3SK228	日立	RF LN A	GaAs	N						4-199A
###	3SK229	日立	RF LN A	GaAs	N						4-199A
###	3SK230	NEC	VHF /CATV Tuner	MOS	N	DE	18	DSX	25m	200m	4-177
###	3SK231	NEC	UHF Tuner	MOS	N	DE	18	DSX	25m	200m	4-177
###	3SK233	日立	UHF TV Tuner	MOS	N	DE	12	DS	35m	150m	4-199D
###	3SK234	日立	VHF TV Tuner	MOS	N	DE	12	DS	35m	150m	4-199D
###	3SK235	日立	U/VHF TV Tuner	MOS	N	DE	12	DS	35m	150m	4-199D
###	3SK240	东芝	UHF RF/MIX	GaAs/M	N	D	-9	GDO	1m	150m	4-176
###	3SK241	松下	U/VHF LN A	GaAs/M	N	D	13	DS	50m	200m	4-212
###	3SK242	NEC	VHF TV Tuner	MOS	N	D	20	DSX	25m	130m	4-352
###	3SK243	NEC	CATV Tuner	MOS	N	DE	18	DSX	25m	130m	4-352
###	3SK244	NEC	UHF TV Tuner	MOS	N	DE	18	DSX	25m	130m	4-352
###	3SK245	NEC	UHF TV Tuner	MOS	N	DE	18	DSX	25m	130m	4-352
###	3SK246	NEC	FM/VHF TV Tuner	MOS	N	DE	18	DSX	25m	130m	4-352
###	3SK247	松下	VHF A	MOS	N	DE	15	DS	30m	150m	4-147B
###	3SK252	NEC	CATV Tuner	MOS	N	DE	18	DSX	25m	200m	4-178
###	3SK253	NEC	UHF TV Tuner	MOS	N	DE	18	DSX	25m	200m	4-178
###	3SK255	NEC	UHF TV Tuner	MOS	N	DE	18	DSX	25m	130m	4-352
###	3SK268	松下	VHF A	MOS	N	DE	15	DS	30m	150m	4-385
###	3SK269	松下	UHF A	MOS	N	D	15	DS	30m	150m	4-385
###	3SK270	松下	VHF/UHF A	MOS	N	D	15	DS	30m	150m	4-385
###	3SK271	松下	UHF A	MOS	N	D	15	DS	30m	150m	4-385
###	3SK272	松下	VHF/UHF A	GaAs/M	N	D	13	DS	50m	150m	4-385
###	3SK273	松下	VHF/UHF A	GaAs/M	N	D	13	DS	50m	200m	4-147B
###	3SK11(H)	日立	A	MOS	N						4-26
###	3SK12(H)	日立	Chop	MOS	N						4-26
###	3SK13(H)	日立	DC	MOS	N						4-26
###	3SK14	NEC	DC, Chop	MOS	N	DE	20	DSX	10m	100m	4-23
###	3SK15	三菱	DC	MOS	N	DE	25	DSX	10m	100m	4-24
###	3SK15A	三菱	DC	MOS	N	DE	25	DSX	10m	100m	4-24
###	3SK16	三菱	Chop, SW	MOS	N	DE	25	DSX	10m	100m	4-24
###	3SK17	三菱	LF A	MOS	N	DE	25	DSX	10m	100m	4-24
###	3SK18	三菱	Chop, SW	MOS	N	DE	15	DSX	10m	100m	4-25
###	3SK19	三菱	VHF RF	MOS	N	DE	15	DSX	10m	100m	4-25
###	3SK20(H)	日立	DC, LF A	MOS	N	DE	20	DSX	10m	100m	4-26
###	3SK21(H)	日立	Chop	MOS	N	DE	20	DSX	10m	100m	4-26
###	3SK22	东芝	FM/VHF RF	J	N	D	-18	GDO	10m	200m	4-27
###	3SK23	东芝		J	N	D	-15	GDO	10m	200m	4-27
###	3SK24	松下		MOS	N						4-39
###	3SK25	松下		MOS	N						4-39
###	3SK28	东芝	VTR, VHF RF	J	N	D	-18	GDS	10m	200m	4-27
###	3SK29	NEC	LF A	MOS	N	DE	20	DSX	10m	80m	4-23
###	3SK30	日立	FM/AM RF/MIX	MOS	N	D			10m	200m	4-29
###	3SK30A	日立	FM/AM RF/MIX	J	N	D			10m	200m	4-29
###	3SK33	NEC	FM/VHF RF	J	N	DE	25	DSX	20m	250m	4-30
###	3SK38	东芝	Chop	MOS	N	E	20	DSS	10m	200m	4-31
###	3SK38A	东芝	Chop	MOS	N	E	20	DSS	10m	200m	4-31
###	3SK71	NEC	C-MIC	MOS	N	D	20	DSX	5m	150m	4-112
###	3SK163		HS A-SW	MOS	N		15	DSX	100m	150m	4-374
###	3SK248	三洋		MOS	N	E	10	DSS	100m	200m	4-245
###	2M150F-050	富士电机		MOS	N	E	500	DSS	50	400	4-328

5000种场效应管参数

更多彩电维修资料请到《[彩电维修资料网](http://www.tv160.net)》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道	方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
###	2M150S-050	富士电机		MOS	N	E	500	DSS	50	400	4-328
###	2N4392	NEC	SW, Chop	J	N	D	-40	GDO	50m	300m	4-73
###	2N4393	NEC	SW, Chop	J	N	D	-40	GDO	50m	300m	4-73
###	3SJ11	NEC	SW	MOS	P	E	-30	DSS	-10m	100m	4-23
###	3SJ11A	NEC	SW, DC	MOS	P	E	-30	DSS	-50m	225m	4-23
###	4AJ11	日立	HS PSW	MOS	N	E	-60	DSS	-8	28	4-382B
###	4AK15	日立	Motor-D	MOS	N	E	60	DSS	8	28	4-297A
###	4AK16	日立	Motor-D	MOS	N	E	60	DSS	5	28	4-297A
###	4AK17	日立	Motor-D	MOS	N	E	60	DSS	10	28	4-297A
###	4AK18	日立	Motor-D	MOS	N	E	60	DSS	2.5	28	4-297A
###	4AK19	日立	HS PSW	MOS	N	E	120	DSS	5	28	4-297A
###	4AK20	日立	Motor-D	MOS	N	E	100	DSS	5	28	4-297A
###	4AK21	日立	Motor-D	MOS	N	E	100	DSS	8	28	4-297A
###	4AK22	日立	Motor-D	MOS	N	E	120	DSS	3	28	4-297A
###	4AK23	日立	Motor-D	MOS	N	E	100	DSS	5	4	4-364A
###	4AK25	日立	Motor-D	MOS	N	E	60	DSS	1.5	24	4-297A
###	4AK26	日立	HS PSW	MOS	N	E	60	DSS	10	28	4-382A
###	4AK27	日立	HS PSW	MOS	N	E	60	DSS	5	28	4-297A
###	4AM11	日立	H-Bridge Motor-D	MOS	*	E	±60	DSS	±5	28	4-297B
###	4AM12	日立	H-Bridge Motor-D	MOS	*	E	±60	DSS	±8	28	4-297B
###	4AM13	日立	H-Bridge Motor-D	MOS	*	E	±60	DSS	±3	28	4-297B
###	4AM14	日立	H-Bridge Motor-D	MOS	*	E	±60	DSS	±8	32	4-364B
###	4AM15	日立	H-Bridge Motor-D	MOS	*	E	±200	DSS	±4	32	4-364B
###	4AM16	日立	HS PSW	MOS	*	E	±60	DSS	±8	28	4-382C
###	4AM17	日立	HS PSW	MOS	*	E	±60	DSS	±8	28	4-382C
###	6AM11	日立	H-Bridge, Motor	MOS	*	E	±60	DSS	±5	36	4-297B
###	6AM12	日立	H-Bridge, Motor	MOS	*	E	±60	DSS	±7	42	4-364C
###	6AM13	日立	H-Bridge Motor-D	MOS	*	E	±60	DSS	±10	42	4-364C
###	CXD7500M		电压制御 VR	MOS	P		-20	DS	±15m	150m	4-273
###	CXD7501M		电压制御VR	MOS	P		-20	DS	±15m	150m	4-273
###	FC11	三洋	LF A, Diff	J	N	D	40	DSX	10m	300m	4-284
###	FC13	三洋	LF A, Diff, A-SW	J	N	D	30	DSX	10m	200m	4-380
###	FHC30FA/LG	富士通	C-Band LN A	GaAsHE	N	D	3.5	DS		290m	4-224/263
###	FHC31FA/LG	富士通	C-Band LN A	GaAsHE	N	D	3.5	DS		290m	4-224/263
###	FHR01FH	富士通	K-Band LN A	GaAsHE	N	D	3.5	DS		180m	4-223
###	FHR02FH	富士通	Ku/K-Band LN A	GaAsHE	N	D	3.5	DS		180m	4-223
###	FHR02X	富士通	Ku/K-Band LN A	GaAsHE	N	D	3.5	DS		180m	
###	FHR10X	富士通	Ku/K-Band LN A	GaAsHE	N	D	3.5	DS		100m	
###	FHX04FA/LG	富士通	X-Band LN A	GaAsHE	N	D	3.5	DS		180m	4-224/263
###	FHX04X	富士通	X-Band LN A	GaAsHE	N	D	3.5	DS		180m	
###	FHX05FA/LG	富士通	X-Band LN A	GaAsHE	N	D	3.5	DS		180m	4-224/263
###	FHX05X	富士通	X-Band LN A	GaAsHE	N	D	3.5	DS		180m	
###	FHX06FA/LG	富士通	X-Band LN A	GaAsHE	N	D	3.5	DS		180m	4-224/263
###	FHX06X	富士通	X-Band LN A	GaAsHE	N	D	3.5	DS		180m	
###	FHX15FA/LG	富士通	X-Band LN A	GaAsHE	N	D	3.5	DS		180m	4-224/263
###	FHX15X	富士通	X-Band LN A	GaAsHE	N	D	3.5	DS		180m	
###	FHX16FA/LG	富士通	X-Band LN A	GaAsHE	N	D	3.5	DS		180m	4-224/263
###	FHX16X	富士通	X-Band LN A	GaAsHE	N	D	3.5	DS		180m	
###	FHX35LG	富士通	X-Band LN A	GaAsHE	N	D	4	DS		290m	4-263
###	FHX35X	富士通	X-Band LN A	GaAsHE	N	D	4	DS		290m	
###	FLC08ME	富士通	C-Band, PA	GaAs	N	D	15	DS		3	4-145
###	FLC15ME	富士通	C-Band, PA	GaAs	N	D	15	DS		6	4-145
###	FLC30ME	富士通	C-Band, PA	GaAs	N	D	15	DS		11.5	4-145
###	FLC053WG	富士通	C-Band, PA	GaAs	N	D	15	DS		3.75	4-202
###	FLC081WF	富士通	C-Band, PA	GaAs	N	D	15	DS		3.3	4-143
###	FLC081XP	富士通	C-Band, PA	GaAs	N	D	15	DS		4.16	
###	FLC091WF	富士通	C-Band, PA	GaAs	N	D	15	DS		4.16	4-130
###	FLC103WG	富士通	C-Band, PA	GaAs	N	D	15	DS		7.5	4-202
###	FLC151WF	富士通	C-Band, PA	GaAs	N	D	15	DS		6.5	4-143
###	FLC151XP	富士通	C-Band, PA	GaAs	N	D	15	DS		8.3	
###	FLC161WF	富士通	C-Band, PA	GaAs	N	D	15	DS		7.5	4-130

5000种场效应管参数

更多彩电维修资料请到《彩电维修资料网》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道	方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
###	FLC253MH-6	富士通	C-Band, PA	GaAs	N	D	15	DS		15	4-200
###	FLC253MH-8	富士通	C-Band, PA	GaAs	N	D	15	DS		15	4-200
###	FLC301MG-4	富士通	C-Band, PA	GaAs	N	D	15	DS		15	4-144
###	FLC301MG-6	富士通	C-Band, PA	GaAs	N	D	15	DS		15	4-144
###	FLC301MG-8	富士通	C-Band, PA	GaAs	N	D	15	DS		15	4-144
###	FLC311MG-4	富士通	C-Band, PA	GaAs	N	D	15	DS		15	4-144
###	FLK012WF	富士通	Ku-Band PA	GaAs	N	D	15	DS		1.15	4-130
###	FLK012XP	富士通	Ku-Band, PA	GaAs	N	D	15	DS		1.15	
###	FLK022WG	富士通	Ku-Band, PA	GaAs	N	D	15	DS		1.875	4-202
###	FLK022XP/X	富士通	Ku-Band, PA	GaAs	N	D	15	DS		1.88	
###	FLK052WG	富士通	Ku-Band, PA	GaAs	N	D	15	DS		3.75	4-202
###	FLK052XV	富士通	Ku-Band, PA	GaAs	N	D	15	DS		3.75	
###	FLK102MH-1	富士通	Ku-Band, PA	GaAs	N	D	15	DS		7.5	4-200
###	FLK102XV	富士通	Ku-Band, PA	GaAs	N	D	15	DS		7.5	
###	FLK202MH-1	富士通	Ku-Band, PA	GaAs	N	D	15	DS		12.5	4-200
###	FLK202XV	富士通	Ku-Band, PA	GaAs	N	D	15	DS		12.5	
###	FLL10ME	富士通	L-Band PA	GaAs/SbN	N	D	15	DS		3	4-145
###	FLL17ME	富士通	L-Band PA	GaAs/SbN	N	D	15	DS		6	4-145
###	FLL35ME	富士通	L-Band PA	GaAs/SbN	N	D	15	DS		11.5	4-145
###	FLL50MK	富士通	L-Band PA	GaAs/SbN	N	D	15	DS		18.5	4-201
###	FLL100MK	富士通	L-Band PA	GaAs/SbN	N	D	15	DS		30	4-201
###	FLL101ME	富士通	L-Band PA	GaAs/SbN	N	D	15	DS		4.16	4-145
###	FLL120MK	富士通	L-Band PA	GaAs	N	D	15	DS		37.5	4-201
###	FLL171ME	富士通	L-Band PA	GaAs/SbN	N	D	15	DS		7.5	4-145
###	FLL2001B-1	富士通	L-Band PA	GaAs/SbN	N	D	15	DS		83.3	4-146
###	FLL2001B-2	富士通	L-Band PA	GaAs/SbN	N	D	15	DS		83.3	4-146
###	FLL2001B-3	富士通	L-Band PA	GaAs	N	D	15	DS		83.3	4-146
###	FLL3001L-1	富士通	L-Band PA	GaAs	N	D	15	DS		100	4-378
###	FLL3001L-2	富士通	L-Band PA	GaAs	N	D	15	DS		100	4-378
###	FLL351ME	富士通	L-Band PA	GaAs	N	D	15	DS		15	4-145
###	FLM0910-2	富士通	X-Ku-Band PA	GaAs	N	D	15	DS		17.5	4-203
###	FLM0910-4C	富士通	X-Ku-Band PA	GaAs	N	D	15	DS		25	4-203
###	FLM0910-8C	富士通	X-Ku-Band PA	GaAs	N	D	15	DS		42.8	4-146
###	FLM1011-12	富士通	X-Band PA	GaAs	N	D	15	DS		57	4-146
###	FLM1011-2	富士通	X-Ku-Band PA	GaAs	N	D	15	DS		17.5	4-203
###	FLM1011-4C	富士通	X-Ku-Band PA	GaAs	N	D	15	DS		25	4-203
###	FLM1011-4D	富士通	X-Band PA	GaAs	N	D	15	DS		25	4-203
###	FLM1011-8C	富士通	X-Ku-Band PA	GaAs	N	D	15	DS		42.8	4-146
###	FLM1011-8D	富士通	X-Band PA	GaAs	N	D	15	DS		42.8	4-146
###	FLM1112-4C	富士通	X-Ku-Band PA	GaAs	N	D	15	DS		25	4-203
###	FLM1213-4C	富士通	X-Ku-Band PA	GaAs	N	D	15	DS		25	4-203
###	FLM1213-4D	富士通	X-Band PA	GaAs	N	D	15	DS		25	4-203
###	FLM1213-8C	富士通	X-Ku-Band PA	GaAs	N	D	15	DS		42.8	4-203
###	FLM1213-8D	富士通	X-Band PA	GaAs	N	D	15	DS		42.8	4-203
###	FLM1414-2	富士通	X-Ku-Band PA	GaAs	N	D	15	DS		17.5	4-203
###	FLM1414-4C	富士通	X-Ku-Band PA	GaAs	N	D	15	DS		25	4-203
###	FLM1414-5	富士通	X-Ku-Band PA	GaAs	N	D	15	DS		33.3	4-203
###	FLM1414-8C	富士通	X-Ku-Band PA	GaAs	N	D	15	DS		42.8	4-203
###	FLM3742-12	富士通	C-Band PA	GaAs	N	D	15	DS		57	4-146
###	FLM3742-12	富士通	C-Band PA	GaAs	N	D	15	DS		57.6	4-379
###	FLM3742-14	富士通	C-Band PA	GaAs	N	D	15	DS		83.3	4-146
###	FLM3742-18	富士通	C-Band PA	GaAs	N	D	15	DS		83.3	4-379
###	FLM3742-25	富士通	C-Band PA	GaAs	N	D	15	DS		100	4-309
###	FLM3742-25	富士通	C-Band PA	GaAs	N	D	15	DS		93.7	4-379
###	FLM3742-4B	富士通	C-Band PA	GaAs	N	D	15	DS		25	4-146
###	FLM3742-8B	富士通	C-Band PA	GaAs	N	D	15	DS		42.8	4-146
###	FLM4450-12	富士通	C-Band PA	GaAs	N	D	15	DS		57	4-146
###	FLM4450-12	富士通	C-Band PA	GaAs	N	D	15	DS		57.6	4-379
###	FLM4450-14	富士通	C-Band PA	GaAs	N	D	15	DS		83.3	4-146
###	FLM4450-18	富士通	C-Band PA	GaAs	N	D	15	DS		83.3	4-379
###	FLM4450-25	富士通	C-Band PA	GaAs	N	D	15	DS		100	4-309

5000种场效应管参数

更多彩电维修资料请到《[彩电维修资料网](http://www.tv160.net)》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道	方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
###	FLM4450-25	富士通	C-Band PA	GaAs	N	D	15	DS		93.7	4-379
###	FLM4450-4B	富士通	C-Band PA	GaAs	N	D	15	DS		25	4-146
###	FLM4450-8B	富士通	C-Band PA	GaAs	N	D	15	DS		42.8	4-146
###	FLM5359-14	富士通	C-Band PA	GaAs	N	D	15	DS		83.3	4-146
###	FLM5359-4B	富士通	C-Band PA	GaAs	N	D	15	DS		25	4-146
###	FLM5359-8B	富士通	C-Band PA	GaAs	N	D	15	DS		42.8	4-146
###	FLM5964-12	富士通	C-Band PA	GaAs	N	D	15	DS		57	4-146
###	FLM5964-12	富士通	C-Band PA	GaAs	N	D	15	DS		57.6	4-379
###	FLM5964-14	富士通	C-Band PA	GaAs	N	D	15	DS		83.3	4-146
###	FLM5964-18	富士通	C-Band PA	GaAs	N	D	15	DS		85.3	4-379
###	FLM5964-25	富士通	C-Band PA	GaAs	N	D	15	DS		100	4-309
###	FLM5964-25	富士通	C-Band PA	GaAs	N	D	15	DS		93.7	4-379
###	FLM5964-4C	富士通	C-Band PA	GaAs	N	D	15	DS		25	4-146
###	FLM5964-6D	富士通	C-Band PA	GaAs	N	D	15	DS		31	4-146
###	FLM5964-8C	富士通	C-Band PA	GaAs	N	D	15	DS		42.8	4-146
###	FLM6472-12	富士通	C-Band PA	GaAs	N	D	15	DS		57	4-146
###	FLM6472-12	富士通	C-Band PA	GaAs	N	D	15	DS		57.6	4-379
###	FLM6472-14	富士通	C-Band PA	GaAs	N	D	15	DS		83.3	4-146
###	FLM6472-18	富士通	C-Band PA	GaAs	N	D	15	DS		83.3	4-379
###	FLM6472-25	富士通	C-Band PA	GaAs	N	D	15	DS		100	4-309
###	FLM6472-25	富士通	C-Band PA	GaAs	N	D	15	DS		93.7	4-379
###	FLM6472-4C	富士通	C-Band PA	GaAs	N	D	15	DS		25	4-146
###	FLM6472-6D	富士通	C-Band PA	GaAs	N	D	15	DS		31	4-146
###	FLM6472-8C	富士通	C-Band PA	GaAs	N	D	15	DS		42.8	4-146
###	FLM7177-12	富士通	C-Band PA	GaAs	N	D	15	DS		57	4-146
###	FLM7177-12	富士通	C-Band PA	GaAs	N	D	15	DS		57.6	4-379
###	FLM7177-4C	富士通	C-Band PA	GaAs	N	D	15	DS		25	4-146
###	FLM7177-8C	富士通	C-Band PA	GaAs	N	D	15	DS		42.8	4-146
###	FLM7785-12	富士通	C-Band PA	GaAs	N	D	15	DS		57	4-146
###	FLM7785-12	富士通	C-Band PA	GaAs	N	D	15	DS		57.6	4-379
###	FLM7785-4C	富士通	C-Band PA	GaAs	N	D	15	DS		25	4-146
###	FLM7785-8C	富士通	C-Band PA	GaAs	N	D	15	DS		42.8	4-146
###	FLM8596-4C	富士通	C-Band PA	GaAs	N	D	15	DS		25	4-203
###	FLM8596-8C	富士通	C-Band PA	GaAs	N	D	15	DS		42.8	4-146
###	FLR014FH	富士通	K-Band PA	GaAs	N	D	15	DS		1	4-223
###	FLR014XP	富士通	K-Band PA	GaAs	N	D	15	DS		1.15	
###	FLR016FH	富士通	K-Band PA	GaAs	N	D	15	DS		1.15	4-223
###	FLR016XP/X	富士通	K-Band PA	GaAs	N	D	15	DS			
###	FLR024FH	富士通	K-Band PA	GaAs	N	D	15	DS		1.25	4-223
###	FLR024XP/X	富士通	K-Band PA	GaAs	N	D	15	DS		1.88	
###	FLR026FH	富士通	K-Band PA	GaAs	N	D	15	DS		1.88	4-223
###	FLR026XP/X	富士通	K-Band PA	GaAs	N	D	12	DS			
###	FLR054XV	富士通	K-Band PA	GaAs	N	D	15	DS		3.75	
###	FLR056XV	富士通	K-Band PA	GaAs	N	D	12	DS			
###	FLR104XV	富士通	K-Band PA	GaAs	N	D	15	DS		7.5	
###	FLR106XV	富士通	K-Band PA	GaAs	N	D	12	DS		7.5	
###	FLS02W	富士通	S-Band PA	GaAs/SbN	N	D	12	DS		1.5	4-93
###	FLS09	富士通	S-Band PA	GaAs/SbN	N	D	15	DS		3	4-94
###	FLS09ME	富士通	S-Band PA	GaAs	N	D	15	DS		3	4-145
###	FLS16	富士通	S-Band PA	GaAs	N	D	15	DS		6	4-94
###	FLS16ME	富士通	S-Band PA	GaAs	N	D	15	DS		6	4-145
###	FLS31	富士通	S-Band PA	GaAs	N	D	15	DS		11.5	4-94
###	FLS31ME	富士通	S-Band PA	GaAs	N	D	15	DS		11.5	4-145
###	FLS50	富士通	S-Band PA	GaAs/SbN	N	D	15	DS		15	4-94
###	FLS50ME	富士通	S-Band PA	GaAs	N	D	15	DS		15	4-145
###	FLX03MB	富士通	X-Band PA/OSC	GaAs	N	D	12	DS		2.5	4-95
###	FLX06MB	富士通	X-Band PA/OSC	GaAs	N	D	12	DS		5	4-95
###	FLX12MB	富士通	X-Band PA/OSC	GaAs	N	D	12	DS		8.8	4-95
###	FLX30MB	富士通	X-Band PA/OSC	GaAs	N	D	12	DS		15	4-95
###	FLX102MH-1	富士通	X-Band PA	GaAs	N	D	15	DS		7.5	4-200
###	FLX202MH-1	富士通	X-Band PA	GaAs	N	D	15	DS		12.5	4-200

5000种场效应管参数

更多彩电维修资料请到《[彩电视维修资料网](http://www.tv160.net)》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道	方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
###	FP401	三洋	HS SW	MOS	N	E	250	DSS	1.6	2/CH	4-383
###	FS2TM-16	三菱	HS PSW	MOS	N	E	800	DSS	2	30	4-215
###	FS2TM-18	三菱	HS PSW	MOS	N	E	900	DSS	2	30	4-215
###	FS2UM-16	三菱	HS PSW	MOS	N	E	800	DSS	2	75	4-267
###	FS2UM-18	三菱	HS PSW	MOS	N	E	900	DSS	2	75	4-267
###	FS2VS-16	三菱	HS PSW	MOS	N	E	800	DSS	2	75	4-330
###	FS2VS-18	三菱	HS PSW	MOS	N	E	900	DSS	2	75	4-330
###	FS2UM-12	三菱	HS PSW	MOS	N	E	600	DSS	2	60	4-267
###	FS2VS-12	三菱	HS PSW	MOS	N	E	600	DSS	2	60	4-330
###	FS2TM-12	三菱	HS PSW	MOS	N	E	600	DSS	2	30	4-215
###	FS3TM-14	三菱	HS PSW	MOS	N	E	700	DSS	3	30	4-215
###	FS3TM-16	三菱	HS PSW	MOS	N	E	800	DSS	3	35	4-215
###	FS3TM-18	三菱	HS PSW	MOS	N	E	900	DSS	3	35	4-215
###	FS3UM-14	三菱	HS PSW	MOS	N	E	700	DSS	3	75	4-267
###	FS3UM-16	三菱	HS PSW	MOS	N	E	800	DSS	3	100	4-267
###	FS3UM-18	三菱	HS PSW	MOS	N	E	900	DSS	3	100	4-267
###	FS3VS-14	三菱	HS PSW	MOS	N	E	700	DSS	3	75	4-330
###	FS3VS-16	三菱	HS PSW	MOS	N	E	800	DSS	3	100	4-330
###	FS3VS-18	三菱	HS PSW	MOS	N	E	900	DSS	3	100	4-330
###	FS3UM-9	三菱	HS PSW	MOS	N	E	450	DSS	3	60	4-267
###	FS3VS-9	三菱	HS PSW	MOS	N	E	450	DSS	3	60	4-330
###	FS3TM-9	三菱	HS PSW	MOS	N	E	450	DSS	3	30	4-215
###	FS3UM-10	三菱	HS PSW	MOS	N	E	500	DSS	3	60	4-267
###	FS3VS-10	三菱	HS PSW	MOS	N	E	500	DSS	3	60	4-330
###	FS3TM-10	三菱	HS PSW	MOS	N	E	500	DSS	3	30	4-215
###	FS4UM-12	三菱	HS PSW	MOS	N	E	600	DSS	4	90	4-267
###	FS4VS-12	三菱	HS PSW	MOS	N	E	600	DSS	4	90	4-330
###	FS4TM-12	三菱	HS PSW	MOS	N	E	600	DSS	4	35	4-215
###	FS5TM-14	三菱	HS PSW	MOS	N	E	700	DSS	5	35	4-215
###	FS5TM-16	三菱	HS PSW	MOS	N	E	800	DSS	5	35	4-215
###	FS5TM-18	三菱	HS PSW	MOS	N	E	900	DSS	5	35	4-215
###	FS5UM-14	三菱	HS PSW	MOS	N	E	700	DSS	5	100	4-267
###	FS5UM-16	三菱	HS PSW	MOS	N	E	800	DSS	5	125	4-267
###	FS5UM-18	三菱	HS PSW	MOS	N	E	900	DSS	5	125	4-267
###	FS5VS-14	三菱	HS PSW	MOS	N	E	700	DSS	5	100	4-330
###	FS5VS-16	三菱	HS PSW	MOS	N	E	800	DSS	5	125	4-330
###	FS5VS-18	三菱	HS PSW	MOS	N	E	900	DSS	5	125	4-330
###	FS5UM-5	三菱	HS PSW	MOS	N	E	250	DSS	5	60	4-267
###	FS5VS-5	三菱	HS PSW	MOS	N	E	250	DSS	5	60	4-330
###	FS5TM-5	三菱	HS PSW	MOS	N	E	250	DSS	5	30	4-215
###	FS5UM-6	三菱	HS PSW	MOS	N	E	300	DSS	5	60	4-267
###	FS5VS-6	三菱	HS PSW	MOS	N	E	300	DSS	5	60	4-330
###	FS5TM-6	三菱	HS PSW	MOS	N	E	300	DSS	5	30	4-215
###	FS5UM-9	三菱	HS PSW	MOS	N	E	450	DSS	5	90	4-267
###	FS5VS-9	三菱	HS PSW	MOS	N	E	450	DSS	5	90	4-330
###	FS5TM-9	三菱	HS PSW	MOS	N	E	450	DSS	5	35	4-215
###	FS5UM-10	三菱	HS PSW	MOS	N	E	500	DSS	5	90	4-267
###	FS5VS-10	三菱	HS PSW	MOS	N	E	500	DSS	5	90	4-330
###	FS5TM-10	三菱	HS PSW	MOS	N	E	500	DSS	5	35	4-215
###	FS7TM-14	三菱	HS PSW	MOS	N	E	700	DSS	7	35	4-215
###	FS7TM-16	三菱	HS PSW	MOS	N	E	800	DSS	7	45	4-215
###	FS7TM-18	三菱	HS PSW	MOS	N	E	900	DSS	7	45	4-215
###	FS7UM-14	三菱	HS PSW	MOS	N	E	700	DSS	7	125	4-267
###	FS7UM-16	三菱	HS PSW	MOS	N	E	800	DSS	7	175	4-267
###	FS7UM-18	三菱	HS PSW	MOS	N	E	900	DSS	7	175	4-267
###	FS7VS-14	三菱	HS PSW	MOS	N	E	700	DSS	7	125	4-330
###	FS7VS-16	三菱	HS PSW	MOS	N	E	800	DSS	7	175	4-330
###	FS7VS-18	三菱	HS PSW	MOS	N	E	900	DSS	7	175	4-330
###	FS7UM-12	三菱	HS PSW	MOS	N	E	600	DSS	7	125	4-267
###	FS7VS-12	三菱	HS PSW	MOS	N	E	600	DSS	7	125	4-330
###	FS7TM-12	三菱	HS PSW	MOS	N	E	600	DSS	7	35	4-215

5000种场效应管参数

更多彩电维修资料请到《[彩电维修资料网](http://www.tv160.net)》查询吧：<http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道	方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
###	FS7SM-12	三菱	HS PSW	MOS	N	E	600	DSS	7	125	4-250
###	FS10SM-16	三菱	HS PSW	MOS	N	E	800	DSS	10	200	4-250
###	FS10SM-18	三菱	HS PSW	MOS	N	E	900	DSS	10	250	4-250
###	FS10TM-14	三菱	HS PSW	MOS	N	E	700	DSS	10	45	4-215
###	FS10UM-14	三菱	HS PSW	MOS	N	E	700	DSS	10	175	4-267
###	FS10VS-14	三菱	HS PSW	MOS	N	E	700	DSS	10	175	4-330
###	FS10UM-5	三菱	HS PSW	MOS	N	E	250	DSS	10	90	4-267
###	FS10VS-5	三菱	HS PSW	MOS	N	E	250	DSS	10	90	4-330
###	FS10TM-5	三菱	HS PSW	MOS	N	E	250	DSS	10	35	4-215
###	FS10UM-6	三菱	HS PSW	MOS	N	E	300	DSS	10	90	4-267
###	FS10VS-6	三菱	HS PSW	MOS	N	E	300	DSS	10	90	4-330
###	FS10TM-6	三菱	HS PSW	MOS	N	E	300	DSS	10	35	4-215
###	FS10UM-9	三菱	HS PSW	MOS	N	E	450	DSS	10	125	4-267
###	FS10VS-9	三菱	HS PSW	MOS	N	E	450	DSS	10	125	4-330
###	FS10TM-9	三菱	HS PSW	MOS	N	E	450	DSS	10	35	4-215
###	FS10SM-9	三菱	HS PSW	MOS	N	E	450	DSS	10	125	4-250
###	FS10UM-10	三菱	HS PSW	MOS	N	E	500	DSS	10	125	4-267
###	FS10VS-10	三菱	HS PSW	MOS	N	E	500	DSS	10	125	4-330
###	FS10TM-10	三菱	HS PSW	MOS	N	E	500	DSS	10	35	4-215
###	FS10SM-10	三菱	HS PSW	MOS	N	E	500	DSS	10	125	4-250
###	FS10UM-12	三菱	HS PSW	MOS	N	E	600	DSS	10	150	4-267
###	FS10VS-12	三菱	HS PSW	MOS	N	E	600	DSS	10	150	4-330
###	FS10TM-12	三菱	HS PSW	MOS	N	E	600	DSS	10	40	4-215
###	FS10SM-12	三菱	HS PSW	MOS	N	E	600	DSS	10	150	4-250
###	FS14SM-14	三菱	HS PSW	MOS	N	E	700	DSS	14	250	4-250
###	FS14SM-16	三菱	HS PSW	MOS	N	E	800	DSS	14	275	4-250
###	FS14SM-18	三菱	HS PSW	MOS	N	E	900	DSS	14	275	4-250
###	FS14UM-9	三菱	HS PSW	MOS	N	E	450	DSS	14	150	4-267
###	FS14VS-9	三菱	HS PSW	MOS	N	E	450	DSS	14	150	4-330
###	FS14TM-9	三菱	HS PSW	MOS	N	E	450	DSS	14	40	4-215
###	FS14SM-9	三菱	HS PSW	MOS	N	E	450	DSS	14	150	4-250
###	FS14UM-10	三菱	HS PSW	MOS	N	E	500	DSS	14	150	4-267
###	FS14VS-10	三菱	HS PSW	MOS	N	E	500	DSS	14	150	4-330
###	FS14TM-10	三菱	HS PSW	MOS	N	E	500	DSS	14	40	4-215
###	FS14SM-10	三菱	HS PSW	MOS	N	E	500	DSS	14	150	4-250
###	FS14SM-12	三菱	HS PSW	MOS	N	E	600	DSS	14	250	4-250
###	FS16UM-5	三菱	HS PSW	MOS	N	E	250	DSS	16	125	4-267
###	FS16VS-5	三菱	HS PSW	MOS	N	E	250	DSS	16	125	4-330
###	FS16TM-5	三菱	HS PSW	MOS	N	E	250	DSS	16	35	4-215
###	FS16SM-5	三菱	HS PSW	MOS	N	E	250	DSS	16	125	4-250
###	FS16UM-6	三菱	HS PSW	MOS	N	E	300	DSS	16	125	4-267
###	FS16VS-6	三菱	HS PSW	MOS	N	E	300	DSS	16	125	4-330
###	FS16TM-6	三菱	HS PSW	MOS	N	E	300	DSS	16	35	4-215
###	FS16SM-6	三菱	HS PSW	MOS	N	E	300	DSS	16	125	4-250
###	FS18SM-14	三菱	HS PSW	MOS	N	E	700	DSS	18	275	4-250
###	FS18SM-9	三菱	HS PSW	MOS	N	E	450	DSS	18	250	4-250
###	FS18SM-10	三菱	HS PSW	MOS	N	E	500	DSS	18	250	4-250
###	FS20UM-5	三菱	HS PSW	MOS	N	E	250	DSS	20	150	4-267
###	FS20VS-5	三菱	HS PSW	MOS	N	E	250	DSS	20	150	4-330
###	FS20TM-5	三菱	HS PSW	MOS	N	E	250	DSS	20	40	4-215
###	FS20SM-5	三菱	HS PSW	MOS	N	E	250	DSS	20	150	4-250
###	FS20UM-6	三菱	HS PSW	MOS	N	E	300	DSS	20	150	4-267
###	FS20VS-6	三菱	HS PSW	MOS	N	E	300	DSS	20	150	4-330
###	FS20TM-6	三菱	HS PSW	MOS	N	E	300	DSS	20	40	4-215
###	FS20SM-6	三菱	HS PSW	MOS	N	E	300	DSS	20	150	4-250
###	FS20SM-12	三菱	HS PSW	MOS	N	E	600	DSS	20	275	4-250
###	FS22SM-9	三菱	HS PSW	MOS	N	E	450	DSS	22	275	4-250
###	FS22SM-10	三菱	HS PSW	MOS	N	E	500	DSS	22	275	4-250
###	FS30SM-5	三菱	HS PSW	MOS	N	E	250	DSS	30	250	4-250
###	FS30SM-6	三菱	HS PSW	MOS	N	E	300	DSS	30	250	4-250
###	FS40SM-5	三菱	HS PSW	MOS	N	E	250	DSS	40	275	4-250

5000种场效应管参数

更多彩电维修资料请到《彩电维修资料网》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道	方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
###	FS40SM-6	三菱	HS PSW	MOS	N	E	300	DSS	40	275	4-250
###	FSC10FA/LG	富士通	C-Band LN A	GaAs/MP	N	D	8	DS		250m	4-224/263
###	FSC10LF	富士通	C-Band LN A	GaAs/MP	N	D	8	DS		250m	4-204
###	FSC10X	富士通	C-Band LN A	GaAs/MP	N	D	8	DS		500m	
###	FSC11FA/LG	富士通	C-Band LN A	GaAs/MP	N	D	8	DS		250m	4-224/263
###	FSC11LF	富士通	C-Band LN A	GaAs/MP	N	D	8	DS		250m	4-204
###	FSC11X	富士通	C-Band LN A	GaAs/MP	N	D	8	DS		500m	
###	FSX02FA/LG	富士通	X-Band LN A	GaAs/MP	N	D	6	DS		200m	4-224/263
###	FSX02LF	富士通	X-Band LN A	GaAs/MP	N	D	6	DS		200m	4-204
###	FSX02X	富士通	X-Band LN A	GaAs/MP	N	D	6	DS		250m	
###	FSX03FA/LG	富士通	X-Band LN A	GaAs/MP	N	D	6	DS		200m	4-224/263
###	FSX03LF	富士通	X-Band LN A	GaAs/MP	N	D	6	DS		200m	4-204
###	FSX03X	富士通	X-Band LN A	GaAs/MP	N	D	6	DS		250m	
###	FSX51WF	富士通	X-Band PA	GaAs	N	D	12	DS		1	4-130
###	FSX51X	富士通	X-Band PA	GaAs	N	D	12	DS		1	
###	FSX52WF	富士通	X-Band PA	GaAs	N	D	12	DS		1.5	4-130
###	FSX52X	富士通	X-Band PA	GaAs	N	D	12	DS		1.5	
###	FSX53W/WF	富士通	X-Band PA	GaAs	N	D	12	DS		3	4-96/130
###	FT6011	富士通	Motor-D	MOS	N	E	60	DSS	3.5	32	4-247B
###	FT6011D	富士通	Motor-D	MOS	N	E	60	DSS	3.5	32	4-247A
###	FT6012	富士通	Motor-D	MOS	N	E	60	DSS	6.5	40	4-247B
###	FT6012D	富士通	Motor-D	MOS	N	E	60	DSS	6.5	40	4-247A
###	FT6015	富士通	Motor-D	MOS	N	E	30	DSS	10	40	4-247
###	FT6021	富士通	Motor-D	MOS	N	E	60	DSS	3.0	28	4-248B
###	FT6021D	富士通	Motor-D	MOS	N	E	60	DSS	3.0	28	4-248A
###	FT6022	富士通	Motor-D	MOS	N	E	60	DSS	6.0	36	4-248B
###	FT6022D	富士通	Motor-D	MOS	N	E	60	DSS	6.0	36	4-248A
###	FT6025	富士通	Motor-D	MOS	N	E	30	DSS	9	36	4-248
###	FT6045	富士通	PSW	MOS	N	E	30	DSS	17	40	
###	FT6046	富士通	PSW	MOS	N	E	30	DSS	45	80	
###	FT6110	富士通	Motor-D	MOS	N	E	120	DSS	2	32	4-247B
###	FT6110D	富士通	Motor-D	MOS	N	E	120	DSS	2	32	4-247A
###	FT6111	富士通	Motor-D	MOS	N	E	120	DSS	3	36	4-247B
###	FT6111D	富士通	Motor-D	MOS	N	E	120	DSS	3	36	4-247A
###	FT6112	富士通	Motor-D	MOS	N	E	120	DSS	4.5	40	4-247B
###	FT6112D	富士通	Motor-D	MOS	N	E	120	DSS	4.5	40	4-247A
###	FT6120	富士通	Motor-D	MOS	N	E	120	DSS	1.5	28	4-248B
###	FT6120D	富士通	Motor-D	MOS	N	E	120	DSS	1.5	28	4-248A
###	FT6121	富士通	Motor-D	MOS	N	E	120	DSS	2.5	32	4-248B
###	FT6121D	富士通	Motor-D	MOS	N	E	120	DSS	2.5	32	4-248A
###	FT6122	富士通	Motor-D	MOS	N	E	120	DSS	4	36	4-248B
###	FT6122D	富士通	Motor-D	MOS	N	E	120	DSS	4	36	4-248A
###	FT6211	富士通	Motor-D	MOS	N	E	200	DSS	3	40	4-247B
###	FT6221	富士通	Motor-D	MOS	N	E	200	DSS	2.5	36	4-248B
###	FT6240	富士通	HS SW	MOS	N	E	200	DSS	5	45	4-264
###	FT6241	富士通	HS SW	MOS	N	E	200	DSS	8	65	4-264
###	FT6260	富士通	HS SW	MOS	N	E	200	DSS	7.5	55	4-265
###	FT6261	富士通	HS SW	MOS	N	E	200	DSS	12	65	4-265
###	FT6540	富士通	HS SW	MOS	N	E	500	DSS	4	70	4-264
###	FT6560	富士通	SW	MOS	N	E	500	DSS	3.5	60	4-265
###	FT6561	富士通	SW	MOS	N	E	500	DSS	6.5	70	4-265
###	FT6562	富士通	SW	MOS	N	E	500	DSS	8.5	75	4-265
###	FT6840	富士通	HS SW	MOS	N	E	800	DSS	2	70	4-264
###	FT6860	富士通	SW	MOS	N	E	800	DSS	1.8	60	4-265
###	FT6861	富士通	SW	MOS	N	E	800	DSS	3	70	4-265
###	FT6862	富士通	SW	MOS	N	E	800	DSS	4.5	75	4-265
###	FTR6120/61	富士通	Head/Motor-D	MOS	N	E	120	DSS	1.5	28	4-248B/A
###	FTR6121/61	富士通	Head/Motor-D	MOS	N	E	120	DSS	2.5	32	4-248B/A
###	FTR6122/61	富士通	Head/Motor-D	MOS	N	E	120	DSS	4	36	4-248B/A
###	FX207	三洋		MOS	P	E	-12	DSS	-4	8	
###	FX208	三洋		MOS	N	E	20	DSS	4	8	

5000种场效应管参数

更多彩电维修资料请到《[彩电维修资料网](http://www.tv160.net)》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
###	KGF1800	冲	X-K-Band LN A	GaAsHE	N D	5	DSX	80m	200m	4-260
###	KGF1801	冲	X-K-Band LN A	GaAsHE	N D	5	DSX	80m	200m	4-260
###	KGF1850	冲	X-K-Band LN A	GaAsHE	N D	4	DSX	100m	200m	4-260
###	KGF1860	冲	X-K-Band LN A	GaAsHE	N D	4	DSX	50m	200m	4-310
###	KGF1870	冲	X-K-Band LN A	GaAsHE	N D	4	DSX	70m	200m	4-310
###	M46F	松下	LF A	J	P D	30	GDS	-30m	250m	
###	M47F	松下	LF LN A	J	N D	-30	GDS	30m	250m	4-38
###	MD1.3N10			MOS	N	100	GDS	1.3		4-319
###	MD1N10			MOS	N	100	DSS	1		4-319
###	MD1P10			MOS	P	-100	DSS	-1		4-319
###	MD05N10			MOS	N	100	DSS	0.5		4-319
###	MD06N20			MOS	N	200	DSS	0.6		4-319
###	MD08N20			MOS	N	200	DSS	0.8		4-319
###	ME2N20			MOS	N	200	DSS	2		4-320
###	ME2N20-F			MOS	N	200	DSS	2		4-321
###	ME3P20			MOS	P	-200	DSS	-3		4-320
###	ME3P20-F			MOS	P	-200	DSS	-3		4-321
###	ME4N20			MOS	N	200	DSS	4		4-(TO-251)
###	ME4N20-F			MOS	N	200	DSS	4		4-(TO-252)
###	ME4P06			MOS	P	-60	DSS	-4		4-320
###	ME4P06-F			MOS	P	-60	DSS	-4		4-(TO-252)
###	ME6N10			MOS	N	100	DSS	6		4-320
###	ME6N10-F			MOS	N	100	DSS	6		4-321
###	ME6P10			MOS	P	-100	DSS	-6		4-320
###	ME6P10-F			MOS	P	-100	DSS	-6		4-321
###	ME7N20			MOS	N	200	DSS	7		4-320
###	ME7N20-F			MOS	N	200	DSS	7		4-321
###	ME8N06E			MOS	N	60	DSS	8		4-320
###	ME8N06E-F			MOS	N	60	DSS	8		4-321
###	ME8P06			MOS	P	-60	DSS	-8		4-(TO-251)
###	ME8P06-F			MOS	P	-60	DSS	-8		4-(TO-252)
###	ME10N10E			MOS	N	100	DSS	10		4-320
###	ME10N10E-F			MOS	N	100	DSS	10		4-321
###	ME12P06			MOS	P	-60	DSS	-12		4-320
###	ME12P06-F			MOS	P	-60	DSS	-12		4-321
###	ME15N06E			MOS	N	60	DSS	15		4-320
###	ME15N06E-F			MOS	N	60	DSS	15		4-321
###	MF2N60E			MOS	N	600	DSS	2		4-(TO-220)
###	MF4N50E			MOS	N	500	DSS	4		4-(TO-220)
###	MF4N60E			MOS	N	600	DSS	4		4-(TO-220)
###	MF5N50E			MOS	N	500	DSS	5		4-(TO-220)
###	MF6N40E			MOS	N	400	DSS	6		4-(TO-220)
###	MF8N10E			MOS	N	100	DSS	8		4-(TO-220)
###	MF8P06			MOS	N	-60	DSS	-8		4-(TO-220)
###	MF10N06E			MOS	N	60	DSS	10		4-(TO-220)
###	MF11N10EL			MOS	N	100	DSS	11		4-(TO-220)
###	MF15N06			MOS	N	60	DSS	15		4-(TO-220)
###	MF21N10EL			MOS	N	100	DSS	21		4-(TO-220)
###	MF30N06E			MOS	N	60	DSS	30		4-(TO-220)
###	MFA174	三菱	VHF PA/OSC	SIT	N D	-250	GDO	2	200	4-225
###	MFA254	三菱	VHF PA/OSC	SIT	N D	-250	GDO	3	100	4-225
###	MG1.5N40			MOS	N	400	DSS	1.5		4-322
###	MG2.5N20			MOS	N	200	DSS	2.5		4-322
###	MG2.5N50			MOS	N	500	DSS	2.5		4-322
###	MG2N20			MOS	N	200	DSS	2		4-(TO-220AB)
###	MG2N25			MOS	N	250	DSS	2		4-322
###	MG2P50			MOS	P	-500	DSS	-2		4-(TO-220AB)
###	MG3N40			MOS	N	400	DSS	3		4-322
###	MG3N50E			MOS	N	500	DSS	3		4-(TO-220AB)
###	MG3N60E			MOS	N	600	DSS	3		4-(TO-220AB)
###	MG4.5N50			MOS	N	500	DSS	4.5		4-322

5000种场效应管参数

更多彩电维修资料请到《彩电维修资料网》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
###	MG4N10			MOS	N	100	DSS	4		4-322
###	MG4N40E			MOS	N	400	DSS	4		4-(TO-220AB)
###	MG4N50E			MOS	N	500	DSS	4		4-(TO-220AB)
###	MG4N80E			MOS	N	800	DSS	4		4-(TO-220AB)
###	MG5.5N40			MOS	N	400	DSS	5.5		4-322
###	MG5N20			MOS	N	200	DSS	5		4-322
###	MG5N40E			MOS	N	400	DSS	5		4-(TO-220AB)
###	MG5P20			MOS	P	-200	DSS	-5		4-322
###	MG6N10			MOS	N	100	DSS	6		4-(TO-220AB)
###	MG6N60E			MOS	N	600	DSS	6		4-(TO-220AB)
###	MG6P20E			MOS	P	-200	DSS	-6		4-(TO-220AB)
###	MG7N20			MOS	N	200	DSS	7		4-(TO-220AB)
###	MG8G4GM1	东芝	DC Motor-D, DDC	MOS	N	E 450	DSS	±8	100	4-226
###	MG8G6EM1	东芝	AC Motor-D	MOS	N	E 450	DSS	±8	100	4-227
###	MG8N10			MOS	N	100	DSS	8		4-322
###	MG8N50			MOS	N	500	DSS	8		4-322
###	MG8N50E			MOS	N	500	DSS	8		4-(TO-220AB)
###	MG8P10			MOS	P	-100	DSS	-8		4-322
###	MG8P20			MOS	P	-200	DSS	-8		4-322
###	MG9N20			MOS	N	200	DSS	9		4-322
###	MG10N06E			MOS	N	60	DSS	10		4-322
###	MG10N10E			MOS	N	100	DSS	10		4-(TO-220AB)
###	MG10N25			MOS	N	250	DSS	10		4-322
###	MG10N40			MOS	N	400	DSS	10		4-322
###	MG10N40E			MOS	N	400	DSS	10		4-(TO-220AB)
###	MG12N06E			MOS	N	60	DSS	12		4-(TO-220AB)
###	MG12N10E			MOS	N	100	DSS	12		4-(TO-220AB)
###	MG12N20			MOS	N	200	DSS	12		4-(TO-220AB)
###	MG12P06			MOS	P	-60	DSS	-12		4-(TO-220AB)
###	MG12P10			MOS	P	-100	DSS	-12		4-322
###	MG14N10			MOS	N	100	DSS	14		4-322
###	MG15C4HM1	东芝	DC Motor-D, DDC	MOS	N	E 150	DSS	±15	65	4-228
###	MG15D4GM1	东芝	DC Motor-D, DDC	MOS	N	E 250	DSS	±15	100	4-226
###	MG15D4HM1	东芝	DC Motor-D, DDC	MOS	N	E 250	DSS	±15	100	4-228
###	MG15D6EM1	东芝	AC Motor-D	MOS	N	E 250	DSS	±15	100	4-227
###	MG15G1AM1	东芝	SW, Motor-D	MOS	N	E 450	DSS	±15	125	4-229
###	MG15G4GM1	东芝	DC Motor-D, DDC	MOS	N	E 450	DSS	±15	125	4-226
###	MG15G6EM1	东芝	AC Motor-D	MOS	N	E 450	DSS	±15	125	4-227
###	MG15N06E			MOS	N	60	DSS	15		4-322
###	MG15N06EL			MOS	N	60	DSS	15		4-(TO-220AB)
###	MG15N06L			MOS	N	60	DSS	15		4-322
###	MG18N20			MOS	N	200	DSS	18		4-322
###	MG23P06			MOS	N	-60	DSS	-23		4-(TO-220AB)
###	MG25N06L			MOS	N	60	DSS	25		4-322
###	MG27N10			MOS	N	100	DSS	27		4-322
###	MG30N06EL			MOS	N	60	DSS	30		4-(TO-220AB)
###	MG30N10E			MOS	N	100	DSS	30		4-(TO-220AB)
###	MG33N10E			MOS	N	100	DSS	33		4-(TO-220AB)
###	MG35N06E			MOS	N	60	DSS	35		4-322
###	MG36N06E			MOS	N	60	DSS	36		4-(TO-220AB)
###	MG40N06EL			MOS	N	60	DSS	40		4-322
###	MG50N06E			MOS	N	60	DSS	50		4-322
###	MG50N06EL			MOS	N	60	DSS	50		4-(TO-220AB)
###	MGF0904	三菱	MW PA	GaAs	N	D -17	GDO	800m	3.1	
###	MGF0905	三菱	MW PA	GaAs	N	D -17	GDO	3.2	10	
###	MGF1102	三菱	MW LN A	GaAs	N	D -6	GDO	80m	300m	
###	MGF1202	三菱	L-C-band LN A	GaAs	N	D -6	GDO	100m	300m	4-166
###	MGF1302	三菱	MW LN A	GaAs	N	D -6	GDO	100m	360m	
###	MGF1303	三菱	MW LN A	GaAs	N	D -6	GDO	80m	240m	
###	MGF1304A	三菱	MW LN A	GaAs	N	D -6	GDO	70m	200m	
###	MGF1305	三菱	MW LN A	GaAs	N	D -6	GDO	70m	200m	

5000种场效应管参数

更多彩电维修资料请到《[彩电维修资料网](http://www.tv160.net)》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道	方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
###	MGF1402	三菱	S-X-Band LN A	GaAs	N	D	-6	GDO	100m	360m	4-122
###	MGF1403	三菱	S-Ku-Band LN A	GaAs	N	D	-6	GDO	80m	240m	4-122
###	MGF1404	三菱	S-Ku-Band LN A	GaAs	N	D	-6	GDO	80m	240m	4-122
###	MGF1405	三菱	MW LN A	GaAs	N	D	-6	GDO	70m	200m	
###	MGF1412	三菱	S-X-Band LN A	GaAs	N	D	-6	GDO	100m	360m	4-122
###	MGF1413	三菱	MW LN A	GaAs	N	D	-6	GDO	100m	300m	
###	MGF1414	三菱	MW LN A	GaAs	N	D	-6	GDO	50m	200m	
###	MGF1423	三菱	MW LN A	GaAs	N	D	-6	GDO	80m	240m	
###	MGF1425	三菱	MW LN A	GaAs	N	D	-6	GDO	60m	200m	
###	MGF1501	三菱	MW LN A	GaAs	N	D	-6	GDO	60m	150m	
###	MGF1502	三菱	MW LN A	GaAs	N	D	-6	GDO	80m	300m	
###	MGF1601	三菱	MW PA	GaAs	N	D	-8	GDO	250m	1	
###	MGF1801	三菱	S-X-Band PA	GaAs	N	D	-8	GDO	250m	1.2	4-167
###	MGF1802	三菱	C-X-Band PA	GaAs	N	D	-8	GDO	250m	1.8	4-170
###	MGF1902	三菱	MW LN A	GaAs	N	D	-6	GDO	100m	360m	
###	MGF1903	三菱	MW LN A	GaAs	N	D	-6	GDO	80m	240m	
###	MGF1904	三菱	MW LN A	GaAs	N	D	-6	GDO	70m	200m	
###	MGF2116	三菱	S-X-Band PA	GaAs	N	D	-11	GDO	550m	3.65	4-169
###	MGF2117	三菱	C-X-Band PA	GaAs	N	D	-11	GDO	550m	3.65	4-170
###	MGF2124	三菱	C-Ku-Band PA	GaAs	N	D	-11	GDO	800m	5	4-124
###	MGF2124F	三菱	C-Ku-Band PA	GaAs	N	D	-11	GDO	800m	5	4-171
###	MGF2124G	三菱	C-Ku-Band PA	GaAs	N	D	-11	GDO	800m	5	4-172
###	MGF2148	三菱	C-Ku-Band PA	GaAs	N	D	-11	GDO	1.6	10	4-124
###	MGF2148F	三菱	C-Ku-Band PA	GaAs	N	D	-11	GDO	1.6	10	4-171
###	MGF2148G	三菱	C-Ku-Band PA	GaAs	N	D	-11	GDO	1.6	10	4-172
###	MGF2172	三菱	S-X-Band PA	GaAs	N	D	11	DSX	2.3	12.5	4-124
###	MGF2205	三菱	S-X-Band PA	GaAs	N	D	11	DSX	3.6	12.5	4-173
###	MGF2407	三菱	MW PA	GaAs	N	D	-15	GDO	250m	1.5	
###	MGF2407A	三菱	MW PA	GaAs	N	D	-15	GDO	250m	1.5	
###	MGF2415	三菱	MW PA	GaAs	N	D	-15	GDO	420m	2.5	
###	MGF2415A	三菱	MW PA	GaAs	N	D	-15	GDO	420m	2.5	
###	MGF2430	三菱	MW PA	GaAs	N	D	-15	GDO	900m	5	
###	MGF2430A	三菱	MW PA	GaAs	N	D	-15	GDO	900m	5	
###	MGF2445	三菱	MW PA	GaAs	N	D	-15	GDO	1.4	10	
###	MGF4301A	三菱	MW LN A	GaAs	N	D	-4	GDO	60m	160m	
###	MGF4302A	三菱	MW LN A	GaAs	N	D	-4	GDO	60m	160m	
###	MGF4303A	三菱	MW LN A	GaAs	N	D	-4	GDO	60m	160m	
###	MGF4304A	三菱	MW LN A	GaAs	N	D	-4	GDO	60m	160m	
###	MGF4305A	三菱	MW LN A	GaAs	N	D	-4	GDO	60m	160m	
###	MGF4401A	三菱	MW LN A	GaAs	N	D	-4	GDO	60m	160m	
###	MGF4402A	三菱	MW LN A	GaAs	N	D	-4	GDO	60m	160m	
###	MGF4403A	三菱	MW LN A	GaAs	N	D	-4	GDO	60m	160m	
###	MGF4404A	三菱	MW LN A	GaAs	N	D	-4	GDO	60m	160m	
###	MGF4405A	三菱	MW LN A	GaAs	N	D	-4	GDO	60m	160m	
###	MGF-X34M	三菱	10GHz PA	GaAs	N	D	11	DSX	2.3	12.5	4-174
###	MGFC36V374	三菱	MW PA	GaAs	N	D	-15	GDO	2.8	25	
###	MGFC36V445	三菱	MW PA	GaAs	N	D	-15	GDO	2.8	25	
###	MGFC36V525	三菱	MW PA	GaAs	N	D	-15	GDO	2.8	25	
###	MGFC36V596	三菱	MW PA	GaAs	N	D	-15	GDO	2.8	25	
###	MGFC36V647	三菱	MW PA	GaAs	N	D	-15	GDO	2.8	25	
###	MGFC36V717	三菱	MW PA	GaAs	N	D	-15	GDO	2.8	25	
###	MGFC36V778	三菱	MW PA	GaAs	N	D	-15	GDO	2.8	25	
###	MGFC39V374	三菱	MW PA	GaAs	N	D	-15	GDO	5.6	42.8	
###	MGFC39V445	三菱	MW PA	GaAs	N	D	-15	GDO	5.6	42.8	
###	MGFC39V525	三菱	MW PA	GaAs	N	D	-15	GDO	5.6	42.8	
###	MGFC39V596	三菱	MW PA	GaAs	N	D	-15	GDO	5.6	42.8	
###	MGFC39V647	三菱	MW PA	GaAs	N	D	-15	GDO	5.6	42.8	
###	MGFC39V717	三菱	MW PA	GaAs	N	D	-15	GDO	5.6	42.8	
###	MGFC39V778	三菱	MW PA	GaAs	N	D	-15	GDO	5.6	42.8	
###	MGFC42V374	三菱	MW PA	GaAs	N	D	-15	GDO	12	75	
###	MGFK25M404	三菱	MW PA	GaAs	N	D	-14	GDO	0.4	3.7	

5000种场效应管参数

更多彩电维修资料请到《[彩电维修资料网](http://www.tv160.net)》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道	方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
###	MGFK30M404	三菱	MW PA	GaAs	N	D	-14	GDO	1.2	7.5	
###	MGFK33M404	三菱	MW PA	GaAs	N	D	-14	GDO	2.4	15	
###	MGFK35M404	三菱	MW PA	GaAs	N	D	-14	GDO	4.5	30	
###	MGFK35V222	三菱	MW PA	GaAs	N	D	-15	GDO	3.5	27.2	
###	MGFK35V273	三菱	MW PA	GaAs	N	D	-15	GDO	3.5	27.2	
###	MGFK35V404	三菱	MW PA	GaAs	N	D	-15	GDO	3.5	27.2	
###	MGFK37V404	三菱	MW PA	GaAs	N	D	-15	GDO	6.6	42.8	
###	MGFK38V222	三菱	MW PA	GaAs	N	D	-15	GDO	6.6	12.8	
###	MGFK38V273	三菱	MW PA	GaAs	N	D	-15	GDO	6.6	42.8	
###	MGFK39V404	三菱	MW PA	GaAs	N	D	-15	GDO	8	42.8	
###	MGFX35V000	三菱	MW PA	GaAs	N	D	-15	GDO	2.8	27.2	
###	MGFX35V051	三菱	MW PA	GaAs	N	D	-15	GDO	2.8	27.2	
###	MGFX35V172	三菱	MW PA	GaAs	N	D	-15	GDO	3.5	27.2	
###	MGFX35V909	三菱	MW PA	GaAs	N	D	-15	GDO	2.8	27.2	
###	MGFX35V950	三菱	MW PA	GaAs	N	D	-15	GDO	2.8	27.2	
###	MGFX38V000	三菱	MW PA	GaAs	N	D	-15	GDO	5.6	42.8	
###	MGFX38V051	三菱	MW PA	GaAs	N	D	-15	GDO	5.6	42.8	
###	MGFX38V172	三菱	MW PA	GaAs	N	D	-15	GDO	6.6	42.8	
###	MGFX38V909	三菱	MW PA	GaAs	N	D	-15	GDO	5.6	42.8	
###	MGFX38V950	三菱	MW PA	GaAs	N	D	-15	GDO	5.6	42.8	
###	MK6N85E			MOS	N		850	DSS	6		4-323
###	MK7N80E			MOS	N		800	DSS	7		4-(T0-247)
###	MK10	三菱	DC-VHF	J	N	D	-30	GDO	10m	150m	4-9
###	MK14N50E			MOS	N		500	DSS	14		4-323
###	MK16N40E			MOS	N		400	DSS	16		4-323
###	MK30N20E			MOS	N		200	DSS	30		4-323
###	MK32N20E			MOS	N		200	DSS	32		4-(T0-247)
###	MK50N06E			MOS	N		60	DSS	50		4-323
###	MK54N05E			MOS	N		50	DSS	54		4-323
###	MP6704	东芝	AC Motor-D	MOS	N	E	500	DSS	±10	75	4-285
###	NE345L-10B	NEC	L-S-Band PA	GaAs	N	D	15	DS	9	50	4-311
###	NE345L-20B	NEC	L-S-Band PA	GaAs	N	D	15	DS	18	100	4-262
###	NE20248	NEC	C-K-Band LN A	GaAs	N	D	4	DSX	60m	200m	4-261
###	NE24200	NEC	MW LN A		N						
###	NE24283A	NEC	MW LN A		N						
###	NE32084	NEC	X-Ku-Band LN A	GaAs	N		4	DS	60m	200m	4-280
###	NE32183A	NEC	X-Ku-Band LN A	A1GaAs	N	D	4	DS	60m	200m	4-279
###	NE32184A	NEC	C-Ku-Band LN A	A1GaAs	N	D	4	DS	60m	165m	4-280
###	NE32184A-1	NEC	C-Ku-Band LN A	A1GaAs	N	D	4	DS	60m	165m	4-280
###	NE32384A	NEC	C-Ku-Band LN A	A1GaAs	N	D	4	DS	60m	165m	4-280
###	NE32400	NEC	MW LN A		N						
###	NE32484A	NEC	C-Ku-Band LN A	InGaAs	N	D	4	DS	70m	165m	4-280
###	NE32684A	NEC	C-Ku-Band LN A		N	D	4	DS	70m	165m	4-280
###	NE33200	NEC	MW LN A		N						
###	NE33284A	NEC	L-X-Band LN A		N	D	4	DS	80m	165m	4-280
###	NE42184A	NEC	C-Ku-Band LN A	A1GaAs	N	D	4	DS	60m	165m	4-280
###	NE42484A	NEC	C-Ku-Band LN A	InGaAs	N	D	4	DS	70m	165m	4-280
###	NE42484A-1	NEC	C-Ku-Band LN A		N						
###	NE76038	NEC	L-Ku-Band LN A	GaAs/M	N	D	5	DS	50m	100m	4-312
###	NE76184A	NEC	L-Ku-Band LN A	GaAs/M	N	D	5	DS	100m	300m	4-280
###	NEZ0910-2A	NEC	X-Band PA	GaAs	N	D	20	DSX	2.4	15	4-205
###	NEZ0910-4A	NEC	X-Band PA	GaAs	N	D	20	DSX	6	39	4-206
###	NEZ0910-6A	NEC	X-Band PA	GaAs	N	D	20	DSX	8	53	4-206
###	NEZ1011-2A	NEC	X-Band PA	GaAs	N	D	20	DSX	2.4	15	4-205
###	NEZ1011-4A	NEC	X-Band PA	GaAs	N	D	20	DSX	6	39	4-206
###	NEZ1011-6A	NEC	X-Band PA	GaAs	N	D	20	DSX	8	53	4-206
###	NEZ1414-2A	NEC	Ku-Band PA	GaAs	N	D	20	DSX	2.4	15	4-205
###	NEZ1414-4A	NEC	Ku-Band PA	GaAs	N	D	20	DSX	6	39	4-206
###	P2H10M440H			MOS	N		500	DSS	85	230	4-325
###	P2H10M440L			MOS	N		500	DSS	70	230	4-325
###	P2H10M441H			MOS	N		450	DSS	85	230	4-325

5000种场效应管参数

更多彩电维修资料请到《[彩电维修资料网](http://www.tv160.net)》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing	
###	P2H10M441L			MOS	N	450	DSS	70	230	4-325	
###	P2H4M440H			MOS	N	500	DSS	30	230	4-325	
###	P2H4M440L			MOS	N	500	DSS	30	230	4-325	
###	P2H4M441H			MOS	N	450	DSS	30	230	4-325	
###	P2H4M441L			MOS	N	450	DSS	30	230	4-325	
###	P2H7M440H			MOS	N	500	DSS	50	230	4-325	
###	P2H7M440L			MOS	N	500	DSS	50	230	4-325	
###	P2H7M441H			MOS	N	450	DSS	50	230	4-325	
###	P2H7M441L			MOS	N	450	DSS	50	230	4-325	
###	PD4M440H			MOS	N	500	DSS	30	230	4-324	
###	PD4M440L			MOS	N	500	DSS	30	230	4-324	
###	PD4M441H			MOS	N	450	DSS	30	230	4-324	
###	PD4M441L			MOS	N	450	DSS	30	230	4-324	
###	PD7M440H			MOS	N	500	DSS	50	350	4-324	
###	PD7M440L			MOS	N	500	DSS	50	350	4-324	
###	PD7M441H			MOS	N	450	DSS	50	350	4-324	
###	PD7M441L			MOS	N	450	DSS	50	350	4-324	
###	PD10M440H			MOS	N	500	DSS	85	730	4-324	
###	PD10M440L			MOS	N	500	DSS	70	500	4-324	
###	PD10M441H			MOS	N	450	DSS	85	730	4-324	
###	PD10M441L			MOS	N	450	DSS	70	500	4-324	
###	PF0004	日立	820~850MHz PA	MOS		17	DD			4-238	
###	PF0007	日立	890~915MHz PA	MOS		17	DD			4-238	
###	PF0008	日立	865~890MHz PA	MOS		17	DD			4-239	
###	PF0009	日立	920~945MHz PA	MOS		17	DD	3		4-239	
###	PF0010	日立	820~850MHz PA	MOS		17	DD	3		4-298	
###	PF0011	日立	890~915MHz PA	MOS		17	DD	3		4-298	
###	PF0012	日立	872~905MHz PA	MOS		17	DD	3		4-298	
###	PF0014	日立	915~940MHz PA	MOS		17	DD	3		4-299	
###	PF0015	日立	824~849MHz PA	MOS		12	DD	2		4-300	
###	PF0016	日立	890~915MHz PA	MOS		12	DD	2		4-300	
###	PF0017	日立	872~905MHz PA	MOS		12	DD	2		4-300	
###	PF0020	日立	820~850MHz PA	MOS		17	DD	3		4-299	
###	PF0022	日立	872~905MHz PA	MOS		17	DD	3		4-299	
###	PM1210B	日立	HS PSW	MOS	N	E	120	DSS	10	50	4-133
###	PM1220B	日立	HS PSW	MOS	N	E	120	DSS	20	80	4-133
###	PM4550C	日立	HS PSW	MOS	N	E	450	DSS	50	300	4-36
###	PM4550J	日立		MOS	N	E	450	DSS	50/CH	300/CH	4-301
###	PM4550N	日立		MOS	N	E	450	DSS	50/CH	300/CH	4-302
###	PM4575J	日立		MOS	N	E	450	DSS	75/CH	350/CH	4-301
###	PM4575N	日立		MOS	N	E	450	DSS	75/CH	350/CH	4-302
###	PM5050J	日立		MOS	N	E	500	DSS	50/CH	300/CH	4-301
###	PM5050N	日立		MOS	N	E	500	DSS	50/CH	300/CH	4-302
###	PM5075J	日立		MOS	N	E	500	DSS	75/CH	350/CH	4-301
###	PM5075N	日立		MOS	N	E	500	DSS	75/CH	350/CH	4-302
###	PM45100K	日立		MOS	N	E	450	DSS	100/CH	400/CH	4-303
###	PM45150K	日立		MOS	N	E	450	DSS	150/CH	500/CH	4-303
###	PM45302F	日立		MOS	N	E	450	DSS	30/CH	200/CH	4-237
###	PM45502C	日立		MOS	N	E	450	DSS	50/CH	300/CH	4-36
###	PM50100K	日立		MOS	N	E	450	DSS	100/CH	400/CH	4-303
###	PM50150K	日立		MOS	N	E	500	DSS	150/CH	450/CH	4-303
###	PM50302F	日立		MOS	N	E	500	DSS	30/CH	200/CH	4-237
###	PM50502C	日立		MOS	N	E	500	DSS	50/CH	300/CH	4-36
###	PU61C56	松下	Motor/Relay-D, S	MOS	N	E	37±7	DSS	6	15	4-350
###	PU7456	松下	Motor/Relay-D	MOS	N	E	35±10	DSS	6	15	4-313
###	PU7457	松下	Motor-D, SW-Reg	MOS	N	E	100	DSS	3	15	4-313
###	PU8432	松下	Motor/Relay-D, S	MOS	N	E	150	DSS	3	15	4-351
###	PU8456	松下	Motor/Relay-D, S	MOS	N	E	35±10	DSS	6	15	4-351
###	RHF1203CL	罗姆	X-Band LN A	InGaAs	N	D	4	DSX	60m	200m	4-266
###	SGH5002E		MW LN A	GaAsHE	N	D	5	DS	70m	340m	4-339
###	SGH5003E		MW LN A	GaAsHE	N	D	5	DS	100m	340m	4-339

5000种场效应管参数

更多彩电维修资料请到《彩电维修资料网》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
###	SGH5602E		MW LN A	GaAsHE	N D	5	DS	70m	340m	4-339
###	SGM2004M		UHF LN A	GaAs/M	N D	12	DSX	55m	150m	4-340
###	SGM2006M/P		UHF LN A	GaAs/M	N D	12	DSX	55m	150m	4-198/340
###	STA501A		Motor/Relay-D	MOS	N E	60	DSS	±5	20	4-377
###	TM100-H		HV RF PA, PSW	SIT	N D	1200	GDO	50×2	500	4-314
###	TM100-M		HV RF PA, PSW	SIT	N D	600	GDO	50×2	500	4-314
###	TM100-N		HV RF PA, PSW	SIT	N D	800	GDO	50×2	500	4-314
###	TM101-H		HV RF PA, PSW	SIT	N D	1200	GDO	50×2	500	4-314
###	TM101-M		HV RF PA, PSW	SIT	N D	600	GDO	50×2	500	4-314
###	TM101-N		HV RF PA, PSW	SIT	N D	800	GDO	50×2	500	4-314
###	TM200-H		HV RF PA, PSW	SIT	N D	1200	GDO	100×2	1000	4-314
###	TM200-M		HV RF PA, PSW	SIT	N D	600	GDO	100×2	1000	4-314
###	TM200-N		HV RF PA, PSW	SIT	N D	800	GDO	100×2	1000	4-314
###	TM201-H		HV RF PA, PSW	SIT	N D	1200	GDO	100×2	1000	4-314
###	TM201-M		HV RF PA, PSW	SIT	N D	600	GDO	100×2	1000	4-314
###	TM201-N		HV RF PA, PSW	SIT	N D	800	GDO	100×2	1000	4-314
###	TM400-H		HV RF PA, PSW	SIT	N D	1200	GDO	100×4	800×4	4-315
###	TM400-M		HV RF PA, PSW	SIT	N D	600	GDO	100×4	800×4	4-315
###	TM400-N		HV RF PA, PSW	SIT	N D	800	GDO	100×4	800×4	4-315
###	TM401-H		HV RF PA, PSW	SIT	N D	1200	GDO	100×4	800×4	4-315
###	TM401-M		HV RF PA, PSW	SIT	N D	600	GDO	100×4	800×4	4-315
###	TM401-N		HV RF PA, PSW	SIT	N D	800	GDO	100×4	800×4	4-315
###	TS300		HV RF PA, HV PSW	SIT	N D	600	GDO	200	3000	4-272
###	TS300H		HV RF PA, HV PSW	SIT	N D	1200	GDO	180	3000	4-272
###	TS300V		HV RF PA, HV PSW	SIT	N D	1500	GDO	180	3000	4-272
###	TX-429D		VR	MOS	N	-25	DB	±15m	100m	4-68
###	YTF150	东芝	SW, DDC	MOS	N E	100	DSX	40	150	4-230
###	YTF151	东芝	SW, DDC	MOS	N E	60	DSX	40	150	4-230
###	YTF152	东芝	SW, DDC	MOS	N E	100	DSX	33	150	4-230
###	YTF153	东芝	SW, DDC	MOS	N E	60	DSX	33	150	4-230
###	YTF220	东芝	SW, DDC	MOS	N E	200	DSX	5	40	4-134
###	YTF221	东芝	SW, DDC	MOS	N E	150	DSX	5	40	4-134
###	YTF222	东芝	SW, DDC	MOS	N E	200	DSX	4	40	4-134
###	YTF223	东芝	SW, DDC	MOS	N E	150	DSX	4	40	4-134
###	YTF230	东芝	SW, DDC	MOS	N E	200	DSX	9	75	4-134
###	YTF231	东芝	SW, DDC	MOS	N E	150	DSX	9	75	4-134
###	YTF232	东芝	SW, DDC	MOS	N E	200	DSX	8	75	4-134
###	YTF233	东芝	SW, DDC	MOS	N E	150	DSX	8	75	4-134
###	YTF240	东芝	SW, DDC	MOS	N E	200	DSX	18	125	4-230
###	YTF241	东芝	SW, DDC	MOS	N E	150	DSX	18	125	4-230
###	YTF242	东芝	SW, DDC	MOS	N E	200	DSX	16	125	4-230
###	YTF243	东芝	SW, DDC	MOS	N E	150	DSX	16	125	4-230
###	YTF250	东芝	SW, DDC	MOS	N E	200	DSX	30	150	4-230
###	YTF251	东芝	SW, DDC	MOS	N E	150	DSX	30	150	4-230
###	YTF252	东芝	SW, DDC	MOS	N E	200	DSX	25	150	4-230
###	YTF253	东芝	SW, DDC	MOS	N E	150	DSX	25	150	4-230
###	YTF440	东芝	SW, DDC	MOS	N E	500	DSX	8	125	4-134
###	YTF441	东芝	SW, DDC	MOS	N E	450	DSX	8	125	4-134
###	YTF442	东芝	SW, DDC	MOS	N E	500	DSX	7	125	4-134
###	YTF443	东芝	SW, DDC	MOS	N E	450	DSX	7	125	4-134
###	YTF450	东芝	SW, DDC	MOS	N E	500	DSX	13	150	4-134
###	YTF451	东芝	SW, DDC	MOS	N E	450	DSX	13	150	4-134
###	YTF452	东芝	SW, DDC	MOS	N E	500	DSX	12	150	4-134
###	YTF453	东芝	SW, DDC	MOS	N E	450	DSX	12	150	4-134
###	YTF520	东芝	SW, DDC	MOS	N E	100	DSX	8	40	4-183
###	YTF521	东芝	SW, DDC	MOS	N E	60	DSX	8	40	4-183
###	YTF522	东芝	SW, DDC	MOS	N E	100	DSX	7	40	4-183
###	YTF523	东芝	SW, DDC	MOS	N E	60	DSX	7	40	4-183
###	YTF530	东芝	SW, DDC	MOS	N E	100	DSX	14	75	4-183
###	YTF531	东芝	SW, DDC	MOS	N E	60	DSX	14	75	4-183
###	YTF532	东芝	SW, DDC	MOS	N E	100	DSX	12	75	4-183

5000种场效应管参数

更多彩电维修资料请到《[彩电维修资料网](http://www.tv160.net)》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道	方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
###	YTF533	东芝	SW, DDC	MOS	N	E	60	DSX	12	75	4-183
###	YTF540	东芝	SW, DDC	MOS	N	E	100	DSX	27	125	4-183
###	YTF541	东芝	SW, DDC	MOS	N	E	60	DSX	27	125	4-183
###	YTF542	东芝	SW, DDC	MOS	N	E	100	DSX	24	125	4-183
###	YTF543	东芝	SW, DDC	MOS	N	E	60	DSX	24	125	4-183
###	YTF610	东芝	SW, DDC	MOS	N	E	200	DSX	2.5	20	4-183
###	YTF611	东芝	SW, DDC	MOS	N	E	150	DSX	2.5	20	4-183
###	YTF612	东芝	SW, DDC	MOS	N	E	200	DSX	2	20	4-183
###	YTF613	东芝	SW, DDC	MOS	N	E	150	DSX	2	20	4-183
###	YTF620	东芝	SW, DDC	MOS	N	E	200	DSX	5	40	4-183
###	YTF621	东芝	SW, DDC	MOS	N	E	150	DSX	5	40	4-183
###	YTF622	东芝	SW, DDC	MOS	N	E	200	DSX	4	40	4-183
###	YTF623	东芝	SW, DDC	MOS	N	E	150	DSX	4	40	4-183
###	YTF630	东芝	SW, DDC	MOS	N	E	200	DSX	9	75	4-183
###	YTF631	东芝	SW, DDC	MOS	N	E	150	DSX	9	75	4-183
###	YTF632	东芝	SW, DDC	MOS	N	E	200	DSX	8	75	4-183
###	YTF633	东芝	SW, DDC	MOS	N	E	150	DSX	8	75	4-183
###	YTF640	东芝	SW, DDC	MOS	N	E	200	DSX	18	125	4-231
###	YTF641	东芝	SW, DDC	MOS	N	E	150	DSX	18	125	4-231
###	YTF642	东芝	SW, DDC	MOS	N	E	200	DSX	16	125	4-231
###	YTF643	东芝	SW, DDC	MOS	N	E	150	DSX	16	125	4-231
###	YTF820	东芝	SW, DDC	MOS	N	E	500	DSX	2.5	20	4-183
###	YTF821	东芝	SW, DDC	MOS	N	E	450	DSX	2.5	40	4-183
###	YTF822	东芝	SW, DDC	MOS	N	E	500	DSX	2	40	4-183
###	YTF823	东芝	SW, DDC	MOS	N	E	450	DSX	2	40	4-183
###	YTF830	东芝	SW, DDC	MOS	N	E	500	DSX	4.5	75	4-183
###	YTF831	东芝	SW, DDC	MOS	N	E	450	DSX	4.5	75	4-183
###	YTF832	东芝	SW, DDC	MOS	N	E	500	DSX	4	75	4-183
###	YTF833	东芝	SW, DDC	MOS	N	E	450	DSX	4	75	4-183
###	YTF840	东芝	SW, DDC	MOS	N	E	500	DSX	8	125	4-183
###	YTF841	东芝	SW, DDC	MOS	N	E	450	DSX	8	125	4-183
###	YTF842	东芝	SW, DDC	MOS	N	E	500	DSX	7	125	4-183
###	YTF843	东芝	SW, DDC	MOS	N	E	450	DSX	7	125	4-183
###	YTFP150	东芝	SW, DDC	MOS	N	E	100	DSX	40	150	4-184
###	YTFP151	东芝	SW, DDC	MOS	N	E	60	DSX	40	150	4-184
###	YTFP152	东芝	SW, DDC	MOS	N	E	100	DSX	33	150	4-184
###	YTFP153	东芝	SW, DDC	MOS	N	E	60	DSX	33	150	4-184
###	YTFP250	东芝	SW, DDC	MOS	N	E	200	DSX	30	150	4-184
###	YTFP251	东芝	SW, DDC	MOS	N	E	150	DSX	30	150	4-184
###	YTFP252	东芝	SW, DDC	MOS	N	E	200	DSX	25	150	4-184
###	YTFP253	东芝	SW, DDC	MOS	N	E	150	DSX	25	150	4-184
###	YTFP450	东芝	SW, DDC	MOS	N	E	500	DSX	13	150	4-184
###	YTFP451	东芝	SW, DDC	MOS	N	E	450	DSX	13	150	4-184
###	YTFP452	东芝	SW, DDC	MOS	N	E	500	DSX	12	150	4-184
###	YTFP453	东芝	SW, DDC	MOS	N	E	450	DSX	12	150	4-184
###	μ PA33A	NEC	DC, Chop	MOS	P		-30	DSS	-20m	0.1/CH	4-22
###	μ PA34A	NEC	DC, Chop	MOS	N		20	DSS	10m	100m	4-22
###	μ PA50A	NEC	LF A	J	N	D	-60	GDO	10m	0.2/CH	4-44
###	μ PA60A	NEC	Diff	J	N	D	-40	GDO	50m	.25/CH	4-111
###	μ PA61A	NEC	Diff	J	N	D	-40	GDO	50m	.25/CH	4-111
###	μ PA62C	NEC		J	N	D	-20	GDO	10m	350m	4-76
###	μ PA63H	NEC	LF A	J	N	D	-60	GDO	10m	.25/CH	4-66
###	μ PA68H	NEC	LF LN A	J	N	D	-50	GDO	10m	.25/CH	4-66
###	μ PA70A	NEC	DC	J	N	D	-40	GDO	50m	250m	4-77
###	μ PA71A	NEC	DC	J	N	D	-40	GDO	50m	250m	4-77
###	μ PA502T	NEC		MOS	N	E	50	DSS	100m	300m	4-317A
###	μ PA503T	NEC		MOS	P	E	-50	DSS	-100m	300m	4-317B
###	μ PA505T	NEC		MOS		E	±50	DSS	±100m	300m	4-317C
###	μ PA572T	NEC	SW	MOS	N	E	30	DSS	±100m	200m	4-317A
###	μ PA573T	NEC	SW	MOS	P	E	-30	DSS	±100m	200m	4-317B
###	μ PA602T	NEC		MOS	N	E	50	DSS	0.1	0.3	4-355B

5000种场效应管参数

更多彩电维修资料请到《[彩电维修资料网](http://www.tv160.net)》查询吧: <http://www.tv160.net> 制作

ID	型号	厂家	用途	构造	沟道	方式	v111(V)	区分	ixing(A)	pdpch(W)	waixing
###	μ PA603T	NEC		MOS	P	E	-50	DSS	-0.1	0.3	4-355B
###	μ PA606T	NEC	SW	MOS	N	E	50	DSS	±100m	300m	4-355A
###	μ PA607T	NEC	SW	MOS	P	E	-50	DSS	±100m	300m	4-355A
###	μ PA1500H	NEC	SW	MOS	N	E	60	DSS	±3/CH	4	4-278
###	μ PA1501H	NEC	SW	MOS	N	E	120	DSS	±3/CH	4	4-278
###	μ PA1520H	NEC	SW	MOS	N	E	30	DSS	±2/CH	28	4-282
###	μ PA1522H	NEC	SW	MOS	N	E	60	DSS	±2/CH	28	4-282
###	μ PA1523H	NEC	SW	MOS	P	E	-60	DSS	±2/CH	28	4-282
###	μ PA1524H	NEC	SW	MOS	N	E	80	DSS	±2/CH	28	4-282
###	μ PA1526H	NEC	SW	MOS	N	E	100	DSS	±2/CH	28	4-282
###	μ PA1527H	NEC	SW	MOS	P	E	-100	DSS	±2/CH	28	4-282
###	μ PA1550H	NEC	SW	MOS	N	E	30	DSS	5/CH	3.5	
###	μ PA1552AH	NEC		MOS			60	DSS	±5	3.5	4-282
###	μ PA1552H	NEC	SW	MOS	N	E	60	DSS	±5/CH	28	4-282
###	μ PA1556AH	NEC		MOS			100	DSS	±5	3.5	4-282
###	μ PA1556H	NEC	SW	MOS	N	E	100	DSS	±5/CH	28	4-282
###	μ PA1570H	NEC	SW	MOS	N	E	30	DSS	±2/CH	28	4-282
###	μ PA1572H	NEC	SW	MOS	N	E	60	DSS	±2/CH	28	4-282
###	μ PA1576H	NEC	SW	MOS	N	E	100	DSS	±2/CH	28	4-282
###	μ PA1600CX	NEC	D	MOS	N		30	0	0.5/CH	1	4-353/354
###	μ PA1601CX	NEC	D	MOS	N		50	0	0.5/CH	1	4-353/354
###	μ PA1602CX	NEC	D	MOS	N		50	0	0.5/CH	1	4-353/354
###	μ PA1603CX	NEC	Motor-D	MOS	N		50	0	1.5/CH	1	4-316
###	μ PA1604CX	NEC	Motor-D	MOS	N		50	0	1.5/CH	1	4-316
###	μ PA1640GS	NEC		MOS			30	0	0.1/CH	1	4-354
###	μ PD16803G	NEC	Motor-D	MOS	N		15	M	±1	1	4-318
###	M91F	松下	UHF PA	GaAs/MP	N	D	10	DS	4		4-329
###	MGF1100	三菱	UHF/SHF LN A	GaAs	N	D	8	DS	60m	150m	4-168