

Features

- Optimize data transmission in ECL systems through proper termination between drivers and receivers
- Minimize overshoot, undershoot, and ringing while increasing noise immunity
- Provide decoupling capacitors
- Minimize space and routing problems, and reduce manufacturing cost per installed resistive function
- Increase board yields and reliability by reducing component count

For information on ECL Terminators, download Bourns' ECL Terminator Application Note.

800 Series - RC Networks ECL Terminator Circuits

General Description

Digital systems incorporating Emitter Coupled Logic (ECL) or other ultra-high switching speed logic families will require signal termination to prevent transmission line effects such as reflections and ringing due to fast transition times.

Bourns 800 series resistor capacitor networks are ideal for termination of high speed transmission lines. Each network is composed of resistors for parallel termination and bypass capacitor(s) for cross talk noise reduction.

The 5 conformal coated SIP circuit variations offered are as follows.

Electrical Characteristics

Resistance Tolerance	±5%
Resistance Power	0.1 watt
Capacitance Tolerance	±20%
Capacitor Dielectric Type	X7R
Capacitance Voltage Rating	

Physical Characteristics


FlammabilityConforms to UL94V-0
LeadframeCopper (Olin 194)
Body MaterialEpoxy/Anhydride
(Conformal Material)
Custom Resistance Range
10 ohms to 50K ohms
Custom Capacitance Range
39pF to 100,000pF

NPO and Z5U dielectrics available on a custom basis.


For Standard Values Used in Capacitors, Inductors, and Resistors, click here.

Product Dimensions

MEDIUM PROFILE




HIGH PROFILE




Typical Part Marking

801 AND 802 Represents total content. Layout may vary.




803 AND 805


Represents total content. Layout may vary.



804

Represents total content. Layout may vary.





*Terminal centerline to centerline measurements made at point of emergence of the lead from the body.

(.010 ± .002)

800 Series - RC Networks ECL Terminator Circuits


801 8, 10 and 12 Pin SIP (4608M-801-RC/CC)


Designed to terminate 6 to 10 transmission lines using parallel termination techniques. Standard resistance values include 50, 68, 75, 82, 90 or 100 ohms and are chosen to match the characteristic impedance ($\rm Z_{O}$) of the transmission line. A 0.01 mF capacitor is provided to help maintain a solid power supply level within the network package, mitigating any cross talk or feedthrough effects. Values for R and C not shown in the following table are available on a custom basis.

Standard 801 Part Numbers

R ±2%	С ±20%	Bourns Part Number
50Ω	0.01µF	4608M-801-500/103
68Ω	0.01µF	4608M-801-680/103
75Ω	0.01µF	4608M-801-750/103
82Ω	0.01µF	4608M-801-820/103
<u>90Ω</u>	0.01µF	4608M-801-900/103
100Ω	0.01µF	4608M-801-101/103

801 Electrical Schematic and Application





802 10 Pin SIP


(4610M-802-RC/CC)


Designed to terminate 6 transmission lines using parallel termination techniques. Popular resistance values include 50, 68, 75, 82, 90 or 100 ohms and are chosen to match the characteristic impedance (Z_0) of the transmission line. Two 0.01 uF capacitors are provided to reduce cross talk between lines and to decrease network package inductance. Values for R and C not shown in the following table are available on a custom basis.

Standard 802 Part Numbers			
R ±2%	C ±20%	Bourns Part Number	
50Ω	0.01µF	4610M-802-500/103	
68Ω	0.01µF	4610M-802-680/103	
75Ω	0.01µF	4610M-802-750/103	
82Ω	0.01µF	4610M-802-820/103	
<u>90Ω</u>	0.01µF	4610M-802-900/103	
100Ω	0.01µF	4610M-802-101/103	

Chandand 000 Dant Number

802 Electrical Schematic and Application






803 8, 10 and 12 Pin SIP 10K ECL (4610H-803-ZoC/CC)

Designed to terminate 6 to 10 transmission lines using Thevenin equivalent parallel termination techniques in systems using 10K ECL. Popular impedance values include 50, 70, 75, 80, 90, 100, 120, 150 or 200 ohms. Standard values for R1 and R2, based on Zo, have been chosen to accommodate 10K ECL designs. A 0.1 µF capacitor is provided to reduce cross talk noise within the network package. Values for $\rm Z_O$ and C not shown in the following table are available on a custom basis. This type of termination is an alternative to parallel termination used when a separate V_{tt} power supply is not available.

Standard 803 Part Numbers

Zo ±2%	R1	R2	C ±20%	Bourns Part No.
50Ω	81 Ω	130Ω	0.1µF	4610H-803-500/104
70Ω	113Ω	182Ω	0.1µF	4610H-803-700/104
75Ω	121Ω	195Ω	0.1µF	4610H-803-750/104
80Ω	130Ω	208Ω	0.1µF	4610H-803-800/104
90Ω	146Ω	234Ω	0.1µF	4610H-803-900/104
100Ω	162 Ω	260Ω	0.1µF	4610H-803-101/104
120Ω	194Ω	312Ω	0.1µF	4610H-803-121/104
150Ω	243Ω	390Ω	0.1µF	4610H-803-151/104
200Ω	325Ω	520Ω	0.1µF	4610H-803-201/104

803 Electrical Schematic and Application



BOURNS®

800 Series - RC Networks ECL Terminator Circuits

BOURNS®


804 12 Pin SIP ECL (4612M-804-RC)


Designed to terminate 6 transmission lines using parallel termination techniques. Popular resistance values include 50 or 100 ohms. A 0.1 μF capacitor is provided for connection to V_{ee} . Two 0.01 μF capacitors are provided for connection to V_{tt} . Values for R and C not shown in the following table are available on a custom basis.

Standard 804 Part Numbers

R	Ct	Ce	Bourns Part Number
±2%	±20%	±20%	
50Ω	0.01μF		4612M-804-500
100Ω	0.01μF		4612M-804-101

804 Electrical Schematic and Application






805 8, 10 and 12 Pin SIP 100K ECL (4610H-805-ZoC/CC)


Designed to terminate 6 to 10 transmission lines using Thevenin equivalent parallel termination techniques in systems using 100K ECL. Popular impedance values include 50, 70, 75, 80, 90, 100, 120, 150 or 200 ohms. Standard values for R1 and R2, based on Z_0 , have been chosen to accommodate 100K ECL designs. A 0.1 µF capacitor is provided to reduce cross talk noise within the network package. Values for Zo and C not shown in the following table are available on a custom basis. This type of termination is an alternative to parallel termination used when a separate V_{tt} power supply is not available.

Standard 805 Part Numbers

Zo ±2%	R1	R2	C ±20%	Bourns Part No.
50Ω	<u>90Ω</u>	113Ω	0.1µF	4610H-805-500/104
70Ω	126Ω	158Ω	0.1µF	4610H-805-700/104
75Ω	135Ω	169 Ω	0.1µF	4610H-805-750/104
80Ω	144Ω	180Ω	0.1µF	4610H-805-800/104
90Ω	161Ω	202Ω	0.1µF	4610H-805-900/104
100Ω	180Ω	225Ω	0.1µF	4610H-805-101/104
120Ω	216Ω	270Ω	0.1µF	4610H-805-121/104
150Ω	270Ω	338Ω	0.1µF	4610H-805-151/104
200Ω	360 Ω	450Ω	0.1µF	4610H-805-201/104

805 Electrical Schematic and Application





How To Order 801


46 08 M - 801 - 500 103
Model (46 = Conformal SIP) Number of Pins (8, 10, 12)
Physical Config. •M = Medium Profile
Electrical Configuration Resistance Code •First 2 digits are significant •Third digit represents the number of zeros to follow. •Units = ohms
Capacitance Code •First 2 digits are significant •Third digit represents the number of zeros to follow. •Units = picofarads
Consult factory for other available options.

How To Order 802


46 10 M - 802 - 500 103	3
Model	
Electrical Configuration Resistance Code • First 2 digits are significant • Third digit represents the number of zeros to follow. • Units = ohms	
Capacitance Code • First 2 digits are significant • Third digit represents the number of zeros to follow. • Units = picofarads	

Consult factory for other available options.

How To Order 803 and 805



How To Order 804



Consult factory for other available options.

REV. 04/06

Specifications are subject to change without notice.

Customers should verify actual device performance in their specific applications.